1

CANADIAN THESES ON MICROFICHE

I.S.B.N.

THESES CANADIENNES SUR MICROFICHE

National Library of Canada
Collections Development Branch

Canadian Theses on
Microfiche Service

Ottawa, Canada
K1A 0N4

Bibliothèque nationale du Canada
Direction du développement des collections

Service des thèses canadiennes
sur microfiche

NOTICE

The quality of this microfiche is heavily dependent upon the quality of the original thesis submitted for microfilming. Every effort has been made to ensure the highest quality of reproduction possible.

If pages are missing, contact the university which granted the degree.

Some pages may have indistinct print especially if the original pages were typed with a poor typewriter ribbon or if the university sent us a poor photocopy.

Previously copyrighted materials (journal articles, published tests, etc.) are not filmed.

Reproduction in full or in part of this film is governed by the Canadian Copyright Act, R.S.C. 1970, c. C-30. Please read the authorization forms which accompany this thesis.

THIS DISSERTATION
HAS BEEN MICROFILMED
EXACTLY AS RECEIVED

AVIS

La qualité de cette microfiche dépend grandement de la qualité de la thèse soumise au microfilmage. Nous avons tout fait pour assurer une qualité supérieure de reproduction.

S'il manque des pages, veuillez communiquer avec l'université qui a conféré le grade.

La qualité d'impression de certaines pages peut laisser à désirer, surtout si les pages originales ont été dactylographiées à l'aide d'un ruban usé ou si l'université nous a fait parvenir une photocopie de mauvaise qualité.

Les documents qui font déjà l'objet d'un droit d'auteur (articles de revue, examens publiés, etc.) ne sont pas microfilmés.

La reproduction, même partielle, de ce microfilm est soumise à la Loi canadienne sur le droit d'auteur, SRC 1970, c. C-30. Veuillez prendre connaissance des formules d'autorisation qui accompagnent cette thèse.

LA THÈSE A ÉTÉ
MICROFILMÉE TELLE QUE
NOUS L'AVONS REÇUE

National Library
of Canada

Bibliothèque nationale
du Canada

Canadian Theses Division

Division des thèses canadiennes

Ottawa, Canada
K1A 0N4

59982

0-315-12069-X

PERMISSION TO MICROFILM — AUTORISATION DE MICROFILMER

• Please print or type — Écrire en lettres moulées ou dactylographier

Full Name of Author — Nom complet de l'auteur

(SURNAME)

TEWFIK LABIB HASSANEIN

Date of Birth — Date de naissance

31 Dec. 1950

Country of Birth — Lieu de naissance

EGYPT

Permanent Address — Résidence fixe

34 Khirat st., Lazoughly, CAIRO, Egypt.

Title of Thesis — Titre de la thèse

Investigation and Modelling of Electrical Conduction
and Piezoresistance in Polycrystalline Silicon

University — Université

CARLETON

Degree for which thesis was presented — Grade pour lequel cette thèse fut présentée

Doctor of Philosophy

Year this degree conferred — Année d'obtention de ce grade

1982

Name of Supervisor — Nom du directeur de thèse

A. R. BOOTHROYD

Permission is hereby granted to the NATIONAL LIBRARY OF
CANADA to microfilm this thesis and to lend or sell copies of
the film.

The author reserves other publication rights, and neither the
thesis nor extensive extracts from it may be printed or other-
wise reproduced without the author's written permission.

L'autorisation est, par la présente, accordée à la BIBLIOTHÈ-
QUE NATIONALE DU CANADA de microfilmer cette thèse et de
prêter ou de vendre des exemplaires du film.

L'auteur se réserve les autres droits de publication; ni la thèse
ni de longs extraits de celle-ci ne doivent être imprimés ou
autrement reproduits sans l'autorisation écrite de l'auteur.

Date

Sep. 29, 1982

Signature

T. L. Hassanein

FACULTY OF ENGINEERING

Investigation and Modelling of Electrical Conduction
and Piezoresistance in Polycrystalline Silicon

by

© TEWFIK LABIB HASSANEIN

B.Sc. (ENG), Cairo University, Egypt, 1973

B.Sc. (MATH), Ain Shams University, Egypt, 1975

M.Eng., Carleton University, Canada, 1977

This thesis was submitted to the Faculty of Graduate Studies
and Research in partial fulfillment of the requirements for the
degree of

DOCTOR OF PHILOSOPHY.

Department of Electronics

Carleton University

Ottawa, Canada

August 1982

The undersigned recommend to the Faculty of Graduate Studies
and Research the acceptance of the thesis:

"INVESTIGATION AND MODELLING OF ELECTRICAL CONDUCTION
AND PIEZORESISTANCE IN POLYCRYSTALLINE SILICON"

submitted by Tewfik Labib Hassanein, B.Sc. ENG., B.Sc. MATH.,
M.Eng., in partial fulfillment of the requirements for the degree
of Doctor of Philosophy.

A.R. Boothroyd

Prof. A.R. Boothroyd
Thesis Supervisor

A.R. Boothroyd

Prof. A.R. Boothroyd
Chairman, Department of
Electronics

Carleton University

August 1982

ABSTRACT

In this thesis, the properties of electrical conduction and piezoresistance of diffused polycrystalline films deposited at atmospheric pressure by the chemical vapour deposition technique are investigated and then related to each other to develop a novel approach to the modelling of electrical conduction.

The measured behaviour of the diffused films indicates that electrical conduction is greatly influenced by the grain boundary, the basic mechanisms involved being thermionic emission and tunneling of current carriers over (and/or through) potential energy barriers created at the boundary due to carriers trapped in the initially neutral grain boundary trapping states.

The influence of segregation of impurity atoms to the grain boundaries on the process of electrical conduction is found to depend on the dopant species, being more profound for phosphorous- than for boron-diffused films. Impurity segregation in the diffused films does not follow the trend reported for ion-implanted films with respect to high temperature annealing, instead it appears to follow a 'fixed segregation' concept in which the number of segregating atoms is unaffected by any heat treatment steps following the impurity diffusion process.

Practically useful films, with stable conduction and piezoresistance characteristics, are those in which the neutral grain interior is dominant. A theoretical model for the piezoresistance

coefficient in these films is developed. The model is applied in conjunction with a conduction model based on thermionic emission and tunneling to determine the active dopant concentration in the grain interior, a critical parameter in the characterization of diffused films. Results of applying the modelling approach involving the above piezoresistance model to the diffused films demonstrate the validity of the approach in the characterization of these films over practical ranges of dopant concentrations and temperatures.

The relatively large, highly stable gauge factor observed for highly doped films accentuates their potential use in the field of silicon transducer applications such as strain gauges.

ACKNOWLEDGEMENTS

The writer wishes to express his deep gratitude to his thesis supervisor, Prof. A.R. Boothroyd, for his invaluable help and guidance throughout the course of this work.

The writer also wishes to thank Mr. L.P. Berndt, Mrs. E.M. Armstrong, and Mrs. J.A. McAinsh, members of the technician staff in the Department of Electronics at Carleton University, for their assistance and dedicated work in the fabrication of the test samples.

Special thanks are due to Dr. R.F. Haythornthwaite of QRL Analysis Corporation for his assistance in taking the scanning electron micrographs of the polysilicon test samples.

Thanks are also due to Mrs. S. Ryan for careful and speedy typing of the manuscript.

CONTENTS

	Page
CHAPTER 1. INTRODUCTION	1
1.1 Historical Review	1
1.2 Thesis Objectives	6
1.3 Thesis Format	6
CHAPTER 2. THEORIES OF ELECTRICAL CONDUCTION IN POLYCRYSTALLINE SILICON	8
2.1 Definition of the Polycrystalline Structure	10
2.2 Conduction Models	11
2.2.1 Grain Boundary Segregation Model	12
2.2.2 Grain Boundary Trapping Model	19
2.2.2.1 Seto's Approach	20
2.2.2.2 Limitations of Seto's Trapping Model	27
2.2.2.3 Other Inconsistencies in the Model and Suggestions for Modifications	29
2.2.3 Latest Developments in Modelling of Conduction in Polysilicon	35
2.2.3.1 Validity and Limitations of Modelling Approaches	41
2.2.3.2 Discussion	46
2.3 Concluding Remarks	47
CHAPTER 3. PIEZORESISTANCE OF POLYCRYSTALLINE SILICON FILMS	50
3.1 Piezoresistive Properties of Single Crystal Silicon	51
3.1.1 Phenomenological Description	51
3.1.1.1 Elastoresistance	51
3.1.1.2 Piezoresistance	52
3.1.1.3 Rotation of Axes	54
3.1.2 Piezoresistance Effect in N-Type Silicon	56
3.1.3 Piezoresistance Effect in P-Type Silicon	64
3.1.4 Effect of High Doping (Statistical Degeneracy)	72
3.2 Piezoresistive Properties of Grain Boundary	76
3.3 Piezoresistance Effect in Polycrystalline Silicon	77
3.4 Concluding Remarks	84

CHAPTER 4. ELECTRICAL CONDUCTION AND PIEZORESISTANCE OF DIFFUSED POLYSILICON FILMS	87
4.1 Experimental Procedure	88
4.1.1 Film Preparation	88
4.1.2 Test Structures	91
4.1.3 History of Experimental Work	93
4.1.4 Measurements	99
4.2 Results of Experiments	107
4.2.1 Electrical Resistivity	108
4.2.2 Temperature Dependence of Electrical Resistivity	110
4.2.3 Piezoresistance Effects	114
4.2.4 High Temperature Annealing Characteristics	120
4.2.5 Grain Size	123
4.3 Concluding Remarks	128
CHAPTER 5. A NEW APPROACH TO THE MODELLING OF ELECTRICAL CONDUCTION IN DIFFUSED POLYSILICON FILMS	131
5.1 Modelling Approach	132
5.2 Further Modelling Aspects	143
5.2.1 Partial Ionization of Impurities	143
5.2.2 Carrier Collisions	145
5.3 Concluding Remarks	148
CHAPTER 6. CONCLUSIONS AND RECOMMENDATIONS	150
6.1 Research Contributions	150
6.1.1 Basic Theory	150
6.1.2 Modelling	152
6.1.3 Transducer Applications	154
6.2 Recommendations for Future Work	155
APPENDIX A. THE SEGREGATION MODEL OF MANDURAH ET AL	157
APPENDIX B. ELECTRICAL CONDUCTION IN POLYCRYSTALLINE SILICON	162
APPENDIX C. PROCESS SIMULATION USING "SUPREM II"	172
APPENDIX D. DEVICE FABRICATION PROCEDURE	174
APPENDIX E. CALCULATIONS OF THE STRESSES IN CANTILEVER BEAMS	176
APPENDIX F. YOUNG'S MODULUS FOR POLYCRYSTALLINE SILICON	180
REFERENCES	183

ILLUSTRATIONS

<u>FIGURE NO.</u>	<u>CAPTION</u>	<u>PAGE</u>
2.1(a)	Model for the crystal structure of a P-type polysilicon film.	22
2.1(b)	Charge distribution within the crystallite and at the grain boundary.	22
2.1(c)	The energy band structure for polysilicon.	22
2.2	Energy-band diagram near a grain boundary under zero applied voltage.	37
3.1	Effect of a [100] stress on the constant energy surfaces in the stressed crystal of silicon.	58
3.2	Valence band of silicon near $K=0$.	66
3.3	A model for polysilicon as an inhomogeneous structure.	79
4.1	Photomicrograph of the polysilicon chip.	92
4.2	Schematic diagram of the mechanical set-up used to determine the piezoresistance coefficient of polysilicon resistors.	102
4.3	Typical plots of natural logarithm of normalized resistivity of boron-diffused polysilicon films vs $1000/T$.	111
4.4	Typical plots of natural logarithm of normalized resistivity of phosphorous-diffused polysilicon films vs $1000/T$.	112
4.5	Typical curves of resistance change as a function of strain for diffused polysilicon films.	119
4.6	Scanning electron micrograph of slice P4-29.	127
5.1	Graph of $(\bar{\pi}_{g g_0}^0)$ vs N_G for P-type impurities in single crystal silicon.	134
5.2	Graph of $(\bar{\pi}_{g g_0}^0)$ vs N_G for N-type impurities in single crystal silicon.	135

<u>FIGURE NO.</u>	<u>CAPTION</u>	<u>PAGE</u>
B.1(a)&(b)	Energy-band diagram near a grain boundary.	164
E.1	Bending moment diagram of a cantilever with a concentrated load applied to the free end.	177

TABLES

<u>TABLE NO.</u>	<u>CAPTION</u>	<u>PAGE</u>
3.1	Comparison between theoretical and experimental values of $\lambda_s(\eta_0)$ for N-type silicon at different temperatures and for different scattering mechanisms.	75
4.1(a) to (c)	Polysilicon test wafers.	96-98
4.2	Variation of resistivities of boron- and phosphorous-diffused polysilicon films with macroscopic dopant concentration.	109
4.3	Dependence of the gauge factor of diffused polysilicon films on active dopant concentration.	118
4.4	High temperature annealing conditions for phosphorous- and boron-diffused polysilicon slices with different resistivities.	121
5.1	Typical values of parameters of diffused polysilicon films.	139

CHAPTER 1

INTRODUCTION

1.1 Historical Review

Polycrystalline silicon (polysilicon) is gaining an increasing interest because of its relative cheapness and the ease of fabrication of films having stable, well-controlled physical and electrical properties. This has been made possible by the development of the chemical vapour deposition (CVD) technique by means of which polysilicon films with high reproducibility can be obtained. Vacuum evaporation and sputtering provide other alternative methods of fabrication^[1]; the polysilicon films produced by these two processes, however, do not have as high repeatability as those fabricated using CVD^[1,2].

Polysilicon has found many applications in the semiconductor industry such as:

1. As a gate material in Insulated Gate Field Effect Transistors (IGFETs)^[1,3,4].
2. As a semiconductor resistor with higher sheet resistivities and lower TCRs than conventional (single crystal) diffused resistors^[5].
3. In solar cells for photovoltaic power systems^[6].
4. As transfer gates in charge-coupled devices^[7,8].
5. In isolation between active elements of integrated circuits^[9,10].

6. As an impurity diffusion source^[11].
7. For contact leads^[11].
8. In the fabrication of P-N junction diodes (with minority carrier lifetime of the order of 20 psec^[12]), and field effect devices (with surface mobility values comparable to those obtained with single crystal silicon^[13,14]).
9. In fabricating semiconductor transducers exploiting the property of piezoresistance, e.g., pressure sensors, with good reproducibility and high pressure sensitivity^[15].

From the outset, the focus in the research was on both the conduction mechanisms and the piezoresistance effects in polysilicon films such as would be laid down by the conventional techniques employed in integrated circuit fabrication. Interest in piezoresistance properties arose naturally from the writer's M.Eng. thesis work^[16], but it was appreciated that any studies of these properties would need to be coupled with good modelling of basic conduction mechanisms themselves. Thus it was expected that these two aspects of the research would be mutually stimulating. At the earliest stage of the research, it was decided that attention would be concentrated on CVD polysilicon films doped by diffusion of impurities, using conventional IC fabrication techniques.

In spite of the range of applications and broad interest in polycrystalline silicon, there has until recently been a surprising lack of understanding of its properties.

At the time of commencement of the research presented in this thesis, and in its early stages (prior to 1980), as far as conduction properties are concerned, the experimental data were scanty, and were, in many cases, reported for one type of dopant without comparing the behaviour of this particular dopant to the behaviour of the opposite impurity type. The reported experimental results were, in some cases, conflicting; an example of this was the trend of mobility variation with doping concentration. While the experimental results of reference [17] showed a maximum in the mobility vs doping concentration, those of references [18] and [19] showed a mobility minimum occurring at approximately the same doping level at which a mobility maximum was reported in reference [17].

The theory that had been presented to describe the conduction process in these films was incomplete; the only comprehensive model being that introduced by Seto^[18] in 1975 based on purely thermionic emission of current carriers over potential energy barriers created at grain boundaries as a result of carrier trapping at the boundary region. This model suffered from several inadequacies and was limited in its applicability to polysilicon films with grain sizes less than 600 Å, as will be shown in Chapter 2.

A few attempts to refine Seto's model were subsequently made by other researchers^[20,21] thereby resulting in some improvement in the prediction. These attempts, however, stopped short of achieving a complete understanding of the physical mechanisms encountered in the current transport process in polysilicon films. This lack of

understanding was reflected in the so-called "fitting parameters" that had to be used to fit their models (which were revised versions of Seto's model, as mentioned above) to the results of their measurements, as discussed in Chapter 2.

The above stated gaps in the knowledge regarding electrical conduction in polysilicon films were highlighted in the research proposal submitted by the writer in October 1980^[22]. In this research proposal, a review of the different theories and conduction models available to that date was presented together with a critical assessment of these models. Specific suggestions for more accurate modelling based on representation of actual physical mechanisms involved in the conduction process, were also proposed by the writer at that time; these ideas are included in Chapter 2.

While the research of this thesis was in progress, similar investigations of conduction properties were being conducted by a research group at Stanford University, the outcome of which was recently published by Mandurah et al in the form of a model for conduction in polysilicon^[23,24]. This conduction model, presented and discussed at length in Chapter 2, was based primarily on certain physical considerations that had also been put forward independently (but not published) by the present writer^[22] as proposals for remedying the shortcomings of the Seto model.

The conduction model of Mandurah et al was shown to predict with good accuracy the electrical conduction in low pressure chemical vapour-deposited (LPCVD) polysilicon films doped by ion-implantation.

In the course of the study presented in this thesis, certain aspects of this model were found to be applicable to atmospheric pressure, chemical vapour deposited (APCVD), diffused polysilicon films while some others proved to be invalid. The details of agreement and disagreement between the predictions of this model and the observed behaviour of diffused polysilicon films investigated in this work are discussed in Chapter 2 with the aim of formulating the writer's approach to the problem of the modelling of electrical conduction in diffused polysilicon films.

Turning now to the piezoresistive properties of polysilicon films, the information available in the literature at the commencement of the research was remarkably scanty. The few experimental results reported were restricted to boron-implanted polysilicon films prepared by CVD^[15,25] or boron-doped, vacuum-evaporated films^[26]; no results had appeared on CVD films doped by impurity diffusion, nor were N-type doped films reported. No attempt had been made to develop a comprehensive theory to explain the observed piezoresistive properties of such films, though a considerable literature on theoretical and experimental aspects of piezoresistance in single crystal silicon was in existence. At the present time, little advance has been made on this situation in the literature. In particular, no work has been reported on the piezoresistive properties of impurity diffused CVD polysilicon films that form the subject of this thesis.

1.2 Thesis Objectives

The thesis presents the experimental and theoretical investigations undertaken by the writer into the conduction and piezoresistance properties of diffused polycrystalline silicon films prepared at Carleton University using the APCVD technique. This investigation had the following original objectives:

1. To characterize the electrical and piezoresistive properties of diffused polycrystalline silicon films; to relate these properties to each other and develop a model for electrical conduction in such films.
2. To investigate the possibility of utilizing the piezo-resistance effect in polysilicon films in the fabrication of practical electro-mechanical transducers such as strain gauges.

The thesis has concentrated mainly on the first of these objectives though the work carried out has allowed useful conclusions to be drawn in regard to the latter.

1.3 Thesis Format

Chapter 2 presents the theories that have been used to explain the electrical conduction in polysilicon films, together with a critical discussion of the efficacy of the different models that have been based on these theories.

Chapter 3 is devoted to the subject of piezoresistance. The piezoresistive effects in single crystal silicon (of both P- and N-

types) is first discussed as the natural starting point for the establishment of the piezoresistance of a polycrystalline structure. This structure is modelled at the end of the chapter as an inhomogeneous material of two different media, the grain interior and the grain boundary, with two different values of electrical resistivity and piezoresistance coefficient. An expression for the predicted piezoresistance coefficient of the composite structure is developed, on that basis, at the end of the chapter.

Chapter 4 presents the experimental investigations carried out on APCVD diffused polysilicon films studied in this work. The preparation of polysilicon test structures and the control of their basic physical parameters are given. The measurements that were conducted on these structures are surveyed with a discussion of the results of these measurements and their implications on the modelling of diffused polysilicon films.

Chapter 5 sets out the writer's novel approach to the modelling of diffused polysilicon films. This approach is shown in this chapter to rely on the piezoresistance of the polysilicon films in conjunction with the conduction model developed by Mandurah et al^[23,24] to achieve a complete characterization of the films.

Chapter 6 summarizes the principal contributions of this work, and outlines additional areas for further study.

CHAPTER 2

THEORIES OF ELECTRICAL CONDUCTION IN POLYCRYSTALLINE SILICON

When compared to single crystal, the polycrystalline structure exhibits three distinct features regarding the process of electrical conduction:

- a. At low values of doping concentration, the observed carrier concentration in polysilicon is very small compared to that of single crystal [17,18,19], the latter being almost equal to the doping concentration. As a threshold value of doping concentration is reached, the carrier concentration in polysilicon starts to grow rapidly approaching the doping concentration at sufficiently high concentrations.
- b. The electrical resistivity of doped polysilicon remains high ($\sim 10^5 \Omega\text{cm}$) up to a certain doping level above which the resistivity drops rapidly to approach that of single crystal silicon [18,21,27].
- c. Electrical conduction in polysilicon is a thermally activated process with an activation energy equal to half the bandgap of single crystal silicon at low doping levels.

This chapter presents a review of the different theories and conduction models that have been put forward to date to explain for these properties and the physical mechanisms responsible for them.

In addition to reviewing the literature, a critical discussion of the various models is also presented and this constitutes one of the contributions of the writer's work.

As already noted in Chapter 1, while the present research was in progress, along the lines set out in the writer's research proposal^[22], a similar investigation into the conduction properties of polycrystalline silicon was being conducted at Stanford University, the outcome of which was recently published by Mandurah et al^[23,24] in the form of a model for conduction in polysilicon. While certain aspects of this model (which accurately represented electrical conduction in their low-pressure, ion-implanted polysilicon) were found to be applicable to atmospheric-pressure, diffused polysilicon films studied in the present work, some others proved to be invalid. The details of agreement and disagreement between the predictions of the Mandurah et al model and the measured behaviour of diffused polysilicon obtained in the work reported here are discussed at the end of this chapter with the aim of formulating the writer's approach to the problem of the modelling of electrical conduction in diffused polysilicon films prepared by CVD at atmospheric pressure. This approach is shown at the end of this chapter to be based on two basic ideas:

1. The application of the Mandurah et al expression for electrical resistivity in terms of the basic physical parameters characterizing the polycrystalline structure, as well as temperature and active dopant concentration.

2. The use of the piezoresistance effect in polysilicon as an independent measurement to aid in the determination of the active dopant concentration. This quantity is difficult to determine for the polycrystalline structure in general, and in particular for diffused polysilicon films (as contrasted to ion-implanted films) due to the lack of accuracy in the determination of the amount of dopant in the diffused films, and also due to possible segregation effects (as shown later in this chapter).

The use of piezoresistance in the modelling approach presented in this thesis is proposed by the writer as a substitute for the segregation model of Mandurah et al that has been found invalid for diffused polysilicon films, as will be shown in Chapter 4.

2.1 Definition of the Polycrystalline Structure

A polycrystalline material is composed of small crystallites joined together by grain boundaries. The angle between the orientations of the adjoining crystallites (i.e. the tilt angle) is often large. Inside each crystallite the atoms are arranged in a periodic manner so that it can be considered as a small single crystal. The grain boundary is a complex structure, usually consisting of a few atomic layers of disordered atoms. Atoms in the grain boundaries represent a transitional region between the differently oriented neighbouring crystallites.

2.2. Conduction Models

There are two schools of thought concerning the effects of the grain boundary on the electrical properties of doped polycrystalline silicon. One approach is founded on the assumption that the grain boundary acts as a sink for impurity atoms due to impurity segregation at the grain boundary^[19,27]. Consequently, the amount of impurity atoms in the crystallites is reduced, which leads to much smaller carrier concentration in polysilicon than that observed with single crystal silicon subject to the same doping conditions. This is also equivalent to saying that the carrier concentration in polysilicon films is expected to be much less than the doping concentration (these are almost equal for single crystalline silicon at room temperature and statistically non-degenerate doping densities). The carrier concentration does not approach the doping concentration until the grain boundary is saturated with impurity atoms.

The other approach^[17,18,21] reasons that since the atoms at the grain boundary are disordered, there are a large number of defects due to incomplete atomic bonding. This results in the formation of trapping states that are capable of trapping carriers and thereby immobilizing them. This reduces the number of free carriers available for electrical conduction. After trapping the mobile carriers, the traps become electrically charged creating a potential energy barrier which impedes the motion of carriers from one crystallite to another, thereby reducing their mobility. Again, based on that model, for the same value of doping, the mobility and carrier concentration of polycrystalline silicon would be less than that of single crystalline material.

In the next two sections, more detailed discussion of each model as worked out by previous investigators will be presented together with a critical discussion of each of the assumptions involved in the models and also any experimental evidence that proves relevant to the discussion.

2.2.1 Grain Boundary Segregation Model

Until recently, the segregation model had not gained serious attention by most of the researchers working on the modelling of conduction in polysilicon, the reason being simply that segregation is a mechanism that is difficult to treat analytically, and also very difficult to verify experimentally. The first analytical treatment of segregation appeared in the literature as recently as November 1980 in the formulation of the Mandurah et al model for dopant segregation in polysilicon^[28]. Until the details of this model were published, segregation of impurity atoms to the grain boundaries had been viewed as a hypothesis that rested on a qualitative theoretical foundation and that needed to be validated through experimentation. The qualitative argument upon which the early ideas of segregation were founded^[27] are as follows:

The grain boundary region is one of highly disordered atomic structure (as mentioned earlier), and therefore it is expected that this disordered texture can provide other than tetrahedral atomic sites as can be accounted for in the existence of interfacial energy. (This is similar to the situation in an amorphous structure that

allows for other than tetrahedral bonds among different atoms).

Accordingly, the number of extra bonds in the grain boundary can be estimated by considering the interfacial energy and the energy to create one bond.

The surface energy of silicon has been experimentally determined to be [29]:

$$E_S = 1230 \text{ erg/cm}^2 \text{ [for (111) surface]}$$

Since the grain boundary encountered in silicon is usually of the large tilt angle type, then the grain boundary energy E_B can be estimated by [30]:

$$E_B \approx \frac{1}{3} E_S$$

Consequently, the density of extra bonds, N_B , is:

$$N_B = \frac{1}{3} \frac{1}{1.1 \text{ eV/bond}} \times A_{GB}$$

where A_{GB} is the area of grain boundaries per unit volume. In a polysilicon film with grain size $L \sim 1 \mu\text{m}$, $A_{GB} = 2 \times 10^4 \text{ cm}^2/\text{cm}^3$, and $N_B \sim 10^{18}$ extra bonds per cubic centimeter.

This simplified treatment shows that the grain boundaries can absorb a large number of impurity atoms even if only a fraction of the above estimated number of extra bonds were to be taken up by impurities, these extra bonds would then render the impurity atoms electronically inactive.

The resistivity of polysilicon therefore remains very high ($>10^5 \Omega\text{cm}$) and the carrier concentration remains very low at doping concentrations below a critical value that is necessary to saturate the extra bonds residing in the grain boundary. Above that critical doping level, the resistivity and carrier concentration in polysilicon should reach the corresponding values for single crystal.

As mentioned earlier, the above treatment is meaningful only if the segregation hypothesis is correct. Here, it should be noted that no direct experimental evidence in support of the segregation hypothesis was available in October 1980, at the time when the proposal for this research was presented; furthermore, certain observations were available at that time which appeared to contradict this hypothesis. These were:

- i) It has been shown^[31] (for silicon alloys containing boron and phosphorous) that segregation of boron at the grain boundary is significant only at extremely high concentrations of impurities, e.g. a concentration of boron atoms equal to 1.3% of the silicon atomic density. No segregation was observed for doping as high as 1.3×10^{20} atoms/cm³.
- ii) If the reduction of carriers (in polysilicon as compared to single crystal) is the result of impurity segregation at the grain boundary, it is expected that the carrier concentration reduction would depend on the impurity element (because the segregation coefficient differs from

one impurity element to another with a consequent difference in the density of atoms segregated in the grain boundaries for different impurity elements).

However, it was observed^[17] that both boron and phosphorous behaved similarly in polysilicon.

- iii) The segregation model does not explain the temperature dependence of polysilicon resistivity which is thermally activated and exhibits a negative temperature coefficient^[18].

Despite the above stated arguments against the segregation hypothesis, it was concluded^[22] that there was no sufficiently strong evidence to justify a complete rejection of the concept. This assertion was based on the well-known fact of the enhanced diffusion of impurities (especially boron and phosphorous) in polycrystalline silicon films due to the diffusion of these impurities along the grain boundaries that constitute easy flow channels for the impurity atoms^[32,33]; this experimentally verified effect (see also Section 4.1.1) makes it enticing to assume that some of the diffusing impurity atoms segregate preferentially at the grain boundary where the disordered structure provides for additional bonds.

It was therefore concluded that segregation remained as a possibility to be investigated and accounted for in the conduction model, once proven to exist. The experiments that were proposed to be carried out on doped polysilicon to test the segregation hypothesis were those involving high temperature annealing, and the logical reasoning to be followed in the interpretation of the results was

as follows: if a significant increase in resistivity occurred after annealing the samples at high temperatures, that could be taken as an evidence to support the segregation assumption, the increase in resistivity in this case being attributable to the migration of impurity atoms from the bulk of crystallites to the grain boundaries where there are sufficiently large number of additional bonds providing energetically more favourable sites for the dopants than in the bulk of grains, with the migration process stimulated by the high temperature of annealing.

Experiments identical to those described above were pursued by Mandurah et al [28] at Stanford University as a part of their attempt to construct a model for conduction in polysilicon prepared by CVD at low pressure and doped by ion implantation. Annealing experiments were carried out on boron-, phosphorous-, and arsenic-implanted polysilicon. The results of their experiments revealed the following facts:

- i) Resistivity of arsenic and phosphorous-implanted polysilicon underwent major changes (up to two orders of magnitude) upon annealing at temperatures lower than that of the post-implant annealing step that is usually carried out to remove the implantation damage and redistribute and activate the dopant atoms.
- ii) The changes in resistivity were more profound for arsenic than for phosphorous under the same annealing conditions.
- iii) The changes in resistivity were reversible with respect to the annealing temperature.

- iv) No appreciable change in resistivity was observed for boron-implanted polysilicon in the same doping range (i.e., 10^{18} to 10^{20} atoms/cm³).

In view of the above-stated experimental observations, Mandurah et al.^[28] concluded that segregation of impurity atoms occurred in polysilicon films deposited at low pressure and doped by ion implantation, the effect being most noticeable for arsenic atoms, less noticeable for phosphorous atoms, and almost non-existent for boron atoms.

Furthermore, from consideration of existing theory of interfacial segregation in a general multicomponent system, the above mentioned investigators were able to deduce a possible semiquantitative model to determine the amount of dopant atoms segregated at the grain boundaries as a function of grain size, annealing temperature and annealing history. Their model is analytically represented by the following equation:

$$\ln \left(\frac{N - N_G}{N_G} \right) = \ln \frac{A Q_S}{N_{Si}} + \frac{Q_o}{k T_A} \quad (2.1)$$

where

N is the average (or macroscopic) dopant concentration, atoms/cm³

N_G is the average dopant concentration in the grains, atoms/cm³

A is the dopant entropy factor, dimensionless

Q_S is the density of segregation sites at the grain boundary, cm⁻²

[For silicon:

$$\frac{Q_S}{N_{Si}} = \frac{1.62 \times 10^{-7}}{L} \text{ cm}^{-3}, \text{ L is the grain size in cms]$$

N_{Si} is the atom density of silicon, cm^{-3}

Q_O is the dopant heat of segregation, Joule

T_A is the annealing temperature, $^{\circ}\text{K}$

k is Boltzmann constant, Joule/ $^{\circ}\text{K}$

A and Q_O are determined experimentally [from a plot of $\ln \left(\frac{N-N_G}{N_G} \right)$ vs $\frac{1}{k T_A}$, N_G being experimentally determined from Hall mobility measurements]; they both are functions of impurity species and impurity concentration.

The physical basis of the model and the derivation of Eqn. (2.1) are treated in detail in Appendix A.

It should be noted at this point that, while the segregation model represented by Eqn. (2.1) was found to accurately predict the value of N_G (the active dopant concentration in the crystalline bulk) for ion-implanted polysilicon, in the present work it proved to be invalid for diffused polysilicon films.

Annealing experiments carried out in the course of this research on boron- and phosphorous-diffused polysilicon films deposited at atmospheric pressure (by the CVD technique) revealed no change in electrical resistivity of polysilicon upon annealing at high temperatures (see Chapter 4).

In view of this finding, it is concluded either that the Mandurah et al model does not apply on diffused polysilicon films or, if it does apply, the parameter Q_0 (the segregation heat) is effectively zero. In any event, it appears that segregation effects are quite different in implanted and diffused films, and it is both interesting and challenging to speculate on the reasons for this difference.

In the present work the need, therefore, arises for an alternative method to determine the value of the active dopant concentration in the bulk of crystallites in the case of diffused polysilicon. A novel approach to this problem is explained in detail in Chapter 5; it relies on the use of the piezoresistance effect in polysilicon (see Chapter 3) in conjunction with Mandurah et al's conduction model [23,24].

2.2.2 Grain Boundary Trapping Model

The grain boundary trapping model is founded, as mentioned earlier, on the assumption that the carriers are trapped at the grain boundaries that contain, due to their highly disordered structure, a large number of traps. This results in a reduction in the number of carriers available for electrical conduction. Moreover, after the carriers are trapped, the traps become electrically charged forming a potential energy barrier which impedes the motion of carriers between neighbouring crystallites and therefore reduces their overall effective mobility.

The basic mechanism used to describe the motion of carriers across grain boundaries (or the potential energy barriers associated with them) is thermionic emission, and a semi-quantitative model of conduction in polysilicon based on this mechanism was first introduced by Seto in 1975^[18]. Since then, some refinements in Seto's model have been suggested by several investigators^[20,21,23,24,34,35] including the writer^[22].

The main features of Seto's approach are outlined below, followed by the writer's critical discussion of the limitations of the model and ideas for improving its accuracy. This material represents an original contribution made in the early stages of the research (as put forward in the research proposal^[22]). As later events were to demonstrate, other workers^[23,24,34,35] were independently coming to similar conclusions on a number of the points made in this discussion.

2.2.2.1 Seto's Approach

This is based on the following assumptions:

1. Polysilicon is considered to be composed of identical crystallites having a grain size of L cm.
2. There is only one type of impurity atom present; the impurity atoms are totally ionized and uniformly distributed with a concentration of N/cm^3 .
3. The single-crystalline silicon energy band is also assumed to be applicable inside the crystallites.

4. The grain boundary is of negligible thickness compared to L and contains Q_T/cm^2 of traps located at energy E_T with respect to the intrinsic Fermi level in the bulk of the crystallite. The traps are assumed to be initially neutral and become charged by trapping a carrier.
5. An abrupt complete depletion approximation is used to calculate the energy band diagram in the crystallites (see Fig. 2.1).
6. Boltzmann's statistics (non-degenerate statistics) apply.
7. Although polysilicon is a three-dimensional substance, Seto's analysis is based on solving Poisson's equation in one-dimensional space.
8. Only the resistance of the grain boundary region is considered in the model; the resistance of the neutral bulk of the crystallites is neglected.
9. The tunneling current was neglected and only the thermionic emission current was considered. Bethe's^[36] model for thermionic emission was used; this model is based on the following assumptions:
 - a) The barrier height $\gg kT$, so that the number of carriers taking part in the transport process remains much less than the total number of carriers, i.e. the equilibrium distribution of carriers in the neutral bulk is undisturbed by the current flow. This condition is also necessary for the barrier not to be obscured by the thermal motion of carriers (with a thermal energy $\sim kT$).

(b) Charge distribution.

(c) Energy band structure.

Fig. 2.1. (a) Model for the crystal structure of a P-type polysilicon film.
 (b) Charge distribution within the crystallite and at the grain boundary.
 (c) The energy band structure for polysilicon.

b) Collisions with lattice phonons in the depletion region are neglected. This assumption is equivalent to saying that the distance at which the barrier height changes from its maximum value by kT (measured from the position of the maximum) is much less than the mean free path for scattering by lattice phonons (specifically optical phonons).

c) Effect of the image force is neglected.

It should be noted that certain of the above quoted assumptions are violated in practice; the consequent limitations of the model are discussed later.

Based on the above listed assumptions, Seto obtained (for P-type polysilicon) the following expression for the thermionic current density across a grain boundary, J_{th} , as a function of the applied voltage, V_o , per grain (in the linear region of the I-V characteristics):

$$J_{th} = q^2 p_a \left(\frac{1}{2\pi m^* kT} \right)^{1/2} \exp\left(\frac{-qV_b}{kT}\right) V_o \quad (2.2)$$

where

V_b is the potential energy barrier height, volts

p_a is the average carrier concentration in the polysilicon film, cm^{-3}

m^* is the effective mass of the carriers

q is the electronic charge, equal to 1.6×10^{-19} Coul.

T is the temperature in degrees Kelvin.

The potential barrier height V_b , the Fermi level E_F , and the average hole density p_a are given by the following two sets of equations corresponding to the two physical situations of totally depleted and partially depleted crystallites, respectively.

For a doping concentration, $N < \frac{Q_T}{L}$ (totally depleted crystallite), the following relationships hold:

$$V_b = \frac{qL^2 N}{8\epsilon} \quad (2.3)$$

$$E_F = E_T - kT \ln \frac{1}{2} \left(\frac{Q_T}{LN} - 1 \right) \quad (2.4)$$

$$p_a = \frac{n_i}{qL} \left(\frac{2\pi\epsilon kT}{N} \right)^{1/2} \cdot \exp \left(\frac{E_F}{kT} \right) \cdot \operatorname{erf} \left[\frac{qL}{2} \left(\frac{N}{2\epsilon kT} \right)^{1/2} \right] \quad (2.5)$$

For a doping concentration, $N > \frac{Q_T}{L}$ (partially depleted crystallite as shown in Fig. 2.1), the corresponding relationships are:

$$V_b = \frac{qQ_T^2}{8\epsilon N} \quad (2.6)$$

$$E_F = kT \ln \frac{N}{n_i} \quad (2.7)$$

$$p_a = N \left\{ \left(1 - \frac{Q_T}{LN} \right) + \frac{1}{qL} \left(\frac{2\pi\epsilon kT}{N} \right)^{1/2} \operatorname{erf} \left[\frac{qQ_T}{2} \left(\frac{1}{2\epsilon kTN} \right)^{1/2} \right] \right\} \quad (2.8)$$

where

N is the impurity atoms concentration, atoms/cm³

Q_T is the density of trapping states at the grain boundary, cm⁻²

E_T is the trap energy level with regard to the intrinsic Fermi level in the neutral bulk of the crystallite

E_F is the Fermi level with regard to the intrinsic Fermi level in the crystallite neutral bulk

n_i is the intrinsic carrier concentration of single crystal silicon, cm^{-3}

ϵ is the dielectric permittivity of single crystal silicon.

Expressions for the resistivity and effective mobility are obtained from Eqn. (2.2) as follows:

$$\rho = \frac{(2\pi m^* kT)^{1/2}}{q^2 L p_a} e^{qV_b/kT} \quad (2.9)$$

$$\mu_{\text{eff}} = \frac{qL}{(2\pi m^* kT)^{1/2}} e^{-qV_b/kT} \quad (2.10)$$

where

ρ is the resistivity of polysilicon, $\Omega \text{ cm}$

μ_{eff} is the effective mobility of charge carriers in the polysilicon film, $\text{cm}^2/\text{volt-sec}$

L is the average grain size, cm .

When trying to fit this theoretical model (Eqn. (2.9) of resistivity, ρ , as a function of doping, N) to his experimental results for boron implanted polysilicon with grain size $200\text{\AA}$, Seto had to apply two fitting constants $\frac{1}{n}$ and f to Eqn. (2.9). These constants multiply, respectively, the potential barrier height, V_b , and the effective Richardson's constant (or equivalently the effective mass, m^*) for thermionic emission (i.e. V_b replaced by V_b/n and m^* by fm^*). Seto's experimentally obtained values of n and f (over the doping

range from 10^{16} to $5 \times 10^{19} \text{ cm}^{-3}$) were

$$n = 6.49, f = 0.12$$

After incorporation of these two parameters in his model, Seto found a good agreement between theoretical prediction and experimental results for his range of doping and particular, rather small, grain size.

The merits of the model can be outlined as follows:

- a. It predicts an average carrier concentration in the polysilicon film that remains very small (only a small fraction of the doping concentration) up to a critical value of doping concentration N_{cr} at which all the trapping states in the grain boundary have been filled; this critical doping concentration is directly proportional to the density of trapping states, N_T , and inversely proportional to the grain size, L_g . Above N_{cr} , the carrier concentration increases rapidly until it reaches the doping concentration.

This prediction is in agreement with the experimentally obtained values of average carrier concentration as a function of doping concentration.

- b. It predicts a conductivity temperature dependence that is represented by a thermally activated process with an activation energy of ~ 0.55 electron volts (i.e. half the energy band gap of silicon at room temperature) in the lightly doped samples, again in agreement with the observed behaviour.

- c. It predicts a minimum in the mobility vs doping concentration curve. This minimum should be expected to occur (based on the model) at the critical value of doping, N_{cr} , at which the potential energy barrier height reaches its maximum value (where the traps have all been filled) and starts to decrease as $\frac{1}{N}$ thereby causing the mobility (which is exponentially dependent upon the barrier height) to increase rapidly as the doping is increased (see Eqn. (2.10)). The predicted mobility variation with doping was verified by the results of Seto's measurements.
- Despite the above mentioned favourable aspects of Seto's model, there are several major inconsistencies and limitations, some of which were pointed out by Seto himself.

2.2.2.2 Limitations of Seto's Trapping Model

The limitations of Seto's model, as stated by him^[18], are:

- a. The contribution to the resistivity by the bulk of the neutral region of the crystallites was neglected (assumption #8). This assumption fails if the resistance of the bulk is comparable to that of the grain boundary. Such a situation is possible if the grain size of the polysilicon film is large and the doping is high.
- b. It has been shown that the surface states of a free silicon surface are not fixed at a discrete energy level but distributed over an energy range^[37]. It is likely that the trapping states in the grain boundary of polysilicon are also distributed over an energy range. Such a distribution should modify the calcula-

ations since the model was based on a δ -function approximation (assumption #4). The effect on mobility and carrier concentration is to cause their changes as a function of doping concentration to be more gradual in the intermediate range of doping around the critical concentration N_{cr} .

- c. In large grain polysilicon, the free carrier concentration in the "depletion region" can be appreciable. Using the depletion approximation (assumption #5) leads to inaccurate values of the barrier height which results in a major inaccuracy in the predicted values of mobility since it is exponentially dependent on the barrier height.
- d. The average carrier concentration is less affected by the deviation from the condition of abrupt complete depletion since the carrier density depends on the barrier shape only in the depletion region where the number of carriers is usually small compared to the number of carriers in the non-depleted or neutral region, the latter being equal to the doping concentration (because of assumption #2, i.e. complete ionization of impurities). A deviation from the actual barrier shape only causes a small error in the carrier concentration except when $Q_T \approx 1N$. Using the values of Q_T and E_T obtained in his experiment, Seto estimated that the depletion approximation was good up to a grain size of about $600\text{\AA}$.

2.2.2.3 Other Inconsistencies in the Model and Suggestions for Modifications

In the course of this study, further limitations and inconsistencies in Seto's model have been found between some assumptions that are involved in the model and the actual physical situation encountered in practice^[22]. They are:

1. The application of Bethe's model^[36] for thermionic emission to the current flow across the grain boundary in polysilicon is questionable especially at small grain sizes due to the following reasons:

- a) The failure of the assumption that the barrier height, V_b , is much greater than kT at small grain sizes. An estimation of an "average barrier height" (with respect to doping level) has been made by the writer, using the simple formula:

$$V_{b_{av}} = \frac{\int_{N_{min}}^{N_{max}} V_b(N) dN}{(N_{max} - N_{min})}$$

where

$$V_b(N) = \frac{qL^2 N}{8\epsilon} \quad , \quad N < \frac{Q_T}{L}$$

$$= \frac{qQ_T^2}{8\epsilon N} \quad , \quad N > \frac{Q_T}{L}$$

N_{min} and N_{max} being, respectively, the minimum and maximum doping concentrations employed in the investigation of the characteristics of polysilicon.

This simple formula for $V_{b_{av}}$ serves as a criterion to allow a quick test of the validity of the assumption that $V_b \gg kT$ in the practical range of doping densities.

For Seto's polysilicon (with a small grain size, $L=200\text{\AA}$), the calculation yields:

$$V_{b_{av}} = 0.63 kT \text{ at room temperature over Seto's doping range: } 10^{16} \text{ to } 5 \times 10^{19} \text{ atoms/cm}^3$$

Therefore, it is seen that the assumption $\frac{V_b}{kT} \gg 1$ is invalid for Seto's polysilicon; the validity of the assumption should improve with increasing grain size.

This inconsistency is reflected, in the writer's opinion, in the large deviation of the value of the fitting parameter n (applied by Seto to fit his model to his measurements) from unity. While a value reasonably close to unity can be viewed as a supporting evidence of a dominant thermionic emission mechanism of current flow across the grain boundary, Seto's value of $n \approx 6.5$ is too far off unity and signals a deviation from Bethe's model for thermionic emission.

It was suggested in [22] that whenever the value of the fitting parameter n deviates considerably from unity care should be taken to consider other mechanisms that can occur simultaneously with thermionic emission and that affect the flow of current carriers. Quantum mechanical tunneling was proposed as one possibility; another was

segregation of impurity atoms at the grain boundary which could lead to a smaller value of the parameter N (which, in turn, directly influences the barrier height, V_b), thereby producing the same effect on V_b as when the latter is divided by the value of the fitting parameter n .

- b) The assumption that carrier collisions in the depletion region are negligible is also questionable on the following basis. The assumption can be valid only if the distance over which the potential energy barrier changes by kT (measured from the position of the potential maximum) is small compared to the mean free path for scattering by optical phonons (which is approximately equal to $60\text{\AA}$ at 300°K ^[38]). However, this distance can reach an appreciable proportion of the mean free path especially at low doping densities where the depletion region extends over most of the crystallite volume. To give an example, this distance is calculated to be equal to $\approx 45\text{\AA}$ at a doping concentration $N=5 \times 10^{17}/\text{cm}^3$ and at a grain size, $L=200\text{\AA}$, a value that is equal to 75% of the mean free path. Consequently, carrier collisions in the depletion region can not be ignored altogether.

It was therefore suggested that a further step in the improvement of the thermionic emission model would be to apply a thermionic emission-diffusion theory similar to the one contributed by Crowell and Sze^[39] in conjunction with current transport across a metal-semiconductor barrier.

2. The fitting parameter, f , that was applied by Seto (and also later by Lu et al of Stanford University^[21,35]) to multiply the effective Richardson's constant for thermionic emission has no physical significance at all. While both theory and experiments agree on a value of m^* for holes in single crystal silicon equal to $0.66m_0$ ^[40] (m_0 being the free electron mass), the value of f used by Seto to fit his model to his measurements was 0.12 and that used by Lu et al was even smaller by a factor of 2 (i.e. $f=0.06$).
3. The assumptions of a complete ionization of impurity atoms and a Boltzmann's statistics become invalid at doping levels above $5 \times 10^{18}/\text{cm}^3$. At this level, only about 70% of boron or phosphorous atoms in single crystal silicon are ionized at room temperature. The model should therefore be modified to account for the existence of an impurity level (and the effect of partial ionization of dopants when the Fermi level is near it) and statistical degeneracy at high doping.
4. The effect of partial occupancy of the trapping states (as determined by the position of the Fermi level with respect to the trap energy level) should be considered throughout the doping range and not only for lightly doped samples as Seto did in his model. This effect should become significant at larger grain sizes as has been already established by experiments^[35].

5. The contribution of the resistance of the neutral bulk of crystallites to the overall resistivity of polysilicon should be accounted for in the proposed refined model. This contribution should be significant at large grain sizes and high doping levels where the resistivities of the bulk and the boundary are comparable. If this effect is neglected, the resistivity of large grain polysilicon becomes smaller than that of single crystal for high doping levels, which is contrary to experimental results.
6. Perhaps one would expect to have an improved model with more accurate prediction by considering a continuous distribution of trapping states in the grain boundary (similar to the situation encountered in silicon surfaces) rather than the delta-function assumption involved in Seto's model. However, the results of an attempt made along that line^[20] favoured the delta-function assumption over that of a continuous (rectangular) distribution; while a model based on the former came in close match with the experimental results, that based on the latter assumption failed to predict the observed behaviour (the polysilicon films in that investigation were sputter-deposited on SiO_2 thermally grown on silicon substrates; the grain size was equal to $300\text{\AA}$). Later success with a model based on a single trapping level suggests that it is a reasonable approximation to the true situation^[23,24,34].

7. Finally, a comment should be made on the trapping model regarding the implication of an existence of two trapping centres (for electrons and holes) symmetrically displaced with respect to the middle of the energy gap in the grain boundary region. In order for the model to be equally applicable to both N and P type impurities in polysilicon, this assumption has to be made. An assumption like this should not be strange to semiconductor physicists since it has been known^[41,42] that the distribution of surface state density for the silicon-silicon dioxide system has two peaks in the bandgap of silicon that are almost symmetrically situated with respect to the middle of the gap (and located closer to the band edges). If the grain boundary in polysilicon can be thought of as being equivalent to two neighbouring silicon surfaces, then it is possible to expect a distribution of trapping states in the grain boundary similar to that encountered with silicon-oxide interfaces.

Some of the above suggested modifications to Seto's model were also considered subsequently by Lu et al^[21]. In particular, the effects of partial ionization of impurity atoms and statistical degeneracy (at high concentrations of impurities), and also the contribution from the bulk of crystallites to the overall resistance of polysilicon, were accounted for in their model for conduction in polycrystalline silicon, the outlines of which were published in March 1980. This model was still based totally on a carrier trapping

mechanism at the grain boundary (no segregation of impurity atoms was considered) and with the above added effects taken into account, it presented an improved version of Seto's model especially at high doping levels where these effects are significant. The fitting parameter n was greatly improved to a value close to unity (1.22 as compared to Seto's value of 6.49) which, in the writer's opinion, reflected a better validity of a thermionic emission mechanism for the polysilicon samples used (with grain size $\sim 1000\text{\AA}$) than in Seto's polysilicon (with grain size $\sim 200\text{\AA}$).

This model, however, stopped short of achieving an understanding of the physical origin of the fitting parameter f whose value in the model was equal to 0.06, and was therefore worse than Seto's value of 0.12 by a factor of 2. The model also did not account, as mentioned earlier, for the possible segregation of impurity atoms to the grain boundaries.

2.2.3 Latest Developments in Modelling of Conduction in Polysilicon

The conduction models that have been discussed so far were all published in the period that preceded the submission of the writer's research proposal^[22] in October 1980. Since that date, several attempts have been made by other investigators (particularly at Stanford University) to establish accurate models to represent the conduction behaviour of polysilicon over practical ranges of physical parameters that are of particular use in integrated circuit fabrication technology. Not surprisingly, a number of the considerations reviewed above were taken into account also by these workers

and formed the basis for improved models: in particular, the effect of quantum mechanical tunneling (and reflection of carriers at the grain boundaries) and the effect of segregation of impurity atoms to the grain boundaries were represented in the model recently published by Mandurah et al [23,24]. This model was found to accurately predict the electrical resistivity of ion-implanted polysilicon (deposited at low pressure) as a function of grain size, doping concentration (over the intermediate range of macroscopic doping concentration that is of practical interest, i.e. 10^{18} - 10^{20} atoms/cm³), doping species and annealing history.

The basic features of the above mentioned model are as follows:

1. The combined mechanisms of dopant segregation, carrier trapping, and quantum mechanical tunneling (or reflection) of carriers at grain boundaries are included.
2. The grain boundary region is assumed to have a finite width (as contrasted to earlier models where the grain boundary region was assumed to have a zero width). The grain boundaries are modelled by rectangular potential energy barriers with a width of approximately 7Å (equivalent to three atomic diameters) and a height of 0.66 eV independent of the dopant species (obtained by fitting the theoretical model to the experimental data). The shape of the grain boundary barriers is shown in Fig. 2.2. The grain boundary is thus assumed to behave as an intrinsic wide-bandgap semiconductor forming a heterojunction with the crystalline grains. Thermionic emission over the

Fig. 2.2. Energy band diagram near a grain boundary under zero applied voltage [23,24].
[$2W$ is the width of the depleted region within a grain.]

potential barriers created within the grains due to carrier trapping at the grain boundaries and then tunneling through the grain boundaries is proposed as the carrier transport mechanism.

3. Complete ionization of the dopant atoms in the grains is assumed so that the carrier concentration in the neutral regions of the grains is equal to the dopant concentration there.
4. In the intermediate ranges of temperatures (25°C to 75°C as noted by Mandurah^[43]) and dopant concentrations (10^{18} to 10^{20} atoms/cm³), the current-voltage relationship derived in the model is represented by the following equation* (details of the derivation are included in Appendix B):

$$J = q \left(\frac{4\pi m_T^* k^2 T^2}{h^3} \right) \cdot \exp \left(\frac{-\xi}{kT} \right) \cdot \frac{\exp(-b_1)}{1 - C_1 kT} \cdot \exp \left(\frac{-qV_b}{kT} \right) \cdot 2 \sinh \left[\frac{1 + (C_1 kT N_G W_{g_b} / Q_T)}{1 + (N_G W_{g_b} / Q_T)} \cdot \frac{qV_o}{2kT} \right] \quad (2.11)$$

* In the published model of Mandurah et al^[23,24], no distinction was made between the different effective masses involved in the expression for the electrical resistivity (e.g. the conductivity effective mass m_C^* , the Richardson's constant effective mass m_T^* , etc.), all these masses were denoted by one symbol m^* .

This erroneous notation is remedied in the above presentation of the model where the different effective masses have been identified by the writer.

with b_1 and C_1 given by^[23,24]

$$b_1 = \frac{4\pi W}{h} g_b (2m_C^*)^{1/2} (q\phi - qV_b)^{1/2} \quad (2.12)$$

$$C_1 = \frac{2\pi W}{h} g_b (2m_C^*)^{1/2} (q\phi - qV_b)^{-1/2} \quad (2.13)$$

where:

m_T^* is the Richardson constant effective mass.

Values of m_T^* for single crystal silicon are as follows^[40]:

$$\begin{aligned} m_T^* &= 0.66 m_0 && \text{for holes} \\ &= 2.20 m_0 && \text{for electrons in } \langle 111 \rangle\text{-oriented silicon} \\ &= 2.10 m_0 && \text{for electrons in } \langle 100 \rangle\text{-oriented silicon} \end{aligned}$$

m_C^* is the conductivity effective mass.

Values of m_C^* for single crystal silicon are as follows^[44]:

$$\begin{aligned} m_C^* &= 0.26 m_0 && \text{for electrons} \\ &= 0.38 m_0 && \text{for holes} \end{aligned}$$

(m_0 being the free electron mass, equal to 9.1×10^{-31} kg).

$-\xi$ is the Fermi energy relative to the edge of the conduction band, i.e. $\xi = E_C - E_F$

W_{g_b} is the grain boundary width.

ϕ is the height of the grain boundary barrier relative to E_C , i.e. $\phi = \phi_{g_b} - \xi$

V_b is the height of the potential energy barrier in the depletion region.

Q_T is the density of trapping states at grain boundary.

V_0 is the average voltage drop per grain across the composite grain-boundary region.

N_G is the average dopant concentration in the grain. N_G is calculated from the semi-quantitative segregation model discussed in Section 2.2.1 (Eqn. (2.1)).

For applied voltages much less than $\frac{kT}{q}$, the grain-boundary resistivity ρ_{g_b} in the linear region is given by:

$$\rho_{g_b} = [q^2 \left(\frac{4\pi n_i^2 kT}{h^3} \right) L_{g_b} \exp\left(-\frac{\xi}{kT}\right) \cdot \frac{\exp(-b_1)}{(1-C_1 kT)} \cdot \exp\left(-\frac{qV_b}{kT}\right) \cdot \frac{(1+(C_1 kT N_G W_{g_b}/Q_T))}{(1+(N_G W_{g_b}/Q_T))}]^{-1} \quad (2.14)$$

By accounting for the voltage drop across the undepleted regions of the grains, the average resistivity of polysilicon ρ_{poly} can be obtained as follows:

$$\rho_{poly} = \frac{L_g}{L} \rho_g + \frac{L_{g_b}}{L} \rho_{g_b} \quad (2.15)$$

where:

L_g is the width of the undepleted portion of the grain.

L_{g_b} is the width of the composite grain-boundary region.

$L_{g_b} = W_{g_b} + 2W$ where $2W$ is the width of depleted region.

L is the average grain size.

ρ_g is the resistivity of the crystalline grain bulk at a doping concentration equal to N_G .

It can be seen from the electrical resistivity model represented by Eqns. (2.14) and (2.15) that the fitting parameters f and n that had to be applied to earlier models^[18,21,35], have been eliminated. Instead, the parameters b_1 and c_1 were introduced to account for the mechanism of tunneling of those carriers with insufficient energies to surmount the grain boundary potential energy barrier through this barrier that is assumed to have a width of about $7\text{\AA}$ and a height of 0.66 eV (relative to the Fermi level). From the different terms involving the constants b_1 and c_1 , the exponential term involving b_1 is the one that most affects the calculation of the resistivity and which makes Eqn. (2.14) dramatically different from previous resistivity models based on merely thermionic emission of carriers over a grain boundary potential energy barrier of zero thickness. The latter mechanism is still represented in Eqn. (2.14) by the exponential term involving the maximum potential energy barrier height in the depletion region V_b .

Segregation of impurity atoms to the grain boundaries of polysilicon films is accounted for in the calculation of N_G , the density of dopant atoms in the grain interior, this parameter being determined from the segregation model of Mandurah et al^[23,24,28], as explained earlier.

2.2.3.1 Validity and Limitations of Modelling Approaches

It should be noted here that the above resistivity model, as represented by Eqns. (2.14) and (2.15) is based on the following assumptions:

1. The solution of the current-voltage relationship is restricted to intermediate temperatures (specified earlier).
2. The average applied voltage per grain V_O is much less than the height of the grain-boundary barrier, i.e. $V_O \ll \phi$.
3. The maximum barrier height in the depletion region of the grains is much less than the height of the grain-boundary barrier, i.e. $V_b \ll \phi$.
4. The applied voltage is much less than the height of the barrier in the depletion region, i.e. $V_O \ll V_b$.
5. The applied voltage V_O across the composite grain-boundary is much less than kT .
6. Complete ionization of the dopant atoms in the grains.

The range of validity of the above assumptions in practical polysilicon films, and the consequent limitations of the above model need to be examined. Relevant considerations are discussed below with reference to the listed assumptions 1-6:

- a. Assumption 1 results in conduction being mainly controlled by carriers tunneling through the grain-boundary barriers after being thermally emitted over the depletion-region barriers; that is, carriers whose values of E_x , the energy component of the incident carrier in the x-direction, are in the range $qV_b < E_x < q\phi$. This is because, at intermediate temperatures, only a few carriers have energies higher than the maximum height of the grain boundary barriers. Thus the contribution to current by thermionic

emission of carriers over grain boundary barriers can be neglected. Furthermore, the grain boundary barriers are much thinner than the barriers in the depleted regions of the grains. Consequently, the probability of tunneling through the composite depletion region and grain boundary barriers is much lower than the probability of tunneling through the grain boundary barrier alone.

- b. Assumption 2 is normally valid in practical polysilicon films where V_0 , the average applied voltage per grain, never exceeds 100 mV. Since ϕ , the height of the grain-boundary barrier usually lies in the range from 0.5 to 0.66 eV for films with intermediate dopant concentrations (i.e., in the range 10^{18} - 10^{20} atoms/cm³), then the assumption that $V_0 \ll \phi$ is usually valid in these practical films.
- c. Assumption 3 is also valid in practical polysilicon films with the above mentioned range of dopant concentrations. For these films, it can be easily shown that the maximum value of V_b at the lowest dopant concentration within this range is of the order of 0.1 eV, V_b being inversely proportional to dopant concentration, as expressed by Eqn. (2.6). The assumption that $V_b \ll \phi$ is therefore valid in practical films with moderate dopant concentrations. At low dopant concentrations, the height of the depletion-region barrier qV_b has a maximum value of approximately

$E_g/2$ [18,20], where E_g is the band gap of single crystal silicon. Thus at low dopant concentrations, qV_b may be comparable to $q\phi$ violating assumption 3. Consequently, assumption 1 is also violated, because the contribution to current by thermionic emission of carriers over the grain-boundary barriers becomes appreciable and cannot be neglected. An approximate current-voltage relationship at low doping concentrations may be obtained, however, by assuming that the probability of tunneling through the grain-boundary barriers is equal to unity, i.e. ignoring the effect of grain boundary barriers on conduction. This is a reasonable assumption since at low doping concentrations, the grain boundary barrier is only slightly higher than the maximum height of the depletion region barrier and, also, the width of the grain boundary barrier ($7\text{\AA}$) is much less than the width of the depleted regions in the grains ($\sim 1000\text{\AA}$) [18,20,21]. Thus in this case, the conduction mechanism is dominated by thermionic emission over the depletion region barriers as proposed earlier by Seto [18] and others [20,21,45].

- d. The assumption that $V_o \ll V_b$ (assumption 4) is not always valid in practical polysilicon films. The value of the average applied voltage, V_o , per grain can be as high as 100 mV which makes it comparable to V_b . This results in the breakdown of the hyperbolic-sine I-V relationship

expressed by Eqn. (2.11). The I-V characteristics, under these circumstances, follow a more complicated law represented by Eqn. (B.20) of Appendix B. It is shown in Chapter 4 that such was the situation encountered with some of the polysilicon films studied in this work for which the large signal I-V data could not be represented by a hyperbolic-sine law.

- e. The assumption that $V_0 \ll kT$ (assumption 5) is, again, not always valid in practical polysilicon films. The condition stated in the assumption, however, defines the linear range of the current-voltage relationship from which follows the expression for the electrical resistivity of these films as expressed by Eqns. (2.14) and (2.15).
- f. The assumption of complete ionization of dopant atoms in the grain interior is known to be valid only up to a certain value of dopant concentration (corresponding to a value of N_G close to 5×10^{18} atoms/cm³) above which the dopant atoms in the grain interior are partially ionized. However, the physical situation is of a highly complicated nature involving other effects such as band-gap narrowing, conduction-band tailing, and impurity-band formation. In the face of these severe difficulties, the effect of incomplete ionization was not considered by Mandurah et al [23,24], though for heavily doped material, these various effects including incomplete ionization of impurities are

expected to modify the overall conduction relationships.

A simplified treatment of partial ionization of impurities is presented in Chapter 5.

The experimental results published with the above model show it is capable of predicting with high accuracy the resistivity of low pressure phosphorous- and arsenic-implanted polysilicon films as a function of dopant species and concentration and annealing history. Although no experimental results were shown for boron-implanted polysilicon, it was stated that the model was expected to apply equally well to the case of boron.

2.2.3.2 Discussion

In the course of the investigation undertaken by the writer on atmospheric pressure, diffused polysilicon films, the effect of high temperature annealing on the resistivity of polysilicon was studied with the aim of establishing experimental evidence concerning segregation of impurity atoms to the grain boundaries, as originally proposed in the research proposal of October 1980^[22], and similar to the annealing experiments carried out by Mandurah et al^[28] on ion-implanted polysilicon (as described in Section 2.2.1).

The annealing experiments were conducted on both boron- and phosphorous-diffused polysilicon films (see Section 4.1.4); the result for both dopants was that the segregation model of Mandurah et al^[23,24,28] represented by Eqn. (2.1) was found not to apply to diffused polysilicon.

This was a significant result in itself in that it indicated that understanding of the process of segregation of impurity atoms to the grain boundaries of polysilicon films is far from complete.

Since the above mentioned segregation model could not be used to calculate the active dopant concentration, N_G , for diffused polysilicon films, an alternative method had to be found in order to determine this important parameter that directly influences the electrical resistivity (as shown in Eqn. (2.14)).

A novel approach for the determination of N_G is proposed in Chapter 5 where it is shown that the piezoresistance effect in diffused polysilicon films can be utilized to obtain the necessary information about the active dopant concentration. The approach combines piezoresistance with the conduction model of Mandurah et al, represented by Eqns. (2.14) and (2.15) to achieve a complete characterization of the films.

2.3 CONCLUDING REMARKS

1. The polycrystalline material is composed of small crystalline grains joined together by grain boundaries. The grain boundaries have the following effects on electrical conduction in polysilicon:
 - a) An electrical resistivity much higher than similarly doped single crystal silicon.
 - b) A considerable reduction in active dopant concentration compared to single crystal silicon.
 - c) A thermally-activated electrical resistivity.

2. The different theories and conduction models that have been devised so far to account for the above mentioned effects have been presented together with a critical discussion by the writer of the limitations and inconsistencies found with these models. The different theories that have been proposed to describe the conduction mechanism in polysilicon can be grouped into two main categories: those constituting the foundation of the segregation model, and those involved in the carrier trapping model. The former is based on the assumption that a large number of impurity atoms segregate preferentially at the grain boundaries where they become electronically inactive. The latter rests on the assumption that a large number of carriers get trapped at the grain boundaries thereby reducing the number of carriers available for conduction and also creating potential energy barriers (due to the charge trapped at the grain boundaries) that impede the motion of carriers between neighbouring crystallites and consequently reduce their mobility.
3. The latest conduction models are based on a combination of the above two schools of thought: the most accurate model available to date combines the mechanisms of dopant segregation, carrier trapping and quantum mechanical tunneling of carriers at the grain boundaries. The grain boundary region is modelled as an intrinsic wide bandgap semiconductor (width $\sim 7\text{\AA}$, height $\sim 1.32\text{ eV}$) forming a heterojunction with the grains.

Thermionic emission over the potential barriers created within the grains (due to carrier trapping at the grain boundaries) and then tunneling through the grain boundaries is considered to be the carrier transport mechanism.

This model predicts with good accuracy the resistivity of polysilicon deposited at low pressure and doped by ion implantation as a function of dopant species and concentration and annealing history.

4. The segregation model that constitutes a part of the above mentioned conduction model does not, however, seem to apply to the diffused polysilicon layers that have been investigated in this research. This calls for an alternative method to assist in the complete characterization of the conduction properties of these layers, in particular to determine their active dopant concentration. An approach to this problem devised by the writer is explained in Chapter 5.

The approach makes use of the piezoresistance effect in polysilicon to infer the active dopant concentration (in the practically useful range of doping concentrations $\sim 10^{18}$ - 10^{20} cm^{-3}). Chapter 3 explains how piezoresistance can be used to achieve this purpose.

CHAPTER 3

PIEZORESISTANCE OF POLYCRYSTALLINE SILICON FILMS

It was shown in Chapter 2 that the polycrystalline structure is composed of small single crystals joined together by grain boundaries. The overall piezoresistive properties of the composite structure are expected to be the resultant of the piezoresistance components of both the crystalline bulk of the grains and their non-crystalline boundaries.

It is therefore necessary to understand the piezoresistive properties of the single crystal, those of the grain boundaries, and the way in which these properties combine before the piezoresistive properties of polysilicon can be deduced.

This chapter is divided into three sections concerned with the above three aspects of the problem. The chapter ends with a development of a model for the piezoresistance coefficient of a polycrystalline structure in terms of the individual coefficients of the grains and the grain boundaries. This model is utilized in conjunction with a recent conductivity model (Eqn. (2.15)) discussed in detail in Chapter 2 to formulate the writer's approach to the problem of modelling of conduction in diffused polysilicon films to which the segregation model represented by Eqn. (2.1) does not apply (as discussed in Chapter 2). The details of this approach and an assessment of its use in the characterization of diffused polysilicon layers are presented in Chapter 5.

3.1 Piezoresistive Properties of Single Crystal Silicon

3.1.1 Phenomenological Description [46,47]

3.1.1.1 Elastoresistance

Application of strain to a crystal causes a change in the electrical resistivity tensor, $\Delta\rho_{\alpha\beta}$, which in the linear strain approximation (in standard Cartesian tensor notation) can be written as [47]:

$$\frac{\Delta\rho_{\alpha\beta}}{\rho_0} = \sum_{\gamma,\delta=1}^3 m_{\alpha\beta,\gamma\delta} \epsilon_{\gamma\delta} \quad (3.1)$$

where $\epsilon_{\gamma\delta}$ is the strain tensor, ρ_0 is the isotropic resistivity of the unstrained crystal and $m_{\alpha\beta,\gamma\delta}$ is a dimensionless fourth rank tensor which is symmetric with respect to interchanging of indices within each pair:

$$m_{\alpha\beta,\gamma\delta} = m_{\beta\alpha,\gamma\delta} = m_{\beta\alpha,\delta\gamma} = m_{\alpha\beta,\delta\gamma} \quad (3.2)$$

The tensor $m_{\alpha\beta,\gamma\delta}$ is known as the elastoresistance tensor.

Its form and the number of independent components depend on the crystal symmetry and the symmetry of the tensor itself relative to the permutation of indices. In cubic crystals such as silicon, germanium and many of the III-V compounds, only three of the elastoresistance tensor components differ from zero.

Since all of the components of the tensors $\underline{m}$, $\underline{\rho}$, and $\underline{\epsilon}$ depend only on the pair of the indices, $\alpha\beta$, it is convenient to adopt a

simplified (engineering) notation, denoting each pair of indices by one number $[\alpha\alpha+\alpha, \alpha\beta+9-(\alpha+\beta)]$. The strain tensor and the resistivity tensor are now characterized by a single index^[47].

$$\epsilon_{11} \rightarrow \epsilon_1, \epsilon_{22} \rightarrow \epsilon_2, \epsilon_{33} \rightarrow \epsilon_3, 2\epsilon_{23} \rightarrow \epsilon_4, 2\epsilon_{31} \rightarrow \epsilon_5 \text{ and } 2\epsilon_{12} \rightarrow \epsilon_6$$

$$\rho_{11} \rightarrow \rho_1, \rho_{22} \rightarrow \rho_2, \rho_{33} \rightarrow \rho_3, 2\rho_{23} \rightarrow \rho_4, 2\rho_{31} \rightarrow \rho_5 \text{ and } 2\rho_{12} \rightarrow \rho_6$$

and the tensor $\underline{m}$ becomes a 6x6 matrix. Thus, Eqn. (3.1) can be written in the form

$$\frac{\Delta \rho_i}{\rho_0} = \sum_{j=1}^6 m_{ij} \epsilon_j \quad (3.3)$$

In a cubic crystal, with the 1, 2 and 3-axis taken along the [100], [010] and [001] crystallographic axes, the elastoresistance tensor takes the form

$$\begin{bmatrix} m_{11} & m_{12} & m_{12} & 0 & 0 & 0 \\ m_{12} & m_{11} & m_{12} & 0 & 0 & 0 \\ m_{12} & m_{12} & m_{11} & 0 & 0 & 0 \\ 0 & 0 & 0 & m_{44} & 0 & 0 \\ 0 & 0 & 0 & 0 & m_{44} & 0 \\ 0 & 0 & 0 & 0 & 0 & m_{44} \end{bmatrix} \quad (3.4)$$

3.1.1.2 Piezoresistance

To determine the piezoresistance effect, one usually applies stress to the crystal and measures the relative change in resistivity per unit stress in a given direction; therefore, it is more convenient,

in practice, to describe the piezoresistance effect in terms of a piezoresistance tensor.

$$\frac{\Delta \rho_{\alpha\beta}}{\rho_0} = \sum_{\gamma, \delta=1}^3 \pi_{\alpha\beta, \gamma\delta} P_{\gamma\delta} \quad (3.5)$$

where $P_{\gamma\delta}$ is the stress tensor, ρ_0 is the isotropic resistivity of the crystal and $\pi_{\alpha\beta, \gamma\delta}$ is the piezoresistance tensor having the same symmetry properties as the tensor $m_{\alpha\beta, \gamma\delta}$.

In the simplified engineering notation^[47]:

$$P_{11} \rightarrow P_1, P_{22} \rightarrow P_2, P_{33} \rightarrow P_3, P_{23} \rightarrow P_4, P_{31} \rightarrow P_5 \text{ and } P_{12} \rightarrow P_6$$

$$\pi_{11,11} \rightarrow \pi_{11}, 2\pi_{12,12} \rightarrow \pi_{66}, \text{ etc.}$$

Similarly, Eqn. (3.5) can be written in the form of Eqn. (3.3):

$$\frac{\Delta \rho_i}{\rho_0} = \sum_{j=1}^6 \pi_{ij} P_j \quad (3.6)$$

For a cubic crystal, the piezoresistance tensor, π_{ij} , is analogous to m_{ij} , and has the form of matrix (3.4). Equation (3.6) can be explicitly expressed in terms of the components of electric field, current and piezoresistance tensor as follows:

$$\frac{E_1}{\rho_0} = J_1 [1 + \pi_{11} P_1 + \pi_{12} (P_2 + P_3)] + \pi_{44} (J_2 P_6 + J_3 P_5) \quad (3.7a)$$

$$\frac{E_2}{\rho_0} = J_2 [1 + \pi_{11} P_2 + \pi_{12} (P_3 + P_1)] + \pi_{44} (J_3 P_4 + J_1 P_6) \quad (3.7b)$$

$$\frac{E_3}{\rho_0} = J_3 [1 + \pi_{11} P_3 + \pi_{12} (P_1 + P_2)] + \pi_{44} (J_1 P_5 + J_2 P_4) \quad (3.7c)$$

For sufficiently small deformations, the strain is directly proportional to the stress:

$$P_i = \sum_{j=1}^6 C_{ij} \epsilon_j \quad (3.8)$$

where C_{ij} = elastic stiffness tensor, which is analogous to π_{ij} , and can be expressed by a matrix of the form (3.4) in cubic crystals.

Substituting Eqn. (3.8) into Eqn. (3.5) and using the fact that, for cubic crystals, $\frac{\Delta \rho_{\alpha\beta}}{\rho_0} = - \frac{\Delta \sigma_{\alpha\beta}}{\sigma_0}$, we can show that the elastoresistance and piezoresistance tensors satisfy a relation analogous to (3.8):

$$m_{ij} = \sum_{k=1}^6 C_{kj} \pi_{ik} \quad (3.9)$$

3.1.1.3 Rotation of Axes

It is desirable to find the piezoresistance coefficient for an arbitrary direction in a crystal. The general transformation equations for the piezoresistance tensor have been worked out by Pfann and Thurston^[48] and the results have been also verified in this study. The transformations are as follows: (Let $\pi_A = \pi_{11} = \pi_{12} = \pi_{44}$.)

$$\pi'_{11} = \pi_{11} - 2\pi_A (\ell_1^2 m_1^2 + m_1^2 n_1^2 + n_1^2 \ell_1^2)$$

$$\pi'_{12} = \pi_{12} + \pi_A (\ell_1^2 \ell_2^2 + m_1^2 m_2^2 + n_1^2 n_2^2)$$

$$\pi'_{44} = \pi_{44} + 2\pi_A (\ell_1^2 \ell_3^2 + m_1^2 m_3^2 + n_1^2 n_3^2)$$

$$\pi'_{15} = 2\pi_A (\ell_1^3 \ell_3 + m_1^3 m_3 + n_1^3 n_3)$$

$$\pi'_{14} = 2\pi_A (\ell_1^3 \ell_2 \ell_3 + m_1^3 m_2 m_3 + n_1^3 n_2 n_3)$$

Analogous Coefficients

$$\pi'_{22}, \pi'_{33}$$

$$\pi'_{23} = \pi'_{32}, \pi'_{31} = \pi'_{13}$$

$$\pi'_{55}, \pi'_{66}$$

$$2\pi'_{51}, \pi'_{26} = 2\pi'_{62}$$

$$\pi'_{34} = 2\pi'_{43}, \pi'_{16} = 2\pi'_{61}$$

$$\pi'_{24} = 2\pi'_{42}, \pi'_{35} = 2\pi'_{53}$$

$$\pi'_{14} = \pi'_{56} = \pi'_{65} = 2\pi'_{41}$$

$$\pi'_{25} = \pi'_{46} = \pi'_{64} = 2\pi'_{52}$$

$$\pi'_{36} = \pi'_{45} = \pi'_{54} = 2\pi'_{63}$$

where the primed coefficients are the transformed piezoresistance coefficients in the rotated axes (1', 2' and 3'), the unprimed ones are the piezoresistance coefficients referred to the crystallographic

axes (1, 2 and 3) and (l_1, m_1, n_1) , (l_2, m_2, n_2) and (l_3, m_3, n_3) are, respectively, the direction cosines of the rotated axes (1', 2' and 3') with respect to the crystallographic axes.

3.1.2 Piezoresistance Effect in N-type Silicon

The interpretation of the piezoresistance effect in N-type silicon in terms of the many-valley model was developed by Smith^[49], Herring and Vogt^[50], and Keyes^[51]. The discussion in this section is based on the work of these authors.

For silicon, there are six positions along the cubic axes for which the conduction band reaches a minimum. The constant energy surface near the band edge consists of six symmetrically located ellipsoids as shown in Fig. 3.1. The electron mobility in the transverse direction of the ellipsoid is approximately five times as large as the mobility in the longitudinal direction ($\mu_t \approx 5\mu_l$).

When small stresses are applied to the crystal, the change induced in the conduction band energy is linearly proportional to the resulting strain components as given by the deformation potential theory:

$$\Delta E_{C1} = Z_d(\epsilon_1 + \epsilon_2 + \epsilon_3) + Z_u\epsilon_1 \quad (3.10a)$$

$$\Delta E_{C2} = Z_d(\epsilon_1 + \epsilon_2 + \epsilon_3) + Z_u\epsilon_2 \quad (3.10b)$$

$$\Delta E_{C3} = Z_d(\epsilon_1 + \epsilon_2 + \epsilon_3) + Z_u\epsilon_3 \quad (3.10c)$$

where ΔE_{C1} is the stress-induced change in the energy minimum in the

[100] and the $[1\bar{0}0]$ directions, ΔE_{C2} is the energy change in the [010] and the $[0\bar{1}0]$ directions, and ΔE_{C3} is the energy change in the [001] and the $[00\bar{1}]$ directions, Z_u and Z_d are the deformation potential constants for silicon.

Consider the case where a uniaxial [100] tensional stress, P_1 , is applied to a silicon crystal. The effect of this stress is to raise the energy levels of the two valleys along the [100] axis and to lower those of the valleys along the [010] and [001] axes, as shown in Fig. 3.1. This causes some of the electrons to transfer from the high energy valleys to the low energy ones. Because of the mobility anisotropy, the redistribution of electrons among the valleys will produce a net change in the conductivity of silicon. On the other hand, a stress applied in the [111] direction will not destroy the symmetry degeneracy of the valleys; therefore, there is no piezoresistance effect.

The starting point in the derivation of the piezoresistance coefficient is to consider the expression of the conductivity tensor for electrons in the i th valley given by^[52]:

$$\sigma_{\alpha\beta}^{(i)} = -\frac{q^2}{4\pi^3} \int \frac{\partial f_0^{(i)}}{\partial E} \tau_{\alpha\beta}^{(i)} v_{\alpha}^{(i)} v_{\beta}^{(i)} d^3K \quad (3.11)$$

where $f_0^{(i)}$ is the electron distribution function, $v_{\alpha}^{(i)} = \frac{1}{\hbar} \frac{\partial E^{(i)}}{\partial k_{\alpha}}$ is the group velocity, and $\tau^{(i)}$ is the relaxation time. The integration is carried over all permissible values of the wave vector $\underline{K}$ in the i th valley.

Fig. 3.1. Effect of a $[100]$ stress on the constant energy surfaces in the stressed crystal of silicon. (There are three valleys, not shown in the figure, symmetrically located along $[\bar{1}00]$, $[0\bar{1}0]$ and $[00\bar{1}]$ axes.)

In the case of non-degenerate statistics:

$$f_o^{(i)} = e^{(E_f - E)/kT} = e^{(E_f - E_C^{(i)})/kT} e^{(E_C^{(i)} - E)/kT}$$

Therefore,

$$f_o^{(i)} = e^{\eta_o^{(i)}} e^{-x} \quad (3.12)$$

where

$$\eta_o^{(i)} = \frac{E_f - E_C^{(i)}}{kT}$$

$$x = \frac{E - E_C^{(i)}}{kT}$$

Then, Eqn. (3.11) reduces to the form:

$$\sigma_{\alpha\beta}^{(i)} = \frac{q^2}{4\pi^3 kT} \int f_o^{(i)} \tau_{\alpha\beta}^{(i)} v_{\alpha}^{(i)} v_{\beta}^{(i)} d^3K \quad (3.13)$$

Upon the application of a shear stress (a term that is used to distinguish a general stress from the hydrostatic pressure for which $P_1 = P_2 = P_3 = P$ and $P_4 = P_5 = P_6 = 0$), each conduction band minimum is shifted by a quantity, $\Delta E_C^{(i)}$, which, in general, differs for different valleys; therefore, the many-valley degeneracy is removed. Since $E_C^{(i)}$ is independent of both the magnitude and direction of the wave vector K , and the stress induced changes in effective masses are negligible, the group velocity does not change, to the first order, with stress. The effect of stress on the carrier relaxation time is more complicated. Intra-valley scattering is not affected by stress, but inter-valley

scattering may change [53,54]. Inter-valley scattering effect will be neglected in this derivation. Under these assumptions, the stress-induced change of the conductivity tensor can be written as:

$$\Delta\sigma_{\alpha\beta}^{(i)} = - \frac{q^2}{4\pi^3 kT} \int \frac{\partial f_0^{(i)}}{\partial E} \Delta E_C^{(i)} \tau_{\alpha\beta}^{(i)} v_\alpha^{(i)} v_\beta^{(i)} d^3K \quad (3.14)$$

By transforming Eqn. (3.14) to an integration over the energy and using integration by parts, it can be shown that Eqn. (3.14) is equivalent to the more familiar expression

$$\Delta\sigma_{\alpha\beta}^{(i)} = q \mu_{\alpha\beta}^{(i)} \Delta n^{(i)} \quad (3.15)$$

where $\mu_{\alpha\beta}^{(i)}$ is the mobility tensor for electrons independent of stress in the non-degenerate case in the i th valley,

$$\mu_{\alpha\beta}^{(i)} = \frac{q}{m_{\alpha\beta}^*} \frac{\langle E\tau \rangle}{3kT/2} \quad (3.16)$$

where $\langle \rangle$ denotes the Boltzmann average for a function of energy:

$$\langle F(E) \rangle = \frac{\int_0^\infty F(E) E^{1/2} e^{-E/kT} dE}{\int_0^\infty E^{1/2} e^{-E/kT} dE} \quad (3.17)$$

where $\Delta n^{(i)}$ is the stress-induced change of electron concentration in a valley given by:

$$\Delta n^{(i)} = \frac{n_0}{kT} \Delta(E_f - E_C^{(i)}) \quad (3.18)$$

where n_0 is the electron concentration in each valley in the unstrained state. Since the total electron concentration is assumed constant,

$$\sum_{i=1}^6 \Delta n^{(i)} = \frac{n_0}{kT} [6\Delta E_f - \sum_{i=1}^6 \Delta E_C^{(i)}] = 0$$

or

$$\Delta E_f = \frac{1}{6} \sum_{i=1}^6 \Delta E_C^{(i)} \quad (3.19)$$

For the case where the uniaxial stress, P_1 , is applied to a silicon crystal along the [100] direction, it can be shown from Eqns. (3.10), (3.18) and (3.19) that the change in the electron population in each valley is given by:

$$\Delta n^{(1)} = \frac{n_0}{kT} [-\frac{2}{3} Z_u \epsilon_1 + \frac{1}{3} Z_u (\epsilon_2 + \epsilon_3)] \quad (3.20)$$

for the [100] or the $\bar{1}00$ valley,

$$\Delta n^{(2)} = \frac{n_0}{kT} [-\frac{2}{3} Z_u \epsilon_2 + \frac{1}{3} Z_u (\epsilon_3 + \epsilon_1)] \quad (3.21)$$

for the [010] or the $0\bar{1}0$ valley, and

$$\Delta n^{(3)} = \frac{n_0}{kT} [-\frac{2}{3} Z_u \epsilon_3 + \frac{1}{3} Z_u (\epsilon_1 + \epsilon_2)] \quad (3.22)$$

for the [001] or the $00\bar{1}$ valley.

we define the elastic compliance matrix $[S_{ij}]$ to be the inverse of the elastic stiffness matrix $[C_{ij}]$ whose elements are expressed by Eqn. (3.8), then we have:

$$\begin{bmatrix} \epsilon_1 \\ \epsilon_2 \\ \epsilon_3 \\ \epsilon_4 \\ \epsilon_5 \\ \epsilon_6 \end{bmatrix} = \begin{bmatrix} S_{11} & S_{12} & S_{12} & 0 & 0 & 0 \\ S_{12} & S_{11} & S_{12} & 0 & 0 & 0 \\ S_{12} & S_{12} & S_{11} & 0 & 0 & 0 \\ 0 & 0 & 0 & \frac{1}{2}S_{44} & 0 & 0 \\ 0 & 0 & 0 & 0 & \frac{1}{2}S_{44} & 0 \\ 0 & 0 & 0 & 0 & 0 & \frac{1}{2}S_{44} \end{bmatrix} \begin{bmatrix} P_1 \\ P_2=0 \\ P_3=0 \\ P_4=0 \\ P_5=0 \\ P_6=0 \end{bmatrix} \quad (3.23)$$

where

$$[S] = [C]^{-1}$$

Therefore, Eqns. (3.20) and (3.21) reduce to:

$$\Delta n^{(1)} = - \frac{2n_o}{3kT} Z_u (S_{11} - S_{12}) P_1, \quad (3.24)$$

$$\Delta n^{(2)} = n^{(3)} = \frac{n_o Z_u}{3kT} (S_{11} - S_{12}) P_1$$

Therefore, the change in the conductivity tensor due to a stress, P_1 , can be found by using Eqn. (3.15):

$$\Delta \sigma_{11}^{(1)} = q \mu_l \left(- \frac{2n_o Z_u}{3kT} \right) (S_{11} - S_{12}) P_1 \quad (3.25)$$

$$\Delta \sigma_{11}^{(2)} = q \mu_t \left(\frac{n_o Z_u}{3kT} \right) (S_{11} - S_{12}) P_1 \quad (3.26)$$

Therefore,

$$\Delta \sigma_{11}(\text{total}) = 2\Delta \sigma_{11}^{(1)} + 4\Delta \sigma_{11}^{(2)} \quad (3.27)$$

and the unstressed conductivity is given by:

$$\sigma_0 = 2q(\mu_l + 2\mu_t)n_0 \quad (3.28)$$

and by definition:

$$\pi_{11} = \frac{\Delta\rho_{11}/\rho_0}{P_1} = - \frac{\Delta\sigma_{11}/\sigma_0}{P_1}$$

i.e.

$$\pi_{11} = - \frac{2}{3} (S_{11} - S_{12}) \frac{Z_u}{kT} \left(\frac{K_{m-1}}{K_{m+1}} \right) \quad (3.29)$$

where $K_m = \frac{\mu_t}{\mu_l}$ is the mobility anisotropy in a valley.

In the lightly doped silicon where Boltzmann's statistics are applicable, the electron transfer model predicts that the elasto-resistance effect in N-type silicon is of the order of $\frac{Z_u}{kT}$. At temperatures above 150°K for silicon^[53], inter-valley scattering becomes increasingly important. Inter-valley scattering is expected to change with stress because of the effect of the stress-induced shifts of energy on the probabilities for scattering from one valley to another^[51,53]. It is difficult to make any quantitative predictions for the contribution of the inter-valley scattering to piezoresistance because the exact scattering mechanism in silicon is not well known. However, for silicon at 300°K, a rough estimate of this contribution can be made in the following manner:

From Eqn. (3.29) with:

$$\pi_{11} = -102.2 \times 10^{-12} \text{ cm}^2/\text{dyne} \text{ (as determined experimentally by Smith}^{[49]}\text{)}$$

$$S_{11} = 0.768 \times 10^{-12} \text{ cm}^2/\text{dyne}^{[47]}$$

$$S_{12} = -0.214 \times 10^{-12} \text{ cm}^2/\text{dyne}^{[47]}$$

$$K_m \approx 5$$

an effective value for Z_u that takes into account the effect of inter-valley scattering on the piezoresistance coefficient π_{11} can be calculated,

$$Z_{u\text{eff}} = 11.16 \text{ eV}$$

But, we know from measurements that the actual value of the deformation potential constant, Z_u , lies somewhere between 8 and 9 eV^[55].

Therefore, the contribution of inter-valley scattering to the deformation potential constant Z_u and consequently to the piezoresistance coefficient π_{11} is about $\frac{11.16-8.5}{11.16} \approx 24\%$ at room temperature.

The discussion of piezoresistance in N-type silicon has been so far concerned with the case of light doping, the effect of heavy doping on the piezoresistance coefficient is discussed in a later section (after the study of the piezoresistive properties of P-silicon).

3.1.3 Piezoresistance Effect in P-type Silicon

Large piezoresistance effects also arise in P-type silicon and germanium due to stress-induced changes in their valence band structures. The phenomenological situation is, however, very different to that in silicon, and is much more difficult to treat analytically;

quantitative understanding has not, as yet, been achieved to the same degree as in N-type silicon. The valence band of silicon^[46] consists of 3 branches (Fig. 3.2), all of which have a single extremum at $\underline{K}=0$. The two upper bands are degenerate: V_1 gives rise to heavy holes and V_2 to light holes. V_3 is called the split-off band, which is usually neglected when performing hole population calculations. The constant energy surfaces associated with V_1 and V_2 both exhibit cubic symmetry; they can be thought of as spheres which have been distorted toward cubic chapes, and are referred to as warped spheres. The V_3 band has a spherical energy surface and thus an isotropic effective mass.

Near the band edge, the hole energy spectrum is given by^[46]:

$$E_O^{(1,2)}(\underline{K}) = AK^2 \pm E_{KK} \quad (3.30)$$

The three axes in $\underline{K}$ -space are along the [100], [010] and [001] directions and

$$E_{KK}^2 = B^2 K^4 + C^2 (K_1^2 K_2^2 + K_2^2 K_3^2 + K_3^2 K_1^2) \quad (3.31)$$

where A, B and C are constants. In Eqn. (3.30), the plus sign corresponds to the energy of the heavy holes, $E^{(1)}$, and the minus sign to the energy of the light holes, $E^{(2)}$.

In many applications, the warped energy surfaces of the V_1 and V_2 bands are approximated by spheres having effective masses equal to averages of the hole masses which are dependent on the direction of $\underline{K}$ ^[46]:

Fig. 3.2. Valence band of silicon near $K=0$ (top); (110) cross-section of the constant energy surface (bottom).

$$E_O^{(1,2)}(\underline{K}) = \frac{\hbar^2 K^2}{2m^*(1,2)} = (A \pm \bar{B})K^2 \quad (3.32)$$

where

$$\bar{B} = (B^2 + \frac{C^2}{5})^{\frac{1}{2}}$$

Application of stress to a silicon crystal tends to reduce the crystal symmetry, and change the hole energy spectrum through deformation of the lattice. The discussion of the piezoresistance effect in P-type silicon presented in this section is based on a publication by Bir and Pikus^[56,57]. The formulas and the approximations involved in their model were all verified and their results were reproduced.

The general expression for the hole spectrum in the strained lattice is given by^[46]:

$$E^{(1,2)}(\underline{K}) = AK^2 + a\epsilon \pm (E_{KK}^2 + E_{\epsilon K}^2 + E_{\epsilon\epsilon}^2)^{\frac{1}{2}} \quad (3.33)$$

where

$$E_{\epsilon K}^2 = Bb[3(K_1^2\epsilon_1 + K_2^2\epsilon_2 + K_3^2\epsilon_3) - K^2\epsilon] + Dd(K_1K_2\epsilon_6 + K_2K_3\epsilon_4 + K_3K_1\epsilon_5)$$

$$E_{\epsilon\epsilon}^2 = \frac{b^2}{2} [(\epsilon_1 - \epsilon_2)^2 + (\epsilon_2 - \epsilon_3)^2 + (\epsilon_3 - \epsilon_1)^2] + \frac{d^2}{4} (\epsilon_4^2 + \epsilon_5^2 + \epsilon_6^2)$$

The ϵ_i 's are the components of the strain tensor.

$$\epsilon = \epsilon_1 + \epsilon_2 + \epsilon_3$$

$$D = (3B^2 + C^2)^{\frac{1}{2}}$$

a, b and d are deformation potential constants: a determines the energy shifts under hydrostatic pressure; b determines the splitting of the valence bands due to dilation along the [100], [010] and [001] axes; d fills this role for the <111> axes.

For practical purposes, it is sufficient to consider the hole energy spectrum in silicon for the low stress and high temperature (>50°K) case when $E_{KK} \gg E_{EK} \gg E_{EE}$. Using this condition and Eqn. (3.32), Eqn. (3.33) can be approximated by:

$$E^{(1,2)}(\underline{K}) = E_O^{(1,2)} + a\varepsilon \pm \frac{1}{2BK^2} \{ Bb[3(K_1^2\varepsilon_1 + K_2^2\varepsilon_2 + K_3^2\varepsilon_3) - K^2\varepsilon] + Dd[K_1K_2\varepsilon_6 + K_2K_3\varepsilon_4 + K_3K_1\varepsilon_5] \} \quad (3.34)$$

where $E_O^{(1,2)}$ is the energy in the unstressed state.

The energy shift $\Delta E^{(1,2)}$ is therefore given by:

$$\Delta E^{(1,2)} = a\varepsilon \pm \frac{3Bb}{2B} \left[\frac{K_1^2\varepsilon_1 + K_2^2\varepsilon_2 + K_3^2\varepsilon_3}{K^2} - \frac{\varepsilon}{3} \right] \pm \frac{Dd}{2B} \left[\frac{K_1K_2\varepsilon_6 + K_2K_3\varepsilon_4 + K_3K_1\varepsilon_5}{K^2} \right] \quad (3.35)$$

From Eqn. (3.35), it is obvious that the stress-induced energy change, $\Delta E^{(1,2)}$, depends only on the direction of $\underline{K}$ (i.e. on the angles θ and ϕ in K-space), but not on its magnitude; therefore, a shear stress tends to distort the constant energy surface and produces a strong anisotropy in the hole group velocity. This is the main source of the hole piezoresistance in silicon in contrast to N-type

silicon where changes in group velocities are negligible compared to the carrier redistribution effect.

To derive a theoretical expression for the stress-induced change in the conductivity tensor, one has to consider the effect of energy spectrum change on the group velocity, the distribution function and the relaxation time.

According to Eqn. (3.13), the change of the hole conductivity in the i th band is given by:

$$\Delta\sigma_{\alpha\beta}^{(i)} = \frac{q^2}{4\pi^3 kT} \left\{ \int \frac{\partial f_0^{(i)} \tau^{(i)}}{\partial E} v_{\alpha}^{(i)} v_{\beta}^{(i)} d^3k + \frac{1}{h} \int f_0^{(i)} \tau^{(i)} \left(\frac{\partial \Delta E^{(i)}}{\partial K_{\alpha}} v_{\beta}^{(i)} + \frac{\partial \Delta E^{(i)}}{\partial K_{\beta}} v_{\alpha}^{(i)} \right) d^3k \right\} \quad (3.36)$$

If the transition probabilities are isotropic, it can be shown that the relaxation time is also isotropic, depending only on the energy:

$$\Delta\tau^{(i)} = \frac{\partial \tau^{(i)}}{\partial E} \Delta E^{(i)} \quad (3.37)$$

In Eqn. (3.36) employing the relation

$$\int \Delta E^{(i)} d\Omega_K = 0 \quad (3.38)$$

for a pure shear strain tensor, where $d\Omega_K$ is the solid angle element in K-space; it can be shown that Eqn. (3.36) can be simplified to:

$$\Delta\sigma_{\alpha\beta}^{(i)} = - \frac{q^2}{4\pi^3 kT} \int \frac{\partial (f_0^{(i)} \tau^{(i)})}{\partial E} v_{\alpha}^{(i)} v_{\beta}^{(i)} \Delta E^{(i)} d^3K \quad (3.39)$$

Therefore,

$$\frac{\Delta \sigma_{\alpha\beta}^{(i)}}{\sigma_0^{(i)}} = \frac{\langle \tau^{(i)} \rangle}{\langle E^{(i)} \tau^{(i)} \rangle} \psi_{\alpha\beta}^{(i)} \quad (3.40)$$

where

$$\psi_{\alpha\beta}^{(i)} = \frac{q}{8\pi} \int \frac{K_{\alpha}^{(i)} K_{\beta}^{(i)}}{K^2} \Delta E^{(i)} d\Omega_K \quad (3.41)$$

Substituting the value of $\Delta E^{(1,2)}$ from Eqn. (3.35), we have:

$$\psi_{12}^{(1,2)} = \pm \frac{3}{20} \frac{Dd}{B} \epsilon_6 \quad (3.42)$$

[Note that $\epsilon_6 \equiv 2\epsilon_{12}$.]

The shear piezoresistance coefficient, π_{44} , is then given by:

$$\pi_{44} = \frac{3}{20} \frac{Dd}{B} \frac{1}{kT(S + \frac{3}{2})} \frac{\left[\frac{m_1}{m_2} \right]^{\frac{1}{2}} - 1}{\left[\frac{m_1}{m_2} \right]^{\frac{1}{2}} + 1} S_{44} \quad (3.43)$$

In the derivation of Eqn. (3.43), it was assumed that the dependence of the relaxation time, $\tau^{(i)}$, on the energy can be expressed by a power law in the following manner:

$$\tau^{(i)}(E) = \tau_0^{(i)} \left(\frac{E - E_v}{kT} \right)^S \quad (3.44)$$

A comment should now be made on the adequacy of the above presented model for the piezoresistance of P-type silicon as judged by comparison with some experimental results.

The value of the room temperature piezoresistance coefficient π_{44} (as obtained experimentally by Smith^[49]) is 138.1×10^{-12} cm²/dyne.

Based on this value of π_{44} , the values of the heavy and light hole effective masses (m_1^* and m_2^*)^[40], the value of the elastic compliance constant, S_{44} ^[47], and the values of the inverse mass band parameters D and $\bar{B}$ ^[58,59] (all appearing in Eqn. (3.43)), a value of the deformation potential constant d as predicted by the theory can be calculated to be ~33 eV.

A value of d much less than this value was reported for silicon as a result of measurements that were carried out by some investigators^[59] after the theoretical model contributed by Bir and Pikus was published. The measurements revealed a value of d of only about 1.5 eV which presents an order of magnitude discrepancy between theory and experiments. It is therefore suggested that the Bir and Pikus model for the piezoresistance of P-silicon is inadequate for the prediction of the large shear piezoresistance effect observed for holes in single crystal silicon, an effect that has been frequently verified experimentally and even utilized in practical transducers (e.g. strain gauges), but whose physical origin remains unexplained and open to conjecture.

The reason for the large discrepancy between theory and experiment in P-silicon is thought to be either the inadequacy of the assumption that the energy surfaces can be approximated by spheres in the absence of stress, or the neglect of the stress-induced changes in the inverse mass band parameters (A , B , C , ... etc.) which is

equivalent to neglecting the effect of stress on the matrix elements (in the matrix representation of hole wave functions), or both.

Both approximations were introduced to facilitate the mathematical analysis and make it possible to obtain a closed form expression for the piezoresistance coefficient of P-silicon; the assumptions, however, do not have a firm physical foundation and therefore it is suggested that a more accurate (though much more complicated) model may be achieved by considering the non-spherical nature of the valence band constant energy surfaces and also the effect of stress on the matrix elements in the matrix representation of hole wave functions.

3.1.4 Effect of High Doping (Statistical Degeneracy) [51]

For heavily doped silicon, the carrier distribution is described by the Fermi-Dirac function instead of the Boltzmann function:

$$f_o = \frac{1}{1 + e^{(E - E_f)/kT}} \quad (3.45)$$

Replacing f_o in Eqn. (3.11) with Eqn. (3.45) and repeating the derivation for the piezoresistance coefficients in both N- and P-type silicon, it can be shown (assuming $\tau = \tau_o \left(\frac{E - E_c(v)}{kT} \right)^S$) for a statistically degenerate silicon that

$$\pi_{ij} = \lambda_s(\eta_o) \pi_{o,ij} \quad (3.46)$$

with

$$\lambda_s(\eta_o) = \frac{F_{S-1/2}(\eta_o)}{F_{S+1/2}(\eta_o)}$$

$$\eta_o = \frac{E_{fo} - E_{co}}{kT}$$

(The zero subscript refers to the unstressed state.)

where $\pi_{o,ij}$ is the piezoresistance coefficient for a non-degenerate silicon given by Eqns. (3.29) and (3.43), and

$$F_S(\eta_o) = \frac{1}{\Gamma(S+1)} \int_0^\infty \frac{x^S dx}{1 + e^{x - \eta_o}}$$

is the well-tabulated Fermi-Dirac integral [60].

The development of theory along these lines results in the following predictions regarding the effect of high doping on the piezoresistance of N- silicon:

- a. A value of piezoresistance coefficient π_{11} (at high doping) that is larger than the experimentally obtained value [61] by a factor that ranges from 2 to 3 depending on the scattering mechanism considered in the model.
- b. A decrease in the magnitude of the piezoresistance coefficient as the doping is increased, and
- c. An accompanying decrease in the temperature dependence of the coefficient.

The reason for the discrepancy between theory and experiment in a) is thought to be mainly due to the lack of accurate information about the physical nature of the scattering processes and their effect on the relaxation time and its energy dependence. In an attempt to improve the theoretical prediction, the writer has studied the effect

of considering two scattering mechanisms acting simultaneously on the predicted value of $\lambda_s(\eta_0)$ in Eqn. (3.46). The value of $\lambda_s(\eta_0)$ was obtained for different values of the index S corresponding to different scattering mechanisms^[62] [S ranged from -0.5, for acoustical phonon scattering, to 1.5 for ionized impurity scattering] at different temperatures and at a sufficiently high doping level ($N_D = 10^{20} \text{ cm}^{-3}$). The result of the calculations (see Table 3.1) shows that $\lambda_s(\eta_0)$ increases monotonically with increasing the value of S from -0.5 to 1.5. This observation, together with the fact that several relaxation times associated with different scattering mechanisms combine according to the addition-of-reciprocals rule^[62] show that a consideration of a multiple scattering mechanism would not result in any improvement in the prediction; instead, a consideration of only the acoustical phonon scattering would yield a predicted value of $\lambda_s(\eta_0)$ that most closely approximates the actual observed value. This was also verified (through calculations) for the case of scattering by acoustical phonons and ionized impurities simultaneously.

The discrepancy is also thought to be partly due to a residual strain that might be present in the silicon lattice at high concentrations of impurity atoms close to the solid solubility limit.

Based on the above discussion, Eqn. (3.46) should be regarded as a qualitative rather than a quantitative means of predicting the magnitude and the temperature dependence of the piezoresistance coefficient in heavily doped silicon. These predictions (i.e. the decrease in the magnitude of π_{1j} and its temperature dependence with

Table 3.1. Comparison between theoretical and experimental [61] values of $\lambda_s(\eta_o)$ for N-type silicon at different temperatures and for different scattering mechanisms (with different values of S). $N_D = 10^{20} \text{ cm}^{-3}$.

$t, ^\circ\text{C}$	-100	-50	0	27	50	100
$T, ^\circ\text{K}$	173	223	273	300	323	373
Theoretical $S = -\frac{1}{2}$ $S = 0$ $S = \frac{1}{2}$ $S = 3/2$ $\lambda_s(\eta_o)$	0.580	0.622	0.656	0.672	0.684	0.708
	0.672	0.709	0.737	0.751	0.761	0.780
	0.745	0.776	0.800	0.811	0.819	0.834
	0.847	0.869	0.885	0.892	0.897	0.907
Experimental $\lambda_s(\eta_o)$ [61]	0.205	0.282	0.346	0.380	0.409	0.440

increasing doping density) have been frequently verified in practice, and the second effect has been utilized in the fabrication of strain gauges and pressure transducers with very low temperature sensitivity.

The foregoing discussion has been concerned with heavily doped N- silicon. Although there have been no theoretical attempts to predict the effect of high doping on the piezoresistance coefficient of P- silicon, it has been experimentally verified that the behaviour is similar to that observed with N- silicon from a qualitative point of view; the magnitude of the piezoresistance coefficient and its temperature dependence decrease with increasing doping density (see, for example, Chapter 10 of Reference 47).

3.2 Piezoresistive Properties of Grain Boundary

There is no information in the literature on the piezoresistance of the grain boundary. Seto^[25] reported some experimental results on the piezoresistive properties of boron-implanted polysilicon films deposited by CVD on aluminum-oxide-insulated molybdenum substrates. Comparing the values of the gauge factor he obtained for his polysilicon films to the calculated average gauge factor of the neutral bulk of the crystallites, he found a good correlation (with a deviation less than 30%); therefore he concluded that the piezoresistance of polysilicon is dominated by the bulk of the crystallites. Seto's polysilicon was heavily doped thereby making the width of the grain boundary region very small compared to the undepleted region; the assumption of a prevailing bulk piezoresistance in this case is expected to be adequate. This assumption, however, will cease to be

valid at lower doping densities where the width of the depleted region of the crystallites becomes a significant portion of the crystallite size, and it is thought that the piezoresistance effect, if any, would be mainly due to the effect of stress on the resistance of the grain boundary through the stress dependence of the mechanism of majority carrier trapping at the grain boundaries; stress could affect the density of these traps and their energy distribution^[63].

In Chapter 4, it is shown that the piezoresistance effect in diffused polysilicon layers is measurable only under conditions of sufficiently high doping concentrations for which the piezoresistance is dominated by the crystalline bulk. As the doping concentration is lowered, random current fluctuations, believed to be associated with the trapping mechanism and its stress dependence, became evident. At a certain (relatively low) level of doping concentration (where the depleted region of a crystallite extends over a non-negligible portion of its size) it was found to be practically impossible to obtain any representative value for the piezoresistive coefficient due to the presence of these random current effects.

3.3 Piezoresistance Effect in Polycrystalline Silicon

The polycrystalline structure (as mentioned in the previous chapter) is composed of small neighbouring single crystals (crystallites) of different crystallographic orientations, joined together by grain boundaries that represent transitional regions between the crystallites and therefore possess a highly disordered structure. Electrical

conduction and consequently piezoresistance of polysilicon can then be analytically studied by treating polysilicon as a composite structure having two distinct materials; the grain interior (or bulk of crystallites) and the grain boundary, with two different electrical conductivities and two different piezoresistance coefficients.

A simple model for the piezoresistance of polysilicon based on this treatment is developed in this section. It is assumed that the polysilicon film is subject to a uniform uniaxial stress whose direction coincides with the direction of current flow in the film, Fig. 3.3. The polysilicon film is modelled as rectangular parallel-piped^s (with dimensions $L_g \times L_g$ in the plane of the film) of single crystal silicon, or crystallites, surrounded by grain boundaries of width L_{gb}^* . The single crystal parallelepipeds are assumed to have their orientations falling into one of the three categories of crystallographic orientations that are frequently encountered in practice, namely the [100], [110], or [111] orientations^[25], with an equal probability of distribution of the densities of these three orientations for all directions in the film.

Under these assumptions, the following relations can be easily obtained:

$$R_{series} = \frac{3m}{t} \left[\rho_{g_o} (1 + \pi \frac{L_{gb}}{L_g} p) + \frac{L_{gb}}{L_g} \rho_{g_{bo}} (1 + \pi \frac{L_g}{L_{gb}} p) \right] \quad (3.47)$$

$$R_{shunt} = \frac{3m}{t} \left(1 + \frac{L_g}{L_{gb}} \right) \rho_{g_{bo}} (1 + \pi \frac{L_g}{L_{gb}} p) \quad (3.48)$$

* Similar treatments of conduction in composite materials were considered by previous investigators [80a, 80b].

Fig. 3.3. A model for polysilicon as an inhomogeneous structure, the building block is shown at the lower right corner.

where R_{series} is the stressed resistance of the series path of the current which comprises the crystalline bulk in series with a grain boundary layer. R_{shunt} is the stressed resistance of the grain boundary in shunt with the series path of the current.

ρ_{g_0} is the unstressed resistivity of the crystallite bulk.

$\rho_{g_b_0}$ is the unstressed resistivity of the grain boundary.

$\bar{\pi}_g$ is the average bulk piezoresistance coefficient for the [100], [110] and [111] crystallographic directions.

$$\bar{\pi}_g = \frac{\pi_{[100]} + \pi_{[110]} + \pi_{[111]}}{3}$$

π_{g_b} is the piezoresistance coefficient of the grain boundary.

m is the density of any of the three crystallographic orientations for any direction in the film.

L_g is the length of the crystallite.

L_{g_b} is the width of the grain boundary region.

t is the thickness of the film.

p is the uniaxial stress.

The total stressed resistance of the polysilicon film is then obtained as a parallel combination of R_{series} and R_{shunt} :

$$R_{\text{poly}} = \frac{R_{\text{series}} \cdot R_{\text{shunt}}}{R_{\text{series}} + R_{\text{shunt}}} = \left(\frac{3m}{t} \right) \rho_{\text{poly}} \quad (3.19)$$

The last relationship is used to derive an expression for the resistivity of the composite structure, ρ_{poly} , under a stress p :

$$\rho_{\text{poly}} = \frac{(1 + \frac{L_g}{L_{g_b}}) \rho_{g_{b_0}} [\rho_{g_0} (1 + \pi_{g_p}) + \frac{L_{g_b}}{L_g} \rho_{g_{b_0}} (1 + \pi_{g_b} p)]}{\rho_{g_0} (\frac{1 + \pi_{g_p}}{1 + \pi_{g_b} p}) + \rho_{g_{b_0}} (1 + \frac{L_g}{L_{g_b}} + \frac{L_{g_b}}{L_g})} \quad (3.50)$$

The unstressed resistivity of the film is given by:

$$(\rho_0)_{\text{poly}} = \frac{(1 + \frac{L_g}{L_{g_b}}) \rho_{g_{b_0}} (\rho_{g_0} + \frac{L_{g_b}}{L_g} \rho_{g_{b_0}})}{\rho_{g_0} + \rho_{g_{b_0}} (1 + \frac{L_g}{L_{g_b}} + \frac{L_{g_b}}{L_g})} \quad (3.51)$$

The piezoresistance coefficient for the composite film can then be obtained as follows:

$$\pi_{\text{poly}} = \frac{\Delta \rho_{\text{poly}} / (\rho_0)_{\text{poly}}}{p} = \frac{\rho_{\text{poly}} - (\rho_0)_{\text{poly}}}{p (\rho_0)_{\text{poly}}}$$

Therefore,

$$\pi_{\text{poly}} = \frac{1}{p} \frac{\rho_{g_0}^2 (\frac{1 + \pi_{g_p}}{1 + \pi_{g_b} p}) \pi_{g_b} p + \rho_{g_0} \rho_{g_{b_0}} (1 + \frac{L_g}{L_{g_b}} + \frac{L_{g_b}}{L_g}) \pi_{g_p} p + \frac{L_{g_b}}{L_g} \rho_{g_0} \rho_{g_{b_0}} (1 + \pi_{g_b} p - \frac{1 + \pi_{g_p}}{1 + \pi_{g_b} p}) + \frac{L_{g_b}}{L_g} \rho_{g_{b_0}}^2 (1 + \frac{L_g}{L_{g_b}} + \frac{L_{g_b}}{L_g}) \pi_{g_b} p}{[\rho_{g_0} (\frac{1 + \pi_{g_p}}{1 + \pi_{g_b} p}) + \rho_{g_{b_0}} (1 + \frac{L_g}{L_{g_b}} + \frac{L_{g_b}}{L_g})] [\rho_{g_0} + \rho_{g_{b_0}} \frac{L_{g_b}}{L_g}]} \quad (3.52)$$

The expression for π_{poly} given by Eqn. (3.52) can be greatly simplified by making certain assumptions that are known to be valid for practical polysilicon films. These are:

- a. $|\bar{\pi}_g p| \ll 1$, for small stresses
- b. $\frac{L_{g_b}}{L_g} \ll 1$, L_{g_b} being on the order of $10\text{\AA}$, i.e. comparable to interatomic distances
- c. $\frac{\rho_{g_o}}{\rho_{g_{b_o}}} \ll 1$, which is equivalent to assuming that the grain boundary has much higher resistivity than the grain interior, a universally accepted assumption.

Under these assumptions, Eqn. (3.52) reduces to:

$$\pi_{\text{poly}} = \frac{\rho_{g_o} \bar{\pi}_g + \frac{L_{g_b}}{L_g} \rho_{g_{b_o}} \pi_{g_b}}{\rho_{g_o} + \rho_{g_{b_o}} \frac{L_{g_b}}{L_g}} \quad (3.53)$$

The piezoresistance coefficient of the polycrystalline film is expressible in terms of the four parameters: ρ_{g_o} , $\rho_{g_{b_o}}$, $\bar{\pi}_g$ and π_{g_b} which are, respectively, the resistivities of the crystallite and the grain boundary, and the piezoresistance coefficients associated with these two regions. Inspection of Eqn. (3.53) reveals the following predictions:

- i) As the grain size L goes to ∞ , the piezoresistance coefficient of the polysilicon film, π_{poly} , approaches that of the crystallite bulk, $\bar{\pi}_g$, which is consistent with what to be expected in practice.

- ii) If the piezoresistance coefficient associated with the grain boundary, π_{gb} , is much less than that of the bulk of crystallites, then Eqn. (3.53) can be further simplified to:

$$\pi_{poly} = \frac{\bar{\pi}_g}{1 + \frac{\rho_{gb}}{\rho_{g_0}} \frac{L_{gb}}{L_g}} \quad (3.54)$$

or

$$\pi_{poly} (\rho_o)_{poly} = \bar{\pi}_g \rho_{g_0} \quad (3.55)$$

Equation (3.55) can be used to determine the effective dopant concentration in polysilicon (over the practically useful range of macroscopic doping concentrations $\sim 10^{18}$ - 10^{20} atoms/cm³ for which the piezoresistance is dominated by the crystalline grains interior) as follows. By measuring the unstressed resistivity of polysilicon $((\rho_o)_{poly})$ and its piezoresistive coefficient (π_{poly}) the left-hand side of Eqn. (3.55) is calculated; consequently, the right-hand side of the equation is known. Since the product on the right-hand side is a function of the doping concentration in single crystal silicon (as both $\bar{\pi}_g$ and ρ_{g_0} are functions of the doping concentration) hence, the active dopant in the grains can be determined using the well documented data for single crystal silicon.

Equation (2.15) can then be used to calculate the grain size of polysilicon [refer to Chapter 2, Section 2.2.3].

The simple procedure described above constitutes the basis of the writer's novel approach to the modelling of diffused polysilicon films presented in Chapter 5 of this thesis.

3.4 Concluding Remarks

1. The piezoresistance effect in polysilicon is the resultant of the contributions of both the bulk of crystallites and the grain boundary.
2. The piezoresistive properties of N- and P- single crystal silicon have been studied. In the case of N- silicon, the piezoresistance effect is reasonably well explained in terms of an electron transfer (or redistribution) mechanism that accounts for at least 75% of the observed stress-sensitivity, with the remaining 25% contributed by the stress-dependent mechanism of inter-valley scattering. The case of P- silicon is complicated by the existence of two degenerate valence band maxima at $K=0$ resulting in constant energy surfaces that are not spherical in nature, thereby making any analytical treatment of the problem much more difficult than the case of the ellipsoidal energy surfaces associated with the conduction band. The piezoresistive properties of P- silicon are mainly due to the stress-induced changes in the group velocity of holes in the valence band. The Bir and Pikus model for the prediction of the piezoresistance coefficient of P-

silicon has been discussed. It has been shown that an order of magnitude discrepancy exists between the value of π_{ij} as predicted by the model and its actual observed value. This discrepancy has been attributed to two main approximations involved in the model: the approximation of constant energy surfaces (in the absence of stress) by spheres, and the neglect of the effect of stress on the matrix elements of the hole Hamiltonian.

In both N- and P- silicon, the piezoresistance coefficient varies with temperature as $1/T$ at low doping levels. The effect of high doping on the magnitude of the piezoresistance coefficient and its temperature dependence has also been studied. The theory for heavily doped N- silicon is reasonably adequate though a discrepancy within a factor ranging from 2 to 3 exists between theory and experiment (depending on the scattering mechanism considered in the theoretical model for piezoresistance). This discrepancy can not be eliminated by a consideration of multiple scattering mechanisms.

In the case of P-silicon, there is no theoretical treatment in the literature of the effect of high doping, the situation being too difficult to handle analytically.

For both N- and P- silicon, experiments show a tendency towards lower values of π_{ij} and its temperature dependence as the doping is increased.

2

3. Experiment suggests that the effects of stress on the grain boundary region are inherently 'noisy'. When the doping of the polysilicon film is sufficiently low for the boundary region to exert significant influence, random current fluctuations preclude measurement of the overall piezoresistance coefficient - such a polysilicon film is unlikely to be of practical importance from the point of view of utilization of the piezoresistance effect.
4. A model has been developed by the writer to predict the piezoresistance coefficient of the polycrystalline structure. The model is based on four basic parameters: the two piezoresistance coefficients of the grain interior and the grain boundaries, and the resistivities of these two regions.
5. The above mentioned model can be used to determine the effective dopant concentration in diffused polysilicon films, a parameter that directly influences the calculation of polysilicon resistivity (as shown in Chapter 2, Section 2.2.3).

CHAPTER 4

ELECTRICAL CONDUCTION AND PIEZORESISTANCE OF DIFFUSED POLYSILICON FILMS

The different theories and models for electrical conduction and piezoresistance of polysilicon films were reviewed in Chapters 2 and 3. In Chapter 2, it was shown that all the models and data available in the literature are obtained for ion-implanted polysilicon; no data on diffused polysilicon is available. It was therefore necessary to obtain such data in order to establish a conduction model for diffused films. It was also necessary to experimentally test the different hypotheses developed for the modelling of ion-implanted layers to see if they are valid for those doped by diffusion. In particular, attention was directed at investigating the possible segregation of impurity atoms at the grain boundaries to establish whether it occurred in the first place, and then to quantitatively characterize it.

Chapter 3 contains a model for piezoresistance of polysilicon that also needed to be validated through calibrated measurements of the stress-induced changes in the resistance of polysilicon films.

This chapter presents the experimental investigation carried out in this work to obtain the above information.

The experimental procedure applied in the investigation of the diffused polysilicon films is laid out in Section 4.1. Section 4.2 includes the results of the experiments together with a discussion of

the implications of the different observations in the modelling of electrical conduction and piezoresistance of diffused polysilicon.

4.1 Experimental Procedure

4.1.1 Film Preparation

The films used in this study were deposited in an atmospheric pressure chemical vapour deposition (CVD) horizontal reactor (r.f. heated) in the department of Electronics at Carleton University. Silane was the source gas, and nitrogen was the diluent. The films were deposited at two different deposition temperatures (700°C and 900°C) to examine the effect of deposition temperature on the grain size of the polysilicon films. The film thickness was $0.5 \mu\text{m} \pm 0.02 \mu\text{m}$, as measured by interferometry^[64]. The substrate was a 300 μm thick <100>-oriented single crystal silicon wafer covered with 4000Å of thermally grown silicon dioxide. In the case of phosphorous-doped polysilicon films, the substrate was P-type, 2-3 Ωcm silicon, while for boron-doped films, the substrate was N-type, 1-2 Ωcm . This arrangement ensured electrical isolation between the deposited films and their substrates even if the grown oxide contained any flaws (such as pinholes) that would render it ineffective as an insulator.

The films were doped by impurity diffusion: boron-doped films were diffused from a boron tri-bromide (BBr_3) source, while phosphorous-doped films were diffused from a phosphorous oxy-chloride (POCl_3) source. A standard two-step diffusion process was employed in which the predeposition time was fixed at 2 minutes, while the

predeposition temperature, was varied from 800°C to 1000°C to obtain different sheet resistance values in the diffused films. The flow rates of dopant gases (i.e. BBr_3 and POCl_3) were also varied to vary the sheet resistance of the films. The drive-in temperature was fixed at 1075°C and the drive-in time at 10 minutes. Thus, the process used for the fabrication of the polysilicon films was essentially the same as for making MOS structures for integrated circuits, the polysilicon film being laid down on 'thermal oxide'.

In patterning the polysilicon films, two different techniques were initially experimented with in order to compare the relative accuracies of the pattern dimensions obtained. In the first technique, the polysilicon pattern was defined by selective etching prior to diffusion of impurities, as usually done in the fabrication of MOS integrated circuits. In the second, the polysilicon pattern was defined by selective impurity diffusion. Results of early tests (involving a comparison of sheet resistance values obtained on different test patterns) which were carried out on the two differently patterned films favoured the first technique over the second, the latter resulting in a significant spread out of the lateral dimensions of the pattern due to the higher diffusivity of dopant atoms in the polycrystalline film, with a consequent larger lateral diffusion than that observed in single crystal silicon. The second technique was therefore abandoned.

Some of the diffused polysilicon wafers were unpatterned - i.e. they had a continuous polysilicon layer over the entire surface

of the wafer; these wafers were used for two purposes: to obtain samples (in the form of squares 1 cm x 1 cm) for inspection of grain size by the scanning electron microscope (SEM), and also for high temperature annealing experiments designed to investigate the segregation of impurity atoms to the grain boundaries, as will be shown later.

Patterned as well as unpatterned single crystal silicon wafers (P-type for phosphorous diffusion and N-type for boron diffusion) were included with the main wafers during the diffusion runs, and served as monitor wafers to help obtain an estimate of the macroscopic dopant concentration in polysilicon films. This was done by the aid of a computer simulation using SUPREM II (Stanford University Process Engineering Models, a program for IC process modelling and simulation) in conjunction with sheet resistance values measured on single crystal monitor wafers (both patterned and unpatterned).

In order to infer the value of macroscopic dopant concentration in diffused polysilicon films from the computer simulation, two assumptions were made:

- 1) The total dopant charge (per unit surface area), deposited during the diffusion process, in the polysilicon film is equal to that in the similarly processed single crystal monitor wafers.
- 2) The dopant atoms in the polysilicon films are uniformly distributed throughout the film thickness, a physically plausible assumption in view of the small film thickness

(0.5 μm) compared to the much larger diffusion length of impurities in polycrystalline silicon.

The dopant concentration in the diffused polysilicon film was then obtained by dividing the polysilicon dopant charge per unit area by the film thickness.

Details of the procedure used with the SUPREM II program for the above mentioned purpose are given in Appendix C.

4.1.2 Test Structures

A polysilicon test chip was designed to provide a range of useful structures, namely:

- a. Standard resistors with different dimensions and with two mutually perpendicular orientations.
- b. 4-point resistors.
- c. Van-der-Pauw patterns.

Figure 4.1 shows these structures with the scale of dimensions indicated in the figure.

The test patterns available on the polysilicon chip were used to check the values of resistivity obtained by different methods (e.g. the resistivity obtained from measurements on Van-der-Pauw pattern^[65] vs that obtained from 4-point resistor measurements, and the measured resistance of a standard resistor). Only those test chips for which the above-mentioned different resistivity measurement techniques yielded good agreement, were considered in this study.

120 μm

Fig. 4.1. Photomicrograph of the polysilicon chip.

To obtain an ohmic contact in the more lightly phosphorous-doped samples, an additional phosphorous diffusion step was carried out (at a temperature of 1000°C) on these samples prior to aluminum deposition. This diffusion step (with a high concentration of phosphorous) resulted in the creation of N^+ - regions that formed the required ohmic contact with the aluminum which was later deposited, patterned, and subsequently annealed at 450°C for 30 minutes.

Details of the processing steps of the test wafers are shown in Appendix D.

4.1.3 History of Experimental Work

Fabrication of test samples was initiated June 1979 by making the necessary masks, at which point equipment problems in the semiconductor fabrication lab brought the experimental work to a complete stop. The problem started with the failure of the epitaxial reactor, a key apparatus in the fabrication process. Procurement of spare parts necessary for repairing the reactor took several months, and the work could not be resumed until February 1980.

Another factor that contributed to the delay in the experimental program was the inadequate air control system in the semiconductor fabrication laboratory that was incapable of controlling the humidity level to the necessary level of 40% or less during the summer months thereby precluding any processing of test slices during the summer, especially those processes that require photoresist application for photo engraving.

Despite the above mentioned unfortunate circumstances in the fabrication environment, five batches of wafers were produced in the period from February 1980 (immediately after restoration of the epitaxial reactor to the working condition) to February 1982.

The wafers of the first batch were all defective: some of the defects observable in those wafers were attributed to the formation of 'oxide skin', a commonly encountered defect in the fabrication of ICs; some others indicated a defective metallization. Steps were taken to overcome these problems and good wafers were obtained in subsequent runs.

The wafers of the second and third batches helped to gain needed information on the calibration of the diffusion system, i.e. the relationship between the parameters of the predeposition and drive-in phases (flow rates of dopant gases, temperatures, times) and the resulting sheet resistances of wafers. Such information was not readily available at the time when the experimental work started and therefore had to be obtained via experimentation. In addition to serving this purpose, the wafers of these two batches provided important information regarding the relative accuracy of pattern definition using the two patterning techniques described in Section 4.1.1. Based on this information, it was decided to abandon the technique of using selective diffusion of impurities to define the polysilicon pattern.

Results reported in this thesis represent measurements obtained from wafers of the fourth and fifth batches only. These batches were

produced in October 1981 and February 1982, respectively: the wafers of the fourth batch P4 (32 wafers) were all phosphorous-diffused, while those of the fifth batch included 48 boron-diffused wafers (constituting batch B5) and 52 phosphorous-diffused wafers (constituting batch P5). Table 4.1 classifies the wafers of these batches according to their processing conditions..

The yield in these last batches (i.e. the percentage of non-defective wafers) was as follows: 65% in batch P4, 42% in batch P5, and 52% in batch B5. These percentages of yield were the highest observed in all of the five batches produced in the course of this investigation. The working wafers of the aforementioned batches (i.e. fourth and fifth batches) were also the best among working wafers of the five batches. Sufficient good, uniform samples (the uniformity criterion is defined below) were obtained. For the rejected wafers (which did not fulfill the uniformity criterion), the scatter in the values of resistivity obtained on the same wafer and from one wafer to another (for identically processed wafers) was very large. For these wafers, values of resistivity were frequently found to vary by one to two orders of magnitude from one location to another on the wafer surface; resistivities of identically processed wafers were also frequently found to vary by the same amount.

The scatter in the resistivity values, both on the same wafer and among identically processed wafers, was found to increase with increasing values of resistivity especially in those cases where the higher resistivity was achieved by using a low predeposition temperature (less than 850°C).

Table 4.1. Polysilicon test wafers.

- (a) Batch P4: phosphorous-diffused polysilicon films
- (b) Batch P5: phosphorous-diffused polysilicon films
- (c) Batch B5: boron-diffused polysilicon films

Predeposition Conditions	Patterned Polysilicon Wafers	Unpatterned Polysilicon Wafers
$T_{pr} = 1000^{\circ}\text{C}$ POCl_3 flow rate $= 7.9 \text{ mg/min}$	P4-1,2, <u>9</u> , <u>10</u>	P4-17,18, <u>25</u> , <u>26</u>
$T_{pr} = 950^{\circ}\text{C}$ flow rate $= 1 \text{ mg/min}$	P4-3,4, <u>11</u> , <u>12</u>	P4-19,20, <u>27</u> , <u>28</u>
$T_{pr} = 900^{\circ}\text{C}$ flow rate $= 1 \text{ mg/min}$	P4-5,6, <u>13</u> , <u>14</u>	P4-21,22, <u>29</u> , <u>30</u>
$T_{pr} = 850^{\circ}\text{C}$ flow rate $= 1 \text{ mg/min}$	P4-7,8, <u>15</u> , <u>16</u>	P4-23,24, <u>31</u> , <u>32</u>

(a)

Predeposition Conditions	Poly Deposition Temp, °C	Patterned Polysilicon Wafers	Unpatterned Polysilicon Wafers
$T_{pr} = 900^{\circ}\text{C}$ POCl_3 flow rate = 7.9 mg/min	700 900	P5- <u>1,2,11*,12*</u> P5- <u>21,22,37*,38*</u> P5- <u>25,26,41*,42*</u>	P5- <u>5,6,15,16</u> P5- <u>29,30,45,46</u> P5- <u>33,34,49,50</u>
$T_{pr} = 950^{\circ}\text{C}$ flow rate = 1 mg/min	700	-	P5- <u>9,10,19,20</u>
$T_{pr} = 800^{\circ}\text{C}$ flow rate = 7.9 mg/min	700 900	P5- <u>3,4,13*,14*</u> P5- <u>23,24,39*,40*</u> P5- <u>27,28,43*,44*</u>	P5- <u>7,8,17,18</u> P5- <u>31,32,47,48</u> P5- <u>35,36,51,52</u>

(b)

Predeposition Conditions	Poly Deposition Temp., °C	Patterned Polysilicon Wafers	Unpatterned Polysilicon Wafers
T _{pr} = 1050°C Max. flow rate of BBr ₃	700	B5- <u>1*</u> , <u>2*</u> , <u>7*</u> , <u>8*</u>	B5- <u>13</u> , <u>14</u> , 19, 20
	900	B5- <u>25*</u> , <u>26*</u> , <u>31*</u> , <u>32*</u>	B5- <u>37</u> , <u>38</u> , 43, 44
T _{pr} = 900°C Max. flow rate of BBr ₃	700	B5- <u>3*</u> , <u>4*</u> , <u>9*</u> , <u>10*</u>	B5- <u>15</u> , <u>16</u> , 21, 22
	900	B5- <u>27*</u> , <u>28*</u> , <u>33*</u> , <u>34*</u>	B5- <u>39</u> , <u>40</u> , 45, 46
T _{pr} = 800°C Max. flow rate of BBr ₃	700	B5- <u>5*</u> , <u>6*</u> , <u>11*</u> , <u>12*</u>	B5- <u>17</u> , <u>18</u> , 23, 24
	900	B5- <u>29*</u> , <u>30*</u> , <u>35*</u> , <u>36*</u>	B5- <u>41</u> , <u>42</u> , 47, 48

(c)

Legend:

Wafers with underlined numbers had an additional annealing step immediately after polysilicon deposition (the annealing was carried out at 1200°C for one hour in a dry nitrogen ambient). Asterisk numbers designate patterned wafers that had a low-temperature deposited silicon dioxide cap (350°C) instead of a thermally grown oxide cap. No systematic trend in the grain size or film texture was observed in either case.

These observations are consistent with the notion that the doping of polysilicon from a diffusion source is difficult to control compared to doping by ion-implantation^[35].

In view of the above mentioned findings, a criterion was set for the selection of 'representative' wafers, i.e. wafers for which measurements could be considered sufficiently reliable to be used in the construction of the modelling approach presented in this thesis. These wafers had to satisfy the requirement that the resistivity values at different locations on the wafer, within a circle with a diameter of 3 cms. in the central portion of the 2-inch (5 cm diameter) wafer, did not vary by more than a factor of 2. All wafers for which results are reported in Chapters 4 and 5 fulfill this requirement.

The data on patterned wafers presented in Chapters 4 and 5 (i.e. resistivity and piezoresistance measurements) were obtained on rectangular polysilicon resistors (with the dimensions $500\text{ }\mu\text{m} \times 25\text{ }\mu\text{m}$ in the plane of the polysilicon film) located near the center of the wafer. For each of these resistors, the resistivity measurements on different patterns on the same chip (i.e. Van-der-Pauw structure, 4-point resistor) were compared and found to agree within $\pm 25\%$.

4.1.4 Measurements

The objective of this study is three-fold: to investigate the electrical conduction in diffused polysilicon films, to examine their piezoresistive properties, and to combine the conductivity and piezo-resistance data in order to establish an approach to the modelling of diffused polysilicon films.

In order to achieve the above stated goals, the following measurements were carried out:

1. Resistivity measurements at room temperature in the linear range of the I-V characteristics, which were performed (as mentioned before) on three film patterns: 4-point resistor, standard resistor, and Van-der-Pauw patterns, on both polysilicon and single crystal silicon wafers processed under the same conditions and having a wide range of sheet resistance with an associated range of macroscopic dopant concentration from 10^{18} to 10^{20} atoms/cm³, as extracted from sheet resistance measurements on single crystal monitor wafers in conjunction with a computer simulation using SUPREM (See Appendix C).
2. Resistivity as a function of temperature in the temperature range from 0°C to 125°C. These measurements were performed on polysilicon slices mounted on a brass block that was placed inside a temperature-controlled oven. The temperature inside the oven was kept constant to within $\pm 1^\circ\text{C}$ for sufficiently long periods of time in order to ensure thermal equilibrium between devices and ambient (the time of each temperature measurement varied between 30 minutes and one hour). The electrical resistivity was measured by a digital multimeter (Fluke 8810A-type) and the temperature of the sample was measured by a thermocouple in direct contact with the brass block that carried the sample.

3. The change in resistivity upon the application of a calibrated mechanical stress, from which the piezoresistance coefficient was calculated. These measurements were carried out on slices cut from polysilicon wafers in the form of rectangles 11-chip long and 2-chip wide (or approximately 2.5×0.5 cms); the slices were mounted as cantilever beams (the polysilicon resistor lying on the upper surface of the cantilever) with one end rigidly clamped, while the opposite end was subjected to a bending moment produced by a micro-manipulator, as shown in Fig. 4.2. By measuring the deflection of the free end of the cantilever slice (using the micromanipulator) and the dimensions of the sample, together with the distance of a particular piezoresistor from the free end, the value of the stress at the location of the stress-sensitive element could be calculated. This value, together with the measured stress-induced change in the electrical resistivity, enabled a direct calculation of the piezoresistance coefficient (or equivalently the gauge factor) of the polysilicon resistor under investigation. For more details on the sample mount and the analysis of stresses in the cantilever slice, the reader is referred to Appendix E.

A value for Young's modulus (or the modulus of elasticity) of polycrystalline silicon is needed in the calculation of stress. Since Young's modulus of silicon is known to

Fig. 4.2. Schematic diagram of the mechanical set-up used to determine the

be a function of crystallographic orientation, an average value was used that takes into account the different orientations that may be present in the polycrystalline silicon film (as mentioned in Chapter 3, Section 3.3). A detailed calculation of Young's modulus for polysilicon is provided in Appendix F.

4. High temperature annealing experiments designed to investigate the segregation of impurity atoms to the grain boundaries by studying the effect of annealing on the electrical resistivity of diffused polysilicon layers (as discussed in Chapter 2). These experiments were performed on unpatterned polysilicon films with macroscopic dopant concentrations ranging from 10^{18} to 10^{20} atoms/cm³. Each sample underwent the following series of experiments:
 - a) Measurement of resistivity prior to annealing using the 4-point probe technique^[66].
 - b) Coating with a 0.5 μ m thick cap of low temperature (350°C) deposited silicon dioxide to prevent dopant outdiffusion and also to protect the polysilicon surface from bombardment by contaminants during the high temperature annealing.
 - c) Annealing (in a standard diffusion furnace) at a temperature between 900°C and 1000°C for long periods of time (1-4 hrs.) in a dry nitrogen ambient.

- d) Oxide cap removal by dipping the slices in a 10% solution of hydrofluoric acid diluted by de-ionized water.
- e) Measurement of resistivity of annealed films, again using the 4-point probe method.
- f) Steps b) to e) repeated with a different annealing temperature (in the above mentioned range).

Slices used in these tests were carefully chosen to maintain a uniformity of sheet resistance on the slice within a factor of 2; the slices were cut from these unpatterned wafers with best uniformity of sheet resistance and from the region with best uniformity on one particular wafer, with a slice width of approximately one centimeter to minimize the spread in the values of sheet resistance. This was necessary to separate any effect of annealing on the sheet resistance of polysilicon wafers from the initial scatter in the values of sheet resistance of these wafers. Furthermore, the sheet resistance (or equivalently the resistivity) of a particular test sample was checked at several locations along the length of the sample (using the 4-point probe) before and after the high temperature annealing.

- 5. Large signal I-V characteristics. This measurement was performed on standard (two-terminal) polysilicon resistors to obtain an estimate of the average grain size of the

polysilicon films. This electrical method of determining the grain size was the only reliable quantitative technique available in this study (electron microscopy apparatus proved to be inadequate due to lack of required high resolution).

Voltages as high as 300 volts were applied across the polysilicon resistor to drive it into the non-linear region of its I-V characteristics represented by the hyperbolic-sine relationship of Chapter 2 (Eqn. (2.11)) repeated below for convenience:

$$J = q \left(\frac{4\pi m_e^* k^2 T^2}{h^3} \right) \exp \left(-\frac{\xi}{kT} \right) \frac{\exp(-b_1)}{1 - C_1 kT} \exp \left(-\frac{q V_b}{kT} \right) 2 \sinh \left[\frac{1 + (C_1 kT N_G^W g_b / Q_T)}{1 + (N_G^W g_b / Q_T)} \cdot \frac{q V_o}{2kT} \right] \quad (4.1)$$

where V_o is the average applied voltage per grain.

This equation can be rewritten as follows:

$$I = \theta \sinh \left[\frac{1 + \left(\frac{C_1 kT N_G^W g_b}{Q_T} \right)}{1 + \left(\frac{N_G^W g_b}{Q_T} \right)} \left(\frac{qV}{2kTl} \right) L \right] \quad (4.2)$$

where

θ is a constant independent of grain size

I is the current through the polysilicon resistor

V is the voltage applied across the polysilicon resistor

L is the average grain size

l is the current path length (or resistor length)

All the remaining symbols are defined in Chapter 2 and are independent of the grain size L.

The above relationship (Eqn. (4.2)) was used to obtain an average value for the grain size L with three pairs of (I,V) data for one particular polysilicon resistor as follows. Assume that, for a certain polysilicon resistor, the following three pairs of I vs V values were obtained: (I_1, V_1) , (I_2, V_2) , and (I_3, V_3) with $V_1 < V_2 < V_3$. From Eqn. (4.2), we obtain

$$\frac{I_1}{I_2} = \frac{\sinh K V_1 L}{\sinh K V_2 L} \quad (4.3)$$

where

$$K = \frac{1 + \left(\frac{C_1 k T N_G^W g_b}{Q_T} \right)}{1 + \left(\frac{N_G^W g_b}{Q_T} \right)} \cdot \frac{q}{2kTl}$$

The above equation (4.3) is transcendental in L, and can be solved numerically to obtain the value of this parameter. This is repeated with $\frac{I_1}{I_3}$ and $\frac{I_2}{I_3}$ on the left-hand side of the equation. The resulting three values of L are then compared and if they agree within $\pm 10\%$ of their arithmetic average, the hyperbolic-sine relationship expressed by Eqn. (4.2) is considered to be valid over the range of applied voltages from V_1 to V_3 .

There were two categories of polysilicon films for which the above explained technique could not be used to infer the average grain size. The first category corresponds to the most heavily doped films whose low sheet resistance caused the power dissipation limit of the polysilicon resistor under test to be exceeded well before sufficiently high voltage values were reached (Power dissipation = V^2/R_{poly}) thereby rendering the hyperbolic sine relationship, Eqn. (4.2), useless. The I-V characteristics for these heavily doped polysilicon resistors were linear up to the resistor breakdown voltage set by the power dissipation capability of the resistor. The second category consists of those films for which the I-V data could not be represented by the hyperbolic sine law due to the non-equality of the voltage drops across the two sides of the depletion region surrounding a grain boundary, as explained in Appendix B.

4.2 Results of Experiments

In this section, a survey is given of the results obtained from the measurements discussed in Section 4.1.4 prior to turning to the treatment of systematic modelling of conduction in Chapter 5. In the present section, the findings of the various experiments performed are described, with reference to specific results obtained, and significant conclusions are drawn. Some of these conclusions are in agreement with those of previous workers; others are at variance with them.

4.2.1 Electrical Resistivity

The electrical resistivity of boron- and phosphorous-diffused polysilicon films at room temperature exhibited the trend reported by previous investigators [18,21,24,27] with respect to dopant concentration, i.e. the resistivity drops with dopant concentration much faster than observed for uniformly-doped single crystal silicon over the range of doping obtained in this study, i.e. from 10^{18} to 10^{20} atoms/cm³ for both boron and phosphorous impurities. Qualitatively, an increase in macroscopic dopant density from about 10^{18} to 10^{20} atoms/cm³ causes the resistivity of polysilicon to drop by three orders of magnitude while the resistivity of uniformly-doped single crystal silicon drops by only one to two orders of magnitude for the same increment in dopant density. It was also confirmed, experimentally, that the resistivity of polysilicon is always higher than equally uniformly doped single crystal silicon up to very high concentrations on the order of 10^{20} atoms/cm³. The above mentioned results are summarized in Table 4.2 for representative samples of boron- and phosphorous-diffused films.

These results point clearly to the role of the grain boundaries in controlling the electrical conductivity of polysilicon. This role can be interpreted in terms of two physical effects: carrier trapping and impurity segregation. In the first, the number of carriers available for electrical conduction is reduced by trapping some of them in the trapping states at the grain boundaries resulting in the accumulation of charges at these boundaries with a consequent formation

Table 4.2. Variation of resistivities of boron- and phosphorous-diffused polysilicon films with macroscopic dopant concentration. The resistivity of single crystal silicon uniformly doped to the same level is shown for comparison [43].

Dopant Species	Sample #	Macroscopic Dopant Concentration (cm^{-3})	Polysilicon Resistivity ($\Omega \text{ cm}$)	Single Crystal Silicon Resistivity ($\Omega \text{ cm}$)
Boron	B5-5	3.98×10^{18}	0.0810	0.0174
	B5-29	5.01×10^{18}	0.0368	0.0156
	B5-28	1.07×10^{19}	0.0262	0.0099
	B5-1	2.10×10^{19}	0.0126	0.0055
Phosphorous	P4-15	4.45×10^{17}	3.5360	0.0307
	P4-14	1.35×10^{18}	0.1417	0.0221
	P4-11	1.27×10^{19}	0.0297	0.0090
	P4-10	9.52×10^{19}	0.0033	0.0010

of potential energy barriers that impede the motion of untrapped carriers and reduce their mobility, as posulated in the carrier trapping model. Alternatively, the grain boundary effect may be explained in terms of preferential segregation of impurity atoms to the grain boundaries where they are rendered electronically inactive, as hypothesized by the segregation model. Evidences for the existence or non-existence of these two mechanisms (i.e. carrier trapping and impurity atoms segregation) as controlling factors in the process of electrical conduction in diffused polysilicon films are discussed in Sections 4.2.2 and 4.2.4 in view of the experimental results presented in these two sections on the temperature effects and heat treatment characteristics, respectively.

4.2.2 Temperature Dependence of Electrical Resistivity

The resistivity vs. temperature data (in the temperature range employed in this study, from 0°C to 125°C) showed that electrical conduction in polysilicon is a thermally-activated process, again in accordance with previously published results [18,20,21]. Typical curves of resistivity vs temperature for boron- and phosphorous-diffused polysilicon films are shown in Figs. 4.3 and 4.4, respectively.

A least squares fit was applied to the above mentioned data using an equation of the form:

$$\rho_{\text{poly}_n} = \left(\frac{T}{T_n}\right)^{\frac{1}{2}} \cdot e^{\frac{qV_b}{k} \left(\frac{1}{T} - \frac{1}{T_n}\right)} \quad (4.4)$$

where

Fig. 4.3. Typical plots of natural logarithm of normalized resistivity of boron-diffused polysilicon films vs $1000/T$. The resistivity is normalized by the resistivity at 127°C (400°K). The solid line represents the theoretical model, Eqn. (4.4).

Fig. 4.4. Typical plots of natural logarithm of normalized resistivity of phosphorous-diffused polysilicon films vs $1000/T$. The resistivity is normalized by the resistivity at 100°C (373°K). The solid line represents the theoretical model, Eqn. (4.4).

ρ_{poly_n} is the resistivity of polysilicon at a temperature T ,
normalized by the resistivity at a temperature T_n .

qV_b is the conductivity activation energy (or potential energy
barrier height, as discussed in Chapter 2).

Equation (4.4) can be obtained from Eqns. (2.14) and (2.15) (of
Chapter 2) by simple manipulations after neglecting the other
temperature-dependent terms, an approximation that can easily be shown
to be valid over the ranges of parameters considered in this study.

Equation (4.4) was found to be accurate to $\pm 5\%$ in representing
the temperature dependence of the electrical resistivity of both
boron- and phosphorous-diffused polysilicon films over the previously
indicated temperature range (i.e. 0°C to 125°C) and for all values of
doping concentrations obtained in this study, i.e. from 10^{18} to 10^{20}
atoms/cm³. This agreement between theoretical prediction and experi-
ment is shown in Figs. 4.3 and 4.4 for boron- and phosphorous-diffused
polysilicon films, respectively.

The results of the resistivity vs temperature experiments
strongly suggest that conduction in diffused polysilicon films involves
thermionic emission (including tunneling of carriers with insufficient
energies to surmount the grain boundary potential energy barrier) of
carriers over potential energy barriers created by space-charge layers
in the grains adjacent to the grain boundaries due to the trapping of
some of the charge carriers at grain boundary trapping states. Such
a conduction mechanism is necessary to explain the exponential dependence
of the electrical resistivity on temperature that was verified

experimentally. It will be shown in Chapter 5 that the expression for electrical resistivity obtained by Mandurah et al^[23,24] and based on a consideration of tunneling in addition to thermionic emission of carriers (i.e. Eqn. (2.14)) was found to apply to the case of diffused polysilicon films investigated in this work.

4.2.3 Piezoresistance Effects

The results of piezoresistance experiments performed on diffused polysilicon films were as follows;

- a) The piezoresistance coefficient was measurable only at dopant concentrations above a certain minimum value, which was experimentally determined to lie within the range from 4×10^{18} to 5×10^{18} atoms/cm³ for boron-diffused polysilicon, and from 1×10^{18} to 2×10^{18} atoms/cm³ for phosphorous-diffused polysilicon. Below this value of dopant density, the piezoresistance coefficient was impossible to measure due to the large fluctuations (that were also very sensitive to vibrations) observed in the electrical resistance of the so lightly doped samples even in the absence of mechanical stress. The presence of such fluctuations is attributed to the noisy mechanism of carrier trapping whereby a carrier is trapped for a certain period of time, after which it is released and then recaptured, and so on. In the more lightly doped samples, the trapping states are not completely filled and the electrical resistivity of polysilicon is dominated by the grain boundary region

and its traps. The observed fluctuations in the resistivity of these lightly doped samples are therefore a consequence of the effect of stress on the trapping states energy and distribution, an effect that is expected to be noisy as demonstrated by the experiment.

A lower limit is therefore set on the dopant concentration in different polysilicon films, below which the films could not be utilized in practical transducers such as strain gauges. It is interesting to note that this lower limit of doping corresponds to a width of combined grain-boundary region, L_{gb} , that represents only about 10% of the total crystallite size L (as will be shown in Chapter 5) thereby restricting the 'useful', measurable, piezoresistance to those samples whose doping densities are so high that the neutral crystalline bulk of a grain occupies more than 90% of its volume.

- b) The 'useful' piezoresistance effect (i.e. the measurable effect) is qualitatively and quantitatively consistent with a model based on a crystallite-dominated piezoresistance. Qualitatively, the observed sense of change in electrical resistance upon application of mechanical stress corresponded to that found for single crystal silicon; this was repeatedly obtained for both boron- and phosphorous-diffused polysilicon resistors under tensile and compressive stresses. Quantitatively, the measured gauge factor of

polysilicon resistors was found to be in excellent agreement with the simplified model represented by Eqn. (3.55) of Chapter 3 which is based on the assumption of a crystallite-dominated piezoresistance coefficient with the overall piezoresistance coefficient being equal to the average of the coefficients for $\langle 100 \rangle$, $\langle 111 \rangle$, and $\langle 110 \rangle$ oriented single crystal silicon. This was verified, indirectly, by comparing the crystallite size obtained by invoking the simplified piezoresistance model to that obtained independently from large signal I-V measurements as described in Section 4.1.4. The excellent agreement between the two values of grain size (as will be shown in Chapter 5) indicated that the simple piezoresistance model was valid in the representation of the piezoresistance of diffused polysilicon films with dopant concentrations above the lower limit mentioned in a) above, i.e. over that range of dopant concentrations within which the piezoresistive effect is measurable and practically useful.

- c) The values of gauge factor ranged from 22 to 25 for boron-diffused polysilicon resistors, and from 14 to 20 for phosphorous-diffused polysilicon resistors. The former values compare favourably with results reported by previous researchers on boron-doped polysilicon deposited on different substrates^[25,26]. The variation of gauge factor of diffused polysilicon films with doping concentration is shown in

Table 4.3. Unlike the gauge factor of single crystal silicon, the gauge factor of diffused polysilicon films did not exhibit a monotonic decrease with increasing dopant concentration. Similar behaviour was reported by Seto^[25] for boron-implanted polysilicon films deposited on aluminum-oxide-insulated molybdenum substrates.

- d) The linearity of the resistance change with strain was better than $\pm 10\%$ up to a strain of 0.8×10^{-3} mm/mm, a value that is equal to 30% of the silicon breaking strain (determined experimentally), the non-linearity increases with increasing strain. No appreciable hysteresis was measured. Figure 4.5 is a typical plot of resistance change of a polysilicon resistor as a function of mechanical strain.
- e) In a single experiment carried out on a phosphorous-diffused polysilicon resistor, the temperature coefficient of gauge factor (TOGF) was measured to be equal to -6.39×10^{-4} /°C over the temperature range from 24.5°C to 77°C. The value of TOGF for N-type single crystal silicon with the same dopant concentration (1.59×10^{18} atoms/cm³) lies between -15.7×10^{-4} and -23.8×10^{-4} /°C. It is therefore seen that phosphorous-diffused polysilicon offers a practical advantage over single crystal silicon regarding transducer applications, this advantage being the decreased temperature sensitivity of gauge factor.

Table 4.3. Dependence of the gauge factor of diffused polysilicon films on active dopant concentration.

Dopant Species	Sample #	Active Dopant Concentration (cm^{-3}) *	Gauge Factor
Boron	B5-29	5.01×10^{18}	25.13
	B5-28	1.07×10^{19}	22.57
	B5-1	1.95×10^{19}	23.86
Phosphorous	P5-41	1.23×10^{18}	14.56
	P5-22	1.59×10^{18}	20.20
	P5-26	3.98×10^{18}	17.34

* The active dopant concentration is the density of dopant atoms inside the grains. This parameter is deduced from the measured piezoresistance of the polysilicon film as shown in Chapter 5.

Fig. 4.5. Typical curves of resistance change as a function of strain for diffused polysilicon films.

Similar results were previously obtained for boron-doped polysilicon deposited on different substrates and doped by ion-implantation^[25] or vacuum evaporation of impurities^[26].

4.2.4 High Temperature Annealing Characteristics

The results of high temperature annealing experiments described in Section 4.1.4 were as follows. No appreciable change in the resistivity of boron- and phosphorous-diffused polysilicon films was detected (within the accuracy of the 4-point probe method) after annealing. The resistivity of each slice was checked at several locations along the length of the slice, as mentioned in Section 4.1.4. The resistivity value at a certain location on a test slice before annealing could always be reproduced after the slice has been annealed by moving the slice until the probes are placed on the same location that was tested before annealing (within a circle of uncertainty with a diameter of 2.0 mm). This result was repeatedly verified for slices with different doping concentrations (or equivalently different resistivities) subjected to different high temperature annealing cycles. Table 4.4 displays the different resistivity slices that were tested for the effect of high temperature heat treatment and the annealing conditions to which these slices were subjected. The three locations on each slice where resistivity was measured by the 4-point probe are referred to in the table by the entries 1, 2 and 3. These locations were spaced at a distance of approximately one centimeter in the central portion of each slice.

Table 4.4. High temperature annealing conditions for phosphorous- and boron-diffused polysilicon slices with different resistivities. Resistivity values listed are those prior to annealing.

Sample #	Resistivity (Ω cm)			Annealing Conditions	
	1	2	3	Time (hours)	Temp ($^{\circ}$ C)
P4-17	0.0274	0.0317	0.0257	4	900
P4-25	0.0064	0.0074	0.0052		
P4-27	1.0242	1.5620	1.9536		
P4-29	2.7368	3.0660	2.7724		
P4-32	0.6250	0.6150	0.6300		
P4-25	0.0064	0.0074	0.0052	2	1000
P5-5	0.0168	0.0114	0.0088		
P5-20	0.0117	0.0074	0.0062		
P5-33	0.0114	0.0182	0.0208		
P5-46	0.0180	0.0153	0.0114		
B5-15	0.0057	0.0079	0.0095		
B5-19	0.0407	0.0469	0.0782		
B5-22	0.0038	0.0059	0.0057		
B5-24	0.0358	0.0365	0.0269		
B5-37	0.0126	0.0102	0.0065		
B5-39	0.0086	0.0105	0.0085		
B5-42	0.0875	0.1250	0.1340		
B5-47	0.0440	0.0391	0.0337		

The remarkable changes in resistivity (especially for higher resistivities comparable to those of slices P4-27 and P4-29 in Table 4.4) of annealed, ion-implanted, samples reported by Mandurah et al^[28] and discussed in Chapter 2, were totally absent in the diffused polysilicon films investigated in this study. The resistivity appeared to be defined entirely by the impurity diffusion process, no significant changes being caused by annealing. In view of the fact that the annealing process could not have affected the crystallite size or configuration^[67], it was concluded that the impurity density in the crystallites was unchanged. This leaves two possibilities:

- a) Either segregation effects were non-existent in the diffused polysilicon films.
- b) Or that segregation does not obey the Mandurah et al model (refer to Appendix A for details of this model) but rather follows a "fixed segregation" pattern in which the number of impurity atoms segregating to the grain boundaries is fixed at its initial value (that may be determined by the parameters of the diffusion process, i.e. temperature, time and dopant concentration, and also by the physical structure of the deposited polysilicon films, i.e. grain size, orientations, etc.) and does not change upon subsequent heat treatment.

It is thought that assumption b) is the one that is more likely to be valid in diffused polysilicon films. The well-documented preferential diffusion of dopant atoms along the grain boundaries of

polysilicon (as discussed in Chapter 2) should favour the segregation of some of these atoms to grain boundaries where many extra bonds are available (due to the highly disordered atomic structure of the grain boundaries) to absorb the foreign atoms.

Once the "fixed segregation" concept has been adopted, the need immediately arises for a method to determine the active dopant concentration in the crystalline bulk of the grains, N_G , as this parameter directly influences the calculation of electrical resistivity.

Since the segregation model of Mandurah et al^[28] could not be used to calculate this parameter for diffused polysilicon films, another approach had to be developed. This approach is explained in Chapter 5 and is based on the use of the piezoresistance effect in diffused polysilicon layers to infer the value of N_G .

4.2.5 Grain Size

The values of the average grain size obtained from large signal I-V measurements (for those samples to which the hyperbolic-sine I-V relationship applied, as discussed in Section 4.1.4) ranged from 1500Å to 3500Å for both boron- and phosphorous-diffused polysilicon films deposited at the two deposition temperatures of 700 and 900°C, and including wafers from batches 4 and 5.

It is useful at this point to give two examples of large signal I-V data, one for each dopant species, to illustrate the method described in Section 4.1.4 for calculating the average grain size L .

Example I: For sample B5-5 (boron-diffused polysilicon film), the following I-V data were obtained:

V, volts	200 (V_1)	220 (V_2)	300 (V_3)
I, ma	3.77	4.39	8.29
$\bar{I}$, ma	3.77	4.38	8.31
I_{av} , ma	3.77 (I_1)	4.385 (I_2)	8.30 (I_3)

where I and $\bar{I}$ are the currents corresponding to the two opposite polarities of the applied voltage V.

Application of the method used in Section 4.1.4 yields the following values of the average grain size L (depending on the choice of the pairs of I vs V data):

$$(V_1, I_1) \text{ and } (V_2, I_2) \rightarrow L = 2378\text{\AA}$$

$$(V_1, I_1) \text{ and } (V_3, I_3) \rightarrow L = 2662\text{\AA}$$

$$(V_2, I_2) \text{ and } (V_3, I_3) \rightarrow L = 2724\text{\AA}$$

Therefore,

$$L(\text{average}) = \frac{2378+2662+2724}{3} = 2588\text{\AA}$$

Maximum positive deviation from L(average) = 5.3%.

Maximum negative deviation from L(average) = 8.1%.

Example II: For sample P4-14 (phosphorous-diffused polysilicon film), the following I-V data were obtained:

V, volts	160 (V_1)	200 (V_2)	240 (V_3)
I, ma	3.57	4.98	6.70
$\bar{I}$, ma	3.67	5.10	6.90
I_{av} , ma	3.62 (I_1)	5.04 (I_2)	6.80 (I_3)

Similar to the previous example, the following values of the average grain size L are obtained:

$$(V_1, I_1) \text{ and } (V_2, I_2) \rightarrow L = 2258\text{\AA}$$

$$(V_1, I_1) \text{ and } (V_3, I_3) \rightarrow L = 2208\text{\AA}$$

$$(V_2, I_2) \text{ and } (V_3, I_3) \rightarrow L = 2164\text{\AA}$$

Therefore,

$$L(\text{average}) = \frac{2258+2208+2164}{3} = 2210\text{\AA}$$

Maximum positive deviation from $L(\text{average}) = 2.2\%$.

Maximum negative deviation from $L(\text{average}) = 2.1\%$.

The above two examples clearly indicate the validity of the hyperbolic-sine relationship expressed by Eqn. (4.2) in the two polysilicon samples involved in the examples over the indicated range of applied voltages (i.e. in the range $V_1 < V < V_3$).

The spread in the values of grain size (from 1500 $\text{\AA}$ to 3500 $\text{\AA}$) is a manifestation of the statistical nature of this parameter in accordance with the findings of independent investigators^[35] who concluded that the use of a single-value grain size was not possible

in the real polycrystalline material due to the wide distribution of grain sizes, especially for films with grain sizes of several micrometers.

No systematic trend was observed regarding the effect of deposition temperature on the grain size. This is probably due to the fact that the deposition rate at 900°C was only double the rate at 700°C (the deposition rates were 1100 Å/min and 550 Å/min, respectively). Even if the films deposited at the lower deposition temperature had an initial fine-grained texture, the subsequent processing steps involving high temperature treatment (such as polysilicon oxidation and impurity diffusion steps, both involving temperatures in excess of 1000°C) must have caused the grains to grow to a size comparable to that of films deposited at the higher deposition temperature.

The above mentioned values of grain size compare favourably (within $\pm 10\%$) with the values of average grain size obtained by applying the modelling approach proposed by the writer in this thesis, as will be shown in Chapter 5. They are also in good agreement with scanning electron micrographs (one of which is shown in Fig. 4.6 for sample P4-29) despite the difficulty and lack of sufficient accuracy in the estimation of the grain size from such pictures due to the limited resolution capability of the available SEM and also due to possible charging of the test samples.

From the SEM picture of Fig. 4.6, an average grain size for sample P4-29 is estimated to be about 2270 Å. In this estimation, the number of dark or light areas encountered along two mutually

* SEM pictures were taken by Dr. R.F. Haythornthwaite at QRD Analysis Corp. in Ottawa.

Fig. 4.6. Scanning electron micrograph of slice P4-29.
Magnification = 20,000 X (one centimeter on the picture
represents an actual length of 0.5 μm)
Tilt angle = 30°

perpendicular lines, with lengths equal to the picture dimensions, intersecting at the centre of the picture, is calculated. The average grain size in each of the two directions is determined by dividing the actual length of each line by the above number, and the arithmetic average of the two calculated values of grain size is taken to be the average grain size in the sample. The value of the average grain size mentioned above is in excellent agreement with the value of $2210\text{\AA}$ calculated for sample P4-14 (the patterned wafer that was processed simultaneously with the unpatterned wafer P4-29) from large signal I-V measurements, as shown before.

4.3 Concluding Remarks

1. The behaviour of the electrical resistivity of diffused polysilicon films points to the role of the grain boundaries in controlling the process of electrical conduction in these films. This role can be interpreted in terms of two alternative mechanisms: carrier trapping or segregation of impurity atoms at the grain boundaries, and results in the resistivity of polysilicon being always higher than equally doped single crystal silicon.
2. The thermally activated conduction process in diffused polysilicon films, as evidenced from resistivity vs temperature experiments, provides a strong supporting evidence in favour of the carrier trapping model with the principal conduction mechanism being thermionic emission (that may include tunneling) of carriers over (or through) potential energy barriers formed

at grain boundaries due to carriers trapped at these boundaries.

3. The segregation model developed recently by Mandurah et al.^[28] was found experimentally to be inapplicable to diffused polysilicon films. The behaviour of both boron- and phosphorous-diffused films when subjected to high temperature annealing revealed that any segregation of impurity atoms at the grain boundaries, established during the high temperature impurity diffusion process, was not influenced by subsequent annealing at a lower temperature. This was quite different to the trend of behaviour reported for the ion-implanted LPCVD films of Mandurah et al. Consequently, this segregation model could not be applied to infer the value of N_G , the active dopant in the grains of the diffused films. A specific method of determining N_G was therefore necessary.
4. The piezoresistive coefficient of boron- and phosphorous-diffused polysilicon films is highly stable and reproducible for those samples in which electrical conduction is dominated by the neutral bulk of the grains, i.e. those samples with dopant concentrations over a certain minimum value (about 5×10^{18} atoms/cm³ as determined experimentally). At lower doping concentrations, the width of the depleted region of a grain becomes significant with a consequent increase in the role played by the grain boundaries in the conduction process. The noise which obscured the piezoresistance effect under these conditions is believed

to be associated with grain boundary trapping mechanisms and their stress dependence.

5. The above piezoresistance effect is shown in Chapter 5 to be useful in the determination of the parameter N_G for diffused polysilicon films, for which the latest segregation model^[28] does not apply.
6. The reasonably large (14 to 25), highly stable gauge factor obtained for boron- and phosphorous-diffused polysilicon films combined with the lower TGF observed for phosphorous-diffused films (compared to single crystal silicon) should make these films attractive in the fabrication of semiconductor transducers such as strain gauges.

CHAPTER 5

A NEW APPROACH TO THE MODELLING OF ELECTRICAL CONDUCTION IN DIFFUSED POLYSILICON FILMS

It was shown in Chapter 4 that the segregation model proposed by Mandurah et al^[28], and applied by them to ion-implanted polysilicon films, was inapplicable to diffused films investigated in this work. Consequently, the model could not be used to infer the value of the active dopant concentration, N_G , in the neutral bulk of the grains of a diffused polysilicon film. The need therefore arose for an alternative method to determine this important parameter that directly controls the electrical resistivity. The approach described below provides such a method. It utilizes the piezoresistance effect in diffused polysilicon films as a tool to enable a reliable estimate of the parameter N_G . The reliability of the approach derives from the high stability and repeatability of the piezoresistance effect observed for both boron- and phosphorous-diffused polysilicon films with dopant concentrations above 5×10^{18} atoms/cm³ (as shown in Chapter 4) and on the property in such films that piezoresistive effects in the neutral bulk of crystallites are dominant.

Although the assumption that the dopant atoms inside the grains are totally ionized is made in the following treatment (to avoid the severe complications pointed out by Mandurah et al^[24] concerning the various effects associated with the problem of partial ionization of impurities as mentioned in Section 2.2.3.1), the analysis allows for

consideration of partial ionization to be included. This is discussed in the following section where an example is given to illustrate the possibility of tackling the problem of partial ionization through a first-order approximation method.

5.1 Modelling Approach

The modelling approach consists of the following steps:

1. The electrical resistivity, ρ_{poly} , and the piezoresistance coefficient, π_{poly} , of the polysilicon film are measured, as described in Section 4.1.3 under 1 and 3, respectively.
2. The model for piezoresistance coefficient of the polysilicon film (presented in Section 3.3) is used to infer the value of N_G in the following way. The piezoresistance model is represented by the following equation (Eqn. (3.55) of Chapter 3):

$$\pi_{\text{poly}}(\rho_o)_{\text{poly}} = \bar{\pi}_g \rho_{g_o} \quad (5.1)$$

The left-hand side of the above equation is now known from 1), consequently the right-hand side is known. From graphs of N_G vs the product $\bar{\pi}_g \rho_{g_o}$ (where $\bar{\pi}_g$ is taken to be the arithmetic average of the single crystal piezoresistance coefficients corresponding to $\langle 100 \rangle$, $\langle 111 \rangle$, and $\langle 110 \rangle$ crystal directions, and ρ_{g_o} is the unstressed resistivity of single crystal silicon at a doping density equal to N_G atoms/cm³), the value of N_G is determined.

In constructing these graphs (of N_G vs $\bar{\pi}_g \rho_{g_0}$), the ρ_{g_0} vs N_G data were obtained from reference [43], while the piezoresistance coefficient vs N_G data were obtained from references [61], [68] and [69]. Figures 5.1 and 5.2 show the graphs of $(\bar{\pi}_g \rho_{g_0})$ vs N_G for P-type and N-type impurities, respectively.

- 3) The resistivity activation energy, or potential energy barrier height, E_b , is determined from resistivity vs temperature data (as indicated in Section 4.2.2).
- 4) The density of trapping states in the grain boundaries, Q_T , is calculated using the following relationship (Eqn. (2.6) of Chapter 2):

$$E_b = q V_b = \frac{q^2 Q_T^2}{8\epsilon N_G} \quad (5.2)$$

- 5) The width of the composite grain - boundary region, L_{g_b} , is calculated from (see Section 2.2.3):

$$L_{g_b} = 2W + W_{g_b} = \frac{Q_T}{N_G} + W_{g_b} \quad (5.3)$$

W_{g_b} is set equal to $7\text{\AA}$ which is equivalent to three atomic diameters, as mentioned in Section 2.2.3. (Note that for silicon, the tetrahedral radius = $1.18\text{\AA}$.)

- 6) The Fermi level E_F with respect to the bottom of the conduction band (top of the valence band) is calculated using the well-known formula:

Fig. 5.1. Graph of (ρ_g) vs N_G for P-type impurities in single crystal silicon.

Fig. 5.2. Graph of $(\bar{\pi}_g \rho_{g_0})$ vs N_G for N-type impurities in single crystal silicon.

$$e^{-\xi/kT} = e^{-(E_{C(v)} - E_F)/kT} = \frac{N_G}{N_{C(v)}} \quad (5.4)$$

where $N_{C(v)}$ is the effective density-of-states in the conduction (valence) band.

- 7) The height of the grain boundary barrier (relative to E_C), ϕ , is calculated using the relationship (see Section 2.2.3):

$$\phi = \phi_{g_b} - \xi \quad (5.5)$$

ϕ_{g_b} is set equal to 0.66 eV, this value was found by Mandurah et al [24] to best fit their model to their measurements (see Section 2.2.3). This was also confirmed in this study.

- 8) The parameters b_1 and c_1 involved in the formula for the electrical resistivity are calculated using Eqns. (2.12) and (2.13) repeated below for convenience*:

$$b_1 = \frac{4\pi W g_b}{h} (2m_c^*)^{\frac{1}{2}} (q\phi - q V_b)^{\frac{1}{2}} \quad (5.6)$$

$$c_1 = \frac{2\pi W g_b}{h} (2m_c^*)^{\frac{1}{2}} (q\phi - q V_b)^{-\frac{1}{2}} \quad (5.7)$$

- 9) The grain boundary resistivity, ρ_{g_b} , is calculated using the formula (Eqn. (2.14)):

$$\rho_{g_b} = [q^2 \left(\frac{4\pi m_c^* kT}{h^3} \right) L g_b \exp\left(-\frac{\xi}{kT}\right) \cdot \frac{\exp(-b_1)}{1 - C_1 kT} \cdot \exp\left(-\frac{q V_b}{kT}\right) \cdot \frac{1 + (C_1 kT N_G W g_b / Q_T)}{1 + (N_G W g_b / Q_T)}]^{-1} \quad (5.8)$$

* For N-type poly: $m_c^* = 0.26 m_0$, $m_T^* = 2.15 m_0$
For P-type poly: $m_c^* = 0.38 m_0$, $m_T^* = 0.66 m_0$ ($m_0 = 9.1 \times 10^{-31}$ Kg).

- 10) A value of the average grain size, L , is obtained by applying the following relationship (Eqn. (2.15)):

$$\rho_{\text{poly}} = \frac{L_g}{L} \rho_g + \frac{L_{g_b}}{L} \rho_{g_b} \quad (5.9)$$

where $L_g = L - L_{g_b}$ is the width of the undepleted portion of the grain, and ρ_g is the single crystal resistivity corresponding to a doping concentration of N_G atoms/cm³.

This value is then compared with the value of L deduced from large signal I-V measurements (described in Section 4.1.4) to verify the validity of the modelling approach. The above stated approach was used in the characterization of those polysilicon films for which the piezoresistive effect is measurable, i.e. for films with doping density above 5×10^{18} atoms/cm³ as mentioned in Chapter 4.

For the more lightly doped films for which the piezoresistance coefficient was impossible to obtain (for the reason discussed in Chapter 4 in relation to the noisy mechanism of carrier trapping), and the above method of determining N_G was therefore not available, a different approach was applied in the characterization of films. This approach consists of the following steps. Firstly, a trial-and-error procedure is used to infer the value of N_G that would result in a value of an average grain size L for the lightly doped films that is equal to the value of grain size calculated for a heavily doped film (based on piezoresistance data obtained for this heavily doped film) deposited in the same run with the lightly doped film. The

procedure is initiated by assuming a value for N_G , going through steps 4) to 10) of the modelling approach, comparing the resulting value of L to that of the heavily doped film, then modifying N_G and repeating the calculation of L and so on until the desired value of L is obtained. Secondly, the large signal I-V data are used in conjunction with the set of parameter values derived in the first step (specifically the parameters: N_G , Q_T , C_1) and the hyperbolic-sine relationship represented by Eqn. (4.2) in an iterative loop to improve the calculated value of L , and the values of the other film parameters.

The results of applying the modelling approach described above to boron- and phosphorous-diffused polysilicon films were as follows:

- a) The values of the average grain size, L , obtained from piezoresistance data came in close agreement with those derived from large signal I-V measurements (within $\pm 10\%$) as shown in Table 5.1. This was true for boron- as well as phosphorous-diffused films for which the piezoresistive effect was measurable. The excellent agreement between the two values of L calculated using the above two methods (i.e. piezoresistance and large signal I-V characteristics) provides a strong evidence for the validity of the modelling approach presented here since the calculations in the two methods are totally independent, the large signal I-V measurements being carried out on the actual devices (polysilicon resistors).

Table 5.1. Typical values of parameters of diffused polysilicon films.

Dopant Species	Sample #	Piezo resist ance Measurable ?	Macroscopic Dopant Conc. (cm^{-3}) [from SUPREM II]	N_G (cm^{-3})	Q_T (cm^{-2})	L_{g_b} ($\text{\AA}$)	L ($\text{\AA}$) [from piezo-resistance]	L ($\text{\AA}$) [from large signal I-V data]
Boron	B5-5	NO	-	3.98×10^{18}	3.08×10^{12}	84.5	-	2588
	B5-29	YES	-	5.01×10^{18}	2.58×10^{12}	58.5	3164	3002
	B5-1	YES	2.1×10^{19}	1.95×10^{19}	4.09×10^{12}	28.0	2362	-
Phosphorous	P4-14	NO	1.35×10^{18}	1.17×10^{18}	1.74×10^{12}	155.4	-	2210
	P5-22	YES	7.16×10^{18}	1.59×10^{18}	1.81×10^{12}	121.1	3544	3387
	P5-41	YES	7.16×10^{18}	1.23×10^{18}	1.76×10^{12}	150.1	3176	3455
	P4-11	YES	1.27×10^{19}	6.76×10^{18}	3.51×10^{12}	59.0	1497	-

- b) The calculated value of the trapping states density Q_T ranged from 3×10^{12} to $4 \times 10^{12} \text{ cm}^{-2}$ for boron-diffused films, and from 1.7×10^{12} to $3.5 \times 10^{12} \text{ cm}^{-2}$ for phosphorous-diffused films. These values compare favourably with results published by previous investigators [18,20,21,24]. Table 5.1 displays typical values of the parameters of diffused polysilicon films.
- c) The value of N_G deduced from piezoresistance data (as described in step 2) of the modelling approach for those samples for which the piezoresistance coefficient was measurable) was found to be consistent with the value of the macroscopic dopant concentration N as inferred from a computer process simulation using SUPREM II (see Appendix C) for those polysilicon wafers for which the corresponding single crystal monitor wafers exhibited good and reliable characteristics - i.e. linear, symmetric I-V relationship, with an agreement within $\pm 25\%$ for sheet resistance values obtained with different test structures (i.e. 4-point resistor, Van-der-Pauw pattern, standard resistor) and 4-point probe measurements on unpatterned wafers. The above group of wafers included all the phosphorous-diffused wafers and only the most heavily doped boron-diffused wafers with a macroscopic boron concentration of $2.1 \times 10^{19} \text{ atoms/cm}^3$ (or those boron-diffused wafers with a predeposition temperature of 1050°C as shown in Table 4.1).

For all other boron-diffused wafers (i.e. wafers with predeposition temperatures of 900 and 800°C in Table 4.1), the corresponding single crystal monitor wafers exhibited bad characteristics (such as non-linearity, asymmetry in the I-V characteristics) and therefore could not be used to infer the value of the macroscopic dopant concentration N . For these wafers, the value of N was assumed to be equal to N_G in view of the recently reported observation^[23,24,28] that segregation of boron atoms to the grain boundaries of polysilicon films is insignificant, an observation that was also confirmed in this study for the group of wafers most heavily doped with boron atoms (and represented by sample B5-1) as can be seen in Table 5.1 where the value of N of 2.1×10^{19} atoms/cm³ is very close to the value of N_G which was found, from piezoresistance measurements, to be equal to 1.95×10^{19} atoms/cm³. The fact that the value of the active dopant concentration N_G deduced from piezoresistance was always less than the macroscopic dopant concentration N (deduced from process computer simulation) for phosphorous-diffused polysilicon films suggests the segregation of some of the phosphorous atoms to the grain boundaries in diffused films.

Any such segregation would then follow a "fixed pattern" that does not change upon the application of any heat treatment steps following the impurity diffusion process,

as discussed in Section 4.2.4. A detailed quantitative study of segregation effects in diffused polysilicon films is beyond the scope of this work. In order for such a study to be carried out, more data need to be collected on the annealing characteristics of diffused films; this would involve producing more useful test wafers and would also require the use of more sophisticated techniques, such as Hall-effect measurements, to determine accurately the changes, if any, in the resistivity of films with annealing. In any event, the conclusion that segregation effects in boron- and phosphorous-diffused polysilicon films are of no practical significance in the fabrication of ICs can comfortably be made in view of experimental evidence established in this work (i.e. any segregation of impurity atoms is unaffected by any heat treatment following the impurity diffusion process thereby rendering the films stable with subsequent high temperature processing), the effects being even less significant with boron- than with phosphorous-diffused films.

- d) The value of the conductivity activation energy estimated from measurement of resistivity as a function of temperature results in a calculated value of L using piezoresistance (for those samples with measurable piezoresistance coefficient) that is in excellent agreement with the value of L derived independently from hyperbolic ~~the~~ I-V relationship, as shown earlier. This lends a strong evidence for the validity of the conduction model represented by Eqn. (5.8) which is the basis for Eqn. (4.2) used to infer the activation

energy, in the representation of the temperature effect on the electrical resistivity of the films over the range of temperatures employed in this study, i.e. from 0°C to 125°C.

Based on the above stated results, it is concluded that the modelling approach presented in this chapter constitutes a reliable and systematic method for the characterization of boron- and phosphorous-diffused polysilicon films over the macroscopic doping range from 1×10^{18} to 1×10^{20} atoms/cm³, and in the temperature range from 0°C to 125°C.

5.2 Further Modelling Aspects

5.2.1 Partial Ionization of Impurities

The foregoing treatment was based, as mentioned earlier, on the assumption of complete ionization of dopant atoms in the grain interior. This assumption, which has also been made by previous investigators^[23,24], is only valid at concentrations below $\sim 5 \times 10^{18}$ /cm³. Above this value, the dopant atoms are only partially ionized. The modelling approach presented in Section 5.1 allows for the effect of partial ionization of impurities to be included (as does the conduction model of Mandurah et al^[23,24] employed in this approach), the analysis becoming much more complicated due to the various phenomena associated with this effect (as mentioned in Section 2.2.3.1). A simple approximate solution to this problem may be obtained based on the following assumptions:

- i) The Fermi-Dirac statistics are used in the calculation of the Fermi level E_F .
- ii) The impurity energy level $E_{A(D)}$ for acceptors (donors) is assumed to lie at the edge of the valence (conduction) band^[62].

The Fermi level is then calculated using the following relationship^[64]:

$$N_G^* = \frac{N_G}{1 + 2e^{-\xi/kT}} = F_{\frac{1}{2}} \left(-\frac{\xi}{kT} \right) N_{V(C)} \quad (5.10)$$

where

N_G is the density of acceptor (donor) atoms in the grain interior obtained from step 2) of the modelling approach.

N_G^* is the density of ionized acceptor (donor) atoms in the grain interior.

$N_{V(C)}$ is the effective density of states in the valence (conduction) band^[64].

$N_V = 1.04 \times 10^{19} / \text{cm}^3$ at room temperature (300°K)

$N_C = 2.80 \times 10^{19} / \text{cm}^3$

$\xi = E_{C(V)} - E_F$

$F_{\frac{1}{2}}$ is the well-tabulated Fermi-Dirac integral^[60].

The factor 2 in the denominator of the left-hand side of Eqn. (5.10) represents degeneracy.

After N_G^* and ξ are calculated from Eqn. (5.10), their values are used in conjunction with the modelling approach represented by steps 1) to 10).

Application of the above method to sample B5-1 resulted in the following new set of parameters for this sample:

$$N_G = 1.95 \times 10^{19} \text{ atoms/cm}^3$$

$$N_G^* = 7.12 \times 10^{18} \text{ atoms/cm}^3$$

$$Q_T = 2.47 \times 10^{12} \text{ cm}^{-2}$$

$$L_{g_b} = 41.7 \text{ } \overset{\circ}{\text{A}}$$

$$L = 4387 \text{ } \overset{\circ}{\text{A}}$$

These parameter values should be compared to those obtained before (in Table 5.1) on the assumption of complete ionization of impurities. Such a comparison is useful in formulating an idea about the qualitative effect of partial ionization of impurities on the deduced values of the polysilicon film parameters. It should be noted, however, that the analysis presented above is only approximate and that a more thorough investigation into the multiple effects associated with partial ionization (as mentioned in Section 2.2.3.1) is needed to improve the modelling accuracy for heavily doped polysilicon films where such effects are expected to be significant.

5.2.2 Carrier Collisions

Another physical aspect that deserves attention in the search for complete modelling of conduction in polysilicon films is the effect of carrier collisions with lattice phonons. This effect, that was earlier pointed out by the writer^[22] and which is briefly discussed in Section 2.2.2.3 in conjunction with suggestions for improvements to

Seto's carrier trapping model^[18], was not considered in the modelling approach presented in this chapter, the effect being minimal over the relatively high doping range and large grain size obtained in this work. The effect, however, is expected to play a significant role in films with more light doping and/or smaller grain sizes. This is explained in the following way. The effect of carrier collisions can be ignored if the distance over which the potential energy barrier changes from its maximum value by kT is very small compared to the mean free path for scattering by optical phonons (equal to $60\text{\AA}$ at 300°K , as mentioned in Section 2.2.2.3). An expression for this distance, d , is developed as follows. Consider a lightly-doped polysilicon film (with the crystallites completely depleted) with a grain size L . The variation of the potential energy, E_b , with distance x (measured from the centre of the grain boundary region) is given by:

$$E_b(x) = E_{b_{\max}} \left(1 - \frac{x}{L/2}\right)^2 \quad (5.11)$$

where $E_{b_{\max}}$ is given by Eqn. (2.3):

$$E_{b_{\max}} = \frac{q^2 L^2 N}{8\epsilon} \quad (5.12)$$

At $x=d$,

$$E_b(d) = E_{b_{\max}} - kT.$$

We therefore obtain from Eqns. (5.11) and (5.12):

$$d = \frac{L}{2} \left[1 - \left(1 - \frac{8\epsilon kT}{q^2 L^2 N}\right)^{\frac{1}{2}}\right] \quad (5.13)$$

It is therefore seen that d is a function of both the grain size L and dopant density N .

Direct calculations using Eqn. (5.13) yield the following results (at 300°K):

		d		
$L, \text{\AA}$	N, cm^{-3}	4×10^{17}	5×10^{17}	1×10^{18}
200		$d=59.6 \text{\AA}$	$d=42.5 \text{\AA}$	$d=18.4 \text{\AA}$
500		$d=17.3 \text{\AA}$	$d=13.8 \text{\AA}$	-

These results clearly indicate that the distance d could become comparable to the carrier mean free path at low doping concentrations and/or small grain sizes, thereby rendering the neglect of the collisions of carriers inadequate. In this case, more accurate modeling may be achieved by considering diffusion, in addition to thermionic emission of current carriers, similar to the approach developed by Crowell and Sze^[39] in conjunction with metal-semiconductor contacts, as mentioned in Section 2.2.2.3.

Such a condition (which was not met in the films studied in the present work due to the relatively high doping levels and large grain sizes obtained) is unlikely to be of practical significance particularly in applications involving the piezoresistive properties of the polysilicon films such as semiconductor strain gauge applications. The piezoresistance effect in such films (with completely depleted crystallites) would be too noisy (as shown earlier) to be of any practical use.

5.3 Concluding Remarks

1. A novel approach to the modelling of conduction in polysilicon has been presented. The approach makes use of the piezoresistance effect in the determination of the active dopant concentration in the grains of highly doped films where the neutral crystalline bulk of a grain occupies most of its volume.
2. The validity of the approach in the characterization of diffused polysilicon films has been verified by comparing the value of the average grain size deduced from the approach to that obtained independently from large signal I-V measurements carried out on polysilicon resistors. Excellent agreement was found between the two values of grain size for both boron- and phosphorous-diffused films for which these two values were obtainable.
3. The values of the polysilicon film parameters, such as L , Q_T , and W_{g_b} , deduced from the approach compare favourably with existing data obtained by previous researchers.
4. The approach allows for the effect of partial ionization of impurity atoms (at impurity concentrations above 5×10^{18} atoms/cm³) to be included. A procedure for an approximate solution to this problem has been given. It has been applied to the characterization of a heavily doped boron-diffused film.
5. Large signal I-V measurements are useful in the characterization of diffused polysilicon films. For lightly doped films (for which the piezoresistance coefficient is not calculable due to the noisy behaviour of piezoresistance in these films), these

measurements provide an alternative means of quantitatively characterizing the films. For the more heavily doped films (for which the piezoresistance coefficient is measurable), the large signal measurements serve as an independent method to check the validity of the modelling approach in the characterization of these films. The large signal data have been used to determine the average grain size for films of both types mentioned above.

CHAPTER 6

CONCLUSIONS AND RECOMMENDATIONS

The principal objectives of this research were:

- to characterize the electrical and piezoresistive properties of diffused polycrystalline-silicon films and to relate these properties to each other to develop a model for electrical conduction.
- to investigate the possibility of utilizing the piezoresistance effect in the fabrication of practical electromechanical transducers.

This chapter describes the major results of the work, which has concentrated mainly on the first of these objectives, and presents recommendations for further investigations.

6.1 Research Contributions

6.1.1 Basic Theory

An important aspect of the research has been the critical appraisal of the state of knowledge of the conduction properties of polycrystalline silicon and of the mechanisms of stress-dependent effects (or piezoresistance effects). Physical theory is far from satisfactory in these fields, being incomplete and often founded on inadequately justified or unverified hypotheses; supporting experimental work is fragmentary.

Incompleteness and the scattered nature of the literature are also an obstacle to understanding in these fields. Thus, a vital part of the work has been that of drawing together and critically assessing the state of knowledge on both single crystal and polycrystalline silicon; specifically, this has entailed study of the basic physics underlying electrical conduction and piezoresistance effects in heavily doped single crystal, polycrystalline and amorphous silicon. The main outcome of this part of the work is presented in Chapters 2 and 3, the material being derived from the sources cited where referenced, and otherwise being originated by the writer. All critical assessments and conclusions are the writer's. The new contributions made are:

1. Identification of incompleteness of understanding of the nature of grain boundaries of diffused polycrystalline silicon in regard to the relative roles of carrier trapping mechanisms and impurity atoms segregation, and also regarding the physical laws that govern segregation. (It has been shown that the latest only semi-quantitative segregation model^[28] available fails to represent the effect of annealing on the resistivity of diffused polysilicon.)
2. Critical assessment of the physical basis of Seto's conduction model.
3. The establishment that tunneling of carriers through the grain boundary potential energy barriers is a mechanism that should be accounted for in the modelling of electrical conduction in polysilicon.

4. Analysis of the effect of different scattering mechanisms on the piezoresistance coefficient for heavily doped N-type silicon in the attempt to close the gap between quantitative theoretical prediction and experimental results.
5. Conclusion that the only existing analytical treatment of piezoresistance effects in P-type silicon is oversimplified from the outset and that the order of magnitude discrepancy between the measured and the predicted value of the deformation potential constant associated with the valence band is due to the starting assumption of approximating the energy surfaces (in the absence of stress) by spheres, and also the neglect of the stress-induced changes in the elements of the hole-Hamiltonian matrix.

6.1.2 Modelling

The following significant results represent the principal contributions to the modelling of electrical conduction and piezoresistance effects in diffused polycrystalline films:

1. The establishment, through direct experimental evidence, that the latest segregation model developed by Mandurah et al [23,24,28] is inapplicable to diffused polysilicon films.
2. The extension of the resistivity model proposed by the above mentioned workers [23,24] to the characterization of boron-diffused polysilicon films (in addition to its use in characterizing films doped with N-type impurities such as phosphorous and arsenic).

3. The identification of the different effective masses involved in the expression for electrical resistivity developed by the above mentioned workers [23,24], as shown in Section 2.2.3.
4. The establishment of a model for the piezoresistance coefficient of diffused polysilicon films over the practical range of macroscopic doping concentration from 10^{18} to 10^{20} atoms/cm³.
5. The establishment, through experiment, that in practically useful polysilicon films, the average piezoresistive properties are dominated by those in the neutral bulk of the grain, and that the piezoresistance effect associated with the grain boundary region (significant at lower doping concentrations) is inherently 'noisy' in nature due, presumably, to random current fluctuations associated with trapping mechanisms in the boundary region and their stress dependence.
6. The development of a novel approach to the modelling of diffused polysilicon films that is based on exploiting the piezoresistance effect to infer the value of the active dopant concentration, an important parameter controlling the electrical resistivity of the films.
7. Determination of the average grain size L from large signal current-voltage characteristics.

8. Demonstration of consistency of thermionic-tunneling model of conduction for boron- and phosphorous-diffused films fabricated by methods of integrated circuits technology, this being made possible by the availability of the independent sources of data provided by 6 and 7 above.
9. The establishment that, for diffused polysilicon films, significant segregation of phosphorous does occur; confirmation that, for boron, segregation is negligible.
10. Demonstration of some ability to include the effect of partial ionization of impurity atoms in the conduction model.

6.1.3 Transducer Applications

The results of piezoresistance measurements presented in Chapter 4 clearly indicate the promising aspects of the piezoresistive effect in diffused polysilicon resistors as far as practical transducers are concerned. The highly stable, reasonably large gauge factor of 14 to 25 obtained with both boron- and phosphorous-diffused films (with dopant concentrations above a certain value) points to the prospects of fabricating a polysilicon strain gauge with a gauge factor higher than that obtained with conventional metal gauges by an order of magnitude. The lower value of the temperature coefficient of gauge factor of phosphorous-diffused polysilicon films (compared to similarly doped single crystal silicon) points to another promising feature of these films, namely a reduced temperature sensitivity of their gauge factor, a particularly desirable quality in practical strain gauges.

A lower limit has also been established (experimentally) on the dopant concentration above which the piezoresistive effect in diffused polysilicon layers is practically useful.

The above practical considerations are of importance in the field of silicon sensor technology where recent advances have made possible a merger of sensors and integrated circuits into "integrated sensors" - silicon chips containing both sensors and conditioning circuits such as amplifiers, linearizing circuits, and compensating circuits. Used in conjunction with microprocessors, these "integrated sensors" could contribute to improved system performance with decreased part count and decreased cost.

6.2 Recommendations for Future Work

Accurate and comprehensive models for polycrystalline silicon are becoming essential for computer-aided process modelling of semiconductor integrated circuits. Based on the results of this research, the following areas are recommended for future investigation:

1. A model for grain growth in polysilicon. This should be capable of predicting the average grain size of the films as a function of deposition conditions, film thickness, doping, and heat treatment.
2. Study of segregation effects in diffused polysilicon films. Better understanding is needed. More sophisticated measurements, that could involve Hall-effect measurements, should be carried out as a means of conducting a thorough investigation of the segregation mechanism. The aim should

be to establish a generalized quantitative model for segregation of impurity atoms to the grain boundaries of a polycrystalline material.

3. Study of grain-boundary passivation. A means needs to be developed to control the effects of grain boundaries on the properties of the films including their piezoresistive coefficient at low doping concentrations.

APPENDIX A

THE SEGREGATION MODEL OF MANDURAH ET AL^[23,24,28]

The physical basis of this model is examined below. A statement of the simplifying assumptions involved in the derivation of the basic equation representing the segregation of impurity atoms at the grain boundaries of polysilicon (Eqn. (2.1) of Chapter 2) is given.

The phenomenon of surface or interface segregation in a multi-component system has been predicted and experimentally observed for a number of years. It can be described using the Gibbs adsorption equation^[70-73]:

$$d\gamma = -S_s dT - \Gamma_A d\mu_A - \Gamma_B d\mu_B \quad (A.1)$$

where γ is the surface energy, S_s is the surface excess entropy, Γ_A and Γ_B are the surface excess concentrations of component A and component B, and μ_A and μ_B are the chemical potentials of the two components. In general, Eqn. (A.1) cannot be solved for real physical systems. One approximation that is often used is to assume that the only entropy term that need be included is the ideal entropy of mixing^[71]. The problem then reduces to setting the chemical potential of the surface and bulk atoms equal so that:

$$E_s + kT \ln \frac{X_s}{1-X_s} = E_b + kT \ln \frac{X_b}{1-X_b} \quad (A.2)$$

where X_s and X_b are the surface and bulk atom fractions of component A,

E_s and E_b are the enthalpies of component A at the surface and in the bulk, respectively. From Eqn. (A.2), we obtain:

$$\frac{X_s}{1-X_s} = \frac{X_b}{1-X_b} \exp \left(\frac{E_b - E_s}{kT} \right) \quad (A.3)$$

In polycrystalline silicon, we are not dealing with free surfaces, but grain boundaries. There has been considerable work done on segregation of solute atoms to grain boundaries for metal systems [74]. In all cases studied where segregation occurs at grain boundaries, it also occurs for the free surface. The major difference between the grain boundary and the free surface is the magnitude of the heat of segregation which would be larger for the free surface.

To calculate the amount of segregation, a general model is taken for the distribution of dopant atoms between the bulk and grain boundaries as described by Eqn. (A.3). This leads to a relationship for the atom fraction of dopant atoms on the grain boundaries X_{GB} ($X_{GB} = \frac{N_{GB}}{N_s}$) in terms of the atom fraction of dopant atoms X_G ($X_G = \frac{N_G}{N_{Si}}$) in the bulk of the grain. For an infinite sample with one grain boundary, X_{GB} may be expressed in terms of X_G , annealing temperature T_A , and a heat of segregation Q as in Eqn. (A.3).

$$\frac{X_{GB}}{1-X_{GB}} = \frac{X_G}{1-X_G} \exp \frac{Q}{kT_A} \quad (A.4)$$

The heat of segregation $Q = E_b - E_s$ is directly determined by the difference in enthalpy between an atom on the grain boundary and one in the bulk and may, in general, be a function of X_G and T_A . If the

binding energies of the dopant atoms in the bulk and on the grain boundary are the same, then $Q=0$. If, however, the interfacial free energy is reduced by placing the dopant atom on the grain boundary, Q will be positive, thus favouring segregation of the dopant atoms to the grain boundary.

Equation (A.2) from which Eqn. (A.4) was derived is based on the assumption that the only entropy term is the ideal entropy of mixing. In general, the vibrational entropy should also be taken into account. Hence Q will include an additional entropy term such that $Q = Q_0 - S T_A$, where Q_0 is the difference in enthalpies, as defined above, and S is the difference in vibrational entropy between a dopant atom on the grain boundary and one in the bulk. This leads to the modification of Eqn. (A.4) by an additional pre-exponential factor A , yielding:

$$\frac{x_{GB}}{1-x_{GB}} = \frac{A x_G}{1-x_G} e^{Q_0/kT_A} \quad (A.5)$$

where

$$A = e^{-S/k}$$

The above analysis assumes that the total number of lattice sites present on the grain boundaries is negligible compared to the total number of sites present in the system (i.e. $\frac{Q_s}{N_{Si}} \ll 1$), a condition usually met by typical polysilicon films used in practice where the grain size is always larger than a few hundred angstroms (note that,

for silicon, $\frac{Q_s}{N_{Si}} = \frac{1.62 \times 10^{-7}}{L}$, L is the grain size in cms.)

For weak segregation in moderately doped materials (i.e.

$X_{GB}, X_G \ll 1$), Eqn. (A.5) can be simplified to:

$$X_{GB} = A X_G \exp \left(\frac{Q_0}{kT_A} \right) \quad (A.6)$$

but

$$X_{GB} = \frac{N_{GB}}{Q_s}, \quad X_G = \frac{N_G}{N_{Si}} \quad (A.7)$$

where the different symbols are defined in Chapter 2. Hence,

$$\frac{N_{GB}}{Q_s} = \frac{A N_G}{N_{Si}} \exp \left(\frac{Q_0}{kT_A} \right)$$

or

$$\ln \frac{N_{GB}}{N_G} = \ln \frac{A Q_s}{N_{Si}} + \frac{Q_0}{kT_A} \quad (A.8)$$

which is Eqn. (2.1) of Chapter 2, with $N_{GB} = N - N_G$.

It should be noted that the above segregation model represented by Eqn. (A.8) is only semi-quantitative; the parameters A and Q_0 (the entropy factor and the segregation heat, respectively) being determined empirically. The values of these two parameters were found to vary with dopant species and concentrations [23,24,28]. It should also be noted that while the above segregation model predicted with good accuracy the high temperature annealing characteristics of ion-implanted polysilicon films [23,24,28], it was found inapplicable to diffused films

investigated in the present work, as explained in Chapter 4 in conjunction with heat treatment experiments performed on the diffused films.

APPENDIX B

ELECTRICAL CONDUCTION IN POLYCRYSTALLINE SILICON

The physical basis of the conduction model of Mandurah et al^[23,24] (discussed in Chapter 2) is explained below. A statement of the assumptions involved in the derivation of the current-voltage relationship represented by Eqn. (2.11) of Chapter 2 is made. It should be emphasized from the outset that although the identification of appropriate effective masses of carriers is essential to the theory, this is not done in references [23,24]. The distinction between the conductivity effective mass and the Richardson constant effective mass is made here by the present writer.

Electrical conduction in a polycrystalline film occurs by carrier motion from one grain to another by tunneling through and/or by thermionic emission over the barriers at the grain boundary. The one-dimensional time-independent tunneling probability $D(E_x)$ for a barrier of height $q V(x)$ is givenⁱⁿ the WKB approximation by^[75-77]:

$$D(E_x) = \exp \left\{ -\frac{4\pi}{h} \int_{x_1}^{x_2} [2m_c^* (q V(x) - E_x)]^{1/2} dx \right\} \quad (B.1)$$

where E_x is the energy component of the incident carrier in the x direction with zero energy taken at the bottom of the conduction band in the neutral region of the grains, and m_c^* , the conductivity effective mass of the carriers, is assumed to be independent of the energy of carriers.

The number of carriers having energy within the range dE_x incident on the barrier per second per unit area is given by^[76]:

$$N(T, \xi, E_x) dE_x = \frac{4\pi m_T^* kT}{h^3} \ln \left\{ 1 + \exp \left[-\frac{(E_x + \xi)}{kT} \right] \right\} dE_x \quad (B.2)$$

where $N(T, \xi, E_x)$ is called the supply function, $\xi = E_C - E_F$, and m_T^* is the Richardson constant effective mass.

Let V_O be the (average) voltage drop across the composite grain boundary region. This voltage will be dropped across the grain-boundary barrier and the two depletion regions on either side of the grain boundary, as shown in Fig. B.1, such that:

$$V_O = V_{g_b} + V_L + V_R \quad (B.3)$$

where V_{g_b} is the voltage drop across the grain-boundary barrier, and V_L and V_R are the voltage drops across the depletion regions on the left and right sides of the grain boundary, respectively. The number of electrons tunneling from right to left N_{LR} and the number of electrons tunneling from left to right N_{RL} can be calculated by integrating $D(E_x)N(T, \xi, E_x)$ over all energies.

$$N_{LR} = \frac{4\pi m_T^* kT}{h^3} \int_0^\infty \ln \left\{ 1 + \exp \left[-\frac{(E_x + \xi - q V_{g_b}/2 - q V_L)}{kT} \right] \right\} D_{LR}(E_x) dE_x$$

and

$$N_{RL} = \frac{4\pi m_T^* kT}{h^3} \int_0^\infty \ln \left\{ 1 + \exp \left[-\frac{(E_x + \xi + q V_{g_b}/2 + q V_R)}{kT} \right] \right\} D_{RL}(E_x) dE_x \quad (B4)$$

Fig. B.1. Energy-band diagram near a grain boundary.
 (a) With zero applied voltage
 (b) With an applied voltage across the grains of polysilicon films.

Here $D_{LR}(E_x)$ and $D_{RL}(E_x)$ are the probabilities of tunneling through the barriers at a grain boundary from left to right and from right to left, respectively. In general, $D_{LR}(E_x)$ and $D_{RL}(E_x)$ are functions of the different voltages dropped across the grain boundary barrier and the depletion regions on its sides to that $D_{LR}(E_x) \neq D_{RL}(E_x)$. Thus the net current density J through a grain boundary can be written as:

$$\begin{aligned}
 J &= q(N_{LR} - N_{RL}) \\
 &= q \left(\frac{4\pi m^* kT}{h^3} \right) \cdot \left[\int_0^\infty \ln \left(1 + \exp \left[\frac{-(E_x + \xi - q V_{gb} / 2 - q V_L)}{kT} \right] \right) D_{LR}(E_x) dE_x \right. \\
 &\quad \left. - \int_0^\infty \ln \left(1 + \exp \left[\frac{-(E_x + \xi + q V_{gb} / 2 + q V_R)}{kT} \right] \right) D_{RL}(E_x) dE_x \right] \quad (B.5)
 \end{aligned}$$

In order to solve Eqn. (B.5), the tunneling probabilities $D_{LR}(E_x)$ and $D_{RL}(E_x)$ have to be obtained first by solving Eqn. (B.1) for the appropriate energy barrier $q V(x)$.

The current-voltage relationship given by Eqn. (B.5) can be greatly simplified by imposing the following limitations:

1. The solution to the current-voltage relationship is restricted to intermediate temperatures.
2. The (average) applied voltage per grain V_0 is much less than the height of the grain-boundary barrier, i.e.
 $V_0 \ll \phi$.
3. The maximum barrier height in the depletion region of the grains is much less than the height of the grain-boundary barrier, i.e. $V_D \ll \phi$.

At intermediate temperatures only a few carriers have energies higher than the maximum height of the grain-boundary barriers. Thus the contribution to current by thermionic emission of carriers over the grain-boundary barriers can be ignored. Furthermore, the grain-boundary barriers are much thinner than the barriers in the depleted regions of the grains. As a result, the probability of tunneling through the composite depletion region and grain-boundary barrier is much lower than the probability of tunneling through the grain-boundary barrier alone. Consequently, the contribution to current by carriers tunneling through this composite barrier can also be ignored. Thus conduction is mainly controlled by carriers tunneling through the grain-boundary barriers after being thermally emitted over the depletion region barriers; that is, carriers whose values of E_x are in the range $q V_b < E_x < q\phi$.

By including the above approximations, Eqn. (B.5) can be written in the following form:

$$J = q \left(\frac{4\pi m^* kT}{h^3} \right)$$

$$\left[\int_{q V_b + q V_{gb}/2}^{q\phi + q V_{gb}/2} \ln \left\{ 1 + \exp \left[\frac{-(E_x + \xi - q V_{gb}/2 - q V_L)}{kT} \right] \right\} D_{LR}(E_x) dE_x \right. \\ \left. + \int_{q V_b - q V_{gb}/2}^{q\phi - q V_{gb}/2} \ln \left\{ 1 + \exp \left[\frac{-(E_x + \xi + q V_{gb}/2 + q V_R)}{kT} \right] \right\} D_{RL}(E_x) dE_x \right] \quad (B.6)$$

Here the limits of integration have been chosen in accordance with assumption 1 to account only for the carriers whose energies are between the top of the depletion region barrier and the top of the grain-boundary barrier. The above equation can be further simplified by considering only the Maxwell-Boltzmann tails of the carrier distributions; thus the logarithms in Eqn. (B.6) can be replaced by the respective exponents to obtain:

$$J = q \left(\frac{4\pi m^* kT}{h^3} \right) \left[\int_{qV_b + qV_{gb}/2}^{q\phi + qV_{gb}/2} D_{LR}(E_x) \exp\left[\frac{-(E_x + q\phi V_{gb}/2 - qV_L)}{kT} \right] dE_x \right. \\ \left. - \int_{qV_b - qV_{gb}/2}^{q\phi - qV_{gb}/2} D_{RL}(E_x) \exp\left[\frac{-(E_x + \phi + qV_{gb}/2 + qV_R)}{kT} \right] dE_x \right] \quad (B.7)$$

Since the current flow is predominantly due to carriers whose values of E_x are only slightly greater than the maximum height of the barriers in the depletion regions, the tunneling probability $D(E_x)$ can be simplified by expanding the integral in Eqn. (B.1) with respect to

$$\alpha_x = qV_b - E_x \quad (B.8)$$

using a Taylor-series expansion [77]:

$$\ln D(E_x) = -[b_1 + c_1 \alpha_x + f_1 \alpha_x^2 + \dots] \quad (B.9)$$

where

$$b_1 = \frac{4\pi}{h} (2m_c^*)^{\frac{1}{2}} \int_{x_1}^{x_2} [q V(x) - q V_b]^{\frac{1}{2}} dx \quad (B.10)$$

$$c_1 = \frac{2\pi}{h} (2m_c^*)^{\frac{1}{2}} \int_{x_1}^{x_2} [q V(x) - q V_b]^{-\frac{1}{2}} dx \quad (B.11)$$

$$f_1 = \frac{\pi}{h} (2m_c^*)^{\frac{1}{2}} \left[\frac{1}{(x_2 - x_1)} \left(\frac{1}{q V(x_1)} - \frac{1}{q V(x_2)} \right) \right. \\ \left. \int_{x_1}^{x_2} \frac{dx}{[q V(x) - q V_b]^{\frac{3}{2}}} \right. \\ \left. - \frac{1}{2} \int_{x_1}^{x_2} \frac{dx}{[q V(x) - q V_b]^{\frac{3}{2}}} \cdot \left(1 - \frac{q V(x)}{(x_2 - x_1)} \left(\frac{x - x_1}{q V(x_2)} - \frac{x_2 - x}{q V(x_1)} \right) \right) \right] \quad (B.12)$$

For applied voltages much less than the height of the grain-boundary barrier (assumption 2), b_1 , c_1 , and f_1 are independent of the applied voltage so that^[76]:

$$D_{LR}(E_x) = D_{RL}(E_x) = D(E_x) \quad (B.13)$$

Following Murphy and Good^[76] and Stratton^[77], it can be shown that the quadratic and higher order terms in Eqn. (B.9) can be neglected if

$$1 - c_1 kT > kT(2f_1)^{\frac{1}{2}} \quad (B.14)$$

Furthermore, due to the use of the WKB approximation for calculating $D(E_x)$, the following condition must also be satisfied [76,77]:

$$q\phi_m - qV_b - kT(1 - c_1 kT)^{-1} > \Omega \quad (B.15)$$

where $D(\Omega) = e^{-\Omega}$ and ϕ_m is the maximum value of $V(x)$.

The constants b_1 and c_1 can be obtained by solving Eqs. (B.10) and (B.11) using the appropriate barrier $qV(x)$. For carriers with energies in the range $qV_b < E_x < q\phi$, the appropriate barrier is the rectangular grain-boundary barrier defined by:

$$qV(x) = 0 \quad \text{for } |x| > W_{gb}/2 \quad (B.16)$$

$$qV(x) = \phi \quad \text{for } |x| < W_{gb}/2$$

Thus carrying out the integration over the width of the barrier, b_1 and c_1 are given by:

$$b_1 = \frac{4\pi W_{gb}}{h} (2m_c^*)^{1/2} (q\phi - qV_b)^{1/2} \quad (B.17)$$

$$c_1 = \frac{2\pi W_{gb}}{h} (2m_c^*)^{1/2} (q\phi - qV_b)^{-1/2} \quad (B.18)$$

Substituting for $D(E_x)$ from Eqs. (B.9) and (B.7) and integrating, the current-voltage relationship can be obtained:

$$\begin{aligned}
 J = & q \left(\frac{4\pi m^* k^2 T^2}{h^3} \right) \exp\left(-\frac{\xi}{kT}\right) \frac{\exp(-b_1 - c_1 q V_b)}{(1 - c_1 kT)} \\
 & \cdot \left[\exp\left[-\frac{q V_{g_b}}{2kT} + \frac{q V_L}{kT}\right] \left\{ \exp\left[-\frac{-(1 - c_1 kT)(q V_b + q V_{g_b}/2)}{kT}\right] \right. \right. \\
 & \quad \left. \left. - \exp\left[-\frac{-(1 - c_1 kT)(q\phi + q V_{g_b}/2)}{kT}\right] \right\} - \exp\left[-\frac{q V_{g_b}}{2kT} - \frac{q V_R}{kT}\right] \right. \\
 & \quad \left. \cdot \left\{ \exp\left[-\frac{-(1 - c_1 kT)(q V_b - q V_{g_b}/2)}{kT}\right] - \exp\left[-\frac{-(1 - c_1 kT)(q\phi - q V_{g_b}/2)}{kT}\right] \right\} \right] \quad (B.19)
 \end{aligned}$$

Since $q\phi \gg q V_b$ (assumption 3), the exponential terms containing $q\phi$ in Eqn. (B.19) are much smaller than the exponential terms containing $q V_b$ and can be ignored. Thus, Eqn. (B.19) can be expanded and written in the following form:

$$\begin{aligned}
 J = & q \left(\frac{4\pi m^* k^2 T^2}{h^3} \right) \exp\left(-\frac{\xi}{kT}\right) \frac{\exp(-b_1)}{(1 - c_1 kT)} \exp\left(-\frac{q V_b}{kT}\right) \\
 & \cdot \left[\exp\left(\frac{q V_L}{kT} + c_1 \frac{q V_{g_b}}{2}\right) - \exp\left(-\frac{q V_R}{kT} - c_1 \frac{q V_{g_b}}{2}\right) \right] \quad (B.20)
 \end{aligned}$$

A much simpler form of the current-voltage relationship can be obtained by restricting the solution to small applied voltages. If the applied voltage is much less than the height of the barrier in the depletion region (i.e. $V_0 \ll V_b$), then the different voltage drops across the depletion regions and across the grain boundary barrier can be given by [78]:

$$V_L = V_R = V_d \quad (B.21)$$

and

$$V_{g_b} = \frac{W_{g_b} N_G}{Q_T} \cdot 2V_d \quad (B.22)$$

where

$$2V_d = V_L + V_R \quad (B.23)$$

and the current-voltage relationship (B.20) can be written as:

$$J = q \left(\frac{4\pi m^*_T k^2 T^2}{h^3} \right) \exp \left(\frac{-\xi}{kT} \right) \cdot \frac{\exp(-b_1)}{1 - c_1 kT} \cdot \exp \left(- \frac{q V_b}{kT} \right) 2 \sinh \left[\frac{1 + c_1 kT \frac{N_G W_{g_b}}{Q_T}}{1 + \frac{N_G W_{g_b}}{Q_T}} \cdot \frac{q V_o}{2kT} \right] \quad (B.24)$$

which is Eqn. (2.11) of Chapter 2.

It should be noted that two effective masses are involved in this equation, b_1 and c_1 being defined in terms of m_c^* .

APPENDIX C

PROCESS SIMULATION USING "SUPREM II"

The following computer program was loaded on SUPREM II to simulate the two-step diffusion process employed in the fabrication of test wafers at Carleton University:

```
1...TTTL          PHOS DIFFUSION
2...GRID          DYSI=0.01,DPTH=3,YMAX=300
3...SUBS          ORNT=100,ELEM=B,CONC=6E15
4...COMM          PREHEAT
5...STEP          TYPE=OXID,TIME=5,TEMP=?,MODL=DRYO
6...COMM          REMOVE OXIDE
7...STEP          TYPE=ETCH,TEMP=18
8...COMM          PHOSPHOROUS PREDEPOSITION
9...STEP          TYPE=PDEP,ELEM=P,CONC=?,TIME=2,TEMP=?,
                  +MODL=MPHO
10...COMM         FLUSH TUBE
11...STEP         TYPE=OXID,TIME=10,TEMP=?,MODL=DRYO
12...COMM         ETCH BACK
13...STEP         TYPE=ETCH,TEMP=18
14...PRINT        HEAD=Y
15...COMM         DRIVE-IN IN DRY O2
16...STEP         TYPE=OXID,TIME=10,TEMP=1075,MODL=DRYO
17...END
```

The above program was used in conjunction with sheet resistance measurement on unpatterned single crystal monitor wafers to determine the operating conditions of the diffusion process, specifically the dopant concentration in the gas phase represented by the parameter "CONC" in statement #9. This was achieved through a trial-and-error procedure in which the above program was run several times with the parameter "CONC" given different values, and the resulting sheet resistance (given in the output "HEAD" information of SUPREM) compared to the actual measured value on a single crystal diffused silicon wafer

with the particular set of predeposition and drive-in parameters simulated by the program. The solution was obtained when the two values of sheet resistance (i.e. SUPREM's value and the measured value) coincided.

The value of the silicon dopant charge (per unit surface area) deposited during the diffusion process which is given in the program output data was then used to calculate the macroscopic dopant concentration in the similarly processed polysilicon film as explained in Chapter 4.

APPENDIX D

DEVICE FABRICATION PROCEDURE

<u>Process Steps</u>	<u>Batches</u>	
	<u>Polysilicon Wafers</u>	<u>Single Crystal Wafers</u>
1. Pre-furnace clean.	x	x
2. Field oxidation (Temp=1200°C, thickness=1.0 μ m)		x
3. First thermal oxidation (Temp=1200°C, thickness=0.1 μ m, dry O ₂)	x	
4. Second thermal oxidation (Temp=1200°C, thickness=0.4 μ m, dry O ₂)	x	
5. Polysilicon deposition (atmospheric pressure, film thickness=0.5 μ m)	x	
6. Polysilicon oxidation (Temp=1075°C, Time=30 min.)	x	
7. Photoresist-Mask-Polysilicon pattern definition	x	
7a. Photoresist-Mask-Etch field oxide (prior to diffusion)		x
8. Phosphorous (or boron) predeposition	x	x
9. Phosphorous (or boron) drive-in (Temp=1075°C, Time=10 min.)	x	x
10. Silox deposition (Temp=350°C, thickness=0.5 μ m)	x	x
11. Photoresist-Mask-Contact Windows	x	x
12. Aluminum Deposition (thickness=1.0 μ m)	x	x
13. Photoresist-Mask-Metal Pattern Definition	x	x
14. Aluminum Anneal (Temp=450°C)	x	x
15. Pyrex Deposition (Temp=350°C, thickness=1.0 μ m)	x	x
16. Photoresist-Mask-Bonding Pads Opening	x	x

NOTES:

The above process steps were applied to patterned wafers, for unpatterned wafers, the process was terminated at step 9, i.e. after drive-in.

Some of the polysilicon wafers had an additional annealing step after depositing the polysilicon film (i.e. after step 5), the annealing was done at 1200°C for one hour in a dry nitrogen ambient. These wafers are identified in Table 4.1.

- * Some of the patterned polysilicon wafers had a cap of low temperature deposited SiO_2 (350°) instead of thermally grown oxide cap (step 6) for the purpose of film patterning. These are also identified in Table 4.1.
- * The oxide grown in step #3 is only for chemically polishing the wafer surface; it is subsequently removed.

APPENDIX E

CALCULATIONS OF THE STRESSES IN CANTILEVER BEAMS

Figure E.1 shows a cantilever beam subjected to a concentrated load F at its free end. The distribution of the bending moment along the length of the cantilever is also shown in the figure.

The cross-section of the cantilever at any point along its length undergoes, in general, two types of stress, namely the normal (or bending) stress p_n , which is normal to the cross-section, and the shear stress, p_{sh} .

The shear stress p_{sh} has a parabolic distribution along the height of the cross-sectional area with a maximum value (at the mid-point of the section) equal to:

$$p_{sh \max} = \frac{3}{2} \frac{F}{A} \quad (E.1)$$

where F is the force and A is the area of the cross-section of the beam.

The normal stress varies linearly across the height of the cross-section with a zero value at the centre; the expression for p_n assumes the form [79]:

$$p_n = \frac{My}{I} \quad (E.2)$$

where I is the moment of inertia of the cross-sectional area about the Z -axis, $I = bh^3/12$;

y is the vertical distance from the neutral axis.

Fig. E.1. Bending moment diagram of a cantilever with a concentrated load applied to the free end.

M is the value of the bending moment at the position x of the cross-sectional area.

The expression for the deflection, δ , of the free end of the cantilever is as follows^[79]:

$$\delta = \frac{Fl^3}{3YI} \quad (E.3)$$

where l is the length of the cantilever and Y is Young's modulus of the material of the beam.

For a device at a distance d from the free end, the bending moment M_o is equal to:

$$M_o = Fd \quad (E.4)$$

Mathematical manipulation of Eqns. (E.2), (E.3) and (E.4), with $h/2$ substituted for y in Eqn. (E.2) (at the surface of the cantilever), yields the following expression which relates the normal stress P_n at the position of the device to the deflection, δ , of the free end of the cantilever:

$$P_n = \frac{3}{2} Y \frac{hd}{l^3} \delta \quad (E.5)$$

The strain ϵ at the position of the device is obtained from Eqn. (E.5) by dividing both sides of the equation by the Young's modulus Y :

$$\epsilon = \frac{3}{2} \frac{hd\delta}{l^3} \quad (E.6)$$

Equation (E.6) was used to calculate the strain in the polysilicon piezoresistor. The values of the different parameters in this equation were as follows:

$$l = 20 \text{ mm}$$

$$h = 0.3 \text{ mm}$$

$$d = 16.8825 \text{ mm}$$

To calculate the stress in the piezo-resistor (and hence the piezoresistance coefficient), a value for Young's modulus of polysilicon equal to 1.585×10^{12} dynes/cm² was used. This value is obtained in Appendix F.

APPENDIX F

YOUNG'S MODULUS FOR POLYCRYSTALLINE SILICON

Consider a row of grains with their orientations falling into one of the three categories of crystal orientations most frequently encountered in practice, namely the [100], [110], or [111] directions, and assume there are m grains within each of the above three categories.

Let a uniaxial stress p be applied to the row of grains, and let the resulting strains be $\epsilon_{[100]}$, $\epsilon_{[110]}$, $\epsilon_{[111]}$ for the differently-oriented grains. We have:

$$\epsilon_{[100]} = \frac{p}{Y_{[100]}} , \quad \epsilon_{[110]} = \frac{p}{Y_{[110]}} , \quad \epsilon_{[111]} = \frac{p}{Y_{[111]}} \quad (F.1)$$

where the Y 's are the values of Young's modulus for the three crystal orientations [100], [110] and [111]. We also have:

$$\epsilon_{[110]} = \frac{\Delta L_{[100]}}{L_0} , \quad \epsilon_{[110]} = \frac{\Delta L_{[110]}}{L_0} , \quad \epsilon_{[111]} = \frac{\Delta L_{[111]}}{L_0} \quad (F.2)$$

where the ΔL 's are the elongations of the differently-oriented grains along the direction of the applied uniaxial stress p , and L_0 is the unstressed grain size.

The total length of the stressed row of grains is:

$$L_R = m(L_0 + \Delta L_{[100]}) + m(L_0 + \Delta L_{[110]}) + m(L_0 + \Delta L_{[111]})$$

or

$$L_R = 3mL_0 + m(\Delta L_{[100]} + \Delta L_{[110]} + \Delta L_{[111]})$$

and the unstressed total length is $3mL_0$ so that the total elongation of the grains row is:

$$\Delta L_{tot} = m(\Delta L_{[100]} + \Delta L_{[110]} + \Delta L_{[111]}) \quad (F.3)$$

Substituting from Eqns. (F.1) and (F.2) into Eqn. (F.3), the total strain, ϵ_{tot} , in the row is obtained as follows:

$$\epsilon_{tot} = \frac{\Delta L_{tot}}{3mL_0} = \frac{p}{3} \left[\frac{1}{Y_{[100]}} + \frac{1}{Y_{[110]}} + \frac{1}{Y_{[111]}} \right] \quad (F.4)$$

If we define Young's modulus for the row of grains (or the polycrystalline row) as

$$Y_{poly} = \frac{p}{\epsilon_{tot}} \quad (F.5)$$

then it is easily seen from Eqn. (F.4) and (F.5) that:

$$Y_{poly} = 3 \left[\frac{1}{Y_{[100]}} + \frac{1}{Y_{[110]}} + \frac{1}{Y_{[111]}} \right]^{-1} \quad (F.6)$$

The values of the Y's for single crystal silicon are^[69]:

$$Y_{[100]} = 1.301 \times 10^{12} \text{ dynes/cm}^2$$

$$Y_{[110]} = 1.690 \times 10^{12} \text{ dynes/cm}^2$$

$$Y_{[111]} = 1.878 \times 10^{12} \text{ dynes/cm}^2$$

Hence the value of Young's modulus for polysilicon films is calculated to be equal to 1.585×10^{12} dynes/cm². This value was used in calculating the piezoresistance coefficient, as mentioned in Chapter 4.

It should be noted here that although the above calculated value of Y_{poly} was based on the starting assumption of equal densities of the three crystallographic orientations $\langle 100 \rangle$, $\langle 110 \rangle$ and $\langle 111 \rangle$ in the polycrystalline films studied in this work (with a $0.5 \mu\text{m}$ thickness), this value should not vary appreciably with deviations from that assumption, the lower limit on the actual value being equal to 1.301×10^{12} dynes/cm² (i.e. $Y_{[100]}$), and the upper limit equal to 1.878×10^{12} dynes/cm² (i.e. $Y_{[111]}$). Moreover, the above assumption is supported by the experimental results of Seto^[25] on boron-implanted polysilicon films (1-2 μm thick), and also by the validity of the modelling approach presented by the writer in Chapter 5 which makes use of the above calculated value of Y_{poly} in the estimation of the piezoresistance coefficient π_{poly} .

3 3

OF / DE

REFERENCES

1. Faggin, F. and Klein, T., "Silicon Gate Technology", Solid-State Electronics, Vol. 13, pp. 1125-1144, 1970.
2. Mountvala, A.J. and Abowitz, G., "Textural Characteristics and Electrical Properties of Vacuum Evaporated Silicon Films", Vacuum, Vol. 15, No. 7, pp. 359-362, 1965.
3. Vadasz, L.L., Grove, A.S., Rowe, T.A. and Moore, G.E., "Silicon Gate Technology", IEEE Spectrum, Vol. 6, pp. 28-35, Oct 1969.
4. Sarace, J.C., Kerwin, R.E., Klein, D.L. and Edwards, R., "Metal-Nitride-Oxide-Silicon Field-Effect Transistors, with Self-Aligned Gates", Solid-State Electronics, Vol. 11, pp. 653-660, 1968.
5. King, F.D., Shewchun, J. et al, "Polycrystalline Silicon Resistors for Integrated Circuits", Solid-State Electronics, Vol. 16, pp. 701-708, 1973.
6. Crossman, Leon D. and Baker, John A., "Polysilicon Technology", in Semiconductor Silicon, Electrochemical Society, pp. 18-31, 1977.
7. Choong-Ki Kim and Snow, E.H., "P-Channel Charge-Coupled Devices with Resistive Gate Structure", Appl. Physics Letters, Vol. 20, No. 12, pp. 514-516, 15 June 1972.
8. Kosonocky, W.F. and Carnes, J.E., "Charge-Coupled Digital Circuits", IEEE J. Solid-State Circuits, Vol. SC-6, No. 5, pp. 314-322, Oct 1971.
9. Kobayashi, I., "Technology for Monolithic High-Power Integrated Circuits Using Polycrystalline Si for Collector and Isolation Walls", IEEE Transactions on Electron Devices, Vol. ED-20, No. 4, pp. 399-404, April 1973.
10. Schnable, G.L., McKelvey, A.F. and Hastings, J.A., "A Chemical Technique for Preparing Oxide-Isolated Silicon Wafers for Microcircuits", Electrochemical Technology, Vol. 4, pp. 57-62, Jan-Feb 1966.
11. Yasutaka, B., Tsuchikawa, H. and Maeda, K., "Properties of Polycrystalline Silicon", in Semiconductor Silicon, Electrochemical Society, pp. 292-303, 1973.

12. Manoliu, J. and Kamins, T.I., "P-N Junctions in Polycrystalline-Silicon Films", Solid-State Electronics, Vol. 15, pp. 1103-1106, 1972.
13. Tsaur, B.Y., Fan, J.C.C., Geis, M.W., Silversmith, D.J., and Mountain, R.W., "Stress-Enhanced Mobility in MOSFETs Fabricated in Zone-Metling-Recrystallized Poly-Si Films", IEDM 81, pp. 232-235, 1981.
14. Lee, K.F., Gibbons, J.F. and Saraswat, K.C., "Thin Film MOSFETs Fabricated in Laser-Annealed Polycrystalline Silicon", Appl. Physics Letters, Vol. 35, No. 2, pp. 173-175, 15 Jul 1979.
15. Jaffe, J.M., "Monolithic Polycrystalline-Silicon Pressure Transducer", Electronics Letters, Vol. 10, No. 20, pp. 420-421, 1974.
16. Hassanein, T.L., "An Investigation of the Effects of Mechanical Stress on Electrical Characteristics of Semiconductor Devices with Reference to Stress Transducers", M.Eng. Thesis, Carleton University, Ottawa, Canada, 1977.
17. Kamins, T.I., "Hall Mobility in Chemically Deposited Polycrystalline Silicon", J. Appl. Physics, Vol. 42, No. 11, pp. 4357-4365, Oct 1971.
18. Seto, J.Y.W., "The Electrical Properties of Polycrystalline Silicon Films", J. Appl. Physics, Vol. 46, No. 12, pp. 5247-5254, Dec 1975.
19. Cowher, M.E. and Sedgwick, T.O., "Chemical Vapour Deposited Polycrystalline Silicon", J. Electrochemical Society, Vol. 119, No. 11, pp. 1565-1570, Nov 1972.
20. Baccarani, G. and Ricco, B., "Transport Properties of Polycrystalline Silicon Films", J. Appl. Physics, Vol. 49, No. 11, pp. 5565-5570, Nov 1978.
21. Lu, N.C.C., Gerzberg, L. and Meindl, J.D., "A Quantitative Model of the Effect of Grain Size on the Resistivity of Polycrystalline Silicon Resistors", IEEE Electron Device Letters, Vol. EDL-1, No. 3, pp. 38-41, Mar 1980.
22. Hassanein, T.L., "Investigation and Modelling of Electrical Conduction and Piezoresistance in Polycrystalline Silicon", Ph.D. Thesis Proposal, Carleton University, Ottawa, Canada, Oct 1980.
23. Mandurah, M.M., Saraswat, K.C. and Kamins, T.I., "A Model for Conduction in Polycrystalline Silicon -- Part I: Theory", IEEE Trans. on Electron Devices, Vol. ED-28, No. 10, pp. 1163-1171, Oct 1981.

24. Mandurah, M.M., Saraswat, K.C., and Kamins, T.I., "A Model for Conduction in Polycrystalline Silicon - Part II: Comparison of Theory and Experiment", IEEE Trans. on Electron Devices, Vol. ED-28, No. 10, pp. 1171-1176, Oct 1981.
25. Seto, J.Y.W., "Piezoresistive Properties of Polycrystalline Silicon", J. Appl. Physics, Vol. 47, No. 11, pp. 4780-4783, Nov 1976.
26. Onuma, Y. and Sekiya, K., "Piezoresistive Properties of Polycrystalline Silicon Thin Film", Japanese J. Appl. Phys., Vol. 11, No. 1, pp. 20-23, Jan 1972.
27. Fripp, A.L., "Dependence of Resistivity on the Doping Level of Polycrystalline Silicon", J. Appl. Physics, Vol. 46, No. 3, pp. 1240-1244, Mar 1975.
28. Mandurah, M.M., Saraswat, K.C., Helms, C.R., and Kamins, T.I., "Dopant Segregation in Polycrystalline Silicon", J. Appl. Phys., Vol. 51, No. 11, pp. 5755-5763, Nov 1980.
29. Jaccodine, R.J., "Surface Energy of Germanium and Silicon", J. Electrochemical Society, Vol. 110, No. 6, pp. 524-527, June 1963.
30. Swalin, R.A., Thermodynamics of Solids, Wiley, New York, p. 244, 1972.
31. Pearson, G.L. and Bardeen, J., "Electrical Properties of Pure Silicon and Silicon Alloys Containing Boron and Phosphorous", Physical Review, Vol. 75, No. 5, pp. 865-883, Mar 1949.
32. Horiuchi, S. and Blanchard, R., "Boron Diffusion in Polycrystalline Silicon Layers", Solid-State Electronics, Vol. 18, pp. 529-532, 1975.
33. Kamins, T.I., Manoliu, J. and Tucker, R.N., "Diffusion of Impurities in Polycrystalline Silicon", J. Appl. Physics, Vol. 43, No. 1, pp. 83-91, Jan 1972.
34. Lu, N.C-C., Gerzberg, L., Lu, C-Y., and Meindl, J.D., "A New Conduction Model for Polycrystalline Silicon Films", IEEE Electron Device Letters, Vol. EDL-2, No. 4, pp. 95-98, Apr 1981.
35. Lu, N. C-C., Gerzberg, L., Lu, C-Y., and Meindl, J.D., "Modelling and Optimization of Monolithic Polycrystalline Silicon Resistors", IEEE Trans. on Electron Devices, Vol. ED-28, No. 7, pp. 818-830, Jul 1981.
36. Bethe, H.A., "Theory of the Boundary Layer of Crystal Rectifiers", M.I.T. Radiation Lab Report No. 43-12, Nov 1942.

37. Many, A., Goldstein, Y. and Grover, N.B., Semiconductor Surfaces, Wiley, New York. 1965.
38. Sze, S.M., Physics of Semiconductor Devices, Wiley, New York, p. 62, 1969.
39. Sze, S.M., Physics of Semiconductor Devices, Wiley, New York, pp. 382-390, 1969.
40. Crowell, CR., "The Richardson Constant for Thermionic Emission in Schottky Barrier Diodes", Solid-State Electronics, Vol. 8, pp. 395-399, 1965.
41. Nicollian, E.H. and Goetzberger, A., "The Si-SiO₂ Interface - Electrical Properties as Determined by the MIS Conductance Technique", Bell System Tech. J., Vol. 46, pp. 1055-1133, 1967.
42. Gray, P.V. and Brown, D.M., "Density of SiO₂-Si Interface States", Applied Physics Letters, Vol. 8, pp. 31-33, 1966.
43. Mandurah, M.M., "The Physical and Electrical Properties of Polycrystalline-Silicon", Ph.D. Dissertation, Stanford University, Stanford, California, June 1981.
44. Muller, R.S. and Kamins, T.I., Device Electronics for Integrated Circuits, Wiley, New York, p. 33, 1977.
45. Korsh, G.J. and Muller, R.S., "Conduction Properties of Lightly Doped Polycrystalline Silicon", Solid-State Electronics, Vol. 21, pp. 1045-1051, 1978.
46. Bir, G.L. and Pikus, G.E., Symmetry and Strain-Induced Effects in Semiconductors, Wiley, New York, 1974.
47. Thurston, R.N., "Use of Semiconductor Transducers in Measuring Strains, Accelerations, and Displacements", Physical Acoustics, Vol. I, Part B, Chapter 11, Academic Press, New York, 1964.
48. Pfann, W.G. and Thurston, R.N., "Semiconducting Stress Transducers Utilizing the Transverse and Shear Piezoresistance Effects", J. Appl. Physics, Vol. 32, No. 10, pp. 2008-2019, Oct 1961.
49. Smith, C.S., "Piezoresistance Effect in Germanium and Silicon", Physical Review, Vol. 94, No. 1, pp. 42-49, 1954.
50. Herring, C. and Vogt, E., "Transport and Deformation-Potential Theory for Many-Valley Semiconductors with Anisotropic Scattering", Physical Review, Vol. 101, No. 3, pp. 944-961, 1956.

51. Keyes, R.W., "The Effects of Elastic Deformation on the Electrical Conductivity of Semiconductors", Solid-State Physics, Academic Press, Vol. 11, p. 149, 1960.
52. Smith, A.C., Janak, J.F. and Adler, R.B., Electronic Conduction in Solids, McGraw-Hill, New York, 1967. Also: Levine, S.N., Quantum Physics of Electronics, MacMillan, New York, 1965.
53. Herring, C., "Transport Properties of a Many-Valley Semiconductor", Bell System Tech. J., Vol. 34, No. 2, pp. 237-290, Mar 1955.
54. Morin, F.J., Geballe, T.H. and Herring, C., "Temperature Dependence of the Piezoresistance of High-Purity Silicon and Germanium", Physical Review, Vol. 105, No. 2, pp. 525-539, 1957.
55. Tekippe, V.J., Chandrasekhar, H.R., Fisher, P. and Ramdas, A.K., "Determination of the Deformation-Potential Constant of the Conduction Band of Silicon from the Piezospectroscopy of Donors", Physical Review B, Vol. 6, No. 6, pp. 2348-2356, 1972.
56. Pikus, G.E. and Bir, G.L., "Effect of Deformation on the Hole Energy Spectrum of Germanium and Silicon", Soviet Physics - Solid State, Vol. 1, pp. 1502-1517, 1959-1960.
57. Pikus, G.E. and Bir, G.L., "The Influence of Deformation on the Electrical Properties of P-Germanium and Silicon", Soviet Physics - Solid State, Vol. 1, pp. 1675-1686, 1959-1960.
58. Dresselhaus, G., Kip, A.F. and Kittel, C., "Cyclotron Resonance of Electrons and Holes in Silicon and Germanium Crystals", Physical Review, Vol. 98, No. 2, p. 368, 1955.
59. Hensel, J.C. and Feher, G., "Cyclotron Resonance Experiments in Uniaxially Stressed Silicon: Valence Band Inverse Mass Parameters and Deformation Potentials", Physical Review, Vol. 129, No. 3, pp. 1041-1062, 1963.
60. Blakemore, J.S., Semiconductor Statistics, Pergamon, New York, 1962.
61. Tufte, O.N. and Stelzer, E.L., "Piezoresistive Properties of Heavily Doped n-Type Silicon", Physical Review, Vol. 133, No. 6A, pp. A1705-A1716, 1964.
62. Fietul, V.I., Heavily Doped Semiconductors, Plenum Press, New York, 1969.
63. Wortman, J.J., Hauser, J.R. and Burger, R.M., "Effect of Mechanical Stress on p-n Junction Device Characteristics", J. Appl. Phys., Vol. 35, No. 7, pp. 2122-2131, 1964.

64. Ghandhi, S.K., *The Theory and Practice of Microelectronics*, Wiley, New York, 1968.
65. Van der Pauw, L.J., "A Method of Measuring Specific Resistivity and Hall Effect of Discs of Arbitrary Shape", *Philips Research Reports*, Vol. 13, No. 1, pp. 1-9, 1958.
66. Smits, F.M., "Measurement of Sheet Resistivities with the Four-Point Probe", *Bell System Tech. J.*, Vol. 37, pp. 711-718, May 1958.
67. Wada, Y. and Nishimatsu, S., "Grain Growth Mechanism of Heavily Phosphorous-Implanted Polycrystalline Silicon", *J. Electrochem. Soc.: Solid-State Science and Technology*, Vol. 125, No. 9, pp. 1499-1504, Sept 1978.
68. Mason, W.P., "Semiconductor Transducers - General Considerations", in *Physical Acoustics: Principles and Methods* (edited by Mason, W.P.), Academic Press, New York, Vol. I, Part B, p. 191, 1964.
69. Runyan, W.R., *Silicon Semiconductor Technology*, Texas Instruments Electronics Series, McGraw-Hill, New York, p. 182, 1965.
70. Wynblatt, P. and Ku, R.C., in: *Interfacial Segregation* (Johnson, W.C. and Blakely, J.M., eds.), ASM, Metals Park, Ohio, 1979.
71. Wynblatt, P. and Ku, R.C., "Surface Energy and Solute Strain Energy Effects in Surface Segregation", *Surf. Sci.*, Vol. 65, pp. 511-531, Jul 1977.
72. McLean, D., *Grain Boundaries*, Oxford University Press, 1957.
73. Burton, J.J., Hyman, E. and Fedak, D.G., "Surface Segregation in Alloys", *J. Catal.*, Vol. 37, pp. 106-113, 1975.
74. Balluffi, R.W. in Ref. 70.
75. Simmons, J.G., "Generalized Formula for the Electric Tunneling Effect Between Similar Electrodes Separated by a Thin Insulating Film", *J. Appl. Phys.*, Vol. 34, pp. 1793-1803, June 1963.
76. Murphy, E.L. and Good, R.H., "Thermionic Emission, Field Emission, and the Transition Region", *Phys. Rev.*, Vol. 102, pp. 1464-1473, June 1956.
77. Stratton, R., "Volt-Current Characteristics for Tunneling Through Insulating Films", *J. Phys. Chem. Solids*, Vol. 23, pp. 1177-1190, 1962.

- 78. Baccarani, G., Impronta, M., Ricco, B. and Ferla, P., "I-V Characteristics of Polycrystalline Silicon Resistors", *Revue de Physique Appliquee*, Vol. 13, p. 777, 1978.
- 79. Timoshenko, S.P., "Mechanics of Materials", Van Nostrand Reinhold, New York, 1972.
- 80a. Arndt, H., "Trapping and Recombination Dynamics in Thin-Film Cadmium Sulphide", Ph.D. Thesis, Carleton University, Ottawa, Canada, Sept. 1972.
- 80b. Volger, J., "Note on the Hall Potential Across an Inhomogeneous Conductor", *Physical Review*, Vol. 79, pp. 1023-1024, 1950.

END

1	0	5	H	0	9	H	8	4
---	---	---	---	---	---	---	---	---

FIN