INFORMATION TO USERS

This manuscript has been reproduced from the microfilm master. UMI films the text directly from the original or copy submitted. Thus, some thesis and dissertation copies are in typewriter face, while others may be from any type of computer printer.

The quality of this reproduction is dependent upon the quality of the copy submitted. Broken or indistinct print, colored or poor quality illustrations and photographs, print bleedthrough, substandard margins, and improper alignment can adversely affect reproduction.

In the unlikely event that the author did not send UMI a complete manuscript and there are missing pages, these will be noted. Also, if unauthorized copyright material had to be removed, a note will indicate the deletion.

Oversize materials (e.g., maps, drawings, charts) are reproduced by sectioning the original, beginning at the upper left-hand corner and continuing from left to right in equal sections with small overlaps.

Photographs included in the original manuscript have been reproduced xerographically in this copy. Higher quality 6" x 9" black and white photographic prints are available for any photographs or illustrations appearing in this copy for an additional charge. Contact UMI directly to order.

**Bell & Howell Information and Learning
300 North Zeeb Road, Ann Arbor, MI 48106-1346 USA
800-521-0600**

UMI[®]

The Fuzzy Logic Control of Aircraft

by

HASSAN FARAH, M.Sc.

**A thesis submitted to
the Faculty of Graduate Studies and Research
in partial fulfilment of
the requirement for the degree of
Master of Engineering, Aerospace**

**Department of Mechanical and
Aerospace Engineering
Ottawa-Carleton Institute
for Mechanical and Aerospace Engineering**

Carleton University

Ottawa, Ontario

January 24, 1999

© 1999, Hassan Farah

National Library
of Canada

Acquisitions and
Bibliographic Services

395 Wellington Street
Ottawa ON K1A 0N4
Canada

Bibliothèque nationale
du Canada

Acquisitions et
services bibliographiques

395, rue Wellington
Ottawa ON K1A 0N4
Canada

Your file *Votre référence*

Our file *Notre référence*

The author has granted a non-exclusive licence allowing the National Library of Canada to reproduce, loan, distribute or sell copies of this thesis in microform, paper or electronic formats.

The author retains ownership of the copyright in this thesis. Neither the thesis nor substantial extracts from it may be printed or otherwise reproduced without the author's permission.

L'auteur a accordé une licence non exclusive permettant à la Bibliothèque nationale du Canada de reproduire, prêter, distribuer ou vendre des copies de cette thèse sous la forme de microfiche/film, de reproduction sur papier ou sur format électronique.

L'auteur conserve la propriété du droit d'auteur qui protège cette thèse. Ni la thèse ni des extraits substantiels de celle-ci ne doivent être imprimés ou autrement reproduits sans son autorisation.

0-612-43339-0

Canada

The undersigned recommend to the Faculty
of Graduate Studies acceptance of the thesis
“The Fuzzy Logic Control of Aircraft”

Submitted by **Hassan Farah M.Sc.**
in partial fulfillment of the requirements
for the degree of Master of Engineering, Aerospace

Professor, J. Z. Sasiadek, Thesis Supervisor

**Chair, Mechanical and Aerospace Engineering
Carleton University**

January 1999

Abstract

The subject of aircraft dynamic stability and aircraft control using a fuzzy logic controller (FLC) is discussed. The mathematical modeling and equations describing air vehicle motion under asymmetric flight are also presented in this work. The solutions of the equations of motion consisting of side force, rolling moment and yawing moment for a step change in rudder, elevator and aileron are given. The control system for specific condition (flight envelope) was designed and the linguistic fuzzy rules and appropriate fuzzy variables are introduced through fuzzy set membership functions. A suitable C-program were written and used for simulation. Finally, the comparison of the performance of the fuzzy logic controller (FLC) and the linear controller based on linear regulator (LQR) is presented..

The research demonstrates that the application of the FLC leads to significant improvement in aircraft control.

Abstract	i
Figures Definition	iv
Tables	vi
List of Acronyms	vii
Aeronautical Variable Definition	viii
Chapter 1	1
Dynamics of Aircraft	1
1.1 Introduction	1
1.2 Literature Review.	5
1.3 Problem Statement	8
Chapter 2	9
Aircraft Modeling	9
2.1 Determination of Dominant Stability Coefficients	9
2.2 Longitudinal Stability Derivatives	13
2.3 Longitudinal Control	14
2.4 Longitudinal Motion	14
Chapter 3	19
Stability Derivative of Aircraft	19
3.1 Lateral Stability Derivatives	19
3.2 Lateral Control	20
3.3 Lateral Motion	21
Chapter 4	24
Mathematical Model of Aircraft	24
4.1 Mathematical Representation of the Dynamics of Aircraft	24
4.2 The Aerodynamic Forces and Moments acting on Aircraft	24

Chapter 5	35
LQR Control of Aircraft	35
5.1 Solution of the Linear Quadratic Regulator (LQR).	35
Chapter 6	39
Fuzzy Logic Control of Aircraft	39
6.1 Introduction	39
6.2 Fuzzy Logic Control Design	41
6.2.1 Fuzzy Rules	45
6.2.2 Operation on Fuzzy Sets	45
6.2.3 Crisp Set	47
6.2.4 Fuzzification	48
6.2.5 Degree of Fulfillment	48
6.2.6 Implication	48
6.2.7 Aggregation	48
6.2.8 Defuzzification	49
6.2.9 Fuzzy Set	49
6.2.10 Membership	49
Chapter 7	55
Simulation and Analysis	55
7.1 Longitudinal Motion	55
7.2 Lateral Motion	57
Chapter 8	58
Conclusions	58
References	84
Appendix: A	88
A.1 Characteristics of Aircraft	88
A.2 Aerodynamics and Control Derivatives	90
Appendix: B	93
Fuzzy Logic Programming For Aircraft Motion	93

Number	Figures Definition	Page
1.	Family of C_m^{α} Curves for Various δ_e	60
2.	Variation of Longitudinal Stability Coefficients with Mach Number.....	60
3.	Loss of rudder effectiveness due to combined variations of angle of attack and sideslip.....	61
4.	Loss of aileron effectiveness at increasing angles of attack in the presence of sideslip for a fighter aircraft.....	61
5.1.	Subsonic damping derivatives for a wing-body configuration at $M=0.7$	62
5.2.	Subsonic cross derivatives for a swept wing fighter aircraft at $M=0.7$	62
5.3.	Variation of cross-coupling derivatives with the angle of attack.....	62
5a.	Body system of axes and related angles. positive directions indicated by arrows..	63
5b.	Vertical flight path angle , vertical plane.....	64
5c.	Horizontal flight path angle, horizontal.....	64
6.	Fuzzy system controller.....	65
7.	Membership functions of premise terms.....	66
8.	Fuzzy controller.....	67
9.	Output membership functions.....	68
10.	Input membership functions with input values.....	69
11.	Computational Mechanism of a FLC.....	70
12a.	Consequent membership function	71
12b.	Implied fuzzy set membership function of rule 2.....	71
13a.	Consequent membership function.....	71
13b.	Implied fuzzy set membership function of rule1.....	71
13c.	Membership functions for input altitude error.....	72
13d.	Membership functions for input velocity error.....	72
13e.	Membership functions for input heading.....	73
13f.	Membership functions for input sideslip.....	73

14.	Angle of attack versus time in longitudinal motion with the application of LQR and fuzzy logic controller.....	74
15.	Angular velocity (Q) versus time in longitudinal motion with the application of LQR and fuzzy logic controller.....	75
16.	Deflection of elevator (δ_e) versus time in longitudinal motion with the application of LQR and fuzzy logic controller.....	76
17.	Angle of attack (α_F) versus time in longitudinal motion with the application of LQR and fuzzy logic controller.....	77
18.	Angle of sideslip (β) versus time without controller, with LQR controller and FLC controller.....	78
19.	Euler angular rotation in roll time in dynamic lateral motion with LQR and fuzzy logic controller.....	79
20.	Roll angular rates versus time in dynamic lateral motion with the LQR and fuzzy logic controller.....	80
21.	Yaw angular velocities versus time in dynamic lateral motion with the LQR and fuzzy logic controller.....	81
22.	Angular deflection of rudder versus time in dynamic lateral motion with the LQR and fuzzy logic controller.....	82
23.	Angular deflection of aileron versus time in dynamic lateral motion with the LQR and fuzzy logic control.....	83

Number	Tables
6.1	Error versus crisp logic values.....47
6.2	Error versus fuzzy logic values.....50
6.3	Error versus fuzzy logic control action values.....50
6.4	Rule base for throttle membership function setting changes.....52
6.5	Logic control values for throttle setting membership functions.....52
6.6	Rule base for pitch angle changes.....53
6.7	Logic control values for pitch angle variation of membership functions.....53
6.8	Rule bases for roll angle and rudder commands.....54
A.1.1	Characteristics of hypothetical aircraft.....88
A.2.1	Aerodynamic and control derivatives.....90

Symbol	List of Acronyms
AI	Artificial intelligence
C.G	Center of gravity
dot	Refers to the rate of change with respect to time
FLC	Fuzzy logic control
NB	Negative big
NM	Negative medium
NS	Negative small
PS	Positive small
PM	Positive medium
PB	Positive big
T	Refers to a value at trim condition
zero	Indicates a value at zero time
(x,y,z)	Illustrates the body axes (mm and cm)

* List of Acronyms symbols were ordered as appeared in text

Symbol	Aeronautical Variable Definition	Unit
a_ω	Wing lift curve slope.....	(per radian)
a_t	Horizontal tail lift curve slope.....	(per radian)
a_F	Vertical tail lift curve slope.....	(per radian)
b	Wing span.....	(m)
c_π	Wing-root chord.....	(m)
c_{tp}	Wing-tip chord.....	(m)
c_a/c	Ratio of aileron chord to wing chord.....	(-)
c_r/c	Ratio of rudder chord to vertical tail chord.....	(-)
c_e/c	Ratio of elevator chord to horizontal tail chord.....	(-)
$\bar{c}$	Wing mean aerodynamic chord.....	(m)
c_{i_p}	Dynamic derivative with respect to roll rate parameter.....	(-)
	$\partial c_i / \partial (pb / 2v), i = L, M, N$	
c_{i_q}	Dynamic derivative with respect to pitch rate parameter.....	(-)
	$\partial c_i / \partial (q \bar{c} / 2v), i = L, M, N$	
c_{i_r}	Dynamic derivative with respect to yaw rate parameter.....	(-)
	$\partial c_i / \partial (rb / 2v), i = L, M, N$	
c_{i_α}	Static derivative with respect to angle of attack.....	(-)
	$\partial c_i / \partial \alpha, i = L, M, N$	

$c_{i\dot{\alpha}}$	Dynamic derivative with respect to α -rate of change parameter.....(-) $\partial c_i / \partial (\dot{\alpha} \bar{c} / 2v), i = L, M, N, z$
$c_{i\beta}$	Static derivative with respect to angle of sideslip.....(-) $\partial c_i / \partial \beta, i = L, M, N, y$
$c_{i\dot{\beta}}$	Dynamic derivative with respect to β -rate of change parameter.....(-) $\partial c_i / \partial (\dot{\beta} \bar{b} / 2v), i = L, M, N, y$
$c_{i\delta a}$	Static derivative with respect to aileron deflection.....(-) $\partial c_i / \partial \delta a, i = L, N, y$
$c_{i\delta e}$	Static derivative with respect to elevator deflection.....(-) $\partial c_i / \partial \delta_e, i = M, x, z$
$c_{i\delta r}$	Static derivative with respect to rudder deflection.....(-) $\partial c_i / \partial \delta_r, i = L, N, y$
c_x, c_y, c_z	Basic force coefficients with respect to x,y,z body axes respectively (aerodynamic force component) / $\bar{q}S$(-)
c_L	Rolling moment coefficient, $L / (\bar{q}Sb)$(-)
c_M	Pitching moment coefficient, $M / (\bar{q}S\bar{c})$(-)
c_N	Yawing moment coefficient, $N / (\bar{q}Sb)$(-)
F	Force.....(n)

g	Acceleration of gravity.....(m/s ²)
h	Altitude.....(m)
I	Moment or product of inertia.....(kgm ²)
l_t	Distance between center of horizontal tail pressure tail and of gravity center of aircraft.....(m)
l_F	Distance between fin aerodynamic center and the center of the gravity of airplane.....(m)
L	Aerodynamic rolling moment.....
M	Aerodynamic pitching moment, or Mach number.....
N	Aerodynamic yawing moment.....
p, q, r	Body angular velocities.....(rad/sec)
S_t	Horizontal tail area.....(m ²)
S_F	Fin area.....(m ²)
S	Gross wing area.....(m ²)
T	Thrust.....(N)
u, v, w	Linear velocities.....(m/sec)
V	Velocity.....(m/s)
x, y, z	Body-fixed axes system.....(mm or cm)
X, Y, Z	Earth fixed orthogonal axes with origin at origin of flight and with Z axis pointing vertically down.....(cm. or mm)
Z_F	Distance between fin aerodynamic center and body x-axis.....(m)
$\bar{q}$	Dynamic pressure.....(n/m ²)
α	Angle of attack.....(deg or radian)
β	Angle of sideslip.....(deg or radian)
Φ	Aircraft bank angle.....(deg or radian)
Φ_A	Aerodynamic roll angle.....(deg or radian)

$\Delta \alpha$	Difference between α and α_T(deg or radian)
θ	Euler angular rotation in pitch.....(deg or radian)
ϕ	Euler angular rotation in roll.....(deg or radian)
ψ	Euler angular rotation in yaw.....(deg or radian)
ρ	Density of air.....(kg/m ³)
τ_a	Aileron effectiveness.....(-)
τ_r	Rudder effectiveness.....(-)
τ_e	Elevator effectiveness.....(-)
γ_v	Vertical flight path angle with respect to horizontal plane.....(rad or deg)
γ_H	Horizontal flight path angle with respect to vertical plane.....(rad or deg)

Subscripts

Superscript	•	refers to rate of change with respect to time
Subscript	0	refers to zero time value

* Variables were ordered as appeared in text

Chapter 1

Dynamics of Aircraft

1.1 Introduction

One of the most important factors to investigate during the aircraft design process is the longitudinal-lateral stability of the vehicle. Aircraft which are not designed to such capabilities could suffer a loss of control in flight. The parameters of longitudinal-lateral motion are the primary phenomena of motion to consider in the analysis of aircraft dynamics [1].

A lateral aerodynamic reaction may occur as a result of the pitching manoeuvre, while the longitudinal forces and moments may be affected by a lateral motion. This problem is complex and mostly dependent on the geometry of the aircraft; its solution is based upon the simultaneous solution of both longitudinal and lateral dynamic equations.

Various configurations are used in many flight applications. Such configurations generate various aerodynamic forces and moments at high angles of attack due to the induced flow created by the vortices which are shed from the lifting surfaces and the body configuration. The strength and the location of these vortices depend on the lifting surfaces, leading-edge shapes and the geometrical shape, and their local altitude in relation to the direction of the velocity vector. These aerodynamic phenomena have become the focus of theoretical and experimental studies to achieve stability and control in aircraft at various angles of attack.

It may be said that properly controlled vortex interactions enable significant variations of the overall lift on the air vehicle with or without change of altitude. This control of vortex interactions can be used as a form of direct control. It is important that the calculations of the aerodynamic characteristics at high angles of attack be accomplished together with the evaluation of the effects of free vortices which are shed from the wing. The equations governing these flows must account for the fact that these vortices are present in the flow field [2].

In the evolution of flows at low angles of attack, boundary layers are confined to the surface with only small effects on the aerodynamic characteristics. As the angle of attack increases to moderate and high levels, the separated layers detach from the surface and move into the flow vortex. For symmetric ($\phi=0$ and $V_o=0$) configuration at zero sideslip, the generated vortex structure is also symmetric up to a certain angle of attack. At higher angles of attack, this symmetric vortex structure may be transformed into an asymmetric (roll, sideslip and turn are typical) structure on the symmetric configuration with zero sideslip. At still higher angles of attack, the cores of the concentrated vortices may burst at a certain point on the lifting surface. The symmetric vortex structure established on the elongated wing can be transformed into an asymmetric structure as the angle of attack is increased at subsonic speeds. At subsonic speeds, the angle of attack at which the flow becomes asymmetric is relatively high in comparison to that at supersonic speeds. For the symmetric flow range, the lift force increases with the increasing angle of attack, while the lateral forces and moments are negligible. At increasing angles of attack, as the flow becomes asymmetric but steady, the lift is still increasing, though at a lower rate, but a new and very important effect is observed: the appearance of a great side force and moment. The direction of the side force and the yawing moment may be reversed at various angles of attack. The relatively large size and the direction reversal of these lateral aerodynamic coefficients is a phenomenon that is of importance for the performance of aircraft with a long nose section. At higher angles of attack the vortex breakdown occurs nearer to the wing apex and then the flow may break up into an unsteady turbulent wake.

Thus, we can distinguish the following flow regimes on configurations as a function of the increasing angle of attack [3,4]:

1. very low angles of attack--attached, symmetric, steady flow; linear lift variation with angle of attack;
2. low angles of attack--attached, symmetric, steady flow with closed separating bubbles; slight linear lift variation with angle of attack;
3. moderate and high angles of attack--separated, symmetric, rolled-up vortices in steady flow; nonlinear lift variation with angle of attack;

4. high angles of attack--separated, asymmetric, rolled-up vortices in steady flow; non-linear lift variation with angle of attack;
5. higher angles of attack--vortex breakdown causing loss of lift and non-steady flow conditions;
6. very high angles of attack--separated, non-steady, turbulent wake; post-stall aerodynamic characteristics.

Linear aerodynamic theories and numerical methods can be used to evaluate the aerodynamic characteristics of configurations in categories 1 and 2 at low angles of attack. and for the calculations of the non-linear aerodynamic characteristics in categories 3 and 4.

The primary goal of this work was to analyze and present the following:

- longitudinal-lateral equations
- analysis of aircraft motion
- reaction to perturbations and the effect of their aerodynamic derivatives
- design control system based on LQR method for specific flight conditions. Linear quadratic regulator (LQR) method is a modern control time-domain techniques to design stability control augmentation systems (SAS) and autopilots. This is accomplished by regulating certain states of the aircraft to zero while obtaining desirable response characteristics;
- design control system based on FLC for an aircraft. Fuzzy logic control (FLC) is a methodology based on the so-called intelligent control which is defined as a combination of Control Theory and Artificial Intelligence (AI) [28, 29];
- comparison between the LQR and FLC [5, 6].

To solve the non-linear variation of the aircraft motion, one must consider the longitudinal and lateral motions of the aircraft and solve them simultaneously taking into account the non-linearities by the equations around an angle of attack where a significant change occurs. The basic longitudinal stability requires constant linear momentum and constant angular momentum. On the other hand, dynamic longitudinal stability considers motion about the pitch axis as a function of time after a perturbation. The pitching moment due to $\alpha\text{-dot}$ (coefficient $c_{m\dot{\alpha}}$) is created by the aerodynamic interaction

between the wings and the horizontal tail [22]. To solve this problem, it was necessary to create a relevant computer program to compute the variables of both longitudinal and lateral motions. The objective of the thesis is to develop and present the fuzzy logic control for aircraft and to compare its performance with the LQR.

1.2 Literature Review

The main function of the flight control system (FCS) of an aircraft is to contribute to its safe and economic operation, such that the intended flight missions can be accomplished and unexpected events can be handled.

In the early days of flight, safety was the main concern for FCS designers. Pilots needed significant effort to maintain some flight conditions under all circumstances. Today, safety is even more important, because many more people are transported, higher costs are involved in establishing safety and the reputation of airlines and aircraft manufacturers is paramount, in an increasing competitive market.

The unusually hazardous nature of aircraft flying is reflected in the total accident rates. With minor fluctuations from year to year, because of the smaller accident base in aircraft flying, the accident rate of military aircraft is higher than that of U.S. general aviation by a factor of 1.5 [52].

Most important, modern FCS have contributed to improved dynamical behavior [4, 8, 11, 18]. Aircraft cannot be flown without a stability augmentation system. The open loop instability, which is related to agility of the aircraft, is utilized to obtain better performance and maneuverability of the closed loop [13, 17, 22]. In the past, the pilot stick was typically connected with rods or cables to the control surfaces. Since then, the increased safety, economical and performance demands have forced aircraft manufacturers to extend FCS to a high level of complexity [53].

The tremendous number of functions and requirements have increased the number of specialists areas for the FCS and makes the work challenging from a technical and management point of view. Specialist who are responsible for mode logic, design, software and hardware development and certification have worked closely together. In the overall process, control laws designers assume a modest, but central position. Their task is influenced by the design requirements, the flight envelope, the aircraft configuration complexity, the stores carriage and weight distribution, the required autopilot modes, the aircraft stability levels and aerodynamic nonlinearity [16, 41]. Global competition forces aircraft manufacturers to continuously improve the efficiency of their engineering

activities.

The complexity of the design task and the related investment made in the past, explain the careful attitude from some aircraft manufacturers to replace their well-established classical techniques [37, 41, 53]. Due to historic reasons, the classical approach in which each mode and flight condition is treated as a separate problem has led to mode proliferation and the need for complex algorithms. Application of advanced techniques promises a significant reduction of design time because it would remove the time-consuming classical “one-loop-at-a-time” approach and reduce the number of design points for which a controller has to be designed.

Mathematical problems that had arisen in the stability control systems occupied the attention of early 20th century mathematicians as Liapunov [22, 49]. Theoretical problems of stabilizing these systems and improving their performance engaged various mathematicians of the period. The classical period of control theory, characterized by frequency-domain analysis, is still going strong with the development of various sophisticated techniques for multi-variable systems. State-space methods are the cornerstone of modern control theory [21, 24, 28, 53]. The essential feature of state-space methods is the characterization of the processes of interest by differential equations instead of transfer functions.

A digital computer is all but essential for performing the calculations that must be done in a typical applications. The demands of piloting an aircraft are considerable, involving the guidance of its motion through varying conditions, receiving instructions and information, and managing the resources available [5, 27]. Accidents are often the result of failures in the stick-and-rudder aspects of piloting to stabilize the aircraft under conditions such as extreme turbulence. Many aircraft have been damaged when turbulence (mass of air) exceeded their control capabilities or caused structural damage in flight [42].

National Transportation Safety Board (NTSB) data indicated that a vortex encounter was the probable cause of at least 51 accidents and incidents from 1983 to 1993, with loss of or severe damage to 40 aircraft. The most frequent physical

environmental hazards to flight safety are the following:

- Air turbulence (in thunderstorm and wake turbulence from preceding aircraft)
- Precipitation (rain, snow, hail and sleet)
- Ground objects (towers, terrain)
- Airborne objects (aircraft, birds and balloons etc.)
- Electromagnetic radiation (sources within aircraft).

In discussing the controlled guidance of aircraft, it is essential to emphasize the importance of aircraft stability control systems in which many of the flight processes are performed automatically by a computer based controller [1, 20, 43]. An examination of the aviation incident and accident data from the past two decades shows two contrary trends. On the one hand, due to the application of stability augmentation systems (SAS) there has been a sharp decline in aviation accidents. The SAS uses sensors to measure the body-axes angular rates of the aircraft and feeds back processed versions of these signals to the servomechanism that drives the aerodynamic control surfaces [17]. In this way, aerodynamic forces and moments proportional to angular velocities and their derivatives can be generated and can utilize an effective stable motion of the air vehicle [2, 10]. On the other hand, despite the application of stability augmented technology, controlled flight still encounters serious safety problems in aviation [7].

1.3 Problem Statement

Guidance and control system technology used in the control of aircraft has been revolutionized by the development of the digital computer. The two concepts which are central to modern control systems are the design based directly on the state-variable model, and the expression of performance specification in terms of a mathematically precise performance criterion which then yields matrix equations for the control gains. The expected benefits of guidance control technology, which freed the crews of newer aircraft from dependence on location-to-location systems of navigation aids, were a reduction in human error and increased safety automation. As a result there was a demand for greater system precision and reliability.

Although many of these benefits have been realized, still serious problems arise which result in many incidents and accidents. One must question whether the maximum possible automation is necessary or desirable, and consider a system that is more compatible with the capabilities and limitations of the humans involved.

The answer to this question is the design of better and more efficient control systems suited for aircraft control. This thesis is presenting a fuzzy logic control design process and comparing the performance of FLC with linear quadratic regulator (LQR).

Chapter 2

Aircraft Modeling

2.1 Determination of Dominant Stability Coefficients

The dynamic cross-coupling in longitudinal-lateral motion causes the occurrence of aerodynamic forces and moments [8]. The time-dependent effects of all parameters in longitudinal-lateral motion were considered, provided that the aerodynamic forces are linearly dependent on $\dot{\alpha}$ and $\dot{\beta}$. The mathematical modeling of the aircraft and the consideration of all parameters in longitudinal-lateral motion makes it possible to solve the problem of aerodynamic forces and moments. Primary consideration is given to the non-linearity motion and its dependence of time. As these two motions are strongly coupled, it was necessary to analyze six degree of freedom motion.

To simplify the analysis of motion of the aircraft, the following equations are considered:

- the external forces and moments
- the auxiliary equations
- the physical characteristics
- the stability and control derivatives and the initial conditions [9].
- The forces and moments acting on the aircraft are determined in terms of dimensionless aerodynamic coefficients as:

$$\text{drag, } D = \bar{q} S c_D \quad (1)$$

$$\text{lift, } L = \bar{q} S c_L \quad (2)$$

$$\text{side force, } Y = \bar{q} S c_Y \quad (3)$$

$$\text{rolling moment, } \bar{L} = \bar{q} S b c_L \quad (4)$$

$$\text{pitching moment, } M = \bar{q} S \bar{c} c_M \quad (5)$$

$$\text{yawing moment, } N = \bar{q} S b c_N \quad (6)$$

where:

$\bar{q}$ = free-stream dynamic pressure

S = wing reference area

b = wing span

$\bar{c}$ = wing mean geometric chord.

The dimensionless force coefficients have been specified for wind axes; the body-axes forces coefficients c_x , c_y , and c_z are also in common use. The moments coefficients may be specified in wind, stability, or body axes, but the same symbols will be used in each case. The various dimensionless coefficients c_D , c_L , ..., c_N are the dependent on the aerodynamic angles alpha and beta and less dependent on other variables. The dependence on the rates of changes of the aerodynamic angles and on the components p, q and r of the center of gravity of the aircraft angular velocity is elaborated in equations (26) and (45). The coefficients are also dependent on control surface deflections and other factors such as engine power level, configuration effects (e.g; landing gear, external tanks, etc) otherwise, the aircraft wouldn't be controllable [10, 48, 49].

The most important longitudinal stability derivatives are

$$c_{L_\alpha}, c_{M_q}, c_{M_\alpha}, c_{L_q} \text{ and } c_{M_\alpha}$$

where:

c_{L_α} , c_{L_q} - damping derivatives that describe the increment in lift due to the

alpha-dot ($d\alpha / dt$) and pitch rate. The alpha-dot-refers to the rate of change of angle of attack with respect to time.

c_{M_q} , c_{M_α} - damping derivatives in moments equations that describe the increment

in lift due to the alpha-dot and pitch rate. The computer analysis study of air vehicle motion in straight and level flight depends on the variables which determine the degree of stability. The dynamic derivatives include the angular rotations (p, q, r), damping

derivatives (c_{L_p} , c_{M_p} , c_{N_r}), cross-coupling derivatives (c_{L_q} , c_{M_r} etc), and derivatives due to the time rate of change of aerodynamic angles ($\dot{\alpha}$, $\dot{\beta}$). Some control derivatives were estimated using the aircraft's physical characteristics.

The simulation of aircraft parameters with disturbance reflects the actual stability derivatives on the aircraft. The length of perturbation time depends on the control surface being disturbed as for rudder perturbation and elevator perturbation. The effect of stability derivatives on the aircraft motion is considered in order to choose the appropriate and desired derivatives, as c_N , c_{L_α} which refer to the dynamic derivatives with respect to pitch, alpha, rate of change; and c_{M_β} , and c_{N_α} static derivatives which correspond to sideslip and angle of attack.

When the control input depends upon the stability derivative as is the case for c_{L_q} and $c_{L_{\dot{\alpha}}}$ the perturbation would be in the elevator setting and the response in β and

Φ would be presented; but if it is for c_{M_r} and $c_{M_{\dot{\beta}}}$, then the rudder setting must be

disturbed and the aircraft response is recorded. The sign for aerodynamic control surface perturbation can be either negative or positive. The effect of dynamic derivatives with respect to yaw and beta rate parameters can be analyzed on the longitudinal aircraft motion by introducing lateral perturbation of the rudder angle.

The result indicates that both longitudinal and lateral perturbations have an effect on the aircraft motion; the most significant is the overall effect of perturbing the rudder for the straight and level flight, as the perturbation could make the air vehicle drift away from the original flight path. The c_{M_β} has more effect on alpha than c_{M_r} and $c_{M_{\dot{\beta}}}$ which indicate

higher degrees of significance for static derivatives. The rate of roll (p) and the rate of change of sideslip $\dot{\beta}$ are high compared to the rate of yaw (r). The rate of pitch (q) is

relatively small. The derivatives of various aerodynamic reactions due to angular velocities (p, q, r) represent the quasi-steady effects. These derivatives form part of the dynamic results obtained during standard wind-tunnel experiments of oscillations around a fixed axis, where the output is always an expression composed of more than derivatives, such as $(c_{M_q} + c_{M_{\dot{\alpha}}})$.

Nonlinear variations of stability derivatives with the angle of attack is shown in Figure 5.1 [8]. The figure shows the variation of the subsonic damping derivatives in pitch $(c_{M_q} + c_{M_{\dot{\alpha}}})$ and yaw $(c_{N_r} - c_{N_{\dot{\beta}}})$ for a wing configuration, for a range of angle of attack

from 0 to 40° , while Figure 5.2, shows the low-subsonic cross derivatives

$(c_{N_p} + c_{N_{\dot{\alpha}}} \sin \alpha)$, and $(c_{L_r} - c_{L_{\dot{\beta}}} \cos \alpha)$ for a swept wing fighter aircraft [2]. Non-linear

variation of some of the cross coupling derivatives is shown in Figure 5.3. Non-linear behavior of the dynamic cross-coupling moment derivatives due to pitching $(c_{N_q} + c_{N_{\dot{\alpha}}})$ and $(c_{L_q} + c_{L_{\dot{\alpha}}})$, and due to yawing $(c_{M_r} - c_{M_{\dot{\beta}}} \cos \alpha)$, can be easily seen at high α , or

even low angle of attack in case of yawing, where sideslip angle is non-zero [10].

The basic test to determine directional stability and dihedral effect is the steady, straight sideslip flight. Directional stability depends on prior knowledge of the control derivatives like $c_{L_{\delta a}}$ and $c_{N_{\delta r}}$. When applying this method (steady, straight sideslip flight) to find the derivative coefficients, it is essential to set up the maneuver as straight level flight in order to trim the data. This means the control of the aircraft (speed and altitude) should not change for at least a short time. This is an effective method as beta (β) is not changing rapidly -- at least no more than one degree per second -- and rudder and aileron have constant track. The rudder and aileron are applied simultaneously to stabilize a sideslip. The rigid-body state is described by:

$$\mathbf{x} = (v, \alpha, q, \theta, h, \beta, r, p, \phi)^T \quad (7)$$

The first five components of $\mathbf{x}$ are called longitudinal variables and the second five represent lateral-directional variables. The rate of change of longitudinal-lateral with respect to time (u, v, w) represent the linear velocity along the axes (x, y, z), while (p, q, r) are the angular velocity.

The (ϕ, φ, θ) are the parameters which determine the aircraft orientation as:

θ - illustrates the rotation on y-axis and called the pitch angle

φ - indicates the rotation on x-axis and called the roll angle

ϕ - shows the rotation on z-axis and called yaw angle

v, α, β - components of the air-relative velocity vector

ϕ, θ, φ - the Euler-angles describing roll, pitch and yaw respectively

The forces equation of F_x, F_y, F_z and moments L, M, N are the external forces.

The values of control effectiveness derivatives $c_{N_{\delta a}}, c_{N_{\delta r}}, c_{Y_{\delta a}}$ and $c_{Y_{\delta r}}$ are determined from the control effectiveness tests. With these values in hand $c_{L_{\beta}}, c_N$ and $c_{Y_{\beta}}$ are determined from the plots of control surface deflections and forces measured at each of the sideslip angle. The yaw rate derivatives c_{L_r} and c_{N_r} are also calculated from data recorded in steady turns initiated with aileron and rudder alone. In this fashion, all of the most important lateral-directional parameters can be estimated with reasonable accuracy.

2.2 Longitudinal Stability Derivatives

All stability derivatives are essential though some are more important than others, particularly those for defining and demonstrating the aerodynamic derivatives of the aircraft for both longitudinal and lateral motion. The aerodynamic derivatives for aircraft configuration and cross-coupling derivatives were achieved on data available in references [2, 19, 47]. The non-dimensional stability derivative c_M is often zero in trimmed motion,

except in cases of asymmetry which is typical in roll, sideslip and turn flight situations. Its magnitude can differ considerably and its sign changes in Mach number and in dynamic pressure. The change of lift coefficient with the change of angle of attack, $c_{L\alpha}$, is always positive for values of angle of attack below the stall value. The wing contributes up to 85 - 90 % of its value.

The non-dimensional stability derivative, $c_{M\alpha}$, is related to the pitching moment coefficient with the angle of attack and referred to as the longitudinal static stability derivative. The value of this dimensional derivative is mostly affected by the position of the aircraft center of gravity. The non-dimensional parameter, $c_{M\alpha}$ does not have much influence on the aircraft motion [11]. The dimension less elevator derivatives provide information about the stability and derivative effectiveness of the control surface and maneuverability of the aircraft. They correlate with geometrical features of the air vehicle and thereby facilitate the preliminary design process.

2.3 Longitudinal Control

For the longitudinal control, the elevator deflection δ_e is involved as the control parameter. The elevator effectiveness, which is very important in aircraft design, c_{δ_e} , is the most control- related parameter in the longitudinal motion of the aircraft. It can be determined by maximizing the lift value of the wing and also the range of center of gravity changes during the flight. Various elevator deflection angles are illustrated in Figure 1. The pitching moment variation is reasonably controlled up to α equal 20 deg. However, as the angle of attack increases, there is a clear loss of elevator effectiveness up to the complete loss of elevator control above $\alpha = 45^\circ$ [12].

2.4 Longitudinal Motion

For better understanding of the angles and the directions of different velocities the reader is advised to refer to Figure 5a. A complete derivation can be found in any text on aircraft dynamics . See Reference [51] for example. Equation for longitudinal motions of

the aircraft, referred to the body-fixed axes are then as follows:

$$\dot{u} = F_x / m - qw + rv \quad (8)$$

where:

dot-bears the meaning of rate of change with respect to time

F_x - force on x-axes

m - mass

u - linear velocity

r - yaw angular velocity

q - pitch angular velocity

The equation of rate of change of linear velocity is [51]

$$\dot{w} = F_z / m - pv + qu \quad (9)$$

where:

F_z - force on z-axes

dot - bears the meaning of rate of change with respect to time

w - linear velocity

p - roll angular velocity

The acceleration of pitch rate is

$$\dot{q} = [M - (I_x - I_z)rp + I_{xz}(r^2 - p^2)] / I_y \quad (10)$$

where:

$I_{xx} = I_x, I_{yy} = I_y, I_{zz} = I_z$ - moment of inertia about x, y and z axes [22]

I_{xz} - cross product of inertia

The acceleration of angular velocity is

$$\dot{\theta} = q \quad (11)$$

The equation of the longitudinal dimensional derivatives can be calculated

$$\begin{aligned}
 X &= -\frac{\bar{q}S}{m V_T} (2c_D + c_{D_v}), \\
 X_\alpha &= -\frac{\bar{q}S}{m} (c_L + c_{D_\alpha}), \\
 X_{\delta\epsilon} &= -\frac{\bar{q}S}{m} c_{D_{\delta\epsilon}}, \\
 Z_v &= -\frac{\bar{q}S}{m V_T} (2c_L + c_{L_v}), \\
 Z_\alpha &= -\frac{\bar{q}}{m} (c_D + c_{L_\alpha}), \\
 Z_\alpha &= -\frac{\bar{q}S\bar{c}}{2mV_T} c_{L_\alpha}, \\
 Z_q &= -\frac{\bar{q}S\bar{c}}{2mV_T} c_{L_q}, \\
 Z_{\delta\epsilon} &= -\frac{\bar{q}S}{m} c_{L_{\delta\epsilon}}, \\
 M_v &= -\frac{\bar{q}S\bar{c}}{J_Y V_T} (2c_M + c_{M_v}), \\
 M_\alpha &= -\frac{\bar{q}S\bar{c}}{J_Y} c_{M_\alpha}, \\
 M_\alpha &= -\frac{\bar{q}S\bar{c} \cdot \bar{c}}{J_Y 2V_T} c_{M_\alpha}, \\
 M_q &= -\frac{\bar{q}S\bar{c} \cdot \bar{c}}{J_Y 2V_T} c_{M_q}, \\
 M_{\delta\epsilon} &= -\frac{\bar{q}S\bar{c}}{J_Y} c_{M_{\delta\epsilon}},
 \end{aligned} \tag{12}$$

The most important longitudinal stability derivatives are : c_{L_α} , c_{M_α} , c_{M_q} , c_{M_v} , $c_{M_{\dot{\alpha}}}$.

The above dimensionless longitudinal derivatives are the most influential derivatives for aircraft motion as shown in Figure 2. The derivative c_{L_α} is the lift curve slope which is typically in the range 1 to 8 rad^{-1} the linear region of the lift curve below stall [22] . The c_{M_α} slope of the pitching moment curve which determines the pitch stiffness for stability. The negative value of c_{M_α} required for stability that the pilot can manage and control.

The derivatives $c_{M_{\dot{\alpha}}}$ and c_{M_q} are pitch damping derivatives. The c_{M_q} is usually of greater magnitude than $c_{M_{\dot{\alpha}}}$. It has a value in the range from 0 to -40 rad^{-1} . The effect of velocity variation on pitching moment is contained in the derivative c_{M_v} . If this derivative is

positive, the aircraft will tend to pitch up with an increase in speed. This results in increased drag and the greater component of gravity along the x-axis will then tend to slow the aircraft down. In practice, the effective center of pressure of an aircraft may move aft with increasing subsonic Mach number, thus creating a tendency to dive (negative $c_{M_{\dot{\alpha}}}$), with associated unstable speed behavior [22]. The basic aircraft states of

interest are the angle of attack α , and the angular velocity, q . An additional state is injected by the actuator of the elevator. The general states and inputs of the plant are as follows [12]:

$$\dot{\mathbf{x}} = \mathbf{Ax} + \mathbf{Bu} \quad (13)$$

$$\mathbf{x} = [\alpha, q, \delta_e, \alpha_F, \epsilon] \quad (14)$$

where:

$\mathbf{x}$ - state of the plant, q - pitch rate, δ_e - elevator deflection

α_F - filtered measurement of the angle of attack

ε - integrator output

$$\mathbf{u} = -\mathbf{ky} \quad (15)$$

$$\mathbf{y} = \mathbf{Cx} \quad (16)$$

the state variables description of the plant are

$$\mathbf{A} = \begin{bmatrix} X_\alpha & M_q & g_0 \cos \gamma_0 & 0 & 0 \\ Z_0 & V_T + Z_q & -g_0 \sin \gamma_0 & 0 & 0 \\ 0 & 1 & -1/\tau_w & -10 & 0 \\ 10 & 0 & 0 & -10 & 0 \\ 0 & -1/\tau_w & 0 & 0 & 0 \end{bmatrix} \quad (17)$$

$$\mathbf{B} = \begin{bmatrix} 0 \\ 0 \\ \frac{1}{\tau} \\ 0 \\ 0 \end{bmatrix} \quad (18)$$

$$\mathbf{C} = \begin{bmatrix} 0 & 0 & 0 & \frac{1}{\tau_e} & 0 \\ 0 & \frac{1}{\tau_e} & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 \end{bmatrix} \quad (19)$$

where:

$\mathbf{A}$, $\mathbf{B}$ and $\mathbf{C}$ are matrices.

Chapter 3

Stability Derivative of Aircraft

3.1 Lateral Stability Derivatives

The side force which results from any sideslip motion of the air vehicle can be achieved from the fin of the aircraft and prevents the sideslip angle, $c_{Y\beta}$. Positive value of the $c_{Y\beta}$ is undesirable as the reversed side force inhibits the pilot's ability to detect sideslip motion early and makes turns difficult to achieve [13]. This parameter contributes significantly to the damping ratio of the change in value of the rolling moment coefficient with sideslip angle, $c_{L\beta}$, the so-called dihedral effect. This is very important for lateral stability and control of the aircraft. This parameter is very effective in maneuvering capability specifically when lateral control motion is close to the stall position by the rudder. The negative value of this parameter is required as it improves the damping ratio of aircraft motion [15]. The variation in the yaw moment coefficient with changes in sideslip angle is considered a static directional or weather stability coefficient. It depends upon the area of the fin and lever arm. The aerodynamic value of this parameter is positive, though the aircraft configuration contribution is negative. For better quality of the parameter and more stability motion, $c_{N\beta}$, should be large, though this might affect the disturbance from side gusts. Change in rolling moment coefficient with change in rolling angular velocity is referred to as the roll damping derivative, c_{Lp} , which can be determined by the geometry of the wing. The value of this parameter is negative, though it may become positive when the wing is stalled. The variation in the yawing moment coefficient with a change in rolling velocity, c_{Np} , is usually negative, although a positive value is desirable. The negative value of this parameter reflects the smaller damping ratio of the aircraft disturbance motion. Change in the rolling moment coefficient with a change

in yawing velocity, c_{L_r} , has a great effect on the spiral mode, but little effect on dutch roll mode. The factor contributing most to this parameter is the lift force from the wing. Being negative or positive depends upon the fin's geometry. The other derivative parameter for lateral motion is related to the yawing moment coefficient, c_{N_r} . It is called the yaw damping derivative; it has a negative value and is the main contributor to damping of the Dutch roll mode and to the stability of the spiral mode [16].

3.2 Lateral Control

The directional and lateral control states of the aircraft motion are $\dot{r}$, $\dot{\beta}$, $\dot{p}$ and ϕ . Similarly, for lateral motion, the control variables are aileron deflection, δ_a , and rudder deflection, δ_r , as indicated in Figures 3. Change in the side force coefficient with rudder deflection, $c_{Y_{\delta_r}}$, is very important when considering an automatic flight control system which uses lateral acceleration as feedback otherwise it is negligible [17]. One of the most important factors for control of the lateral dynamics derivative coefficient, $c_{L_{\delta_a}}$, is the aileron effectiveness as in Figure 4. This derivative is essential for a low speed flight to counter asymmetric gusts which tend to roll the aircraft. The yawing moment coefficient, $c_{N_{\delta_r}}$, which results from a rudder deflection, has an equal importance to that of aileron effectiveness, is referred to as rudder effectiveness [18].

The coefficient of rudder deflection can be calculated

$$c_{Y_{\delta_r}} = a_F \tau_r S_F / S \quad (20)$$

where:

$c_{Y_{\delta_r}}$ - is the coefficient of rudder deflection with the change of side force

a_F - vertical tail lift curve slope

τ_r - rudder effectiveness

S_F - fin area

S - gross wing area

The yawing coefficient with respect to the rudder deflection is

$$c_{N_{\delta_r}} = -a_F \tau_r S_F / SL_F / b \quad (21)$$

where:

$c_{N_{\delta_r}}$ - the yawing coefficient which results from the rudder deflection

L_F - distance between center fin aerodynamic center and the center of gravity of aircraft

b - wing span

The dynamic lateral derivative is

$$c_{L_{\delta_r}} = a_F \tau_r S_F / SZ_F / b \quad (22)$$

where:

$c_{L_{\delta_r}}$ - lateral dynamic derivative coefficient which results from aileron effectiveness

Z_F - distance between fin aerodynamic center and body x-axis

3.3 Lateral Motion

$$\dot{p} = [L - (I_x - I_y)qr + I_{xz}(\dot{r} + pq)] / I_x \quad (23)$$

where:

dot - refers to rate of change with respect to time

(x, y, z) refers to x, y, z body axes

L - aerodynamic of rolling moment

I_i - moments of inertia on x, y, z axes $-(i = x, y \text{ and } z)$

p, q, r - body angular velocities

$\dot{p}$ - acceleration of roll rate parameter

The acceleration of yaw parameter can be defined as

$$\dot{r} = [N - (I_y - I_x)pq + I_x(\dot{p} - qr)] / I_z \quad (24)$$

where:

N - aerodynamic yawing moment

$\dot{r}$ - acceleration of yaw rate

The thrust of the aircraft is

$$T = (-c_z \tan \alpha_0 - c_x) \bar{q}_0 S \quad (25)$$

where:

T - thrust

$\bar{q}_0$ - initial value of dynamic pressure

c_x - force coefficient on x-axes; c_z - force coefficient on z-axis

α_0 - initial value of angle of attack

S - gross wing area

The Euler angular rotation in yaw can be calculated as

$$\dot{\psi} = (q \sin \phi + r \cos \phi) \sec \theta \quad (26)$$

where:

θ, ϕ, ψ - Euler angular rotation in pitch, roll and yaw

q, r - body angular velocities

The linear acceleration can be defined

$$\dot{v} = F_y / m - ru + p\omega \quad (27)$$

where:

$\dot{v}$ - linear acceleration

F_y - force on y-axis

P - roll rate parameter

u - linear velocity

The derivatives c_{L_p} , c_{n_p} , c_{N_r} , and c_{L_r} are all damping moment derivatives.

The roll damping derivative c_{L_p} usually lies in the range -0.1 to 0.8 rad^{-1} . It increases in magnitude in the transonic region and then decreases again at higher Mach numbers. The importance of this derivative is that it determine the roll-rate performance of a highly maneuverable aircraft. The yaw damping derivative is c_{N_r} ; it is always negative and is in the near zero. This variable may increase in magnitude in the transonic region.

The derivatives c_{N_p} and c_{L_r} are cross-derivatives that exist because of the coupling of the rolling and yawing motion of an aircraft; they tend to be difficult to measure and change significantly with mach number. c_{N_p} usually lies in the range from -0.5 to 0.1 rad^{-1} and can change from negative to positive values in the transonic region. The derivative of yawing, c_{L_r} , lies between zero and 0.6 rad^{-1} . It may vary considerably in value and is also a function of the lift coefficient [18].

Chapter 4

Mathematical Model of Aircraft

4.1 Mathematical Representation of the Dynamics of Aircraft

Here the non-linear first order differential equations which represent aircraft motion related to the (x, y, z) body-fixed system of axes are determined. The equations represent Newton's Law of transition along the rotation about the axis. As these equations refer to the body-fixed axes, the parameters bearing a dot indicate the rate of change with respect to time and represent the linear components along the three body axes (x, y, z) respectively; while (p, q, r) are the components of the body-axis angular vectors as shown in Figure 5a. The angles (θ, ψ, ϕ) are the aircraft Euler angles which determine the orientation of the air vehicle as roll, pitch and attitude. As a whole, aircraft motion can be described by the following variables: $v, \alpha, q, \theta, h, \beta, r, p, \phi, \varphi$. The first five components are longitudinal motion variables, the second five are lateral directional variables. The longitudinal and lateral motion of an aircraft about its straight and level flight path with perturbation can be expressed by two independent equations as follows [19, 20].

4.2 The Aerodynamic Forces and Moments acting on Aircraft

The sum of forces and moments acting on the three body axes of the aircraft are illustrated by the following parameters [21]:

F_x, F_y, F_z, L, M and N respectively.

The external forces and moments acting on the aircraft are :

- force due to gravity (weight);
- forces due to power plant (thrust);
- aerodynamic forces.

For the purpose of analysis, a symmetric aircraft is assumed-- that is, an aircraft having the

initial conditions which will reduce the number of variables needed to describe the aerodynamic reactions in straight and level flight with respect to the instantaneous values of the disturbance velocities u, v, w, p, q, r and their time derivatives. The aerodynamic forces and moments are described as a function of the state variable, that is, as yaw angle, sideslip angle, etc. The aerodynamic reaction can be expressed in the form of stability derivatives multiplied by the corresponding variables.

The aerodynamics forces, moments and rate of change of the air vehicle position in relation to a fixed point on the earth are defined by the equations shown below. Also, the initial conditions of the state of straight and level flight and the equations for angles of sideslip, (β) , and alpha, (α) , with their rate of change, are required to develop the analysis of aircraft motion. The rolling moment depends on various other variables such as beta, the dihedral effect of the wings, pitching moment, and yawing moment. To get some insight into the difference of $c_{x\beta}$, it is essential to consider the moment contributions of the tail, wings and the fuselage. The effect of the vertical tail is to weathercock into the wind, which is a positive sideslip and creates a positive yawing moment,

$$F_x = T - mg \sin \theta + (c_x + c_{x\delta_e} \delta_e) \bar{q} S \quad (28)$$

where:

F_x - force on x-coordinate

T - thrust

c_x - coefficient of force with respect to x body axes

$c_{x\delta_e}$ - derivative coefficient which results from elevator deflection

$\bar{q}$ - dynamic pressure

S - gross wing area

The sum of forces on y coordinate is

$$F_y = mg \cos \theta \sin \phi + (c_{y\beta} + c_{y\delta_a} + c_{y\delta_r}) \bar{q} S \quad (29)$$

where:

F_y - force on y-coordinate

$c_{y\beta}$ - dynamic derivative with respect to beta rate of change

$c_{y\delta_r}$ - dynamic derivative coefficient with respect to rudder deflection

δ_a - deflection of aileron

The sum of forces on z-axes can be defined

$$F_z = mg \cos \theta \cos \phi + [(c_{z_T} - c_{z_\alpha} (\alpha - \alpha_T) + c_{z_q} (q \bar{c} / 2v) + c_{z_{\dot{\alpha}}} (\dot{\alpha} \bar{c} / 2v) + c_{z_{\delta_e}} \delta_e] \bar{q} s \quad (30)$$

where:

x - represent subscripts of derivative coefficient on the x-axes

y - represent subscripts of derivative coefficient on the y-axes

z - represent subscripts of derivative coefficient on the z-axes

F_z - force on z-coordinate

c_{z_r} - dynamic derivative with respect to yaw rate

c_{z_α} - dynamic derivative of angle of attack

This equation is representing the sum of the moments on x-axes

$$L = [c_{L_T} + c_{L_\alpha} (\alpha - \alpha_T) + c_{L_\beta} \beta + c_{L_p} (p \bar{b} / 2v) + c_{L_q} (q \bar{c} / 2v) + c_{L_{\dot{\alpha}}} (\dot{\alpha} \bar{c} / 2v) + c_{L_r} (r \bar{b} / 2v) + c_{L_{\dot{\beta}}} (\dot{\beta} \bar{b} / 2v) + c_{L_{\delta_a}} \delta_a + c_{L_{\delta_r}} \delta_r] \bar{q} s b \quad (31)$$

where:

L - sum of moments on x-axes

c_{L_T} - dynamic derivative coefficient of moment with respect to thrust

c_{L_α} - dynamic derivative coefficient of moment resulted from alpha

$c_{L\beta}$ - dynamic derivative coefficient of moment resulted from beta

c_{Lp} - dynamic derivative coefficient of moment resulted from angular roll rate (p)

c_{Lq} - dynamic derivative coefficient of moment resulted from angular pitch rate (q)

$c_{L\dot{\alpha}}$ - dynamic derivative coefficient resulted from the rate change of alpha (α)

c_{Lr} - dynamic derivative coefficient resulted a yaw rate (r)

$c_{L\dot{\beta}}$ - dynamic derivative coefficient resulted from the rate of change of sideslip angle

angle

$c_{L\delta_a}$ - dynamic derivative coefficient resulted from aileron deflection

$c_{L\delta_r}$ - dynamic derivative coefficient resulted from rudder deflection

The sum of moments on y-axis is

$$M = [c_{M_T} + c_{M_{\alpha}} (\dot{\alpha} - \dot{\alpha}_T) + c_{M_{\beta}} \dot{\beta} + c_{M_p} (pb / 2v) + c_{M_q} (q \bar{c} / 2v) + c_{M_{\dot{\alpha}}} (\dot{\alpha} \bar{c} / 2v) + c_{M_r} (rb / 2v) + c_{M_{\dot{\beta}}} (\dot{\beta} b / 2v) + c_{M_{\delta_e}} \delta_e] q \bar{s} \bar{c} \quad (32)$$

where:

c_{M_T} - derivative coefficient of moment from the thrust

$c_{M_{\alpha}}$ - dynamic derivative coefficient resulted from the angle of attack

$c_{M_{\beta}}$ - dynamic derivative coefficient resulted from sideslip angle

c_{M_i} - dynamic derivative coefficient resulted from roll, pitch and yaw rate

(where i = p, q and r)

$c_{M_{\dot{\alpha}}}$ - dynamic derivative coefficient resulted from alpha rate of change

$c_{M_{\dot{\beta}}}$ - dynamic derivative coefficient resulted from beta rate of change

$c_{M_{\delta e}}$ - dynamic derivative coefficient resulted from the deflection of elevator

The moment on z-axis can be defined

$$N = [c_{N_T} + c_{N_\beta} \beta + c_{N_\alpha} (\alpha - \alpha_T) + c_{N_p} (pb / 2v) + c_{N_r} (rb / 2v) + c_{N_{\dot{\alpha}}} (\dot{\alpha} b / 2v) + c_{N_{\dot{\beta}}} (\dot{\beta} b / 2v) + c_{N_{\dot{q}}} (\dot{q} \bar{c} / 2v) + c_{N_{\dot{\alpha}}} (\dot{\alpha} \bar{c} / 2v) + c_{N_{\delta_a}} \delta_a + c_{N_{\delta_r}} \delta_r] \bar{q} S \quad (33)$$

where:

N - sum of moment on z-axis

c_{N_T} - derivative coefficient resulted from thrust

c_{N_α} - derivative coefficient resulted from alpha

c_{N_β} - derivative coefficient resulted from sideslip

c_{N_i} - derivative coefficient resulted from roll, pitch and yaw rate

(where $i = p, q$ and r)

$c_{N_{\dot{\alpha}}}$ - dynamic coefficient resulted from the change of alpha rate

$c_{N_{\dot{\beta}}}$ - dynamic coefficient resulted from the change of sideslip rate

$c_{N_{\delta e}}$ - dynamic coefficient resulted from elevator deflection

$c_{N_{\delta r}}$ - dynamic coefficient resulted from rudder deflection

$S, \bar{q}$ - gross wing area and dynamic pressure respectively

The rate of change of aircraft position with respect to x-axis can be defined

$$\dot{X} = u \cos \psi \cos \theta + v (\cos \psi \sin \theta \sin \phi - \sin \psi \cos \phi) + w (\cos \psi \sin \theta \cos \phi + \sin \psi \sin \phi) \quad (34)$$

where:

$\dot{X}$ - acceleration of aircraft with respect to x-axis

u, v, w - linear velocities on x, y and z axis

θ, ϕ, ψ - Euler angular rotation in pitch, roll and yaw

The acceleration of aircraft with respect to y-axis can be calculated

$$\begin{aligned}\dot{Y} &= u \sin \psi \cos \theta + v(\sin \psi \sin \theta \sin \phi + \cos \psi \cos \phi) \\ &= + w(\sin \psi \sin \theta \cos \phi - \cos \psi \sin \phi)\end{aligned}\quad (35)$$

where:

$\dot{Y}$ - the rate of change of aircraft position with respect to y-axis

The acceleration of aircraft position with respect to z-axis can defined

$$\dot{Z} = u \sin \theta + v \cos \theta \sin \phi + w \cos \theta \cos \phi \quad (36)$$

where:

$\dot{Z}$ - The rate of change of aircraft with respect to z-axis

The initial value of dynamic pressure is

$$\bar{q}_0 = nm g / [c_z (\sin \alpha_0 \tan \alpha_0 + \cos \alpha_0) S] \quad (37)$$

where:

$\bar{q}_0$ - initial value of dynamic pressure

c_z - control derivative on z-axis

α_0 - initial value of angle of attack

The resultant linear velocity is

$$V = \sqrt{(u^2 + v^2 + w^2)} \quad (38)$$

where:

u, v, w - are the linear velocities

The angle of attack may be calculated from

$$\alpha = \arctan(w / u) \quad (39)$$

where:

α - angle of attack

The sideslip angle can be calculated from

$$\beta = \arctan(v / u) \quad (40)$$

where:

β - sideslip angle

The initial value of Euler angular rotation in pitch can be defined

$$\theta_0 = \arcsin(\sin\Phi_0 \sin\beta_0 - \cos\Phi_0 \sin\delta \cos\beta_0) \quad (41)$$

where:

$\theta_0, \Phi_0, \beta_0$ - initial values of angular rotation in pitch, bank, and sideslip angles respectively.

The initial value of Euler rotation in yaw is

$$\psi_0 = \arcsin[(\sin\Phi_0 \sin\delta \cos\beta_0 - \cos\Phi_0 \sin\delta_0) / \cos\theta_0] \quad (42)$$

The initial value of Euler acceleration in yaw can be defined

$$\dot{\psi} = g \sin\theta_0 [\cos\Phi_0 \cos\alpha_0 + \tan\theta_0 \sin\alpha_0] v_0 \quad (43)$$

where:

v_0 - initial linear velocity

the density of air

$$\rho_0 = 1.2253e^{-(h_0 / 10150)} \quad (44)$$

where:

h_0 - is the initial altitude

The rate of change of Euler angular rotations in pitch and roll can be defined

$$\begin{aligned}\dot{\theta} &= q \cos \phi - r \sin \phi \\ \dot{\phi} &= p + \sin \phi \tan \theta + r \cos \phi \tan \theta\end{aligned}\quad (45)$$

where:

dot - refers to rate of change with respect to time

θ - pitch angle

ϕ - roll angle

The initial velocity is

$$v_0 = \sqrt{(2\bar{q}_0 / \rho_0)} \quad (46)$$

where:

$$\rho_0 = 1.2253e^{-(h_0 / 10150)}$$

The initial value of roll rate is

$$p_0 = -\dot{\psi}_0 \sin \theta_0 \quad (47)$$

where:

ψ_0, θ_0 - initial values of yaw and pitch respectively

The Euler initial angular velocity in roll is

$$\dot{\phi}_0 = \arcsin[(\sin \Phi_0 \cos \beta_0 - \cos \Phi_0 \sin \delta \sin \beta_0) / \cos \theta_0] \quad (48)$$

The dynamic derivatives can be calculated

$$c_{LT} = -c_{Lp} (p_0 b / 2v_0) - c_{Lq} (q_0 \bar{c} / 2v_0) - c_{Lr} (r_0 b / 2v_0) \quad (49)$$

where:

c_{LT} - dynamic derivative resulted from thrust

c_{Lp} - dynamic derivative resulted from from the roll rate

c_{Lr} - dynamic derivative moment resulted from the yaw rate

c_{Lq} - dynamic derivative resulted from pitch rate

The dynamic derivative resulted from the control of thrust is

$$c_{zT} = c_z - c_{zq} (q_0 \bar{c} / 2v_0) \quad (50)$$

where:

c_z - force coefficient on z-axis

c_{zq} - dynamic derivative resulted from pitch rate

The dynamic derivative moment resulted from the yaw rate is

$$c_{MT} = -c_{Mq} (q_0 \bar{c} / 2v_0) - c_{Mr} (r_0 b / 2v_0) \quad (51)$$

where:

c_{MT} - dynamic derivative with respect to thrust

c_{Mq} - dynamic derivative with respect to pitch rate

c_{Mr} - dynamic derivative with respect to yaw rate

$\bar{c}$ - wing mean aerodynamic chord

The control derivative of thrust is

$$c_{NT} = -c_{Np} (p_0 b / 2v_0) - c_{Nr} (r_0 b / 2v_0) - c_{Nq} (q_0 \bar{c} / 2v_0) \quad (52)$$

where:

c_{Np} - dynamic derivative with respect to roll rate

c_{Nr} - dynamic derivative with respect to yaw rate

c_{Nq} - dynamic derivative with respect to pitch rate

The initial of value of angular velocity is

$$\dot{r}_0 = \dot{\psi}_0 \cos \theta_0 \cos \phi_0 \quad (53)$$

where:

ψ_0, θ_0, ϕ_0 - initial values of Euler angular rotation in yaw, pitch, and roll

The initial value of pitch rate can be defined

$$q_0 = \dot{\psi}_0 \cos \theta_0 \sin \phi_0 \quad (54)$$

The acceleration of rate of change alpha-dot is

$$\dot{\alpha} = (u \dot{w} - \dot{u} w) / (u^2 + w^2) \quad (55)$$

where:

w - is the linear velocity

The horizontal flight path angle with respect to vertical plane is

$$\gamma_H = \arctan(\dot{Y} / \dot{X}) \quad (56)$$

The vertical flight path angle with respect to horizontal plane is

$$\gamma_V = \sqrt{\arctan[-\dot{Z} / (\dot{X}^2 + \dot{Y}^2)]} \quad (57)$$

When all coefficient matrices of the aircraft are obtained , it shows that longitudinal and the lateral equations are decoupled and can be solved separately, although the lateral equations depend on the steady state longitudinal parameters MT, γ_e and θ_e . In Figure 5b and Figure 5c shows the horizontal and vertical path angles γ_H and γ_V .

The lateral-directional matrices are shown as:

$$\mathbf{A} = \begin{bmatrix} Y_{\beta} & g \cos \theta_e & Y_p & Y_r - Y_T & Y_{\delta a} & Y_{\delta r} & 0 \\ 0 & 0 & \cos \gamma_e / \cos \theta_e & \sin \gamma_e / \cos \theta_e & 0 & 0 & 0 \\ L_{\beta} & 0 & L_p & L_r & L_{\delta a} & L_{\delta r} & 0 \\ N_{\beta} & 0 & N_p & N_r & N_{\delta a} & N_{\delta r} & 0 \\ 0 & 0 & 0 & 0 & -1/\tau_a & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & -1/\tau_r & 0 \\ 0 & 0 & 0 & 1/\tau_w & 0 & 0 & -1 \end{bmatrix} \quad (58)$$

$$\mathbf{B} = \begin{bmatrix} 0 & 0 \\ 0 & 0 \\ 0 & 0 \\ 0 & 0 \\ 1/\tau & 0 \\ 0 & 1/\tau \\ 0 & 0 \end{bmatrix} \quad (59)$$

$$\mathbf{C} = \begin{bmatrix} 0 & 0 & 0 & 1/\tau_w & 0 & 0 & -1 \\ 0 & 0 & 1/\tau_w & 0 & 0 & 0 & 0 \\ 1/\tau_w & 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & 1/\tau_w & 0 & 0 & 0 & 0 & 0 \end{bmatrix} \quad (60)$$

$$\mathbf{u} = \begin{bmatrix} u_a \\ u_r \end{bmatrix} \quad (61)$$

Chapter 5

LQR Control of Aircraft

5.1 Solution of the Linear Quadratic Regulator (LQR).

In this chapter the application of the LQR method is considered. This control scheme is accomplished by the non-linear compensation of the feedback control action, shaping filters and switching logic based on longitudinal-lateral parameters. This multivariable proportional Integral (LQR) control with matrix gains is computed by means of the standard LQ with the application of the following procedure and technique. It is important in the selection of using LQ based method to establish and assume **Q** and **R** to be diagonal matrices. It is known that the LQR has the following properties :

- simplicity in the computation of the gain matrices
- low order of the compensator .

The problem of the aircraft stability may be solved by using feedback application for all control gains and the performance criterion. After selecting the above parameters, the gains can be computed by matrix equations. As indicated above, the plant is described by the state-variable model [22, 23],

$$\dot{\mathbf{x}} = \mathbf{Ax} + \mathbf{Bu} \quad (62)$$

$$\mathbf{y} = \mathbf{Cx} \quad (63)$$

where:

x - is the system state vector

u - is the input vector

A, **B**, **C** - are matrices of the state variable model

With $\mathbf{x}(t) \in \mathbb{R}^n$ the state, $\mathbf{u}(t) \in \mathbb{R}^m$ the control input, and $\mathbf{y}(t) \in \mathbb{R}^p$ the measured output.

The controls feedback is :

$$\mathbf{u} = -\mathbf{Ky} \quad (64)$$

where:

K is an $m \times p$ matrix of a constant feedback coefficients.

Since the regulator problem only involves stabilizing the aircraft and inducing good closed-loop time responses, $\mathbf{u}(t)$ will be taken as a pure feedback with no auxiliary input. In order to obtain an adequate response in the control stability of the closed-loop system, we will select a performance criterion in the time domain. The goal to drive any initial condition error to zero can be achieved by selecting the control input $\mathbf{u}(t)$ to minimize the quadratic performance index $J(t)$ of the type

$$\min J = \frac{1}{2} \int_0^{\infty} (\mathbf{x}^T \mathbf{Q} \mathbf{x} + \mathbf{u}^T \mathbf{R} \mathbf{u}) dt \quad (65)$$

where $\mathbf{Q}$ and $\mathbf{R}$ are symmetric positive weighting matrices. Positive semidefiniteness of a square matrix $\mathbf{M}$ (denoted $\mathbf{M} \geq 0$) is equivalent to all its eigenvalues being nonnegative, and also to the requirement that the quadratic form $\mathbf{x}^T \mathbf{M} \mathbf{x}$ be nonnegative for all vectors. Therefore, the definite assumption on $\mathbf{Q}$ and $\mathbf{R}$ guarantee that J is nonnegative and lead a sensible minimization problem.

By substituting the control (64) into (62) the closed-loop system equations are determined to be

$$\dot{\mathbf{x}} = (\mathbf{A} - \mathbf{B} \mathbf{K} \mathbf{C}) \mathbf{x} \equiv \mathbf{A}_c \mathbf{x} \quad (66)$$

where:

$\mathbf{A}$, $\mathbf{B}$, $\mathbf{C}$ - matrices

$\mathbf{K}$ - gain value

The Performance Index can be related in terms of $\mathbf{K}$ as

$$J = \frac{1}{2} \int_0^{\infty} \mathbf{x}^T (\mathbf{Q} + \mathbf{C}^T \mathbf{K}^T \mathbf{R} \mathbf{K} \mathbf{C}) \mathbf{x} dt \quad (67)$$

The problem is now to select the gain so that J is minimized subject to the dynamical constraint (66).

where:

$\mathbf{Q}$ and $\mathbf{R}$ are symmetric positive semidefinite weighing matrices

J - performance index

$\mathbf{x}^T$ - transpose of the $\mathbf{x}$ -matrix

Selecting the gain value $\mathbf{K}$ so J is minimized subject to the dynamical constraints of equation (73).

To simplify the dynamical optimization problem, we convert it into an equivalent static. that is easier to solve the problem. It is assumed that we can achieve a positive semidefinite, symmetric matrix $\mathbf{P}$ and J which may be expressed as:

$$\frac{d}{dt}(\mathbf{x}^T \mathbf{P} \mathbf{x}) = -\mathbf{x}^T (\mathbf{Q} + \mathbf{C}^T \mathbf{K}^T \mathbf{R} \mathbf{K} \mathbf{C}) \mathbf{x} \quad (68)$$

Then J may be written as

$$J = \frac{1}{2} \mathbf{x}^T(0) \mathbf{P} \mathbf{x}(0) - \frac{1}{2} \lim_{t \rightarrow \infty} \mathbf{x}^T(t) \mathbf{P} \mathbf{x}(t) \quad (69)$$

Assuming that the closed-loop system is asymptotically stable so that $\mathbf{x}(t)$ vanishes with time. Supposing that the $\mathbf{x}(t)$ disappears with time as it closes to ∞ , this leads to

$$J = \frac{1}{2} \mathbf{x}^T(0) \mathbf{P} \mathbf{x}(0) \quad (70)$$

If $\mathbf{P}$ satisfies the equation (68) then we may apply (66) and obtain the following:

$$-\mathbf{x}^T (\mathbf{Q} + \mathbf{C}^T \mathbf{K}^T \mathbf{R} \mathbf{K} \mathbf{C}) \mathbf{x} = \frac{d}{dt}(\mathbf{x}^T \mathbf{P} \mathbf{x}) = \dot{\mathbf{x}}^T \mathbf{P} \mathbf{x} + \mathbf{x}^T \mathbf{P} \dot{\mathbf{x}} \quad (71)$$

$$\mathbf{x}^T (\mathbf{A}_c^T \mathbf{P} + \mathbf{P} \mathbf{A}_c) \mathbf{x} \quad (72)$$

Since this must hold for all initial conditions, and hence for all state trajectories $\mathbf{x}(t)$ may be expressed as

$$\mathbf{g} \equiv \mathbf{A}_c^T \mathbf{P} + \mathbf{P} \mathbf{A}_c + \mathbf{C}^T \mathbf{K}^T \mathbf{R} \mathbf{K} \mathbf{C} + \mathbf{Q} = 0 \quad (73)$$

This equation is known as a Lyapunov Equation

In short, for any fixed value of the feedback, there is a matrix $\mathbf{P}$ which meets the requirement for the equation (73) with a stable closed loop system: the performance index, J , is provided in terms of $\mathbf{P}$. This indicates that $\mathbf{P}$ is independent of the state which is the $n \times n$ matrix.

Therefore only the initial condition $\mathbf{x}(0)$ is applicable to compute the closed loop under the influence of the feedback control (64) $\mathbf{u} = -\mathbf{K}\mathbf{y}$. This provides us with an opportunity to compute the gain values. Now, applying the trace identity

$$\text{tr}(\mathbf{AB}) = \text{tr}(\mathbf{BA}) \quad (74)$$

and their dimensional matrices $\mathbf{A}$ and $\mathbf{B}$, we may write (70) as the following :

$$J = \frac{1}{2} \text{tr}(\mathbf{PX}) \quad (75)$$

Where:

$n \times n$ symmetric matrix $\mathbf{X}$ is expressed by

$$\mathbf{X} \equiv \mathbf{x}(0)\mathbf{x}^T(0) \quad (76)$$

It is concluded that the problem of selecting gain value to minimize (67) subject to the dynamical restrictions (66) on the states, is equivalent to the algebraic solution of selecting the $\mathbf{K}$ parameters to minimize (75) subject to the constraints (73) on the auxiliary matrix $\mathbf{P}$.

This problem is solved by using the Lagrange multiplier approach for the constraint to LQR by determining the Hamiltonian

$$H = \text{tr}(\mathbf{PX}) + \text{tr}(\mathbf{gS}) \quad (77)$$

where:

tr - is a trace identity

with $\mathbf{S}$ a symmetric $n \times n$ matrix of Lagrange multipliers which still needs to be determined.

Then our constrained optimization problem is equivalent to the simpler problem of minimizing (77) without constraints. To accomplish this we need only set the partial derivatives of H with respect to all the independent variables $\mathbf{P}$, $\mathbf{S}$ and $\mathbf{K}$ equal to zero. In summary, for any fixed feedback matrix $\mathbf{K}$ if there exists a constant, symmetric, positive-semidefinite matrix $\mathbf{P}$ that satisfies (73), and if the closed-loop system is stable, the cost J is given in terms of by (70). This is an important result in that the $n \times n$ auxiliary matrix $\mathbf{P}$ is independent of the state. Given a feedback matrix $\mathbf{K}$, $\mathbf{P}$ may be computed from the Lyapunov equation (73). Then only the initial condition $\mathbf{x}(0)$ is required to compute the closed-loop cost under the influence of the feedback control (64). That is, it may compute the cost of applying the feedback control $\mathbf{u} = \mathbf{K}\mathbf{y}$ before we apply it. It is necessary to use this result to compute the gain $\mathbf{K}$ that minimizes the LQR by using the trace identity (74).

CHAPTER 6

Fuzzy Logic Control of Aircraft

6.1 Introduction

One of the latest methodologies, FLC is based on the so-called intelligent control which is defined as a combination of Control Theory and Artificial Intelligence (AI) [28, [29]. Among many new possible methodologies based on AI, fuzzy logic has been given much attention because of its relative simplicity. The basic idea of a fuzzy logic controller, which is to imitate the control actions of a human operator, can generally be represented as a collection of “if-then” rules [30, 31]. Unlike binary (yes or no) information, fuzzy logic is a multi-valued logic that permits certain degrees for normal versus slow, high, and medium set membership, which can provide an effective way of overcoming the problem of inaccurate data in a binary system.

Fuzzy logic's benefits are fault tolerance and the ability to provide accurate response to ambiguous data. A fuzzy logic controller provides an algorithm which converts the linguistic control strategies, based on expert information, into an automatic control strategy. The methodology of the FLC appears to be very useful when the flight processes are too complex for systems analysis; FLC interprets data qualitatively and accurately. Generally, fuzzy logic control provides a clear application of the maximum input and maximum output (MIMO) systems. In the FLC approach, the membership functions are defined in order to obtain MIMO structures of longitudinal and lateral motion adjust.

The application of fuzzy logic to engineering problems represents only a fraction of its real potential. As a method of encoding and using human knowledge, fuzzy logic systems provide the facilities necessary to break through the computational difficulties associated with traditional decision support and expert systems. Fuzzy logic systems have not yet found their way into aircraft control due to a number of factors that range from

user unfamiliarity with this method and suspicion that there is something fundamentally wrong with a reasoning system that announces its own imprecision.

Fuzzy logic controllers are basically non-linear, and general enough to provide the desired non-linear control actions through careful adjustment [32]. Fuzzy logic seems to be a promising method for non-linear control of the aircraft. In the context of the general description of knowledge based systems (KBS) FLC can be introduced to perform a specific task of closed loop control. The applications of a knowledge based controller can be identified as:

- a direct expert control system (DECS) and
- a supervisory expert control system (SECS) [33].

With the application of fuzzy sets and fuzzy operations, it is possible to implement a design for a fuzzy logic reasoning system as a controller. The structure of the fuzzy controller is illustrated in Fig.6. The control strategy is kept in the form of if-then rules within the rule base. These rules actually represent the mapping of the input variables to the output actions. The dynamic filters are utilized so as to avoid the introduction of error and derivatives of error into the output integration. Scaling is performed to retain the signals between the input parameter and the output limits for the fuzzy process (rules). The membership functions produce a clear interface between the linguistic knowledge and the numerical process variables. The fuzzification defines the membership degree of the input. The reasoning mechanism combines this information with the rule base and defines the fuzzy output of the rule-base system. The application of fuzzy logic serves to mimic the control behavior of human action in a direct configuration or otherwise in a supervisory control environment. As the rule base indicates a mapping between the antecedent and the consequent variable, external dynamic filters are utilized to introduce the desired dynamic behavior of the controller (Fig. 6). The supervisory controller is a secondary controller which augments the existing controller for various conditions. The advantage of this system is the duplication of the already existing system. The fuzzy logic controller may be designed according to two different methods:

1. Design the controller from the knowledge available from the domain experts

2. Develop a fuzzy model of the plant from the measurements, first principles and expert knowledge, and use this model to design a controller or incorporate this model in a model-based control scheme [48, 49].

6.2 Fuzzy Logic Control Design

Fuzzy logic is the process of solving problems with uncertain (ambiguous) data to represent a crisp-logic system. The application of fuzzy logic is based on the concept that all control actions are a matter of degree (negative big, negative medium , negative small, zero, positive small, positive medium and positive big) In a fuzzy logic process, the three logic operations – and, or, and not-- return a degree of membership that is a number valued between 0 and 1.

We will only concentrate on the direct approach, which will serve as a guideline for the design. The design of the controller is characterized by the following steps:

- Determine the controller inputs and outputs

The determination of inputs and outputs, the rule base, the membership functions, scaling factors, the inference options, stability, etc., characterize the design of the fuzzy logic controller. The determination of inputs and outputs is the primary step in ascertaining the plant dynamics of the system..The control strategy is stored in the form of if-then rules in the rule base. In order to compensate for the non-linearities and other undesired phenomena, variables other than error and its derivatives may be used as the controller inputs. Moreover, scaling is performed to keep the signals between the inputs and output limits for which the fuzzy rules are defined. The membership functions provide a smooth interface from the linguistic knowledge to the numerical process variables. It is important to know that with an increasing number of inputs, the complexity of the fuzzy controller (i.e., the number of linguistic terms and the total number of rules) increases considerably. In this situation, rule base simplification and reduction techniques are required for keeping the number of rules small [34].

Determine the rule base

The rule base is a crucial aspect of the design and is based entirely on using the fuzzy model of the process from which the fuzzy control rules are derived, in combination with good understanding, knowledge and experience of the system's operating conditions. For better understanding of the expert based knowledge and their membership functions the reader is advised to refer to Table 6.4, Table 6.6 and Table 6.8. The expert knowledge is presented in form of IF a_i (input) Then c_i rules (output).

- **Define the membership functions**

The number of rules required to determine a complete rule base increases exponentially with the number of linguistic terms per input variable. On the one hand, the number of terms per parameter should be low in order to keep the rule base maintainable. On the other hand, with few terms, flexibility in the rule base will be restricted with respect to the achievable nonlinearity in the control mapping. The membership functions may be a part of the expert's knowledge and much attention has been paid to the application of knowledge based control techniques for flight control (fuzzy logic control). In this application, fuzzy systems are used as supervisory, expert systems. The knowledge is captured through the use of If-Then rules and linguistic terms. Suppose that the longitudinal task of the pilot is to control the altitude and velocity of the aircraft. For example, if the pilot realizes that the aircraft flies too low and too slow, he will increase thrust in order to increase the energy of the aircraft. On the other hand, if the aircraft flies too low but the velocity is too high, then the pilot will increase the pitch angle. Thrust in fact increases the total energy, while an exchange between kinetic and potential energy can be achieved by pitch angle changes (via the tailplane). The computation of the FLC can be defined assuming that the rules illustrated in Table 6.4, Table 6.6 and Table 6.8 are a part of a fuzzy controller's rule base [50].

Based on these heuristics, the following rules base are defined for longitudinal motion of the aircraft as throttle setting and pitch angle commands, respectively (Table 6.4 and Table 6.6). The labels are defined negative very big (NVB), negative big (NB), negative medium (NM), negative small (NS), negative very small (NVS), zero (Zero),

positive very small (PVS), positive small (PS), positive medium (PM), positive big (PB) and positive very big (PVB). The number of rules is chosen quite large in order to make local modifications of the controller possible. The linguistic terms are represented by a fuzzy sets and related to series of membership functions which is defined on the universe of discourse X as a function between $[0,1]$ and illustrated in Figures 10, 11, 13c, 13d, 13e and 13f [31]. The position and shape (e.g. triangular, trapezoidal or bell-shaped) of the membership functions are defined such that the initial input-output function of the FLC is linear between the bounds. However, in our case triangular shapes are preferred because they are related to linear actions. The membership functions for longitudinal and lateral FLC are between $[-1,1]$ as indicated in Figures 13c, 13d and Figures 13e and 13e respectively. In this membership functions are pairwise overlapping and that their sum is always 1. In an altitude and velocity errors of 0.5 belongs for 50% to the set of a positive small error (PS) and for 50% to the set of a positive medium error (PM). In other words, the membership degrees $\mu_{PS}(0.5)$ and $\mu_{PM}(0.5)$ are both half (0.5).

Pilot heuristics are again considered for the lateral control motion of the aircraft. The selected variables to be controlled are heading angle, ψ , the sideslip angle, β , rudder deflection, δ_r . A human pilot will generally handle heading and lateral deviation by roll/aileron commands and sideslip by rudder deflection. As we consider the control strategy of the pilot consists of several subtasks, e.g. roll angle control. If the desired roll angle is positive large (roll angle “error” positive large), then the pilot impose a positive lateral displacement on the stick:

If roll angle error is positive large, **Then** lateral stick position is positive large.

The rule describes a proportional relation between roll angle error and lateral stick position. In Table 6.8, a rule base is defined with heading error, ψ_e , and the desired heading change, $\Delta\psi_e$, as antecedents, and roll angle command as consequent. The rule base for sideslip error and rudder error are shown as well.

- **Inference options**

The inference options also influence the shape of the mapping between inputs and outputs. The most used inference method is max-min method, where the minimum operator is used for determining the degree of fulfillment and the implication, and the maximum operator for rule aggregation. The degree of fulfillment for the antecedent of each rule is computed using fuzzy operators and determines to which degree the i th rule is valid (Figure 11).

- **Controller Fine-tuning**

The implementation of human heuristics is formalized by fuzzy in a systematic way. The scaling factors, which determine the overall gain of the fuzzy controller and also the relative gains of the individual controller inputs, have mainly a global effect. The effect of the modification of membership functions and rules is more localized, for example changing the consequent of an individual rule. The effect of the change of the rule consequent is the most localized and influences only that region where the rule's antecedent holds. The stability analysis of the controller is mainly based on time response.

- **Stability analysis**

The analysis of the controller is mainly based on the responses.

In order to simplify the design, it is important to initialize the FLC as a linear function between the input and the output bounds. This restricts the choice of membership functions and operators, and the controller becomes easier to analyze. One way to obtain linear initialization is to use pairwise overlapping and triangular membership functions where the sum of the membership functions equals 1. The defuzzified consequents must be defined such that the total mapping of the FLC is a linear function [35]. The defuzzified consequents are the numerical values after defuzzification of each individual rule consequent. Secondly, product operators must be used for determining the degree of fulfillment and implication. The aggregation and defuzzification phase are then combined in one step by the so-called fuzzy-mean method, whereby the FLC output y is determined as a "weighted" sum of defuzzified consequents.

6.2.1 Fuzzy Rules

Fuzzy rules combine two or more input fuzzy sets, called antecedent sets, and associate with them an output, or consequent, set. The antecedent sets are combined by means of operators that are analogous to the usual logical conjunctives “and” “or,” etc. An example of fuzzy rule for the stability of the aircraft motion might be “If the angle of theta is positive and the angle rate of change (theta-dot) is positive, then apply a large force positive force.

One method of storing and representing fuzzy rules is through the use of fuzzy associative memory (FAM) Matrix. Table 6.4 shows a FAM matrix in which there are two inputs α and β . Each input variable has seven fuzzy sets associated with it, which we labeled “NB,” “NM,” “NS,” “ZE,” “PS,” “PM,” and “PB,” for “Negative Big,” “Negative Medium,” “Negative Small,” “Zero,” “Positive Small,” “Positive Medium,” and “Positive Big” (These need not be the same for each input variable). Each FAM matrix entry is an output fuzzy set that is the consequent of a fuzzy rule. “Zero” is a fuzzy set that would typically represent a range of values near 0, not just the single numerical value 0.

FAM matrices can have dimensions higher than two. The number of inputs, or antecedents, to the fuzzy rules determines the dimension. Three inputs would result in a FAM matrix that looks like a three-dimensional cube. Higher numbers of inputs produce “hypercube” FAM matrices.

6.2.2 Operation on Fuzzy Sets

Let be a set $U = \{x_1, x_2, x_3, \dots\}$ where x_i could be discrete or continuous. U is called the universe of discourse [34], x_i represents a generic element of U . Let A and B be two fuzzy sets in U with membership functions μ_A and μ_B , respectively. The operation of union, intersection and complement for fuzzy sets are defined via their membership functions (Figure 9). Let $\int \mu_{(i)}$ be the area under the membership function $\mu_{(i)}$. In this case, the center of gravity method can be computed as:

$$U^{asp} = \frac{\sum_i b_i \int \mu_{(i)}}{\sum_i \int \mu_{(i)}} \quad (79)$$

where:

b - center of the membership function

Definition 1.

Union: The membership function $\mu_{A \cup B}$ of the union $A \cup B$ is defined for all $x \in U$ by

$$\mu_{A \cup B} = \mu_A(x) \vee \mu_B(x) = \max\{\mu_A(x), \mu_B(x)\} \quad (80)$$

Definition 2.

Intersection: The membership function $\mu_{A \cap B}$ of the intersection $A \cap B$ is defined for $x \in U$ by

$$\mu_{A \cap B} = \mu_A(x) \wedge \mu_B(x) = \min\{\mu_A(x), \mu_B(x)\} \quad (81)$$

Definition 3.

Complement: The membership function $\mu_{\neg A}$ of the complement of a fuzzy set is defined for all $x \in U$ by

$$\mu_{\neg A}(x) = 1 - \mu_A(x) \quad (82)$$

which converts the linguistic control strategies based on expert information into an automatic control strategy. The methodologies of FLC appears very useful when processes are too complex for analysis by conventional quantitative techniques, and attractive sources of information are interpreted qualitatively, inexactly, or uncertainly. A fuzzy variable is used to represent an unknown value. A variable symbol can be a single capital letter, a capital letter followed by one or more digits, two capital letters followed by zero or more characters, or an underscore followed by any character.

6.2.3 Crisp Set

The crisp set can be described according to the traditional definition of a set in classical logic as indicated in Figure 6. Crisp sets have strict membership criteria according to which an object is either completely included or excluded from the set. For example, an error lies between -1 and +1. In crisp logic, two logic values are used to define the error as if the error were above or below zero; thus, the error is positive or negative respectively. The mapping of the error and the crisp logic value are illustrated in table 6.1 and Figure 7.

Table 6.1 Error versus crisp logic values

Error	Crisp logic value	term description
-1.0	-1	NB (negative big)
-0.6	-1	NM (negative medium)
-0.2	-1	NS (negative small)
0.0	0	Zero
0.2	1	PS (positive small)
0.6	1	PM (positive medium)
1.0	1	PB (positive big)

Crisp logic: name for the boolean logic to differentiate it from fuzzy logic, in which the three logic operations--and, or, and not--return either to 1 or 0.

Triangular membership functions are defined for the terms small, medium and big in the respective domains, see Figure 11. The computational mechanism of the FLC proceeds in five steps: Fuzzification, Degree of Fulfilment, Implication, Aggregation and Defuzzification.

6.2.4. Fuzzification

Fuzzification is the process for converting crisp numerical input to fuzzy logic value by combining actual input values with stored membership functions as shown in Figure 6 and Figure 11. The membership degrees of the antecedent variables are computed as follows:

$$(\mu_{\text{small}}(e), \mu_{\text{medium}}(e), \mu_{\text{medium}}(\Delta e), \mu_{\text{big}}(\Delta e)).$$

6.2.5 Degree of Fulfilment

The degree of fulfilment for the antecedent of each rule is computed using fuzzy logic operators. The degree of fulfilment β_i determines to which degree the i th rule is valid as shown in Figure 11. The product operator is used:

$$\begin{aligned}\beta_1 &= \mu_{\text{small}}(e) \otimes \mu_{\text{medium}}(\Delta e) \\ \beta_2 &= \mu_{\text{medium}}(e) \otimes \mu_{\text{big}}(\Delta e).\end{aligned}$$

6.2.6 Implication

The degree of fulfilment is used to modify the consequent of the corresponding rule. This operation represents the if-then implication defined as a t-norm, i.e. a conjunction operator (e.g. product). Hence the fuzzy outputs of the rules become:

$$\begin{aligned}\mu'_1(u) &= \beta_1 \bullet \mu_{\text{small}}(u) \\ \mu'_2(u) &= \beta_2 \bullet \mu_{\text{medium}}(u)\end{aligned}$$

6.2.7 Aggregation

The consequents of all rules are combined into a single fuzzy set. The aggregation operator depends on the implication function used; for conjunctions, it is a disjunction operator (e.g max):

$$\text{FLC output}(u) = \max(\mu'_1(u), \mu'_2(u))$$

6.2.8 Defuzzification

Defuzzification is a process in which fuzzy output is converted into crisp, numerical results as indicated in Figure 6. Defuzzification can be considered as an operator that replaces a fuzzy set by a representative value.

6.2.9 Fuzzy Set

An ordinary set divides the universe into those items that are completely in the set and those items that are completely outside of the set. We can describe this phenomenon by assigning the value 1 to all those items which are members of the set and the value 0 to all items which are not members of the set. For ordinary sets, only these two values are possible. The function which assigns these values is called the characteristic function of the set. Fuzzy sets allow the possibility of degrees of membership. That is, any of the values between 0 and 1 (including 0 and 1) may be assigned. Fuzzy sets are determined by their membership functions. We can concentrate on a representation for the membership function and use triangular functions, although, other types of functions can be used as membership functions.

6.2.10 Membership

Fuzzy sets have values between 0 and 1 that indicate the degree to which an element has membership in the set. At 0, the element has no membership; while at 1, it has full membership. The function which assigns this value is called the membership function associated with the fuzzy set.

For analyzing the parameters of aircraft motion, the linguistic terms are presented by membership functions [36]. The position and shape of a fuzzy set membership function depends on the particular application. The variable 'error' in figure 9, a series of triangular-shaped membership functions is shown. Notice that in this case, the membership functions are overlapping and that the sum is always one. The possible mapping of error and fuzzy logic value is shown in Table 6.2.

Table-6.2 Error versus fuzzy logic values

Error	Fuzzy logic	Term description
-1.0	-1	NB (negative big)
-0.6	-0.3	NM (negative Medium)
-0.2	-0.1	NS (negative small)
0.0	0.0	Zero
0.2	0.1	PS (positive small)
0.6	0.3	PM (positive medium)
1.0	1	PB (positive big)

The fuzzy membership functions defined for the consequents rules can also be illustrated in Table 6.3 . In Figure 8, a series of membership functions is shown for variable control action. The large set of consequent membership functions is required to initialize the controller by a linear mapping.

Table 6.3 Error versus fuzzy logic control action values

Error	Fuzzy logic control values	Term description
-0.1	-1	NVB (negative very big)
-0.8	-0.4	NB (negative big)
-0.6	-0.3	NM (negative medium)
-0.4	-0.2	NS (negative small)
-0.2	-0.1	NVS (negative very small)
0.0	0.0	Zero
0.2	0.1	PVS (positive very small)
0.4	0.2	PS (positive small)
0.6	0.3	PM (positive medium)
0.8	0.4	PB (positive big)
1.0	1	PVB (positive very big)

In order to apply the rules, one needs to combine the membership functions using logical connectives such as “and” (conjunction), or “or” (disjunction). The most commonly used conjunction operators are the minimum and the product operators. Usually, the maximum or sum operator is used for disjunction. The mapping of error and fuzzy logic control action is illustrated in Table 6.3.

The following rules are designed to pave the way to introducing the fuzzy controller concept to the control system of the aircraft. Figure 9 represents the fuzzy membership functions as defined for the consequents of the rules. A large set of consequent membership functions is required in order to initialize the controller by a linear mapping. For the longitudinal motion, the mapping includes a pitch angle controller with pitch rate damping; for the lateral motion, a roll angle holds system and yaw damper. Through the use of 7 membership functions on the input, we derive 49 rules for each control variable are derived using the energy concept (considering the kinetic related to velocity, and potential related to altitude energy of the aircraft) [50]. The knowledge is captured through the use of If -Then rules and linguistic terms like small, big etc. Suppose that the longitudinal task of the pilot is to control the altitude and velocity of the aircraft. For example, if the pilot realizes that the aircraft flies too low and too slow, he will increase thrust in order to increase the energy of the aircraft. On the other hand, if the aircraft flies too low but the velocity is too high, then the pilot will increase the pitch angle. Thrust in fact increases the total energy, while an exchange between kinetic and potential energy can be achieved by pitch angle changes (via the tailplane).

The increase of thrust reflects the increase of the total energy, and pitch angle divides the energy into kinetic and potential. Based on the above definition of the energy principle, two rule bases for pitch angle and throttle setting can be developed. With the rule base for throttle setting changes, the membership functions indicated in Table 6.4 and Table 6.5 can be obtained.

Table 6.4. Rule base for throttle membership function setting changes.

$v_e - h_e$	NB	NM	NS	ZE	PS	PM	PB
NB	NE	NVB	NB	NM	NS	NVS	ZE
NM	NVB	NB	NM	NS	NVS	ZE	PVS
NS	NB	NM	NS	NVS	ZE	PVS	PS
NE	NM	NS	NVS	ZE	PVS	PS	PM
PS	NS	NVS	ZE	PVS	PS	PM	PB
PM	NVS	ZE	PVS	PS	PM	PB	PVB
PB	ZE	PVS	PS	PM	PB	PVB	PE

Table 6.5. The logic control values of throttle setting membership functions

$v_e - h_e$	NB	NM	NS	ZE	PS	PM	PB
NB	-1	-1	-0.4	-0.3	-0.2	-0.1	0
NM	-1	-0.4	-0.3	-0.2	-0.1	0	0.1
NS	-0.4	-0.3	-0.2	-0.1	0	0.1	0.2
NE	-0.3	-0.2	-0.1	0	0.1	0.2	0.3
PS	-0.2	-0.1	0	0.1	0.2	0.3	0.4
PM	-0.1	0	0.1	0.2	0.3	0.4	1
PB	0	0.1	0.2	0.3	0.4	1	1

The rule base for pitch angle is illustrated in Tables 6.6 and 6.7.

Table 6.6 The rule base for pitch angle changes

v_e — h_e .	NB	NM	NS	ZE	PS	PM	PB
NB	ZE	NVS	NS	NM	NB	NVB	NE
NM	PVS	ZE	NVS	NS	NM	NB	NVB
NS	PS	PSV	ZE	NVS	NS	NM	NB
ZE	PM	PS	PVS	ZE	NVS	NS	NM
PS	PB	PM	PS	PVS	ZE	NVS	NS
PM	PVB	PB	PM	PS	PVS	ZE	NVS
PB	PE	PVB	PB	PM	PS	PVS	ZE

Table 6.7 The logic control values for pitch angle variations of membership functions

v_e — h_e .	NB	NM	NS	ZE	PS	PM	PB
NB	0	-0.1	-0.2	-0.3	-0.4	-1	NE
NM	0.1	0	-0.1	-0.2	-0.3	-0.4	-1
NS	0.2	0.1	0	-0.1	-0.2	-0.3	-0.4
ZE	0.3	0.2	0.1	0	-0.1	-0.2	-0.3
PS	0.4	0.3	0.2	0.1	0	-0.1	-0.2
PM	1	0.4	0.3	0.2	0.1	0	-0.1
PB	PE	1	0.4	0.3	0.2	0	

In Table 6.8, a rule base is illustrated with heading error $\psi_e = \psi_{ref} - \psi$ and the extra desired heading change $\Delta\psi_e$ as antecedents, and roll angle command as consequent.

Table 6.8 Rule bases for roll angles and rudder commands.

$\psi_e(\rightarrow)$ $\Delta\psi_e(\downarrow)$	NB	NS	ZE	PS	PB
NB	NE	NVB	NB	NS	ZE
NS	NVB	NB	NS	ZE	PS
ZE	NB	NS	ZE	PS	PB
PS	NS	ZE	PS	PB	PVB
PB	ZE	PS	PB	PVB	PE

Chapter 7

Simulation and Analysis

7.1 Longitudinal Motion

An investigation of the performance of a fuzzy controller and a LQR controller was carried out. The effects of these controllers were observed with particular attention given to longitudinal-lateral stability control. The attitude of the fuzzy controller serves as an inner loop for the longitudinal motion of the aircraft. The simulation results of the alpha and elevator deflection parameters are almost the same in both controllers, though the fuzzy controller seems a little faster than LQR controller. This might be due to the angle of attack measurement: the actuator of the LQR controller is quite noisy and the resulting friction causes a time delay as shown in Figure 15. On the other hand, the better performance of the fuzzy controller over LQR is obvious on the angular velocity simulation: It can be noted that both controllers exhibit a time delay in the control of angular velocity $q(t)$ but, the fuzzy controller stabilizes a little faster and reaches zero as indicated in Figure 15. The measured outputs $y(t)$ are pitch q and angle of attack α . However since alpha measurement are quite noisy, a low-pass filter is used to provide filtered measurements of α_F and produces the same results as alpha is shown in Figure 17. An integrator (ϵ) was applied to ensure a zero steady state; the output graph shows a better performance of the fuzzy controller compared with that of the LQR controller as elaborated in Figure 18. The integrator output is ϵ .

In the fuzzy controller, the angle of attack, the angular velocity $q(t)$, and the integrator are used as feedback gains $K\alpha$, Kq and KI respectively. The longitudinal task of the crew is to regulate and control the total power of the air vehicle. If the velocity of the aircraft is too low, the pilot has to take action to increase the engine thrust in order to maintain control. On the other hand, if the aircraft flies too low but the velocity is high, then the pilot should increase the pitch angle. The engine thrust increases the total power of the aircraft, while the exchange (or the difference between potential and kinetic energy)

can be achieved by the pitch angle variations through the aircraft elevator (tailplane). Based on the above assessment, the rule base commands for throttle and pitch angle settings were defined. The labels of the settings are: negative big (NB), negative medium (NM), negative small (NS), zero (ZE), positive small (PS), positive medium (PM), and positive big (PB). These terms are directly related to a series of membership functions between -1 and 1. The scaling factor with relative terms is translated into the domain between -1 and 1. The control actions are the throttle setting and the pitch angle commands. Referring to Table 6.4, if the velocity error is PM , the aircraft motion is too slow and the altitude error is zero; then the pilot must take action to increase the throttle change to apply more power as PS to the situation of the flight. The logic control values of Table 6.4 are indicated in Table 6.5. As clearly illustrated in the simulation results of the fuzzy and LQR controllers for longitudinal motion of the aircraft, the fuzzy control application gives better results than those of the LQR, as the damping frequency is much faster and the situation is stabilized to zero more quickly. Looking at the control of angular velocity and angle of attack, the results show that the amplitude of the fuzzy controller is greater and stabilizes the situation more quickly than the LQR controller which has a time delay interval. These encouraging results demonstrate the better effectiveness of the fuzzy controller over the LQR in the application of knowledge-based control techniques for flight controllers. It is important to point out that for longitudinal motion, the discrepancy between the linear quadratic (LQR) and fuzzy logic controller (FLC) are very small as indicated in Figure 16 and Figure 17.

7.2 Lateral Motion

The results of dynamic simulation of lateral motion show far better performance of the fuzzy controller than the LQR. The difference in performance here was greater than that in the longitudinal simulation. The simulation results clearly indicate the stability and good performance of multi-variable frequency-domain techniques.

The fuzzy logic controller provides a transparent interface between the altitude control of the aircraft and a high level of human action. The FLC requires more of human intuition than the solving of equations of multi-variables for specific formulae. The performance of the longitudinal and lateral are evaluated by of a time responses under the conditions of Table 6.4 , Table 6.6 and Table 6.8.. The test of the sideslip angle under the requirement of the time response shows that the fuzzy logic controller is more effective and stabilizes faster than the LQR controller (Figure 18). The results of the roll angular velocity in dynamic motion without controller, fuzzy logic and LQR with controller are illustrated in Figure 20. In this case, it is very clear that the fuzzy controller has better performance as it has less amplitude and stabilizes faster in less than 3 seconds, while the amplitude of LQR has a little greater which results in a delay and effects its performance. Referring to the simulation results of the yaw rate in Figure 21, rudder deflection in Figure 22 and aileron displacement in Figure 23. They indicate the nature of the fuzzy controller and its performance provides a better results than the linear quadratic regulator (LQR). The simulation results, show that the application of fuzzy logic controller gives better performance than LQR controller in the lateral motion of the aircraft.

Chapter 8

Conclusions

For LQR, and fuzzy logic controllers, most of the performance is predetermined when the strategy and the design is defined. The FLC is a systematic procedure, but fine optimizing the time responses of the FLC requires a trial and error process. However, using very restricted, clear guidelines and with a basic understanding of controller parameter changes, satisfactory results can be achieved. Aerodynamic derivatives for configuration at the required flight conditions must be considered, and great attention should be given to these derivatives as they have a tremendous influence on aircraft motion.

The fuzzy logic controller is considered a real-time expert system implementing the actions of a human operator. The fuzzy logic controller is more effective than the LQR as it doesn't require any explicit mathematical model description; instead the actions of a human operator are modeled. This results in a more efficient controller design, but only if explicit operator knowledge is available in a suitable form. Fine-tuning the performance of the controller is a trial and error process, but by using the provided guidelines and understanding the influence of the controller parameters, a satisfactory controller can be developed.

The control strategy is kept in the form of If-then rules within the rule base. They actually represent mapping of the input variables to the output actions. The dynamic filters are utilized to input the error and derivatives of error and to introduce the output integration. Scaling is performed to retain the signals between the input output parameter and the limits for the fuzzy process (rules) as defined. The membership functions produce a clear interface from the linguistic knowledge to the numerical process variables. The fuzzification defines the membership degrees of the input to the antecedent fuzzy sets. The reasoning mechanism combines this information with the rule base and defines the fuzzy

output of the rule-based system. The application of fuzzy is to mimic the control behavior of the human action in a direct configuration or otherwise in a supervisory control environment. As the rule base indicates a mapping between the antecedent and the consequent variable, external dynamic filters are utilized to introduce the desired dynamic behavior of the controller. The supervisory controller is a secondary controller which augmented the existing controller for various conditions. The advantage of this system is a duplication of the already existing system.

The performed simulation demonstrated that the fuzzy logic controller (FLC) is an efficient tool in control of the aircraft. More generally, the FLC is especially useful and applicable to all non-linear dynamic systems where the mathematical model is unknown or partially known.

In this case of the aircraft, the application of the FLC improved the dynamics of transient responses and therefore made the control efforts more efficient.

Fig. 1 Family of $C_m\alpha$ Curves for Various δ_e [10]

Fig.2 Variation of Longitudinal Stability Coefficients with Mach Number [14]

Fig. 3 Loss rudder effectiveness due to combined variations of angle of attack and sideslip [15]

Fig. 4 Loss of aileron effectiveness at increasing angles of attack in the presence of sideslip for a fighter aircraft [17]

Fig. 5.1 Sub-sonic damping derivatives for a wing-body configuration at $M=0.7$ [31]

Fig. 5.2 Sub-sonic cross derivatives for a swept wing fighter aircraft at $M=0.7$ [12]

Fig. 5.3 Variation of cross-coupling derivatives with the angle of attack [33]

Fig. 5a Body system of axes and related angles, positive directions indicated by arrows

Fig. 5b Vertical flight path angle γ_v , vertical plane

Fig. 5c Horizontal flight path angle γ_H , horizontal plane

Fig. 6 Fuzzy system controller

Fig.7 Membership functions of premise terms.

Fig.8 Fuzzy controller

Fig. 9 Output membership functions

Fig.10 Input membership functions with input values

Fig. 11 Computational Mechanism of FLC

Fig. 12 (a) consequent membership unction and
(b) implied fuzzy set membership function.

Fig. 13 (a) consequent membership function and
(b) implied fuzzy set membership function.

Fig. 13 (c) Membership functions for input altitude error

Fig. 13 (d) Membership functions for input velocity error

Fig. 13 (e) Membership functions for input heading

Fig. 13 (f) Membership functions for input sideslip

Fig. 14 Longitudinal motion (α - Angle of attack versus Time)

Fig. 15 Longitudinal motion (Angular Velocity versus Time)

Fig. 16 Longitudinal motion (δ_e – Elevator deflection versus Time)

Fig. 17 Longitudinal motion (α_f – Filtered measurement of angle of attack versus Time)

Fig. 18 Lateral motion (Sideslip angle versus Time)

Fig. 19 Lateral motion (Euler angular rotation versus Time)

Fig. 20 Lateral motion (Angular velocity versus Time)

Fig. 21 Lateral motion (Yaw rate versus Time)

Fig. 22 Lateral motion (Rudder deflection versus Time)

Fig. 23 Lateral motion (Aileron deflection versus Time)

References

- [1] Luenberger, D. G., "An Introduction to Observers," IEEE Trans. On Automatic Control, pp.596-603, December 1971.
- [2] Grafton S. B. & Libbey C. E., "Dynamic Stability Derivatives of Twin Jet Fighter Model for Angles of Attack from -10^0 to 110^0 ,". NASA, TN D6091, 1971.
- [3] Rom, J., "High Angle of Attack Aerodynamics," Springer-Verlag, 1992.
- [4] Visbal, M. R., "Dynamic Stall of Constant Rate Pitching Aerofoil. J. Aircraft," 27 (may),1990.
- [5] Huang, Chien Y., et al., "Analysis and Simulation of Nonlinear Control Strategies to High Angle-of-Attack Maneuvers," Proceeding of AIAA Guidance, Navigation, and Control Conference, New Orleans, Lo 1991.
- [6] Favilla., J., "Fuzzy Traffic Control: Adaptive Strateies," Second IEEE International Conference on Fuzzy Systems, 1993.
- [7] Anderson, B. D. and Moore, J. B., "Linear Optimal Control", Prentice Hall, 1992.
- [8] Orlik-Ruchemann, K. J., "Aerodynamics Coupling between Lateral and Longitudinal Degrees of Freedom," AIAA journal, Vol 15, No.12, Dec.1977.
- [9] Pontryagin, L. S., " Ordinary Differential Equations," Addison Wesley, 1962
- [10] Orlik-Ruchemann, K. J., Hanf, E.S., Laberge, J.G. " Direct and Cross-Coupling Subsonic Moment Derivatives due to Oscillatory Pitching an Yawing of an Aircraft like Model at Angles of Attack up to 40^0 in AMES ," NRC NAE LTR-UA -38, Nov.1976.
- [11] Johnson, H. I., "Flight Testing Aircraft for Longitudinal Maneuvering Characteristics," Vol. 2, AGARD Flight Test Manual, Pergamon Press, New York, 1959.
- [12] Nelson, R.C., "Flight Stability and Control Automatic Control," McGraw-Hill Book Company, New York, 1989.
- [13] Babister , A.W., "Aircraft Dynamic Stability and Response," Pergamon Press, 1980.

- [14] Mclean, D., "Automatic Flight Control System," Prentice-Hall International, 1990
- [15] Coe, P.L., Graham, A.B., and Chambers, J.R., "Summary of Information on Low Speed Lateral-Directional Derivatives Due to Rate of Change of Sideslip Angle," NASA TN D7972, Sep. 1975.
- [16] Hancock, G.J. & MAbey, D., "Unsteady Aerodynamics of Controls," AGARD CP 465, 1978.
- [17] Atzhorn, D., and Stengel, R., "Design and Flight Test of a Lateral-Directional Command Augmentation System," J.Guid.Cont.Dyn., Vol.7, No.3, May-Jun 1984.
- [18] Hancock, G. J., "An Introduction to the Flight Dynamics of Rigid Aeroplanes," Ellis Horwad Limited 1995.
- [19] "Unsteady Aerodynamics-Fundamentals and Applications to Aircraft Aerodynamics.." AGARD CP 386, 1985.
- [20] Etkin, B., "Dynamics of Flight-Stability and Control, (2nd Edition) ," John Wiley & Sons, New York 1982.
- [21] Nelson, R. C., "Flight Stability and Automatic Control," McGraw-Hill, 1989.
- [22] Brian, L. Stevens, Frank L. Lewis, "Aircraft Control and Simulation," 1992 by John Wiley & Sons, Inc.
- [23] Blakelock, J. H., "Automatic Control of Aircraft and Missiles (2nd Edition)," John Wiley & sons, Inc., New York 1991.
- [24] Smith, G.A., and G. Meyer, " Aircraft Automatic Flight Control System with Model Inversion ", Journal of Guidance, Control and Dynamics, Vol 10, No.3, May-June 1987.
- [25] Mclean, D., "Automatic Flight Systems," Prentice-Hall International, 1990.
- [26] Isermann, R., Lachmann, K.H., Matko, D., " Adaptive Control Systems ," Prentice Hall, 1991.
- [27]. Huang, Chien Y., "Multivariable Control Law for Flat-Turn Straffing Maneuver by a Supermaneuverable Aircraft," Proc. of AIAA Guidance, Navigation, and Control Conference, Aug. 1990.
- [28] Friedland Bernard, "Control System Design, " McGraw-Hill, Inc. 1986.

- [29] Zadeh, L.A., "Outline of a New Approach to the Analysis of Complex Systems and Decision Processes," IEEE Trans. on Systems, Man and Cybernetics, 1973.
- [30] Lee, C.C., "Fuzzy Logic in Control Systems: Fuzzy Logic Controller- part 1," IEEE Trans. Systems, Vol. 20, March 1990.
- [31] Bezdek, J.C., "Fuzzy Model- What are they, and Why?," IEEE Trans. Fuzzy System, Vol. 1, NO. 1, February 1993.
- [32] Banks, J. and Carson, J. S., "Discrete event System Simulation," Prentice-Hall, 1984.
- [33] Reusch Bernd, "Computational Intelligence Theory and Applications," International Conference, 5th Fuzzy Days Dortmund, Germany, April 1997 Proceedings, Springer.
- [34] Baldwin, J. F., Martin T.P., Pilsworth B.W., "Fuzzy and Evidential Reasoning in Artificial Intelligence," Research Studies Press LTD., 1995, London.
- [35] Sasiadek, J. Z and Mazzawi Albert N., "Fuzzy and Adaptive Control of Aircraft" Carleton University, Ottawa, Ontario, Canada 1993.
- [36] Law and D.Kalton., "Simulation Modelling and Analysis," New York, McGraw-Hill Inc, 1991.
- [37] "Fixed Wing Stability and Control: Theory and Flight Test Techniques," USNTPS-FTM- NO.103, Naval Air Test Center, Patuxent River, Maryland, January 1975 (Revised November 1981).
- [38] Zadeh, L: "Fuzzy Sets Information and Control," vol. 8 (1965).
- [39] McCormick, B.W., "Aerodynamics, Aeronautics, and Flight Mechanics," McGraw-Hill, 1979.
- [40] Tobak, M., "On the Use of the Indicial Function Concept in the Analysis of Unsteady Motion of Wings and Wing-Tail Combinations," NACA Report 1188, 1954.
- [41] Meyer, G. And L. Cicolani, "Applications of Nonlinear System Inverses to Automatic Flight Control Design-System Concepts and Flight evaluations",

- Theory and Applications of Optimal Control in Aerospace Systems. AGARD, July 1981.
- [42] Jones, J.G., "UK Research on Aeronautical Effects of Surface Winds and Gusts," AGARD Report 626, 1974.
 - [43] Roskam, J., "Airplane Flight Dynamics and Automatic Control," part 1. Roskam Aviation and Engineering Corporation, Lawrence, Kansas, 1979.
 - [44] Beaufere, Henry, et. Al., "Control Power Requirements for Statically Unstable Aircraft, Vol. I and II," AFWAL-TR-87-3018, June 1987.
 - [45] Martorella, P., et al., "Control Definition Study for Advanced Vehicle," NASA Contractor Report 3738, Nov. 1983.
 - [46] Hopkins, H.R., "A Scheme of Notation and Nomenclature for Aircraft Dynamics and Associated Aerodynamics," ARC R&M 3562, 1970.
 - [47] Curry, W. H. and Orlik-ruckamann, K. J., "Sensitivity of aircraft motion to aerodynamics cross-coupling at high angles of attack", AGARD-CP-235, Paper 34, Nov. 1973.
 - [48] Babushka R. and Verbrugger, "An overview of fuzzy modeling for control". Control Engineering Practices, 4(11):1593-1606, 1996.
 - [49] Daafour J., Arzelier D., Garcia G., and Bernusson J., "RCAM design challenge presentation document: the Lyapunov approach", Technical Publication TP-088-14, Group for Aeronautical Research and technology in EUROPE GARTEUR-FM (AG08), 1997.
 - [50] Lambregts A. A., "Vertical flight path and speed control autopilot design using total energy principles", Technical reports, AIAA 83-2239, 1983.
 - [51] Etkin, B., "Dynamics of Atmospheric Flight", John Wiley and Sons. Inc., New York, 1982.
 - [52] DeHaven, H., "The relation of Injuries to Structure in Survivable Aircraft Accidents," National Research Council, CAB Report no. 440, July 1970.
 - [53] Bernard Friedland, "Control System Design an Introduction to State-Space Methods", McGraw-Hill, Inc., N.Y. 1986.

Appendix : A

A.1 Characteristics of aircraft

The aerodynamic derivatives of hypothetical aircraft configuration based on data available in references [2, 8, 10].

Table A.1.1

Parameter	value	unit
q_0	0.0	(rad/sec)
c_{N_T}	0.0	
Φ_0	0.0	(rad)
c_{M_T}	0.0	
p_0	0.0	(rad/sec)
c_{Z_T}	0.841	
r_0	0.0	(rad/sec)
T	100400	(N)
c_{L_T}	0.0	
ρ_0	0.4593	(kg/m ³)
θ_0	2	(rad)
ψ_0	0.0	(rad)
$\bar{q}_0$	3414	(N/m ²)
c_{tp}	1.2	(m)
c_{nt}	7.16	(m)

m	17510	(kg)
$\bar{c}$	4.88	(m)
I_z	183000	(kgm ²)
I_x	36605	(kgm ²)
S	50.2	(m ²)
I_y	162700	(kgm ²)
a_F	4.0	(Per radian)
l_t	7.85	(m)
a_ω	1.2	(Per radian)
c_e/c	0.45	
τ_e	0.4	
τ_r	0.18	
c_r/c	0.164	
c_a/c	0.24	
τ_a	0.21	
S_F	6.27	(m)
Z_F	2	(m)
S_t	16	(m)

A.2 Aerodynamic and control derivatives

The parameters of the control derivatives are based on data available in references [2, 47].

Table A.2.1

Parameter	value
c_z	-0.841
c_x	-0.04
c_{L_α}	0.0
c_y	0.0
c_{L_q}	$0.5-30\Delta\alpha$
$c_{L_{\dot{\alpha}}}$	$0.5-30\Delta\alpha$
c_{L_r}	0.25
c_{L_β}	-0.3
c_{M_α}	-0.6
c_{L_p}	-0.3
c_{M_β}	-0.1
c_{M_q}	$7-120\Delta\alpha$

$c_{M\alpha}$	$-7-120\Delta\alpha$
c_{Mp}	0.0
$c_{y\delta a}$	0.0
$c_{L\delta a}$	-0.0143
c_{Lp}	-0.3
$c_{N\delta a}$	0.00214
$c_{y\delta r}$	0.101
$c_{N\delta r}$	-0.0604
$c_{L\delta r}$	0.017
$c_{N\alpha}$	$0.5-60\Delta\alpha$
c_{Nr}	$-0.5-6\Delta\alpha$

$C_{N_{\beta}}$	$0.2-6\Delta\alpha$
-----------------	---------------------

Appendix: B

```
*****
*
*
*   THE FUZZY LOGIC PROGRAMMING FOR AIRCRAFT MOTION
*
*
*
*****
```

```
#include<stdio.h>
#include<stdlib.h>
#include<math.h>
```

```
#define pi 3.14159
```

```
float cal_dif(float[],float,float,int);
float member_function(int,int,float,float,float);
float member_functionG(int,int,float,float,float);
float fuzzy_control(float[]);
float ucrisp(int,float[],float[],float,float);
```

```
void main(void)
{
float x[50],xa[50],xn[50],k1[50],k2[50],k3[50],k4[50],u,t,h,g0,g1,H;
int j,i,l,No_of_eqs;
```

```
FILE *fp;
if((fp=fopen("gs2"."wb"))==NULL)
{
    printf("cannot open directory file\n");
    exit (1);
}
/*initialization*/
x[1]=.1; x[2]=0; x[3]=0; g0=2; g1=.1; H=5;
u=0; t=0; h=0.001;
No_of_eqs=3;
for(j=0;j<=3100;j++)
{
    x[1]=g0*x[1]; x[2]=g1*x[2];
```

```
/*fuzzy controller*/
u=fuzzy_control(x);
u=H*u;          printf("u=%f--",u);

/*The differential equations of Aircraft by the Runge-Kutta method*/
x[1]=x[1]/g0;  x[2]=x[2]/g1;
for(l=0;l<=310;l++)
{
    if(j==l*10)
        fprintf(fp,"A%d=[%f%f%f%f];\n",l,t,u,x[1]);
}
for(i=1;i<=No_of_eqs;i++)
{
    xn[i]=x[i];
}
for(i=1;i<=No_of_eqs;i++)
{
    xa[i]=xn[i];
    k1[i]=cal_diff(xa,u,h,i);
}
for(i=1;i<=No_of_eqs;i++)
{
    xa[i]=xn[i]+k1[i]/2;
}
for(i=1;i<=No_of_eqs;i++)
{
    k2[i]=cal_diff(xa,u,h,i);
}
for(i=1;i<=No_of_eqs;i++)
{
    xa[i]=xn[i]+k2[i]/2;
}
for(i=1;i<=No_of_eqs;i++)
{
    k3[i]=cal_diff(xa,u,h,i);
}
for(i=1;i<=No_of_eqs;i++)
{
    xa[i]=xn[i]+k3[i];
}
for(i=1;i<=No_of_eqs;i++)
{
    k4[i]=cal_diff(xa,u,h,i);
}
```

```
    }
    for(i=1;i<=No_of_eqs;i++)
    {
        x[i]=xn[i]+(k1[i]+2*k2[i]+2*k3[i]+k4[i])/6;
        printf("x=%f",x[i]);
    }
    t=t+h; printf("t=%f",t);
}
printf("finish-----"); getch();
fclose(fp);
}

/*STATE-SPACE EQUATION OF Aircraft*/
float cal_dif(float xa[],float u,float h,int i)
{
    float a,b,k[50];
    k[1]=xa[2]*h;
    a=9.8*sin(xa[1])+cos(xa[1])*(-xa[3]-0.25*pow(xa[2],2)*sin(xa[1]))/1.5;
    b=0.5*(4/3-pow(cos(xa[1]),2)/3);
    k[2]=h*a/b;
    k[3]=h*(-100*xa[3]+100*u);
    return k[i];
}

/*MAIN FUNCTION OF FUZZY CONTROLLER*/
float fuzzy_control(float x[])
{
    float xd,mf1[11],mf2[11],w,cl,u;
    int i,N;
    N=10;
    for(i=0;i<=N;i++)
    {
        xd=-x[1]; w=pi/4; cl=w*N/2; /*xd--e and de/dt,w--the base-width of
        membership*/
        mf1[i]=member_functionG(N,i,xd,w,cl); /*functions,cl--saturation
        point,N--number*/
        xd=-x[2]; w=pi/8; cl=w*N/2; /*of linguistic values*/
        mf2[i]=member_functionG(N,i,xd,w,cl);
    }
    w=10,cl=w*N/2;
    u=ucrisp(N,mf1,mf2,w,cl);
    return u;
}
```

/*GET MEMBERSHIP FUNCTIONS*/

float member_function(int N,int i,float xd,float w,float cl)

```
{
    float mf[22];
    mf[i]=0;
    if(i<N/2)
    {
        if(xd<0)
        {
            if(xd<=-cl)
            mf[0]=1;
            else
            {
                if(((i-N/2-1)*w<=xd)&&(xd<=(i-N/2)*w))
                mf[i]=1-(-(i-N/2)*w+xd)/w;
                else if(((i-N/2)*w<xd)&&(xd<=(i-N/2+1)*w))
                mf[i]=1+((i-N/2)*w-xd)/w;
                else
                mf[i]=0;
            }
        }
        else
        mf[i]=0;
    }
    else if(i==N/2)
    {
        if((-w<xd)&&(xd<w))
        {
            if(xd<=0)
            mf[N/2]=1+xd/w;
            else
            mf[N/2]=1-xd/w;
        }
        else
        mf[N/2]=0;
    }
    else
    {
        if(xd>0)
        {
            if(xd>=cl)
            mf[N]=1;
        }
    }
}
```



```
        else
        {
            if(((i-N/2+1)*w>=xd)&&(xd>=(i-N/2)*w))
                mf[i]=1-(xd-(i-N/2)*w)/w;
            else if(((i-N/2)*w>xd)&&(xd>=(i-N/2-1)*w))
                mf[i]=1+(xd-(i-N/2)*w)/w;
            else
                mf[i]=0;
        }
    }
    else
        mf[i]=0;
}
return mf[i];
}
```

```
/*FUZZIFICATION AND Calculation OUTPUT*/
float ucrisp(int N,float mf1[],float mf2[],float w,float cl)
{
    float prem[11][11],rule[11][11],ucrisp,u,num,den;
    int i,j;
    for(i=0;i<=N;i++)
    {
        for(j=0;j<=N;j++)
        {
            /* if(mf1[i]>mf2[j])
            prem[i][j]=mf2[j];
            else
            prem[i][j]=mf1[i]; */premi[i][j]=mf1[i]*mf2[j];

            if(i+j<=5)
                rule[i][j]=10;
            else if(i+j==6)
                rule[i][j]=9;
            else if(i+j==7)
                rule[i][j]=8;
            else if(i+j==8)
                rule[i][j]=7;
            else if(i+j==9)
                rule[i][j]=6;
            else if(i+j==10)
                rule[i][j]=5;
        }
    }
}
```

```
        else if(i+j==11)
            rule[i][j]=4;
        else if(i+j==12)
            rule[i][j]=3;
        else if(i+j==13)
            rule[i][j]=2;
        else if(i+j==14)
            rule[i][j]=1;
        else
            rule[i][j]=0;
    }
}
num=0; den=0;
for(i=0;i<=N;i++)
{
    for(j=0;j<=N;j++)
    {
        num=num+prem[i][j]*w*(rule[i][j]-N/2);
        den=den+prem[i][j];
        /* num=num+2*w*(prem[i][j]-pow(prem[i][j],2)/2)*w*(rule[i][j]-N/2);
        den=den+2*w*(prem[i][j]-pow(prem[i][j],2)/2); */
    }
}
ucrisp=num/den;
if(fabs(ucrisp)>=cl)
    ucrisp=cl;
else
    ucrisp=ucrisp;
return ucrisp;
}
float member_functionG(int N,int i,float xd,float w,float cl)
{
    float mf[22],o;
    o=.4*w;
    if(fabs(xd-w*(i-N/2))>=w)
        mf[i]=0;
    else if (fabs(xd)>=cl)
        mf[i]=1;
    else
        mf[i]=exp(-0.5*pow(((xd-w*(i-N/2))/o),2));
    return mf[i];
}
```

A0=[0.000000 20.148453 0.100000];
A1=[0.020000 -1.143031 0.098902];
A2=[0.040000 1.654076 0.096849];
A3=[0.060000 1.664974 0.095405];
A4=[0.080000 1.054246 0.093757];
A5=[0.100000 1.462252 0.092191];
A6=[0.120000 1.238251 0.090656];
A7=[0.140000 1.280184 0.089131];
A8=[0.160000 1.251911 0.087642];
A9=[0.180000 1.223184 0.086172];
A10=[0.200000 1.209648 0.084728];
A11=[0.220000 1.185504 0.083308];
A12=[0.240000 1.166929 0.081912];
A13=[0.260000 1.146971 0.080538];
A14=[0.280000 1.127580 0.079188];
A15=[0.300000 1.108680 0.077859];
A16=[0.320000 1.089928 0.076553];
A17=[0.340000 1.071586 0.075268];
A18=[0.360000 1.053513 0.074005];
A19=[0.380000 1.035753 0.072763];
A20=[0.400000 1.018292 0.071541];
A21=[0.420000 1.001122 0.070339];
A22=[0.440001 0.984240 0.069158];
A23=[0.460001 0.967642 0.067996];
A24=[0.480001 0.951324 0.066853];
A25=[0.500001 0.935278 0.065730];
A26=[0.520000 0.919502 0.064625];
A27=[0.540000 0.903991 0.063538];
A28=[0.560000 0.888741 0.062470];
A29=[0.580000 0.873748 0.061419];
A30=[0.599999 0.859006 0.060386];
A31=[0.619999 0.844511 0.059370];
A32=[0.639999 0.830260 0.058371];
A33=[0.659999 0.816251 0.057389];
A34=[0.679998 0.802473 0.056423];
A35=[0.699998 0.788929 0.055473];
A36=[0.719998 0.775612 0.054539];
A37=[0.739998 0.762519 0.053620];
A38=[0.759997 0.749646 0.052717];
A39=[0.779997 0.736987 0.051829];
A40=[0.799997 0.724546 0.050956];
A41=[0.819997 0.712312 0.050098];

A42=[0.839996 0.700284 0.049254];
A43=[0.859996 0.688456 0.048423];
A44=[0.879996 0.676831 0.047607];
A45=[0.899996 0.665399 0.046805];
A46=[0.919995 0.654162 0.046016];
A47=[0.939995 0.643111 0.045240];
A48=[0.959995 0.632245 0.044477];
A49=[0.979994 0.621565 0.043727];
A50=[0.999994 0.611063 0.042989];
A51=[1.019994 0.600740 0.042264];
A52=[1.039994 0.590587 0.041551];
A53=[1.059994 0.580609 0.040850];
A54=[1.079993 0.570795 0.040161];
A55=[1.099993 0.561151 0.039483];
A56=[1.119993 0.551668 0.038817];
A57=[1.139992 0.542343 0.038162];
A58=[1.159992 0.533179 0.037517];
A59=[1.179992 0.524163 0.036884];
A60=[1.199992 0.515303 0.036261];
A61=[1.219991 0.506592 0.035649];
A62=[1.239991 0.498027 0.035047];
A63=[1.259991 0.489608 0.034455];
A64=[1.279991 0.481328 0.033873];
A65=[1.299990 0.473190 0.033301];
A66=[1.319990 0.465189 0.032739];
A67=[1.339990 0.457321 0.032186];
A68=[1.359990 0.449588 0.031642];
A69=[1.379989 0.441985 0.031107];
A70=[1.399989 0.434511 0.030582];
A71=[1.419989 0.427160 0.030065];
A72=[1.439989 0.419935 0.029557];
A73=[1.459988 0.412832 0.029057];
A74=[1.479988 0.405850 0.028566];
A75=[1.499988 0.398985 0.028083];
A76=[1.519988 0.392235 0.027609];
A77=[1.539987 0.385597 0.027142];
A78=[1.559987 0.379075 0.026683];
A79=[1.579987 0.372661 0.026232];
A80=[1.599987 0.366357 0.025789];
A81=[1.619986 0.360158 0.025352];
A82=[1.639986 0.354063 0.024924];
A83=[1.659986 0.348072 0.024502];
A84=[1.679986 0.342183 0.024088];

A85=[1.699985 0.336391 0.023681];
A86=[1.719985 0.330699 0.023280];
A87=[1.739985 0.325102 0.022886];
A88=[1.759984 0.319600 0.022499];
A89=[1.779984 0.314189 0.022119];
A90=[1.799984 0.308872 0.021744];
A91=[1.819984 0.303645 0.021377];
A92=[1.839983 0.298505 0.021015];
A93=[1.859983 0.293453 0.020659];
A94=[1.879983 0.288484 0.020310];
A95=[1.899983 0.283599 0.019966];
A96=[1.919982 0.278800 0.019628];
A97=[1.939982 0.274081 0.019296];
A98=[1.959982 0.269439 0.018970];
A99=[1.979982 0.264880 0.018649];
A100=[1.999981 0.260394 0.018333];
A101=[2.019982 0.255985 0.018023];
A102=[2.039983 0.251651 0.017718];
A103=[2.059984 0.247392 0.017418];
A104=[2.079985 0.243202 0.017123];
A105=[2.099986 0.239082 0.016833];
A106=[2.119987 0.235035 0.016548];
A107=[2.139988 0.231056 0.016268];
A108=[2.159989 0.227143 0.015993];
A109=[2.179990 0.223296 0.015722];
A110=[2.199991 0.219514 0.015456];
A111=[2.219992 0.215797 0.015194];
A112=[2.239993 0.212141 0.014937];
A113=[2.259994 0.208549 0.014684];
A114=[2.279994 0.205018 0.014435];
A115=[2.299995 0.201548 0.014191];
A116=[2.319996 0.198132 0.013951];
A117=[2.339997 0.194776 0.013714];
A118=[2.359998 0.191477 0.013482];
A119=[2.379999 0.188234 0.013254];
A120=[2.400000 0.185046 0.013029];
A121=[2.420001 0.181911 0.012809];
A122=[2.440002 0.178829 0.012592];
A123=[2.460003 0.175800 0.012379];
A124=[2.480004 0.172824 0.012169];
A125=[2.500005 0.169894 0.011963];
A126=[2.520006 0.167017 0.011760];
A127=[2.540007 0.164187 0.011561];

A128=[2.560008 0.161404 0.011365];
A129=[2.580009 0.158672 0.011173];
A130=[2.600009 0.155985 0.010984];
A131=[2.620010 0.153341 0.010798];
A132=[2.640011 0.150744 0.010615];
A133=[2.660012 0.148189 0.010435];
A134=[2.680013 0.145679 0.010258];
A135=[2.700014 0.143211 0.010084];
A136=[2.720015 0.140785 0.009913];
A137=[2.740016 0.138400 0.009746];
A138=[2.760017 0.136055 0.009580];
A139=[2.780018 0.133749 0.009418];
A140=[2.800019 0.131482 0.009259];
A141=[2.820020 0.129255 0.009102];
A142=[2.840021 0.127064 0.008948];
A143=[2.860022 0.124912 0.008796];
A144=[2.880023 0.122795 0.008647];
A145=[2.900023 0.120714 0.008500];
A146=[2.920024 0.118669 0.008356];
A147=[2.940025 0.116658 0.008215];
A148=[2.960026 0.114681 0.008076];
A149=[2.980027 0.112738 0.007939];
A150=[3.000028 0.110828 0.007804];

B=[A0;A1;A2;A3;A4;A5;A6;A7;A8;A9;A10;A11;A12;A13;A14;A15;A16;A17;A18;A19]
;
C=[A20;A21;A22;A23;A24;A25;A26;A27;A28;A29;A30;A31;A32;A33;A34;A35;A36;A37];
D=[A38;A39;A40;A41;A42;A43;A44;A45;A46;A47;A48;A49;A50;A51;A52;A53;A54;A56];
E=[A57;A58;A59;A60;A61;A62;A63;A64;A65;A67;A68;A69;A70;A71;A72;A73;A74;A75];
F=[A76;A77;A78;A79;A80;A81;A82;A83;A84;A85;A86;A87;A88;A89;A90;A91;A92;A93];
G=[A94;A95;A96;A97;A98;A99;A100;A101;A102;A103;A104;A105;A106;A107;A108];
H=[A109;A110;A111;A112;A113;A114;A115;A116;A117;A118;A119;A120;A121;A122];
I=[A123;A124;A125;A126;A127;A128;A129;A130;A131;A132;A133;A134;A135;A136];
;
J=[A137;A138;A139;A140;A141;A142;A143;A144;A145;A146;A147;A148;A149;A150]
;

```
K=[B;C;D;E;F;G;H;I;J];
L=K';
X=L(1,:);
Y=L(2,:);
Z=L(3,:);
subplot(2,2,1)
plot(X,Y)
grid on
axis([0 2 -5 30])
xlabel('time(sec) Gaussian  $\sigma=0.5*w$ ')
ylabel('input force(N)')
subplot(2,2,2)
plot(X,Z)
grid on
axis([0 3 -0.05 0.15])
xlabel('g0=2,g1=1,h=5')
ylabel('angular position(rad)')
V0=[0.000000 27.729303 0.100000];
V1=[0.020000 -2.437318 0.097573];
V2=[0.040000 -0.078307 0.091964];
V3=[0.060000 2.577582 0.088072];
V4=[0.080000 0.147573 0.083995];
V5=[0.100000 1.177288 0.080054];
V6=[0.120000 0.884411 0.076404];
V7=[0.140000 0.797745 0.072858];
V8=[0.160000 0.840908 0.069497];
V9=[0.180000 0.756299 0.066289];
V10=[0.200000 0.736924 0.063225];
V11=[0.220000 0.701210 0.060304];
V12=[0.240000 0.666650 0.057516];
V13=[0.260000 0.637501 0.054857];
V14=[0.280000 0.607036 0.052319];
V15=[0.300000 0.579077 0.049898];
V16=[0.320000 0.552143 0.047589];
V17=[0.340000 0.525816 0.045385];
V18=[0.360000 0.501842 0.043283];
V19=[0.380000 0.478410 0.041278];
V20=[0.400000 0.456200 0.039366];
V21=[0.420000 0.435023 0.037542];
V22=[0.440001 0.414791 0.035802];
V23=[0.460001 0.395518 0.034142];
V24=[0.480001 0.377127 0.032559];
V25=[0.500001 0.359596 0.031049];
```

V26=[0.520000 0.342875 0.029609];
V27=[0.540000 0.326932 0.028236];
V28=[0.560000 0.311725 0.026926];
V29=[0.580000 0.297227 0.025676];
V30=[0.599999 0.283404 0.024485];
V31=[0.619999 0.270224 0.023348];
V32=[0.639999 0.257654 0.022264];
V33=[0.659999 0.245669 0.021231];
V34=[0.679998 0.234240 0.020245];
V35=[0.699998 0.223345 0.019305];
V36=[0.719998 0.212956 0.018408];
V37=[0.739998 0.203049 0.017553];
V38=[0.759997 0.193603 0.016738];
V39=[0.779997 0.184597 0.015960];
V40=[0.799997 0.176010 0.015219];
V41=[0.819997 0.167820 0.014512];
V42=[0.839996 0.160014 0.013837];
V43=[0.859996 0.152570 0.013194];
V44=[0.879996 0.145473 0.012581];
V45=[0.899996 0.138705 0.011996];
V46=[0.919995 0.132253 0.011439];
V47=[0.939995 0.126100 0.010907];
V48=[0.959995 0.120234 0.010400];
V49=[0.979994 0.114639 0.009917];
V50=[0.999994 0.109307 0.009456];
V51=[1.019994 0.104224 0.009016];
V52=[1.039994 0.099373 0.008597];
V53=[1.059994 0.094750 0.008197];
V54=[1.079993 0.090342 0.007816];
V55=[1.099993 0.086138 0.007453];
V56=[1.119993 0.082130 0.007106];
V57=[1.139992 0.078310 0.006776];
V58=[1.159992 0.074669 0.006461];
V59=[1.179992 0.071192 0.006160];
V60=[1.199992 0.067882 0.005874];
V61=[1.219991 0.064724 0.005601];
V62=[1.239991 0.061713 0.005340];
V63=[1.259991 0.058841 0.005092];
V64=[1.279991 0.056104 0.004855];
V65=[1.299990 0.053493 0.004629];
V66=[1.319990 0.051005 0.004414];
V67=[1.339990 0.048632 0.004209];
V68=[1.359990 0.046368 0.004013];

V69=[1.379989 0.044213 0.003826];
V70=[1.399989 0.042157 0.003648];
V71=[1.419989 0.040195 0.003479];
V72=[1.439989 0.038324 0.003317];
V73=[1.459988 0.036542 0.003162];
V74=[1.479988 0.034842 0.003015];
V75=[1.499988 0.033221 0.002875];
V76=[1.519988 0.031676 0.002741];
V77=[1.539987 0.030202 0.002614];
V78=[1.559987 0.028796 0.002492];
V79=[1.579987 0.027456 0.002376];
V80=[1.599987 0.026179 0.002266];
V81=[1.619986 0.024963 0.002160];
V82=[1.639986 0.023798 0.002060];
V83=[1.659986 0.022692 0.001964];
V84=[1.679986 0.021637 0.001873];
V85=[1.699985 0.020629 0.001786];
V86=[1.719985 0.019672 0.001703];
V87=[1.739985 0.018754 0.001623];
V88=[1.759984 0.017883 0.001548];
V89=[1.779984 0.017051 0.001476];
V90=[1.799984 0.016257 0.001407];
V91=[1.819984 0.015502 0.001342];
V92=[1.839983 0.014778 0.001279];
V93=[1.859983 0.014093 0.001220];
V94=[1.879983 0.013435 0.001163];
V95=[1.899983 0.012812 0.001109];
V96=[1.919982 0.012215 0.001057];
V97=[1.939982 0.011647 0.001008];
V98=[1.959982 0.011105 0.000961];
V99=[1.979982 0.010588 0.000917];
V100=[1.999981 0.010095 0.000874];
V101=[2.019982 0.009626 0.000833];
V102=[2.039983 0.009179 0.000794];
V103=[2.059984 0.008752 0.000757];
V104=[2.079985 0.008344 0.000722];
V105=[2.099986 0.007957 0.000689];
V106=[2.119987 0.007584 0.000657];
V107=[2.139988 0.007234 0.000626];
V108=[2.159989 0.006897 0.000597];
V109=[2.179990 0.006575 0.000569];
V110=[2.199991 0.006269 0.000543];
V111=[2.219992 0.005977 0.000517];

V112=[2.239993 0.005699 0.000493];
V113=[2.259994 0.005433 0.000470];
V114=[2.279994 0.005181 0.000449];
V115=[2.299995 0.004940 0.000428];
V116=[2.319996 0.004712 0.000408];
V117=[2.339997 0.004493 0.000389];
V118=[2.359998 0.004282 0.000371];
V119=[2.379999 0.004083 0.000353];
V120=[2.400000 0.003894 0.000337];
V121=[2.420001 0.003713 0.000321];
V122=[2.440002 0.003540 0.000306];
V123=[2.460003 0.003376 0.000292];
V124=[2.480004 0.003219 0.000279];
V125=[2.500005 0.003070 0.000266];
V126=[2.520006 0.002925 0.000253];
V127=[2.540007 0.002790 0.000241];
V128=[2.560008 0.002659 0.000230];
V129=[2.580009 0.002537 0.000220];
V130=[2.600009 0.002418 0.000209];
V131=[2.620010 0.002304 0.000200];
V132=[2.640011 0.002199 0.000190];
V133=[2.660012 0.002094 0.000181];
V134=[2.680013 0.001998 0.000173];
V135=[2.700014 0.001905 0.000165];
V136=[2.720015 0.001814 0.000157];
V137=[2.740016 0.001733 0.000150];
V138=[2.760017 0.001651 0.000143];
V139=[2.780018 0.001576 0.000136];
V140=[2.800019 0.001501 0.000130];
V141=[2.820020 0.001433 0.000124];
V142=[2.840021 0.001364 0.000118];
V143=[2.860022 0.001301 0.000113];
V144=[2.880023 0.001242 0.000107];
V145=[2.900023 0.001184 0.000102];
V146=[2.920024 0.001127 0.000098];
V147=[2.940025 0.001075 0.000093];
V148=[2.960026 0.001025 0.000089];
V149=[2.980027 0.000980 0.000085];
V150=[3.000028 0.000932 0.000081];

D1=[V0;V1;V2;V3;V4;V5;V6;V7;V8;V9;V10;V11;V12;V13;V14;V15;V16;V17;V18;V19];

D2=[V20;V21;V22;V23;V24;V25;V26;V27;V28;V29;V30;V31;V32;V33;V34;V35;V36;

```
V37];
D3=[V38;V39;V40;V41;V42;V43;V45;V46;V47;V48;V49;V50;V51;V52;V53;V54;V55;
V56];
D4=[V57;V58;V59;V60;V61;V62;V63;V64;V65;V67;V68;V69;V70;V71;V72;V73;V74;
V75];
D5=[V76;V77;V78;V79;V80;V81;V82;V83;V84;V85;V86;V87;V88;V89;V90;V91;V92;
V93];
D6=[V94;V95;V96;V97;V98;V99;V100;V101;V102;V103;V104;V105;V106;V107;V10
8;V109];
D7=[V110;V111;V112;V113;V114;V115;V116;V117;V118;V119;V120;V121;V122;V1
23;V124];
D8=[V125;V126;V127;V128;V129;V130;V131;V132;V134;V135;V136;V137;V138;V1
39];
D9=[V140;V141;V142;V143;V144;V145;V146;V147;V148;V149;V150];
K3=[D1;D2;D3;D4;D5;D6;D7;D8;D9];
L3=K3';
X3=L3(1,:);
Y3=L3(2,:);
Z3=L3(3,:);
subplot(2,2,3)
plot(X3,Y3)
grid on
axis([0 2 -5 30])
xlabel('time(sec)o=0.5w')
ylabel('input force(N)')
subplot(2,2,4)
plot(X3,Z3)
grid on
axis([0 3 -0.05 0.15])
ylabel('angular position(rad)')
xlabel('g0=5,g1=1,h=5')
```