1

of/de

1

MICROCOPY RESOLUTION TEST CHART
NATIONAL BUREAU OF STANDARDS
STANDARD REFERENCE MATERIAL 1010a
(ANSI and ISO TEST CHART No. 2)

National Library
of Canada

Acquisitions and
Bibliographic Services Branch

395 Wellington Street
Ottawa, Ontario
K1A 0N4

Bibliothèque nationale
du Canada

Direction des acquisitions et
des services bibliographiques

395, rue Wellington
Ottawa (Ontario)
K1A 0N4

Your file Votre référence

Our file Notre référence

NOTICE

The quality of this microform is heavily dependent upon the quality of the original thesis submitted for microfilming. Every effort has been made to ensure the highest quality of reproduction possible.

If pages are missing, contact the university which granted the degree.

Some pages may have indistinct print especially if the original pages were typed with a poor typewriter ribbon or if the university sent us an inferior photocopy.

Reproduction in full or in part of this microform is governed by the Canadian Copyright Act, R.S.C. 1970, c. C-30, and subsequent amendments.

AVIS

La qualité de cette microforme dépend grandement de la qualité de la thèse soumise au microfilmage. Nous avons tout fait pour assurer une qualité supérieure de reproduction.

S'il manque des pages, veuillez communiquer avec l'université qui a conféré le grade.

La qualité d'impression de certaines pages peut laisser à désirer, surtout si les pages originales ont été dactylographiées à l'aide d'un ruban usé ou si l'université nous a fait parvenir une photocopie de qualité inférieure.

La reproduction, même partielle, de cette microforme est soumise à la Loi canadienne sur le droit d'auteur, SRC 1970, c. C-30, et ses amendements subséquents.

Canada

RANDOM ALTERNATIVE ROUTING

by

Michael Fox

**A thesis submitted to
the Faculty of Graduate Studies and Research
in partial fulfillment of the requirements for the degree of**

Master of Science

**Department of Mathematics and Statistics
Carleton University
Ottawa, Canada
January, 1994**

**© Copyright, 1994
Michael Fox**

National Library
of Canada

Acquisitions and
Bibliographic Services Branch

395 Wellington Street
Ottawa, Ontario
K1A 0N4

Bibliothèque nationale
du Canada

Direction des acquisitions et
des services bibliographiques

395, rue Wellington
Ottawa (Ontario)
K1A 0N4

Your file Votre référence

Our file Notre référence

The author has granted an irrevocable non-exclusive licence allowing the National Library of Canada to reproduce, loan, distribute or sell copies of his/her thesis by any means and in any form or format, making this thesis available to interested persons.

L'auteur a accordé une licence irrévocable et non exclusive permettant à la Bibliothèque nationale du Canada de reproduire, prêter, distribuer ou vendre des copies de sa thèse de quelque manière et sous quelque forme que ce soit pour mettre des exemplaires de cette thèse à la disposition des personnes intéressées.

The author retains ownership of the copyright in his/her thesis. Neither the thesis nor substantial extracts from it may be printed or otherwise reproduced without his/her permission.

L'auteur conserve la propriété du droit d'auteur qui protège sa thèse. Ni la thèse ni des extraits substantiels de celle-ci ne doivent être imprimés ou autrement reproduits sans son autorisation.

ISBN 0-315-89722-8

Canada

Masters Theses
PUBLISH ABSTRACT ONLY
AGREEMENT

Abstract No. _____

INDICATE YOUR APPROVAL OF THIS AGREEMENT BY SIGNING ITEM #11

PERSONAL DATA (Please type or print)

1. Full name Fox
(last)
Michael (first) Robert (middle)
2. Year of birth 1968
3. Country of citizenship Canada
4. Present mailing address
14 Viewmont Dr.
Napawan, Ont.
K2G 3C2
- Future mailing address _____
- Effective date _____ Telephone number (613) 324-2679

DO NOT WRITE IN THIS SPACE

Vol/Issue _____
School Code _____
Advisor _____

Abstract Length _____
TP Date _____

MASTERS DEGREE DATA

5. Full name of university conferring degree
Carleton University
6. Abbreviation for degree awarded M.Sc. 7. Date degree awarded Feb. '94

TITLE/SUBJECT DATA

8. Attach a copy of your thesis title page and abstract to this Agreement Form.
9. Subject Category for your thesis. Enter 4-digit code from list on opposite side.

014105

ABSTRACT REPRINTS

10. Please send _____ reprints of my abstract. (Minimum order 100 copies)
First set of 100	\$ 30.00
Additional sets of 100 @ \$5.00 each set	\$ _____
Subtotal	\$ _____
Sales tax for state of ship-to	\$ _____
10% shipping and handling	\$ _____
Enclosed please find my check for	TOTAL \$ _____

This is an agreement between the author and University Microfilms Inc., Ann Arbor, Michigan, providing for the publication of an abstract (of not more than 150 words) of the thesis in *Masters Abstracts International*, which is distributed on a subscription basis. If more than 150 words are contained in the abstract, it will be returned to the author for abridging. Mathematical formulas, diagrams, and other illustrative materials are not recommended for the printed abstract.

11. I agree to the provisions of this agreement.

Signature

Michael Fox

Date Jan. 17, '94

ABSTRACT

A fully connected network with random alternative routing is studied. A simplified model is presented and analyzed. The model is compared to our original network and illustrated by an example. A local mean field limit is established taking the spatial structure removed from the simplified model into account. The idea of propagation of chaos is introduced, and illustrated by a simple example, validating an assumption used in our simplified model. Finally, other routing strategies are briefly discussed and compared to that of random alternative routing.

**The undersigned recommend to the Faculty of Graduate Studies
and Research acceptance of the thesis**

**"RANDOM ALTERNATIVE ROUTING"
submitted by Michael Fox
in partial fulfilment of the requirements for
the degree of Master of Science**

Thesis Supervisor

Chair, Department of Mathematics & Statistics

**Carleton University
January, 1994**

ACKNOWLEDGEMENTS

I would like to take the opportunity to show my gratitude to my supervisor Dr. Don Dawson. I thank him for his direction, as well as for having proposed this topic to me. I would also like to thank Diane Berezowski who made my first foray into $\text{\TeX}$ relatively painless. Without her assistance, this thesis would not have finished on time. Finally, I wish to thank my friends for their constant encouragement, especially Dave and Debbie, who should have seen this completed.

TABLE OF CONTENTS

Acceptance Sheet.....	ii
Abstract.....	iii
Acknowledgements.....	iv
Table of Contents.....	v
List of Figures.....	vii
 CHAPTER I: Introduction.....	 1
 CHAPTER II: Communication Network Model	
2.1 Introduction.....	2
2.2 The Network Model.....	2
2.3 A Simplified Model.....	3
2.4 Mathematical Preliminaries.....	5
2.5 A Dynamical Law of Large Numbers.....	7
2.6 The Mean Field Limit Equilibrium.....	9
2.7 Comparison of the Network and Simplified Model by Simulation.....	12
2.8 Loss Probability.....	15
2.9 Diffusion Approach.....	16
2.10 Conclusion.....	17
 CHAPTER III: Mean Field Limit	
3.1 Introduction.....	18
3.2 A Local Mean Field Limit.....	18
3.3 Conclusion.....	19
 CHAPTER IV: Propagation of Chaos	
4.1 Introduction.....	20
4.2 Propagation of Chaos.....	20
4.3 Conclusion.....	24
 CHAPTER V: Additional Routing Strategies	
5.1 Introduction.....	25
5.2 Trunk Reservation and Multiple Alternatives.....	25

5.3 Further Routing Schemes.....	28
5.4 Learning Automata	28
5.5 Conclusion	29
CHAPTER VI: Concluding Remarks	30
APPENDIX A: Mathematica Programs	
A.1 Original Network Simulation	31
A.2 Projection of Ξ	33
A.3 Path of Process describing Simplified Model.....	34
A.4 Equilibrium Point for Simplified Model	35
REFERENCES	36

LIST OF FIGURES

Figure	Description	Page
1	Equilibrium blocking probabilities for simplified model.....	12
2	Trajectories for limit process $x(\cdot)$	13
3	Trajectory for original network with initial point A	14
4	Trajectory for original network with initial point A'	14

1. Introduction

Advances in technology have allowed telecommunication networks to move beyond simple directing of calls from node to node. Rerouting of calls to use excess capacity not being used in the network has become possible, and computers allow different routing strategies to be tested before they are implemented.

We will look at one of the simplest routing schemes. If a call is being attempted, the call can be placed either directly or through one of a set of possible alternate routes. If the call can be placed directly it is, but if this is impossible the system tries to route the call through one of the possible alternate routes chosen at random. If the call cannot be sent along this route, the call is lost. This routing strategy is called Random Alternative Routing.

Initially, it appears that this might be a beneficial scheme for directing calls as there are several routes which could accomodate the call. This is, however, deceptive. If the alternate routing occupies more lines, the call ties up lines for a longer duration than a direct call. Alternatively, it may increase the inefficiency of the system in some other manner and the effectiveness of the network might actually diminish.

In this thesis, we explore the following topics. Chapter 2 follows the work of Gibbens, Hunt, and Kelly [3], in which our communication network model is described, some analysis performed, and is illustrated by an example. As well, the idea of approximating the network by a diffusion is introduced, allowing a one-dimensional approach to analysing the network.

In Chapter 3, the model is modified to allow the spatial structure of the network to be taken into account and the mean field limit of Anantharam [1] is discussed. Chapter 4 introduces the idea of propagation of chaos as described by Graham and Méléard [4], and a simple example is given. Finally, in Chapter 5 the concepts of Gibbens, Hunt, and Kelly [3] are re-visited, and other possible routing schemes are mentioned and compared to that of random alternative routing.

2. Communication Network Model

2.1 Introduction

In this chapter we introduce the network we wish to work with. All work is done on simplifications of this model, initially with the graphical properties removed, and then a further simplification to that of only individual circuits allows a diffusion approximation. At all stages the efficiency of Random Alternate Routing is considered.

2.2 The Network Model

We consider a network with N nodes. The network is symmetric and fully connected, and so each pair of nodes is connected by a link containing C circuits, giving a total of $K = N(N - 1)/2$ links. Calls made between two nodes, say α, β ($\alpha \neq \beta$), arrive as a Poisson process of rate ν , and all calls arrive independently. If there is an available circuit between the α and β , then the call can be routed directly along this link, and one unused circuit becomes occupied. If all circuits on the link between α and β are occupied, the call will have to try an alternate route. A third node, γ , is randomly chosen from the remaining $N - 2$ nodes and an attempt to divert the call through this node is made. If there is a free circuit available on both the link between α and γ , and on the link between β and γ , the call is routed along this path. One unused circuit from each of the links is then occupied. If either of the links is full, the call cannot enter the network, and the call is lost. Each circuit, once it is occupied by either a direct call or a rerouted call, is held for the holding period of the call. This holding period is independent of earlier arrival times and holding periods, and is exponentially distributed with mean one.

This network can be viewed as a finite state space Markov process and we can derive equations for the equilibrium distribution. However since this space is quite complicated, it is necessary to take the graph structure of the network into consideration. It is difficult to analyse the process, even in equilibrium.

2.3 A Simplified Model

To simplify the analysis, we define a simplified model for this network. Consider K links, each having C circuits. Calls requesting link k as their first choice arrive as a Poisson process of rate ν . If all the circuits of link k are occupied, and the call is blocked, the call is diverted through two other links chosen at random from the remaining $K - 1$ links. Each pair of links has equal probability of being chosen. If there are unoccupied circuits available in the two chosen links, the call is sent through these links. If either of the links doesn't have the capacity to handle the call, the call is lost. When a circuit is occupied, it is held for a period of time which is exponentially distributed with unit mean. All circuit holding times are independent of each other and of earlier arrival times. In particular, a call that requires two links holds the circuits of each link independently for a length of time which is exponential in distribution, and so these circuits will become free at different times. The model simplifies the original network in two ways: the circuit holding times are independent, and the graph structure relationship between links has been lost.

Although this simplified model is an approximation of the original network, we expect that its behaviour will be very similar to that of the original system for large K . The approximation is much simpler to analyse and can be described by the following Markov process. Let $n_j^K(t)$ be the number of links with j circuits in use at time t , $j = 0, 1, \dots, C$. Let

$$x_j^K(t) = \frac{n_j^K(t)}{K}, \quad \mathbf{x}^K(t) = (x_j^K(t))_j, \quad j = 0, \dots, C.$$

So $\sum_{j=0}^C x_j^K(t) = 1$ for all t . It is now obvious that $\mathbf{x}^K := (x_0^K, \dots, x_C^K)$ has state space Δ , where

$$\Delta = \left\{ \mathbf{x}^K \in \mathbb{R}_+^{C+1} : \sum_{i=0}^C x_i^K = 1 \right\}.$$

For $i \neq j, 0 \leq i, j \leq C$, let T_{ij} be a linear operator defined on $\mathbf{x}^K$ given by

$$T_{ij}\mathbf{x}^K = \mathbf{x}^K + \frac{1}{K}(\mathbf{e}_j - \mathbf{e}_i)$$

where $\mathbf{e}_i$ is the unit vector in the i th direction. Then $\mathbf{x}^K$ is a Markov process with transition rates

$$\begin{aligned} \mathbf{x} &\rightarrow T_{j,j+1}\mathbf{x}^K & \text{at rate} & \quad \nu x_j^K K, & j = 0, 1, \dots, C-1 \\ \mathbf{x} &\rightarrow T_{j,j-1}\mathbf{x}^K & \text{at rate} & \quad j x_j^K K, & j = 1, 2, \dots, C \\ \mathbf{x} &\rightarrow T_{i,i+1}T_{j,j+1}\mathbf{x}^K & \text{at rate} & \quad 2\left(\frac{K^2}{(K-1)(K-2)}\right)\nu K x_C^K x_i^K x_j^K, \\ & & & & i < j, i, j = 0, 1, \dots, C-1 \\ \mathbf{x} &\rightarrow T_{j,j+1}^2\mathbf{x}^K & \text{at rate} & \quad \left(\frac{K^2}{(K-1)(K-2)}\right)\nu K x_C^K x_j^K \left(\frac{K x_j^K - 1}{K}\right), \\ & & & & j = 0, 1, \dots, C-1. \end{aligned}$$

It is clear how the first two transition rates are determined, but the final two are not as obvious. For the transition, $\mathbf{x} \rightarrow T_{i,i+1}T_{j,j+1}\mathbf{x}^K$, the arrival rate is the rate at which calls are blocked on their first choice, a rate of $\nu K x_C^K$, and then rerouted through lines having i and j circuits occupied respectively. A line with i circuits occupied is chosen first from $K-1$ lines with probability $\frac{x_i^K}{1-x_C^K}$, and then a line with j circuits occupied is chosen from the remaining $K-2$ lines with probability $\frac{K}{K-2}x_j^K$. Alternately, a line with j circuits occupied can be chosen first, and then a line with i circuits chosen. Thus, the resulting probability of an overflowing call being rerouted through two lines having i and j circuits occupied

respectively is $2\frac{K^2}{(K-1)(K-2)}x_i^K x_j^K$, and the above transition rate follows. The remaining transition rate follows identically.

With this process we can prove results that we can expect to give insight into the behaviour of the original fully connected network.

2.4 Mathematical Preliminaries

Before this model can be analyzed, it is necessary to introduce some concepts that will be used.

Definition 1. The space of right continuous functions $x : [0, \infty) \rightarrow \Delta$ with left limits, where Δ is defined as the state space above, is denoted by $D_\Delta[0, \infty)$.

Definition 2. Let $\tilde{C}(S)$ be the space of real-valued bounded continuous functions on the metric space (S, d) with norm $\|f\| = \sup_{x \in S} |f(x)|$. A sequence $\{P_n\} \subset \mathcal{P}(S)$, the space of probability measures on S , is said to *converge weakly* to $P \in \mathcal{P}(S)$ if

$$\lim_{n \rightarrow \infty} \int f dP_n = \int f dP, \quad f \in \tilde{C}(S).$$

Definition 3. Given a measurable space $(\Omega, \mathcal{F})$, a *filtration* is a family $\{\mathcal{F}_t\}$ of sub- σ -algebras of $\mathcal{F}$ such that $\mathcal{F}_s \subset \mathcal{F}_t$ if $s < t$.

Definition 4. A real stochastic process, $M(t)$, is called a *martingale* with respect to $\{\mathcal{F}_t\}$ if

- (i) $M(t)$ is integrable for each $t \in [0, \infty)$.
- (ii) $M(t)$ is adapted, that is $M(t)$ is $\mathcal{F}_t$ -measurable for each t .
- (iii) for each $s, t \in [0, \infty)$ with $s < t$, $E(M(t)|\mathcal{F}_s) = M(s)$, a.s., where $E(\cdot|\mathcal{F}_s)$

denotes the conditional expectation.

Definition 5. Let M be a right continuous $\{\mathcal{F}_t\}$ martingale. Then there exists a right continuous increasing process, denoted by $[M]$, such that for each $t \geq 0$ and each sequence of partitions $\{u_k^{(n)}\}$ of $[0, t]$ with $\max_k (u_{k+1}^{(n)} - u_k^{(n)}) \rightarrow 0$,

$$\sum_k (M(u_{k+1}^{(n)}) - M(u_k^{(n)}))^2 \xrightarrow{P} [M](t)$$

as $n \rightarrow \infty$. Given two right continuous $\{\mathcal{F}_t\}$ martingales, M_1, M_2 ,

$$[M_1, M_2] = \frac{1}{2}([M_1 + M_2] - [M_1] - [M_2]).$$

Now we state a theorem required in the following section. It is stated without proof, and is Theorem 1.4 from Ethier and Kurtz [2] (p.339).

Theorem 1. For $n = 1, 2, \dots$, let $\{\mathcal{F}_t^n\}$ be a filtration and let $M_n = (M_1^n, \dots, M_d^n)$ be an $\{\mathcal{F}_t^n\}$ martingale with sample paths in $D_{\mathbb{R}^d}[0, \infty)$ and $M_n(0) = 0$. Let $A_n = ((A_n^{ij}))$ be symmetric $d \times d$ matrix-valued processes such that A_n^{ij} has sample paths in $D_{\mathbb{R}}[0, \infty)$ and $A_n(t) - A_n(s)$ is nonnegative definite for $t > s \geq 0$. Assume the following condition holds:

(i) For each $T > 0$.

$$\lim_{n \rightarrow \infty} E \left[\sup_{t \leq T} |M_j^n(t) - M_j^n(t-)| \right] = 0 \quad \text{for } j = 1, \dots, d$$

and

(ii) Suppose that for each $t \geq 0$ and $i, j = 1, 2, \dots, d$,

$$A_n^{ij}(t) \rightarrow 0$$

as $n \rightarrow \infty$ in probability, where $A_n^{ij} = [M_n^i, M_n^j]$. Then $M_n \Rightarrow 0$.

2.5 A Dynamical Law of Large Numbers

We now prove a functional law of large numbers for the $\mathbf{x}^K$ process defined above. This process is defined on the filtered probability space $(D_\Delta[0, \infty), \mathcal{F}, \{\mathcal{F}_t\}_{t \geq 0})$ where x_s denotes the s -component of $\mathbf{x} \in D_\Delta[0, \infty)$ and $\mathcal{F}_t$ is the smallest σ -algebra of subsets of $D_\Delta[0, \infty)$ containing the sets $\{x_s \in (a, b)\}$ for $0 \leq s \leq t$ and $a \leq b$. $\mathcal{F}$ is the smallest σ -algebra containing all the $\mathcal{F}_t$. Let $\Rightarrow$ denote convergence in distribution as $K \rightarrow \infty$ of random elements in the state space Δ , or the space of all sample paths $D_\Delta[0, \infty)$, that is, weak convergence of their probability laws.

Theorem 2. *If $\mathbf{x}^K(0) \Rightarrow \mathbf{x}(0)$ then $\mathbf{x}^K(\cdot) \Rightarrow \mathbf{x}(\cdot)$, where $\mathbf{x}(\cdot)$ is the unique deterministic solution to the equations*

$$x_0(t) = x_0(0) + \int_0^t \{x_1(u) - (\nu + \lambda(u))x_0(u)\} du \quad (1)$$

$$x_j(t) = x_j(0) + \int_0^t \{(\nu + \lambda(u))x_{j-1}(u) - (\nu + \lambda(u) + j)x_j(u) + (j+1)x_{j+1}(u)\} du \quad j \neq 0, C \quad (2)$$

$$x_C(t) = x_C(0) + \int_0^t \{(\nu + \lambda(u))x_{C-1}(u) - Cx_C(u)\} du \quad (3)$$

and

$$\lambda(t) = 2\nu x_C(t)(1 - x_C(t)). \quad (4)$$

Proof. Let

$$\mathbf{v}(\mathbf{x}^K(t)) = \lim_{h \downarrow 0} E \left[\frac{\mathbf{x}^K(t+h) - \mathbf{x}^K(t)}{h} \middle| \mathbf{x}^K(t) \right]$$

$$D^K(t) = \int_0^t \mathbf{v}(\mathbf{x}^K(u)) du$$

$$\mathbf{M}^K(t) = \mathbf{x}^K(t) - \mathbf{x}^K(0) - D^K(t).$$

Note that $\mathbf{v} : \Delta \rightarrow \mathbb{R}^{C+1}$ is given by

$$\mathbf{v}(\mathbf{x})_j = (\nu + \lambda)x_{j-1} - (\nu + \lambda + j)x_j + (j+1)x_{j+1}$$

where $\lambda = 2\nu x_C(1 - x_C)$ and is Lipschitz continuous and uniformly bounded.

Then M^K is an $\{\mathcal{F}_t\}$ -martingale. In order to prove weak convergence, it is necessary to check the conditions of the theorem stated above, that is

- (i) $\lim_{K \rightarrow \infty} E \left[\sup_{t \leq T} |M_j^K(t) - M_j^K(t-)| \right] = 0, \quad \text{for each } T > 0, \quad j = 0, \dots, C.$
- (ii) $[M_i^K, M_j^K](t) \rightarrow 0.$

But,

$$\begin{aligned} M^K(t) - M^K(t-) &= x^K(t) - x^K(0) - D^K(t) - (x^K(t-) - x^K(0) - D^K(t-)) \\ &= x^K(t) - x^K(t-) + \int_{t-}^t v(x^K(u))du \end{aligned}$$

The final term can be ignored since it is continuous, so

$$|M^K(t) - M^K(t-)| \leq \frac{2}{K}$$

and we see (i) holds. We know

$$[M_i^K, M_j^K](t) = \frac{1}{K^2} [\text{The number of jumps for } T_{i,i+1} T_{j,j+1}].$$

So $[M_i^K, M_j^K](t) \rightarrow 0$ in probability, since these jumps occur at rate less than or equal to some multiple of K . Hence, we have $M^K \Rightarrow 0$ by Theorem 1.

Since the $v(\cdot)$ are uniformly bounded, the laws of D^K are relatively compact (Theorem 8.6 Ethier and Kurtz [2] p. 137). Therefore the laws of $\{x^K\}$ are also relatively compact (Theorem 3.3 Ethier and Kurtz [2] p. 110). Now along any convergent subsequence of $\{x^K\}$, $M^K \Rightarrow 0$ and the corresponding limit of x satisfies the deterministic nonlinear equation

$$x(t) - x(0) - \int_0^t v(x(u))du = 0$$

Since $v(\cdot)$ is Lipschitz continuous, this equation has a unique solution by Picard's Theorem. This implies that all convergent subsequences converge to the same limit and therefore

$$x^K(\cdot) \Rightarrow x(\cdot).$$

2.6 The Mean Field Limit Equilibrium

In this section we will study the equilibrium of the limit dynamics $x(\cdot)$.

Definition 6. An *equilibrium* or (*fixed point*) of the dynamical system $x(\cdot)$ is a point, x such that $x(t) = x$ for all t if $x(0) = x$. Note that any x such that $v(x) = 0$ is a fixed point.

We now wish to introduce a theorem which will give us a fixed point for the limit process associated with our simplified model. Some fixed point should attract the process, and eventually the process will converge to the value of the fixed point.

Theorem 3. *The limit process $x(\cdot)$ has a fixed $x = (x_j)_{j=0,\dots,C}$ with point of the form*

$$x_j = E(\xi, j) = \frac{\xi^j}{j!} \left(\sum_{i=0}^C \frac{\xi^i}{i!} \right)^{-1} \quad j = 0, 1, \dots, C$$

where ξ is any solution of the equation

$$\xi = \nu + 2\nu E(\xi, C)(1 - E(\xi, C)).$$

Proof. From equations (1)-(4), we see that

$$\begin{aligned} \sum_{i=0}^j x_i(t) &= \sum_{i=0}^j x_i(0) + \int_0^t \{x_1(u) - (\nu + \lambda(u))x_0(u)\} du \\ &\quad + \sum_{i=0}^j \int_0^t \{(\nu + \lambda(u))x_{j-1}(u) - (\nu + \lambda(u) + j)x_j(u) \\ &\quad + (j+1)x_{j+1}(u)\} du \\ &= \sum_{i=0}^j x_i(0) + \int_0^t \{(j+1)x_{j+1}(u) - (\nu + \lambda(u))x_j(u)\} du \\ &\quad j = 0, 1, \dots, C-1. \end{aligned}$$

Therefore, if $\mathbf{x} = (x_0, x_1, \dots, x_C) \in \Delta$ is to be a fixed point of the above system of equations, it is necessary that

$$(j+1)x_{j+1} = (\nu + \lambda)x_j \quad j = 0, 1, \dots, C-1$$

where

$$\lambda = 2\nu x_C(1 - x_C).$$

From this we can recursively find the x_j 's in terms of x_0 . We see

$$x_j = \frac{(\nu + \lambda)^j}{j!} x_0,$$

but, $\sum_{i=0}^C x_i = 1$ and so

$$\sum_{j=0}^C \frac{(\nu + \lambda)^j}{j!} x_0 = 1$$

or,

$$x_0 = \left(\sum_{j=0}^C \frac{(\nu + \lambda)^j}{j!} \right)^{-1}$$

Thus, a fixed point $\mathbf{x}$ is of the form

$$x_j = \frac{\xi^j}{j!} \left(\sum_{i=0}^C \frac{\xi^i}{i!} \right)^{-1} \quad j = 0, 1, \dots, C$$

where

$$\begin{aligned} \xi &= \nu + \lambda \\ &= \nu + 2\nu x_C(1 - x_C) \\ &= \nu + 2\nu E(\xi, C)(1 - E(\xi, C)). \end{aligned}$$

Here

$$E(\xi, C) = \frac{\xi^C}{C!} \left(\sum_{i=0}^C \frac{\xi^i}{i!} \right)^{-1} \quad (5)$$

is Erlang's formula for the loss probability of a totally connected network without any alternate routing and a call arrival rate of ξ .

Under the transformation $B = E(\xi, C)$, we see that the above equation is equivalent to

$$B = E(\nu + 2\nu B(1 - B), C) \quad (6)$$

The parameter B coincides with the link blocking probability, x_C . This equation is usually derived from an approximation that links block independently as follows. If links block independently, the probability that a call overflows is B , and the probability that another link of a two-link path will accept the call is $(1 - B)$. Thus the arrival rate of overflowing calls is $2\nu B(1 - B)$ and the overall arrival rate is $\xi = \nu + 2\nu B(1 - B)$. Therefore,

$$B = E(\xi, C) = E(\nu + 2\nu B(1 - B), C)$$

as in equation (6).

Since C is fixed, we can look for a solution to (6). However since this is a nonlinear equation, there might be more than one solution. The solution is plotted in Figure 1 as a function of the parameter ν/C for the cases $C = 120, 1000$. In the case of $C = 120$, the the solution of (6) is unique, each call arrival ratio, ν/C , leading to a certain link blocking probability, B . In the $C = 1000$ case however, this uniqueness breaks down. Over a certain range of ν/C , B has multiple solutions. Note that one of these solutions corresponds to a high blocking probability due to the fact that many circuits are employed by the alternate routing. One possible method of determining the stability of these points is suggested in Section 8.

It should be noted that for the network with $C = 120$ circuits, no case could be found in which Random Alternative Routing improved on the blocking probability of the of direct routing.

Fig. 1. Equilibrium blocking probabilities for simplified model

2.7 Comparison of the Network and Simplified Model by Simulation

In order to illustrate the result we consider an example. All the above calculations are carried out for our simplified model, and it is of interest to compare the model's behaviour to that of the fully connected network.

Consider a network with $N = 11$ nodes, with a call arrival rate $\nu = 115$, and a circuit capacity of $C = 120$ along each link. For this network, the process describing the simplified model predicts a fixed point at $x_c = 0.265$ and $\bar{x} = 117.4$.

Figures 2, 3 and 4 give plots of $\bar{x} = \sum_{i=0}^C ix_i$ versus x_c for theoretical and simulated results. These seem to be appropriate choices as $\bar{x}$ measures the total usage of the network, and x_c , the link blocking probability, controls the rates of the process.

Figure 2 shows the projected paths of the integral equations for the simplified process for initial points A and A' , where $\bar{x}$. Note that the high blocking probability drops very quickly as busy lines make circuits available, and then the process

Fig. 2 Trajectories for limit process $x(\cdot)$

starts to move toward the predicted fixed point. The blocking probability stays roughly constant as average circuit usage increases, which occurs as calls arrive more frequently than they leave. Finally with a high average circuit usage, the blocking probability starts to increase again as lines get filled.

Simulating our original model, we can now compare this to our simplified model. Figure 3 shows the simulation of a model with initial point A . The lighter line traces the path of a fully connected network as described in our original model. Again starting with a high blocking probability and a relatively low average circuit usage, the blocking probability drops as circuits clear and the average circuit usage increases as calls arrive and alternate routes start to fill the lines. We see that this follows a rough approximation to the theoretical result, the dark line, and eventually the sample points group around the theoretical fixed point predicted by our simplified model. Figure 4 shows very similar results for a network with initial point A' .

Fig. 3 Trajectory for original network with initial point A

Fig. 4 Trajectory for original network with initial point A'

Let

$$\Xi = \left\{ \mathbf{x} : x_i = \frac{\xi^i}{i!} \left(\sum_{j=0}^C \frac{\xi^j}{j!} \right)^{-1} ; \xi \in (0, \infty) \right\}, \quad (7)$$

a one-dimensional submanifold of the space Δ . It is natural to consider the space Ξ as it will contain the fixed point of the process as defined above. If $\lambda(t)$ is fixed at a value λ , then the path of the integral equations move quickly towards Ξ , and then more slowly toward the fixed point, as seen in Figure 2. The value of λ for this example is 44.837. It is also interesting to note that in the simulations shown in Figures 3 and 4, the sample points of our networks move towards Ξ , and then remain in the neighbourhood of Ξ .

2.8 Loss Probability

It seems natural to now consider the overall probability of a call not getting through. For a call not to make it through it must first be blocked at it's requested link, and then one of the alternate links must be blocked as well. Thus, the overall network loss probability is given by

$$L = x_C[1 - (1 - x_C)^2]. \quad (8)$$

For the examples simulated this value is 0.122. If alternative routing is not allowed, and a call is lost if blocked on its requested link, then the network loss probability is determined by Erlang's formula. In this simulation, the call arrival rate would be $\xi = 115$, and we see the network loss probability is $L = 0.047$. Note that allowing alternative routing through two links actually increases the loss probability of the network for large enough values of ν ! This leads us to question whether random alternative routing is actually beneficial or whether another routing strategy might not be preferable. This idea is discussed in Chapter 5.

2.9 Diffusion Approach

Consider a fully connected network with random alternate routing. Let $n(t) \in \{0, 1, \dots, CK\}$. We use $n(t)$ to represent the number of circuits in use throughout the network at time t . Let $n(\cdot)$ have transition rates

$$\begin{aligned} n \rightarrow n+1 & \quad \text{at rate} \quad \nu K(1 - B_n) \\ n \rightarrow n+2 & \quad \text{at rate} \quad \nu K B_n \{(1 - B_n)^2\} \\ n \rightarrow n-1 & \quad \text{at rate} \quad n \end{aligned}$$

where (B_n, ρ_n) solves

$$B_n = E(\rho_n, C), \quad n = \rho_n(1 - B_n),$$

where ρ_n is the call arrival rate of all calls at a link.

The transition rates of $n(\cdot)$ then correspond to that of the total number of circuits, $\sum_{j=0}^C j K x_j(t)$, in use from our simplified model provided KB_n links are full in that model. In other words, the transition rates for $n(\cdot)$ approximate our simplified model when the process is near the one-dimensional sub-manifold Ξ . Moreover when CK is large it is natural to approximate $n(\cdot)/CK$ by a diffusion $Z(\cdot)$ on the interval $[0, 1]$. This diffusion will give information on the behaviour of the system in equilibrium when K is large, but finite.

The appropriate diffusion is determined by the drift $\mu(z)$ and infinitesimal variance $\sigma^2(z)$ given by

$$\begin{aligned} \mu(z) &= \lim_{h \downarrow 0} E \left[\frac{n(h) - n(0)}{hCK} \middle| \frac{n(0)}{CK} = z \right] \\ &= \frac{\nu}{C} [(1 - B(z)) + 2B(z)\{(1 - B(z))^2\}] - z \\ \sigma^2(z) &= \lim_{h \downarrow 0} V \left[\frac{n(h) - n(0)}{hCK} \middle| \frac{n(0)}{CK} = z \right] \\ &= \frac{\nu}{C^2 K} [(1 - B(z)) + 4B(z)\{(1 - B(z))^2\}] + \frac{z}{CK} \end{aligned}$$

where V denotes variance and

$$B(z) = B_{[z,CK]}$$

and with reflecting barriers at 0 and 1.

We could then consider the equilibrium density $\psi(z)$ for the diffusion $Z(\cdot)$. This is given by

$$\psi(z) = Z^{-1} \frac{\exp(\int_0^z 2\mu(y)/\sigma^2(y)dy)}{\sigma^2(z)}$$

with normalizing constant Z^{-1} .

Let $T(x; y)$ be the first time that the diffusion hits y given that it starts at x . Let $f(x; y) = E[T(x; y)]$. Then (Karlin and Taylor [6] p.193) $f(x; y)$ satisfies

$$\frac{1}{2}\sigma^2(x)\frac{\partial^2 f}{\partial x^2} + \mu(x)\frac{\partial f}{\partial x} = -1$$

with boundary conditions

$$\begin{aligned} f(y; y) &= 0 \\ \frac{\partial f(0; y)}{\partial x} &= 0 & x > y \\ \frac{\partial f(1; y)}{\partial x} &= 0 & y > x. \end{aligned}$$

If $x_1 < x_2 < x_3$ are the three fixed points, this diffusion approximation gives some insight into their relative stability. The expected hitting times $f(x_1; x_2)$ and $f(x_3; x_2)$ describe the time it takes x_1 (respectively x_3) to “tunnel” to x_2 and consequently gives information as to their relative stability.

2.10 Conclusion

Under the assumptions of our simplified model, we have managed to discover a few features of Random Alternative Routing. We were able to calculate a deterministic solution for the path of network of the form of our simplified model, and an equilibrium point discovered. The main result were the discovery that Random Alternative Routing is actually inferior to that of direct routing for larger call arrival rates and the appearance of multiple equilibrium points as the number of circuits increased. A second approach to examining these multiple fixed points was introduced in the form of a diffusion approximation.

3. Mean Field Limit

3.1 Introduction

In our simplified model, the graph structure of our original network is removed for simplicity of analysis. Now we would like to consider a related model where the spatial structure is taken into consideration. We will use a lattice model in this case.

3.2 A Local Mean Field Limit

If we consider the sites of the lattice as links each composed of C circuits, we can give each site a value corresponding to the number of occupied circuits in that link. As before, engaged circuits are held for an exponential time with unit mean, and calls arrive at rate ν . When a call arrives, it occupies a free circuit if one is available. If none is available, it randomly chooses two links in its neighbourhood (as defined below), and routes through these links if there are available circuits on both links. Otherwise the call is lost.

Now let $\mathbf{Z}^d/M$ denote the lattice in $\mathbf{R}^d$ consisting of points $\mathbf{z} = (z_1, \dots, z_d)$, where the z_i have form $z_i = k_i/M$ for some $k_i \in \mathbf{Z}$. The points of $\mathbf{Z}^d/M$ are then called the sites of the lattice. Let W denote $\{0, 1, \dots, C\}$. We consider a Markov process $(\eta_t^M, t \geq 0)$ with state space $W^{\mathbf{Z}^d/M}$ which models a network with C circuits in $\mathbf{R}^d$ with local alternative random routing, that is, random routing in the neighbourhood $[-1, 1]^d$. Denote a generic element of $W^{\mathbf{Z}^d/M}$ by η and call $\eta(x)$ the value at site x , as mentioned above. Let M^* denote $\binom{(2M+1)^d - 1}{2}$, the number of $[-1, 1]^d$ neighbours of x . The Markov process of the model portrayed above is described by the transitions

$$\begin{aligned} \eta(x) &\rightarrow \eta(x) - 1 && \text{at rate } \eta(x), \\ \eta(x) &\rightarrow \eta(x) + 1 && \text{at rate } \nu \text{ if } \eta(x) \neq C, \\ (\eta(x), \eta(y), \eta(z)) &\rightarrow (\eta(x), \eta(y) + 1, \eta(z) + 1) && \text{at rate } \nu/M^* \\ &&& \text{if } x, y, z \text{ are distinct sites with} \end{aligned}$$

$$\eta(x) = C, \eta(y) < C, \eta(z) < C \text{ and } y, z \in x + [-1, 1]^d.$$

This is a Markov process even though the number of sites is infinite.

For $x \in \mathbb{Z}^d/M$, let $u_M(t, x, k)$ denote $P(\eta_t^M(x) = k), 0 \leq k \leq C$. The definition of $u_M(t, x, k)$ can be extended to $\mathbb{R}^d$ naturally. Now if we let the initial $u(0, x, k), 0 \leq k \leq C$, be continuous functions with bounded derivative and $\sum_{k=0}^C u(0, x, k) = 1$, it can be shown that if the initial configurations, $u_M(0, x, k)$, converges pointwise to $u(0, x, k)$ as $M \rightarrow \infty$, $u_M(t, x, k), 0 \leq k \leq C$, converges pointwise to $u(t, x, k)$ which satisfy the following integrodifferential equations.

$$\begin{aligned} \frac{\partial u(t, x, 0)}{\partial t} &= u(t, x, 1) \\ &\quad - \nu \left[1 + 2^{1-2d} \int \int_{q, r \in [-1, 1]^d} u(t, x + q, C) \right. \\ &\quad \left. \times (1 - u(t, x + q + r, C)) dq dr \right] u(t, x, 0), \\ \frac{\partial u(t, x, k)}{\partial t} &= (k + 1)u(t, x, k + 1) \\ &\quad + \nu \left[1 + 2^{1-2d} \int \int_{q, r \in [-1, 1]^d} u(t, x + q, C) \right. \\ &\quad \left. \times (1 - u(t, x + q + r, C)) dq dr \right] u(t, x, k - 1) \\ &\quad - \left(k + \nu \left[1 + 2^{1-2d} \int \int_{q, r \in [-1, 1]^d} u(t, x + q, C) \right. \right. \\ &\quad \left. \left. \times (1 - u(t, x + q + r, C)) dq dr \right] \right) u(t, x, k) \\ &\hspace{15em} \text{for } 0 < k < C, \\ \frac{\partial u(t, x, C)}{\partial t} &= -Cu(t, x, C) \\ &\quad + \nu \left[1 + 2^{1-2d} \int \int_{q, r \in [-1, 1]^d} u(t, x + q, C) \right. \\ &\quad \left. \times (1 - u(t, x + q + r, C)) dq dr \right] u(t, x, C - 1). \end{aligned}$$

3.3 Conclusion

We have seen that even if we allow the network to retain its spatial structure, we are able to determine something about the state of localized areas of the network as we allow it to get large. Although a solution exists, it is far from the considerably simpler solution if the structure is removed.

4. Propagation of Chaos

4.1 Introduction

In Chapter 2, our simplified model removed the graphical structure of our original model and so all links were exchangeable. Theorem 3 implies that they are asymptotically independent in the limit as the number of nodes goes to infinity. It is therefore natural to ask if we can show that a subset of the links between these nodes are independent in this limit for our original network model.

4.2 Propagation of Chaos

Returning to our original model of Section 2.2, let us denote by X_{ab}^K the number of calls routed directly from node a to node b in a network with a total of K links. This does not allow for rerouted calls to be considered. So let us also denote by $X_{ab}^{c,K}$ the number of calls from node a to node b routed through node c .

Definition 7. The laws of $(X_{ab}^K(t))_{1 \leq a < b \leq N}$ are said to be $\bar{P}$ -chaotic if for all $k \in \mathbb{N}$, fixed distinct links $a_1 b_1, \dots, a_k b_k$, and for all bounded, continuous real-valued $f_i, i = 1, \dots, k$,

$$\lim_{K \rightarrow \infty} E \left(\prod_{i=1}^k f_i(X_{a_i b_i}^K(t)) \right) = \prod_{i=1}^k \int f_i(x_i) \bar{P}(dx_i)$$

The propagation of chaos result for the original system states that if the laws of $(X_{ab}^K(0))_{1 \leq a < b \leq N}$ are $\bar{P}_0$ -chaotic, then the laws of $(X_{ab}^K(t))_{1 \leq a < b \leq K}$ are $\bar{P}_t$ -chaotic for all $t \geq 0$ where $\bar{P}_t$ is determined by $\bar{P}_0$ and a specific nonlinear martingale problem.

In order to illustrate these ideas we now consider the simplified case of $C = \infty$ in which no alternative routing is required. Assume that initially K calls are in progress and these have been assigned at random to the K links. We now hope to

determine the distribution of the individual $X_{a_i b_i}^K(0)$, where $X_{a_i b_i}^K(0)$ is the number of circuits occupied initially between nodes a_i and b_i in a network with K links.

$$\begin{aligned} P_0\{X_{a_1 b_1}^K(0) = n_1, X_{a_2 b_2}^K(0) = n_2\} \\ = \frac{K!}{n_1! n_2! (K - n_1 - n_2)!} \left(\frac{1}{K}\right)^{n_1} \left(\frac{1}{K}\right)^{n_2} \left(1 - \frac{2}{K}\right)^{K - n_1 - n_2} \end{aligned}$$

but as we let $K \rightarrow \infty$,

$$\begin{aligned} P_0\{X_{a_1 b_1}^K(0) = n_1, X_{a_2 b_2}^K(0) = n_2\} \\ \rightarrow \frac{1}{n_1! n_2!} e^{-2} \\ = \frac{1}{n_1!} e^{-1} \frac{1}{n_2!} e^{-1} \end{aligned} \quad (9)$$

So we find the distribution of $X_{a_1 b_1}^K(0)$.

$$\begin{aligned} P_0\{X_{a_1 b_1}^K(0) = n_1\} &= \sum_{n_2=0}^{\infty} P\{X_{a_1 b_1}^K(0) = n_1, X_{a_2 b_2}^K(0) = n_2\} \\ &= \sum_{n_2=0}^{\infty} e^{-1} \frac{1}{n_1!} e^{-1} \frac{1}{n_2!} \\ &= e^{-1} \frac{1}{n_1!} \end{aligned} \quad (10)$$

Similarly,

$$P_0\{X_{a_2 b_2}^K(0) = n_2\} = e^{-1} \frac{1}{n_2!} \quad (11)$$

Thus $X_{a_1 b_1}^K(0)$ and $X_{a_2 b_2}^K(0)$ are Poisson(1) random variables. Furthermore, we see from equations (9)-(11), that

$$P_0\{X_{a_1 b_1}^K(0) = n_1, X_{a_2 b_2}^K(0) = n_2\} = P_0\{X_{a_1 b_1}^K(0) = n_1\} P_0\{X_{a_2 b_2}^K(0) = n_2\}.$$

and consequently, the random variables are independent.

If we now consider the calls initially in the system at time 0, we would like to know how they are distributed in the network at time t . Since calls leave the

system exponentially with unit mean, a call in the system at time 0 will still be in the system with probability e^{-t} . The above reasoning then follows with the probability of a call being on link $a_i b_i$ being e^{-t}/K , and we see the calls in the system at time 0 have a Poisson(e^{-t}) distribution.

Subsequently new calls arrive at rate νK . Obviously, the number of calls in the network at time zero is equal to the number of links, and the distribution of the links must be dependent on that of the other links. Therefore, as a whole, the links in the network are dependent but we will now show that they are P_t chaotic where P_t is a family of Poisson laws.

Now we wish to determine the joint distribution of $X_{a_i b_i}^K(t)$, $i = 1, \dots, k$, where $X_{a_i b_i}^K(t)$ is the number of circuits occupied at time t between nodes a_i and b_i in a network with N nodes due to calls that have arrived during $(0, t]$. The calculations shall be done for only two links, $a_1 b_1$ and $a_2 b_2$, but would follow for any general number of links, k . We first consider the calls still in the system at time t that were in progress at time 0 and then the calls in the system at time t that have arrived during the interval $(0, t)$.

The calls in the system at time t that have arrived during the interval $(0, t)$ are obtained as follows.

$$\begin{aligned}
 & \mathbf{P}\{X_{a_1 b_1}^K(t) = n_1, X_{a_2 b_2}^K(t) = n_2\} \\
 &= \sum_{n=n_1+n_2}^{\infty} \mathbf{P}\{X_{a_1 b_1}^K(t) = n_1, X_{a_2 b_2}^K(t) = n_2 | X^K(t) = n\} \mathbf{P}\{X^K(t) = n\} \\
 &= \sum_{n=n_1+n_2}^{\infty} \binom{n}{n_1, n_2} \left(\frac{1}{K}\right)^{n_1} \left(\frac{1}{K}\right)^{n_2} \left(1 - \frac{1}{K} - \frac{1}{K}\right)^{n-n_1-n_2} e^{-\nu K t} \frac{(\nu K t)^n}{n!} \\
 &= \sum_{n=n_1+n_2}^{\infty} \frac{n!}{n_1! n_2! (n - n_1 - n_2)!} \left(\frac{1}{K} \nu K t\right)^{n_1} \left(\frac{1}{K} \nu K t\right)^{n_2} \\
 &\quad \times \left(\left(1 - \frac{1}{K} - \frac{1}{K}\right) \nu K t\right)^{n-n_1-n_2} \frac{e^{-\nu K t}}{n!} \\
 &= \sum_{n=n_1+n_2}^{\infty} e^{-\nu t} \frac{(\nu t)^{n_1}}{n_1!} e^{-\nu t} \frac{(\nu t)^{n_2}}{n_2!} e^{-(1-\frac{2}{K})\nu K t} \frac{\left((1 - \frac{2}{K})\nu K t\right)^{(n-n_1-n_2)}}{(n - n_1 - n_2)!} \\
 &= e^{-\nu t} \frac{(\nu t)^{n_1}}{n_1!} e^{-\nu t} \frac{(\nu t)^{n_2}}{n_2!}
 \end{aligned} \tag{12}$$

Now we wish to find the distribution of $X_{a_1 b_1}^K(t)$.

$$\begin{aligned}
 \mathbf{P}\{X_{a_1 b_1}^K(t) = n_1\} &= \sum_{n_2=0}^{\infty} \mathbf{P}\{X_{a_1 b_1}^K(t) = n_1, X_{a_2 b_2}^K(t) = n_2\} \\
 &= \sum_{n_2=0}^{\infty} e^{-\nu t} \frac{(\nu t)^{n_1}}{n_1!} e^{-\nu t} \frac{(\nu t)^{n_2}}{n_2!} \\
 &= e^{-\nu t} \frac{(\nu t)^{n_1}}{n_1!}
 \end{aligned} \tag{13}$$

Similiarly,

$$\mathbf{P}\{X_{a_2 b_2}^K(t) = n_2\} = e^{-\nu t} \frac{(\nu t)^{n_2}}{n_2!} \tag{14}$$

So we see both $X_{a_1 b_1}^K$ and $X_{a_2 b_2}^K$ are Poisson(ν). Again we see from equations (12)-(14), that

$$\mathbf{P}\{X_{a_1 b_1}^K(t) = n_1, X_{a_2 b_2}^K(t) = n_2\} = \mathbf{P}\{X_{a_1 b_1}^K(t) = n_1\} \mathbf{P}\{X_{a_2 b_2}^K(t) = n_2\}.$$

Thus, $X_{a_1 b_1}^K(t)$ and $X_{a_2 b_2}^K(t)$ are independent. The reasoning follows for any finite k links as mentioned above, and so at some initial point k links are independent and by propagation of chaos, remain independent since the distribution of the total number of calls in the system at time t is given by the convolution $\mathbf{P}_0 * \mathbf{P}$ and $\mathbf{P}_0$ and $\mathbf{P}$ are independent, thus this completes the proof of propagation of chaos.

The analogous result for the original network is much more difficult to prove and is given in the following result that follows from the work of Graham and Méléard [4].

Theorem 4. *Assume the laws of $(X_{ab}^K(0))_{1 \leq a < b \leq N}$ are $\bar{P}_0$ -chaotic. Then the laws of $(X_{ab}^K(t))_{1 \leq a < b \leq N}$ are $\bar{P}_t$ -chaotic probability laws on $\{0, 1, \dots, C\}$. The law $\bar{P}_t$*

is given by the t -marginal distribution of the solution of the nonlinear martingale problem:

$$\begin{aligned} & \phi(X(t)) - \phi(X(0)) \\ & - \int_0^t ((\phi(X(s-)) + 1) \\ & - \phi(X(s-))) 1_{X(s-) < C} \\ & \times (\nu + 2\nu\gamma_C(s)(1 - \gamma_C(s))) \\ & + (\phi(X(s-)) - 1 - \phi(X(s-)))X(s-)ds \end{aligned}$$

is a $\bar{P}$ -martingale for every function ϕ defined on $\{0, 1, \dots, C\}$, where

$$\gamma_C(s) = \bar{P}(X(s) = C).$$

We conclude this section with the remark that the probability law $\bar{P}_t$ on $\{0, 1, \dots, C\}$ is the same as that obtained in the Theorem 2 so that the simplified and original models agree in the $K \rightarrow \infty$ limit.

4.3 Conclusion

The results of this chapter justify one assumption used in the simplification of our original network model, that is the exchangeability of links, and thus our two models are shown to agree in the limit as the number of links go to infinity.

5. Additional Routing Strategies

5.1 Introduction

We saw in Chapter 2 that Random Alternative Routing can actually serve to decrease the efficiency of the network. As noted earlier Random Alternative Routing is the simplest alternate routing scheme. In this chapter some more complicated routing strategies are considered.

5.2 Trunk Reservation and Multiple Alternatives

Returning to the results of Chapter 2, we saw that permitting random alternative routing actually can increase the loss probability of a network. If we now consider allowing blocked calls to try more than one alternative route, we would expect the increase in the loss probability to be even greater. As noted previously, blocked calls might end up requiring two circuits, and possibly blocking a direct call, perpetuating the inefficient use of circuits. An obvious resolution of this problem, is to reserve a certain number of circuits, say s , of each link for direct calls only. If there is excess capacity on the link (fewer than $C - s$ circuits are being used), alternatively routed calls can use the link, but if only reserved circuits are available, ($C - s$ or more circuits are already in use) a routed call is not allowed access. The call must then try another link or is lost, depending on whether multiple alternative are allowed. This method of giving priority at a link is known as trunk reservation, and the constant s is called the trunk reservation parameter.

As before the given model for a fully connected network of N nodes is difficult to analyse, so we simplify as before. Again we consider $K = N(N - 1)/2$ links, and if the call is blocked on its original link of choice, it tries two links chosen at random from the remaining $K - 1$ links. In this case though, the call can only be routed if there are less than $C - s$ circuits occupied on each link. Otherwise, the call must

try another pair of links from the remaining $K - 3$ links. Again it must check if there is capacity above the trunk reservation parameter before being routed, and the call is lost if after trying r pairs of links it is unable to be routed. As with the original model in Chapter 2 the holding times are independent. We define $n_j^K(t)$ and $x^K(t)$ as in Chapter 2. Now the following result can be established by methods analagous to those used in Chapter 2.

Theorem 5. *If $x^K(0) \Rightarrow x(0)$ in Δ then $x^K(\cdot) \Rightarrow x(\cdot)$ in $D_\Delta[0, \infty)$ where $x(\cdot)$ is the unique solution to the equations*

$$x_0(t) = x_0(0) + \int_0^t \{x_1(u) - [\nu + \lambda(u)]x_0(u)\} du \quad (15)$$

$$x_j(t) = x_j(0) + \int_0^t \{[\nu + \lambda(u)](x_{j-1}(u) - x_j(u)) + (j+1)x_{j+1}(u) - jx_j(u)\} du \quad j = 1, 2, \dots, C-s-1 \quad (16)$$

$$x_{C-s}(t) = x_{C-s}(0) + \int_0^t \{[\nu + \lambda(u)]x_{C-s-1}(u) - x_{C-s}(u) + (C-s-1)x_{C-s-1}(u) - (C-s)x_{C-s}(u)\} du \quad (17)$$

$$x_j(t) = x_j(0) + \int_0^t \{\nu(x_{j-1}(u) - x_j(u)) + (j+1)x_{j+1}(u) - jx_j(u)\} du \quad j = C-s+1, \dots, C-1 \quad (18)$$

$$x_C(t) = x_C(0) + \int_0^t \{\nu x_{C-1}(u) - Cx_C(u)\} du \quad (19)$$

and

$$\lambda(t) = 2\nu x_C(t) \left(\sum_{m=0}^{C-s-1} x_m(t) \right)^{-1} \left\{ 1 - \left[1 - \left(\sum_{m=0}^{C-s-1} x_m(t) \right)^2 \right]^r \right\}. \quad (20)$$

Thus, $x = (x_0, x_1, \dots, x_C) \in \Delta$ is a fixed point of this system of equations if

$$(j+1)x_{j+1} = (\nu + \lambda)x_j \quad j = 0, 1, \dots, C-s-1$$

$$(j+1)x_{j+1} = \nu x_j \quad j = C-s, \dots, C-1$$

where

$$\lambda = 2\nu B_1(1 - B_2)^{-1} \{1 - [1 - (1 - B_2)^2]^r\}$$

$$B_1 = x_C, \quad B_2 = \sum_{i=C-s}^C x_i.$$

The network loss probability corresponding to a solution of the fixed point equations is derived in the same fashion as that of our earlier model. A call is blocked on it's direct link with probability B_1 and then blocked on an alternate pair with probability $1 - (1 - B_2)^2$. Since a blocked call can try up to r alternate pairs, the network loss probability is

$$L = B_1[1 - (1 - B_2)^2]^r. \quad (21)$$

Using again a network with $N = 11$ nodes, $C = 120$ circuits and a call arrival rate of $\nu = 115$, we can test various other routing strategies. Consider first a network which allows five retries and no trunk reservation. We find in this case the overall network loss probability is $L = 0.294$, a huge increase over that of a single retry which we recall had a loss probability of $L = 0.122$.

Next consider several cases in which a network reserves $s = 5$ circuits and different alternative routing strategies are considered. If we first allow no alternative routing, we find an overall loss probability for the network of $L = 0.047$, the same as if no trunk reservation existed. Next allowing a single retry we find $L = 0.045$. And finally allowing 5 retries we find $L = 0.048$.

The first thing we notice is that with a trunk reservation of only five circuits, the loss probability varies by very little with the given routing schemes. But we also notice that random alternative routing (a single retry) actually reduces the overall loss probability when used in conjunction with trunk reservation.

5.3 Further Routing Schemes

Some other routing schemes which it might have been useful to explore are that of routing through loops of length l , and least full routing.

The first of these methods is similar to that of random alternate routing in that when a call is not able to be put through on its first choice, an alternate route is chosen from a pre-determined set of routes. Unlike random alternate routing the set of alternative routes consists of not just of pairs of links through a third node, but of all possible loops between the two nodes of length l or less. While this seems to provide a greater choice for routing calls, this is probably a very poor routing strategy. Alternately routed calls tie up at least two, and possibly more (up to l), links and longer loops are unable to accept the rerouted call if only one of its links is full. This scheme merely magnifies all the problems of random alternate routing.

A better strategy might be least full routing. This allows that a call unable to be placed directly is routed through the pair of links that is "least full". That is, the pair of links which has the greatest excess capacity. This method would appear to best embody the spirit of alternative routing as it reroutes calls through links where there is the greatest excess capacity. A possible disadvantage is that the state of every line in the network must be known at all times.

Neither of these methods will be analyzed in any detail. They are mentioned only as possible areas of future inquiry.

5.4 Learning Automata

All the previous schemes for rerouting calls choose from a set of alternate routes with equal probabilities ignoring the past states of these routes. In contrast, an approach which allows a node to "learn" might permit a more efficient routing.

If an adaptive or learning algorithm is used, the probability that an alternative route is chosen is altered by feedback information concerning the completion or rejection of earlier calls.

Simulation study utilizing a five node network led to the following conclusions (Narendra, Wright and Mason [9]; Narendra and Mars [8])

i) Certain learning schemes lead to close to optimal solutions in simple networks.

ii) Learning schemes do better than fixed rule solutions when randomization is required.

iii) Learning schemes tend to equalize blocking probabilities even if call arrival rates differ.

iv) Breakdowns within the network are dealt with more efficiently if additional capacity is available.

Since probabilities must be updated with each call, practical application for any real network is prohibited by high real-time processing. Another drawback is that each update uses only limited information about the network, that is only the fate of the last call is used in the revision.

Although no learning automata method is currently proposed for implementation (Hurley, Seidl and Sewell [5]), many of these ideas have already been absorbed into strategies already in use.

5.5 Conclusion

We see that there are many approaches to routing blocked calls, and at least one example combining two methods served to improve on the efficiency of the network.

6. Concluding Remarks

Our objective was to study the effects of a routing strategy on a telecommunication network, specifically that of Random Alternate Routing. The main idea was the introduction of a simplified process to model our original network. Through simulation the model was seen to be qualitatively good, and the theoretical result of propagation of chaos confirmed that one of our assumptions, the exchangeability of links, was valid for a large network.

Through the analysis of our simplified model, a disadvantage of the routing scheme appeared. Certain networks allow different equilibrium points, and a routing strategy that improves the local efficiency of the network, does so causing global degradation.

Several problems for research present themselves from this thesis. The methods presented in this thesis can be used to analyze many of the alternative routing schemes referred to above, such as trunk reservation, multiple retries, loops of length l , and "least full" routing. The diffusion approximation can be used to examine the multiple equilibria of certain networks.

Appendix A. Mathematica Programs

A.1 Original Network Simulation

Define the global variables:

$c = C$, the number of circuits.

$data = \{\{\text{the initial average circuit load, the initial number of full circuits}\}\}$

$n = N$, the number of nodes.

$net(i,j)$ = the initial of occupied circuits between nodes, if $i \neq j$;

$net(i,i) = 0$.

$s = s$, the trunk reservation on each line.

$t1$ = the number of data points.

$t2$ = the number of iterations between data points.

$v = \nu$, the call arrival rate.

Network[$t1$.Integer, $t2$.Integer, s .Integer] :=

Block[{ i, j }, $k = (n*(n - 1))/2$;

Do[Do[NetworkSingleStep[s], { $t2$ }];

AppendTo[$data$, {Sum[Count[$net[[i]]$], c], { i , 1, n }}/(2*k),

Sum[$net[[i,j]]$, { i , 1, n }, { j , 1, n }}/(2*k)]], { $t1$ }}]

NetworkSingleStep[s .] :=

Block[{ sum }, $sum = \text{Sum}[net[[i,j]], \{i, 1, n\}, \{j, 1, n\}]/2$;

If[Random[] $\geq (v*k)/(v*k + sum)$, LeaveChoice, EnterChoice[s]]]

LeaveChoice := Block[{ $q = 0, r, s$ },

While[$q == 0$, $r = \text{Random}[\text{Integer}, \{1, n\}]$; $s = \text{Random}[\text{Integer}, \{1, n\}]$;

If[$r \neq s$, If[$net[[r,s]] \neq 0$, $net[[r,s]] -= 1$; $net[[s,r]] -= 1$; $q += 1$]]]

```

EnterChoice[s_] := Block[{q, r = 0, t = 0},
  While[r == t, r = Random[Integer, {1, n}]; t = Random[Integer, {1, n}]];
  q = r; If[net[[r,t]] != c, net[[r,t]] += 1; net[[t,r]] += 1,
  While[q == r || q == t, q = Random[Integer, {1,n}]];
  If[net[[r,q]] < c-s && net[[t,q]] < c-s,
  net[[r,q]] += 1; net[[q,r]] += 1; net[[t,q]] += 1; net[[q,t]] += 1]]

```

A.2 Projection of Ξ

Define the global variables:

$c = C$, the number of circuits.

$data = \{\}$, the empty set.

$incr$ = the increments in increase of given x_C .

$init$ = the initial x_C used in the calculation if Ξ .

t = the number of data points.

$v = \nu$, the call arrival rate.

$XiPath[incr., init., t.Integer] :=$

Block[{xbar, xc, xi}, xc = init;

Do[xi = v*(1 + 2*xc*(1 - xc)); xbar = Sum[i*erl[xi, i], {i, 0, c}];

AppendTo[data, {xc, xbar}]; xc += incr, {t + 1}]]

$erl[xi., j.] := factf[xi, j]/Sum[factf[xi, i], \{i, 0, c\}]$

$factf[xi., i.] := xi^i/i!$

A.3 Path of Process describing Simplified Model

Define the global variables:

$c = C$, the number of circuits.

$data = \{\}$, the empty set.

$incr$ = time increments at which the process is observed.

$init[i] = x_i(0)$, the initial values of the process, x_j .

$lam = \lambda$, the fixed lambda.

$time$ = the integral equations are calculated until this time.

$v = \nu$, the call arrival rate.

```
eqns=Join[Table[Derivative[1][x[i]][t]==
  (v + lam)*x[i - 1][t] - (v + lam + i)*x[i][t] + (i + 1)*x[i + 1][t],
  {i, 1, c-1}], {Derivative[1][x[0]][t]==
  - (v + lam)*x[0][t] + x[1][t],
  Derivative[1][x[c]][t]== (lam + v)*x[c-1][t] - c*x[c][t]},
  Table[x[i][0]==init[i], {i, 0, c}]]
```

```
ProcessPath := Block[{avg, j = 0, k, temp},
  temp=Evaluate[Table[x[i][t], {i, 0, c}], {t, 0, time, incr}] /.
  NDSolve[eqns, Table[x[i], {i, 0, c}], {t, 0, time}]];
  For[k = 1, k < c + 1, k++, ex[k] = temp[[1,k+1]]];
  Do[avg = Sum[k*ex[k][[j+1]], {k, 1, c}];
    AppendTo[data, {ex[c][[j+1]], avg}];
    j += 1, {Floor[time/incr]+1}]]
```

A.4 Equilibrium Points for Simplified Model

Define the global variables:

$c = C$, the number of circuits.

$data = \{\}$, the empty set.

BiStable[init., incr., t_Integer] :=

Block[{r, s = 0.5, u, b = init},

Do[u = r /. FindRoot[b == erl[r*c*(1 + 2*b*(1 - b)), c], {r, s}]; s = u;

AppendTo[data, {u, b}]; b += incr, {t}]]

erl[xi., j.] := factf[xi, j]/Sum[factf[xi, i], {i, 0, c}]

factf[xi., i.] := xi^i/i!

References

- [1] Anantharam, V. (1991). A mean field limit for a lattice caricature of dynamic routing in circuit switched networks. *The Annals of Applied Probability* 4, 481-503.
- [2] Ethier, S.N. and Kurtz, T.G. (1986). *Markov Processes: Characterization and Convergence*. John Wiley and Sons, New York.
- [3] Gibbens, R.J., Hunt, P.J., and Kelly, F.P. (1990). Bistability in communication networks. *Disorder in Physical Systems*. Oxford University Press, 113-128.
- [4] Graham, C. and Méléard, S. (1993). Propagation of chaos for a fully connected loss network with alternate routing. *Stochastic Processes and their Applications* 44, 159-180.
- [5] Hurley, B.R., Seidl, C.J.R., and Sewell, W.F. (1987). A Survey of Dynamic Routing Methods for Circuit-Switched Traffic. *IEEE Communications Magazine* Vol. 25 9.
- [6] Karlin, S. and Taylor, H.M. (1981). *A Second Course in Stochastic Processes*. Academic Press, London.
- [7] Narendra, K. and Thathachar, M.A.L. (1989). *Learning Automata: An Introduction*. Prentice-Hall, New Jersey.
- [8] Narendra, K.S. and Mars, P. (1983). The Use of Learning Algorithms in Telephone Traffic Routing - A Methodology. *Automatica* 19, 495-502.
- [9] Narendra, K.S.E., Wright, E.A., and Mason, L.G. (1977). Application of Learning Automata to Teletraffic Routing and Management. *IEEE Trans. on Syst., Man and Cybern.*, SMC- 7, 785-792.
- [10] Ross, S. (1989). *Introduction to Probability Models*. Academic Press, San Diego.
- [11] Wolfram, S. (1988). *Mathematica: A System for Doing Mathematics by Computer*. Addison-Wesley Publishing Company, Inc., New York

END

1 | 8 - 0 7 - 9 4

FIN